

Welcome to E-XFL.COM

What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

Details

E·XFI

| Product Status | Active |
|----------------------------|--------------------------------------------------------------|
| Core Processor | S08 |
| Core Size | 8-Bit |
| Speed | 40MHz |
| Connectivity | I ² C, LINbus, SCI, SPI |
| Peripherals | LVD, POR, PWM, WDT |
| Number of I/O | 16 |
| Program Memory Size | 16KB (16K x 8) |
| Program Memory Type | FLASH |
| EEPROM Size | - |
| RAM Size | 1K x 8 |
| Voltage - Supply (Vcc/Vdd) | 2.7V ~ 5.5V |
| Data Converters | A/D 12x10b |
| Oscillator Type | Internal |
| Operating Temperature | -40°C ~ 105°C (TA) |
| Mounting Type | Surface Mount |
| Package / Case | 20-TSSOP (0.173", 4.40mm Width) |
| Supplier Device Package | 20-TSSOP |
| Purchase URL | https://www.e-xfl.com/pro/item?MUrl=&PartUrl=s9s08sg16e1vtjr |

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong





Table 1-2 provides the functional version of the on-chip modules.

| Module | Version | |
|---------------------------------|---------|---|
| Analog Comparator (5V) | (ACMP) | 3 |
| Analog-to-Digital Converter | (ADC10) | 1 |
| Central Processor Unit | (CPU) | 3 |
| Inter-Integrated Circuit | (IIC) | 2 |
| Internal Clock Source | (ICS) | 2 |
| Low Power Oscillator | (XOSC) | 1 |
| Modulo Timer | (MTIM) | 1 |
| On-Chip In-Circuit Emulator | (DBG) | 2 |
| Real-Time Counter | (RTC) | 1 |
| Serial Peripheral Interface | (SPI) | 3 |
| Serial Communications Interface | (SCI) | 4 |
| Timer Pulse Width Modulator | (TPM) | 3 |

Table 1-2. Module Versions



Chapter 2 Pins and Connections

When an on-chip peripheral system is controlling a pin, data direction control bits still determine what is read from port data registers even though the peripheral module controls the pin direction by controlling the enable for the pin's output buffer. For information about controlling these pins as general-purpose I/O pins, see Chapter 6, "Parallel Input/Output Control."

The MC9S08SG32 Series devices contain a ganged output drive feature that allows a safe and reliable method of allowing pins to be tied together externally to produce a higher output current drive. See Section 6.3, "Ganged Output" for more information for configuring the port pins for ganged output drive.

NOTE

To avoid extra current drain from floating input pins, the reset initialization routine in the application program should either enable on-chip pull-up devices or change the direction of unused pins to outputs so they do not float.

When using the 20-pin devices, either enable on-chip pullup devices or change the direction of non-bonded PTC7-PTC4 and PTA7-PTA6 pins to outputs so the pins do not float.

When using the 16-pin devices, either enable on-chip pullup devices or change the direction of non-bonded out PTC7-PTC0 and PTA7-PTA6 pins to outputs so the pins do not float.

| Die Neuelau | | | Priority | | | | | | | | |
|-------------|---------------------|--------|----------|----------------------|----------------------|-------------------|------------------|--------------------|--|--|--|
| р Р | 'in Numb | er | | Lowest | | Highest | | | | | |
| 28-pin | 20-pin ¹ | 16-pin | Port Pin | Alt 1 | Alt 2 | Alt 3 | Alt 4 | Alt 5 | | | |
| 1 | | | PTC5 | | | | | ADP13 | | | |
| 2 | _ | | PTC4 | | | | | ADP12 | | | |
| 3 | 1 | 1 | | | | | | RESET ² | | | |
| 4 | 2 | 2 | | | | | BKGD | MS | | | |
| 5 | | | | | | | | V _{DD} | | | |
| 6 | 3 | 3 | | | | | V _{DDA} | V _{REFH} | | | |
| 7 | | _ | | | | | V _{SSA} | V _{REFL} | | | |
| 8 | 4 | 4 | | | | | | V _{SS} | | | |
| 9 | 5 | 5 | PTB7 | SCL ³ | EXTAL | | | | | | |
| 10 | 6 | 6 | PTB6 | SDA ³ | XTAL | | | | | | |
| 11 | 7 | 7 | PTB5 | TPM1CH1 ⁴ | SS | PTC0 ⁵ | | | | | |
| 12 | 8 | 8 | PTB4 | TPM2CH1 ⁶ | MISO | PTC0 ⁵ | | | | | |
| 13 | 9 | | PTC3 | | | PTC0 ⁵ | ADP11 | | | | |
| 14 | 10 | _ | PTC2 | | | PTC0 ⁵ | ADP10 | | | | |
| 15 | 11 | _ | PTC1 | | TPM1CH1 ⁴ | PTC0 ⁵ | ADP9 | | | | |
| 16 | 12 | — | PTC0 | | TPM1CH0 ⁴ | PTC0 ⁵ | ADP8 | | | | |
| 17 | 13 | 9 | PTB3 | PIB3 | MOSI | PTC0 ⁵ | ADP7 | | | | |
| 18 | 14 | 10 | PTB2 | PIB2 | SPSCK | PTC0 ⁵ | ADP6 | | | | |

Table 2-1. Pin Availability by Package Pin-Count



Chapter 2 Pins and Connections

Chapter 3 Modes of Operation

Background commands are of two types:

- Non-intrusive commands, defined as commands that can be issued while the user program is running. Non-intrusive commands can be issued through the BKGD/MS pin while the MCU is in run mode; non-intrusive commands can also be executed when the MCU is in the active background mode. Non-intrusive commands include:
 - Memory access commands
 - Memory-access-with-status commands
 - BDC register access commands
 - The BACKGROUND command
- Active background commands, which can only be executed while the MCU is in active background mode. Active background commands include commands to:
 - Read or write CPU registers
 - Trace one user program instruction at a time
 - Leave active background mode to return to the user application program (GO)

The active background mode is used to program a bootloader or user application program into the FLASH program memory before the MCU is operated in run mode for the first time. When the MC9S08SG32 Series is shipped from the Freescale Semiconductor factory, the FLASH program memory is erased by default unless specifically noted so there is no program that could be executed in run mode until the FLASH memory is initially programmed. The active background mode can also be used to erase and reprogram the FLASH memory after it has been previously programmed.

For additional information about the active background mode, refer to the Development Support chapter.

3.5 Wait Mode

Wait mode is entered by executing a WAIT instruction. Upon execution of the WAIT instruction, the CPU enters a low-power state in which it is not clocked. The I bit in CCR is cleared when the CPU enters the wait mode, enabling interrupts. When an interrupt request occurs, the CPU exits the wait mode and resumes processing, beginning with the stacking operations leading to the interrupt service routine.

While the MCU is in wait mode, there are some restrictions on which background debug commands can be used. Only the BACKGROUND command and memory-access-with-status commands are available when the MCU is in wait mode. The memory-access-with-status commands do not allow memory access, but they report an error indicating that the MCU is in either stop or wait mode. The BACKGROUND command can be used to wake the MCU from wait mode and enter active background mode.

3.6 Stop Modes

One of two stop modes is entered upon execution of a STOP instruction when STOPE in SOPT1. In any stop mode, the bus and CPU clocks are halted. The ICS module can be configured to leave the reference clocks running. See Chapter 11, "Internal Clock Source (S08ICSV2)," for more information.



| Vector Priority | Vector Number | Address (High/Low) | Vector Name | Module | Source | Enable | Description |
|--------------------|------------------|-----------------------|----------------|-------------------|------------------------------------------------------------------|----------------------------------|-------------------------------------------------------------------------------------------|
| | 31 | 0xFFC0/0xFFC1 | _ | | _ | _ | _ |
| Lowest | owest 30 0xFFC | | Vacmp | ACMP | ACF | ACIE | Analog comparator |
| | 29 | 0xFFC4/0xFFC5 | | _ | | — | — |
| | 28 | 0xFFC6/0xFFC7 | | — | _ | — | — |
| | 27 | 0xFFC8/0xFFC9 | — | — | _ | — | — |
| | 26 | 0xFFCA/0xFFCB | Vmtim | MTIM | TOF | TOIE | MTIM overflow |
| | 25 | 0xFFCC/0xFFCD | Vrtc | RTC | RTIF | RTIE | Real-time interrupt |
| | 24 | 0xFFCE/0xFFCF | Viic | IIC | IICIS | IICIE | IIC control |
| | 23 | 0xFFD0/0xFFD1 | Vadc | ADC | COCO | AIEN | ADC |
| | 22 | 0xFFD2/0xFFD3 | _ | _ | _ | — | — |
| | 21 | 0xFFD4/0xFFD5 | Vportb | Port B | PTBIF | PTBIE | Port B Pins |
| | 20 | 0xFFD6/0xFFD7 | Vporta | Port A | PTAIF | PTAIE | Port A Pins |
| | 19 | 0xFFD8/0xFFD9 | _ | | _ | _ | _ |
| | 18 | 0xFFDA/0xFFDB | Vscitx | SCI | TDRE, TC | TIE, TCIE | SCI transmit |
| | 17 | 0xFFDC/0xFFDD | Vscirx | SCI | IDLE, RDRF, LDBKDIF, RXEDGIF | ILIE, RIE, LBKDIE, RXEDGIE | SCI receive |
| | 16 | 0xFFDE/0xFFDF | Vscierr | SCI | OR, NF, FE, PF | ORIE, NFIE, FEIE, PFIE | SCI error |
| | 15 | 0xFFE0/0xFFE1 | Vspi | SPI | SPIF, MODF, SPTEF | SPIE, SPIE, SPTIE | SPI |
| | 14 | 0xFFE2/0xFFE3 | Vtpm2ovf | TPM2 | TOF | TOIE | TPM2 overflow |
| | 13 | 0xFFE4/0xFFE5 | Vtpm2ch1 | TPM2 | CH1F | CH1IE | TPM2 channel 1 |
| | 12 | 0xFFE6/0xFFE7 | Vtpm2ch0 | TPM2 | CH0F | CH0IE | TPM2 channel 0 |
| | 11 | 0xFFE8/0xFFE9 | Vtpm1ovf | TPM1 | TOF | TOIE | TPM1 overflow |
| | 10 | 0xFFEA/0xFFEB | _ | _ | _ | — | — |
| | 9 | 0xFFEC/0xFFED | _ | — | | — | — |
| | 8 | 0xFFEE/0xFFEF | | _ | _ | — | — |
| | 7 | 0xFFF0/0xFFF1 | | — | | | _ |
| | 6 | 0xFFF2/0xFFF3 | Vtpm1ch1 | TPM1 | CH1F | CH1IE | TPM1 channel 1 |
| | 5 | 0xFFF4/0xFFF5 | Vtpm1ch0 | TPM1 | CH0F | CH0IE | TPM1 channel 0 |
| | 4 | 0xFFF6/0xFFF7 | | — | | — | — |
| | 3 | 0xFFF8/0xFFF9 | Vlvd | Systemcon trol | LVWF | LVWIE | Low-voltage warning |
| | 2 | 0xFFFA/0xFFFB | | | _ | _ | _ |
| | 1 | 0xFFFC/0xFFFD | Vswi | Core | SWI Instruction | — | Software interrupt |
| ¥ Highest | 0 | 0xFFFE/0xFFFF | Vreset | System control | COP, LVD, RESET pin, Illegal opcode, Illegal address | COPE LVDRE — — — | Watchdog timer Low-voltage detect External pin Illegal opcode Illegal address |

Table 5-2. Vector Summary



6.6.3 **Port C Registers**

Port C is controlled by the registers listed below.

6.6.3.1 Port C Data Register (PTCD)



Figure 6-19. Port C Data Register (PTCD)

Table 6-18. PTCD Register Field Descriptions

| Field | Description |
|------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 7:0 PTCD[7:0] | Port C Data Register Bits — For port C pins that are inputs, reads return the logic level on the pin. For port C pins that are configured as outputs, reads return the last value written to this register. Writes are latched into all bits of this register. For port C pins that are configured as outputs, the logic level is driven out the corresponding MCU pin. Reset forces PTCD to all 0s, but these 0s are not driven out the corresponding pins because reset also configures all port pins as high-impedance inputs with pull-ups disabled. |

6.6.3.2 Port C Data Direction Register (PTCDD)

| | 7 | 6 | 5 | 4 | 3 | 2 | 1 | 0 |
|--------|--------|--------|--------|--------|--------|--------|--------|--------|
| R | PTCDD7 | PTCDD6 | PTCDD5 | PTCDD4 | PTCDD3 | PTCDD2 | PTCDD1 | PTCDD0 |
| W | - | | | - | | - | - | |
| Reset: | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |

Figure 6-20. Port C Data Direction Register (PTCDD)

Table 6-19. PTCDD Register Field Descriptions

| Field | Description |
|-------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 7:0 PTCDD[7:0] | Data Direction for Port C Bits — These read/write bits control the direction of port C pins and what is read for PTCD reads. |
| | Input (output driver disabled) and reads return the pin value. Output driver enabled for port C bit n and PTCD reads return the contents of PTCDn. |



| Bit-Mani | pulation | Branch | | Rea | d-Modify-W | /rite | • | Coi | ntrol | · / | | Register | /Memorv | | |
|-------------------------|------------------------|----------------------|-----------------------|-----------------------|-----------------------|-----------------------|--------------------------------|------------------------|----------------------|----------------------|----------------------|----------------------|----------------------|----------------------|---------------------|
| 00 5 | 10 5 | 20 3 | 30 5 | 40 1 | 50 1 | 60 5 | 70 4 | 80 9 | 90 3 | A0 2 | B0 3 | C0 4 | D0 4 | E0 3 | F0 3 |
| BRSET0 | BSET0 | BRA | NEG | NEGA | NEGX | NEG | NEG | RTI | BGE | SUB | SUB | SUB | SUB | SUB | SUB |
| 3 DIR | 2 DIR | 2 REL | 2 DIR | 1 INH | 1 INH | 2 IX1 | 1 IX | 1 INH | 2 REL | 2 IMM | 2 DIR | 3 EXT | 3 IX2 | 2 IX1 | 1 IX |
| 01 5 | 11 5 | 21 3 | 31 5 | 41 4 | 51 4 | 61 5 | 71 5 | 81 6 | 91 3 | A1 2 | B1 3 | C1 4 | D1 4 | E1 3 | F1 3 |
| BRCLR0 | BCLR0 | BRN | CBEQ | CBEQA | CBEQX | CBEQ | CBEQ | RTS | BLT | CMP | CMP | CMP | CMP | CMP | CMP |
| 3 DIR | 2 DIR | 2 REL | 3 DIR | 3 IMM | 3 IMM | 3 IX1+ | 2 IX+ | 1 INH | 2 REL | 2 IMM | 2 DIR | 3 EXT | 3 IX2 | 2 IX1 | 1 IX |
| 02 5 | 12 5 | 22 3 | 32 5 | 42 5 | 52 6 | 62 1 | 72 1 | 82 5+ | 92 3 | A2 2 | B2 3 | C2 4 | D2 4 | E2 3 | F2 3 |
| BRSET1 | BSET1 | BHI | LDHX | MUL | DIV | NSA | DAA | BGND | BGT | SBC | SBC | SBC | SBC | SBC | SBC |
| 3 DIR | 2 DIR | 2 REL | 3 EXT | 1 INH | 1 INH | 1 INH | 1 INH | 1 INH | 2 REL | 2 IMM | 2 DIR | 3 EXT | 3 IX2 | 2 IX1 | 1 IX |
| 03 5 | 13 5 | 23 3 | 33 5 | 43 1 | 53 1 | 63 5 | 73 4 | 83 11 | 93 3 | A3 2 | B3 3 | C3 4 | D3 4 | E3 3 | F3 3 |
| BRCLR1 | BCLR1 | BLS | COM | COMA | COMX | COM | COM | SWI | BLE | CPX | CPX | CPX | CPX | CPX | CPX |
| 3 DIR | 2 DIR | 2 REL | 2 DIR | 1 INH | 1 INH | 2 IX1 | 1 IX | 1 INH | 2 REL | 2 IMM | 2 DIR | 3 EXT | 3 IX2 | 2 IX1 | 1 IX |
| 04 5 BRSET2 3 DIR | 14 5 BSET2 2 DIR | BCC 2 REL | 34 5 LSR 2 DIR | 44 1 LSRA 1 INH | 54 1 LSRX 1 INH | 64 5 LSR 2 IX1 | ⁷⁴ 4 LSR 1 IX | 84 1 TAP 1 INH | 94 2 TXS 1 INH | A4 2 AND 2 IMM | AND 2 DIR | AND 3 EXT | D4 4 AND 3 IX2 | E4 3 AND 2 IX1 | F4 3 AND 1 IX |
| 05 5 BRCLR2 3 DIR | 15 5 BCLR2 2 DIR | 25 3 BCS 2 REL | 35 4 STHX 2 DIR | 45 3 LDHX 3 IMM | LDHX 2 DIR | 65 3 CPHX 3 IMM | 75 5 CPHX 2 DIR | 85 1 TPA 1 INH | 95 2 TSX 1 INH | A5 2 BIT 2 IMM | B5 3 BIT 2 DIR | BIT 3 EXT | BIT 3 IX2 | BIT 2 IX1 | BIT 1 IX |
| 06 5 | 16 5 | 26 3 | 36 5 | 46 1 | 56 1 | 66 5 | 76 4 | 86 3 | 96 5 | A6 2 | B6 3 | C6 4 | D6 4 | E6 3 | F6 3 |
| BRSET3 | BSET3 | BNE | ROR | RORA | RORX | ROR | ROR | PULA | STHX | LDA | LDA | LDA | LDA | LDA | LDA |
| 3 DIR | 2 DIR | 2 REL | 2 DIR | 1 INH | 1 INH | 2 IX1 | 1 IX | 1 INH | 3 EXT | 2 IMM | 2 DIR | 3 EXT | 3 IX2 | 2 IX1 | 1 IX |
| 07 5 | 17 5 | 27 3 | 37 5 | 47 1 | 57 1 | 67 5 | 77 4 | 87 2 | 97 1 | A7 2 | B7 3 | C7 4 | D7 4 | E7 3 | F7 2 |
| BRCLR3 | BCLR3 | BEQ | ASR | ASRA | ASRX | ASR | ASR | PSHA | TAX | AIS | STA | STA | STA | STA | STA |
| 3 DIR | 2 DIR | 2 REL | 2 DIR | 1 INH | 1 INH | 2 IX1 | 1 IX | 1 INH | 1 INH | 2 IMM | 2 DIR | 3 EXT | 3 IX2 | 2 IX1 | 1 IX |
| 08 5 | 18 5 | 28 3 | 38 5 | 48 1 | 58 1 | 68 5 | 78 4 | 88 3 | 98 1 | A8 2 | B8 3 | C8 4 | D8 4 | E8 3 | F8 3 |
| BRSET4 | BSET4 | BHCC | LSL | LSLA | LSLX | LSL | LSL | PULX | CLC | EOR | EOR | EOR | EOR | EOR | EOR |
| 3 DIR | 2 DIR | 2 REL | 2 DIR | 1 INH | 1 INH | 2 IX1 | 1 IX | 1 INH | 1 INH | 2 IMM | 2 DIR | 3 EXT | 3 IX2 | 2 IX1 | 1 IX |
| 09 5 | 19 5 | 29 3 | 39 5 | 49 1 | 59 1 | 69 5 | 79 4 | 89 2 | 99 1 | A9 2 | B9 3 | C9 4 | D9 4 | E9 3 | F9 3 |
| BRCLR4 | BCLR4 | BHCS | ROL | ROLA | ROLX | ROL | ROL | PSHX | SEC | ADC | ADC | ADC | ADC | ADC | ADC |
| 3 DIR | 2 DIR | 2 REL | 2 DIR | 1 INH | 1 INH | 2 IX1 | 1 IX | 1 INH | 1 INH | 2 IMM | 2 DIR | 3 EXT | 3 IX2 | 2 IX1 | 1 IX |
| 0A 5 | 1A 5 | 2A 3 | 3A 5 | 4A 1 | 5A 1 | 6A 5 | 7A 4 | 8A 3 | 9A 1 | AA 2 | BA 3 | CA 4 | DA 4 | EA 3 | FA 3 |
| BRSET5 | BSET5 | BPL | DEC | DECA | DECX | DEC | DEC | PULH | CLI | ORA | ORA | ORA | ORA | ORA | ORA |
| 3 DIR | 2 DIR | 2 REL | 2 DIR | 1 INH | 1 INH | 2 IX1 | 1 IX | 1 INH | 1 INH | 2 IMM | 2 DIR | 3 EXT | 3 IX2 | 2 IX1 | 1 IX |
| 0B 5 | 1B 5 | 2B 3 | 3B 7 | 4B 4 | 5B 4 | 6B 7 | 7B 6 | 8B 2 | 9B 1 | AB 2 | BB 3 | CB 4 | DB 4 | EB 3 | FB 3 |
| BRCLR5 | BCLR5 | BMI | DBNZ | DBNZA | DBNZX | DBNZ | DBNZ | PSHH | SEI | ADD | ADD | ADD | ADD | ADD | ADD |
| 3 DIR | 2 DIR | 2 REL | 3 DIR | 2 INH | 2 INH | 3 IX1 | 2 IX | 1 INH | 1 INH | 2 IMM | 2 DIR | 3 EXT | 3 IX2 | 2 IX1 | 1 IX |
| 0C 5 | 1C 5 | 2C 3 | 3C 5 | 4C 1 | 5C 1 | 6C 5 | 7C 4 | 8C 1 | 9C 1 | | BC 3 | CC 4 | DC 4 | EC 3 | FC 3 |
| BRSET6 | BSET6 | BMC | INC | INCA | INCX | INC | INC | CLRH | RSP | | JMP | JMP | JMP | JMP | JMP |
| 3 DIR | 2 DIR | 2 REL | 2 DIR | 1 INH | 1 INH | 2 IX1 | 1 IX | 1 INH | 1 INH | | 2 DIR | 3 EXT | 3 IX2 | 2 IX1 | 1 IX |
| 0D 5 | 1D 5 | 2D 3 | 3D 4 | 4D 1 | 5D 1 | 6D 4 | 7D 3 | | 9D 1 | AD 5 | BD 5 | CD 6 | DD 6 | ED 5 | FD 5 |
| BRCLR6 | BCLR6 | BMS | TST | TSTA | TSTX | TST | TST | | NOP | BSR | JSR | JSR | JSR | JSR | JSR |
| 3 DIR | 2 DIR | 2 REL | 2 DIR | 1 INH | 1 INH | 2 IX1 | 1 IX | | 1 INH | 2 REL | 2 DIR | 3 EXT | 3 IX2 | 2 IX1 | 1 IX |
| 0E 5 BRSET7 3 DIR | 1E 5 BSET7 2 DIR | 2E 3 BIL 2 REL | 3E 6 CPHX 3 EXT | 4E 5 MOV 3 DD | 5E 5 MOV 2 DIX+ | 6E 4 MOV 3 IMD | 7E 5 MOV 2 IX+D | 8E 2+ STOP 1 INH | 9E Page 2 | AE 2 LDX 2 IMM | BE 3 LDX 2 DIR | CE 4 LDX 3 EXT | DE 4 LDX 3 IX2 | EE 3 LDX 2 IX1 | FE 3 LDX 1 IX |
| 0F 5 | 1F 5 | 2F 3 | 3F 5 | 4F 1 | 5F 1 | 6F 5 | 7F 4 | 8F 2+ | 9F 1 | AF 2 | BF 3 | CF 4 | DF 4 | EF 3 | FF 2 |
| BRCLR7 | BCLR7 | BIH | CLR | CLRA | CLRX | CLR | CLR | WAIT | TXA | AIX | STX | STX | STX | STX | STX |
| 3 DIR | 2 DIR | 2 REL | 2 DIR | 1 INH | 1 INH | 2 IX1 | 1 IX | 1 INH | 1 INH | 2 IMM | 2 DIR | 3 EXT | 3 IX2 | 2 IX1 | 1 IX |

Table 7-3. Opcode Map (Sheet 1 of 2)

| Inherent |
|------------|
| Immediate |
| Direct |
| Extended |
| DIR to DIR |
| IX+ to DIR |
| |

REL IX IX1 IX2 IMD DIX+ Relative Indexed, No Offset Indexed, 8-Bit Offset Indexed, 16-Bit Offset IMM to DIR DIR to IX+

Stack Pointer, 8-Bit Offset Stack Pointer, 16-Bit Offset Indexed, No Offset with Post Increment Indexed, 1-Byte Offset with Post Increment

SP1 SP2 IX+

IX1+

Opcode in Hexadecimal F0 3 SUB Number of Bytes 1 IX HCS08 Cycles Instruction Mnemonic Addressing Mode



Chapter 8 Analog Comparator 5-V (S08ACMPV3)



 Δ = Pin can be enabled as part of the ganged output drive feature

Figure 8-1. MC9S08SG32 Series Block Diagram Highlighting ACMP Block and Pins

MC9S08SG32 Data Sheet, Rev. 8



Chapter 10 Inter-Integrated Circuit (S08IICV2)



NOTE

- PTC7-PTC0 and PTA7-PTA6 are not available on 16-pin Packages
- PTC7-PTC4 and PTA7-PTA6 are not available on 20-pin Packages
- + For the 16-pin and 20-pin packages: $V_{\mbox{DDA}}/V_{\mbox{REFH}}$ and $V_{\mbox{SSA}}/V_{\mbox{REFL}}$ are
- double bonded to V_{DD} and V_{SS} respectively.

 Δ = Pin can be enabled as part of the ganged output drive feature

Figure 10-1. MC9S08SG32 Series Block Diagram Highlighting IIC Block and Pins

MC9S08SG32 Data Sheet, Rev. 8



10.4.1.3 Data Transfer

Before successful slave addressing is achieved, the data transfer can proceed byte-by-byte in a direction specified by the R/\overline{W} bit sent by the calling master.

All transfers that come after an address cycle are referred to as data transfers, even if they carry sub-address information for the slave device

Each data byte is 8 bits long. Data may be changed only while SCL is low and must be held stable while SCL is high as shown in Figure 10-9. There is one clock pulse on SCL for each data bit, the msb being transferred first. Each data byte is followed by a 9th (acknowledge) bit, which is signalled from the receiving device. An acknowledge is signalled by pulling the SDA low at the ninth clock. In summary, one complete data transfer needs nine clock pulses.

If the slave receiver does not acknowledge the master in the ninth bit time, the SDA line must be left high by the slave. The master interprets the failed acknowledge as an unsuccessful data transfer.

If the master receiver does not acknowledge the slave transmitter after a data byte transmission, the slave interprets this as an end of data transfer and releases the SDA line.

In either case, the data transfer is aborted and the master does one of two things:

- Relinquishes the bus by generating a stop signal.
- Commences a new calling by generating a repeated start signal.

10.4.1.4 Stop Signal

The master can terminate the communication by generating a stop signal to free the bus. However, the master may generate a start signal followed by a calling command without generating a stop signal first. This is called repeated start. A stop signal is defined as a low-to-high transition of SDA while SCL at logical 1 (see Figure 10-9).

The master can generate a stop even if the slave has generated an acknowledge at which point the slave must release the bus.

10.4.1.5 Repeated Start Signal

As shown in Figure 10-9, a repeated start signal is a start signal generated without first generating a stop signal to terminate the communication. This is used by the master to communicate with another slave or with the same slave in different mode (transmit/receive mode) without releasing the bus.

10.4.1.6 Arbitration Procedure

The IIC bus is a true multi-master bus that allows more than one master to be connected on it. If two or more masters try to control the bus at the same time, a clock synchronization procedure determines the bus clock, for which the low period is equal to the longest clock low period and the high is equal to the shortest one among the masters. The relative priority of the contending masters is determined by a data arbitration procedure, a bus master loses arbitration if it transmits logic 1 while another master transmits logic 0. The losing masters immediately switch over to slave receive mode and stop driving SDA output. In this case,



Arbitration is lost in the following circumstances:

- SDA sampled as a low when the master drives a high during an address or data transmit cycle.
- SDA sampled as a low when the master drives a high during the acknowledge bit of a data receive cycle.
- A start cycle is attempted when the bus is busy.
- A repeated start cycle is requested in slave mode.
- A stop condition is detected when the master did not request it.

This bit must be cleared by software writing a 1 to it.



Chapter 11 Internal Clock Source (S08ICSV2)

The CLKS bits can also be changed at anytime, but the RDIV bits must be changed simultaneously so that the resulting frequency stays in the range of 31.25 kHz to 39.0625 kHz. The actual switch to the newly selected clock will not occur until after a few full cycles of the new clock. If the newly selected clock is not available, the previous clock will remain selected.

11.4.3 Bus Frequency Divider

The BDIV bits can be changed at anytime and the actual switch to the new frequency will occur immediately.

11.4.4 Low Power Bit Usage

The low power bit (LP) is provided to allow the FLL to be disabled and thus conserve power when it is not being used. However, in some applications it may be desirable to enable the FLL and allow it to lock for maximum accuracy before switching to an FLL engaged mode. Do this by writing the LP bit to 0.

11.4.5 Internal Reference Clock

When IRCLKEN is set the internal reference clock signal will be presented as ICSIRCLK, which can be used as an additional clock source. The ICSIRCLK frequency can be re-targeted by trimming the period of the internal reference clock. This can be done by writing a new value to the TRIM bits in the ICSTRM register. Writing a larger value will slow down the ICSIRCLK frequency, and writing a smaller value to the ICSTRM register will speed up the ICSIRCLK frequency. The TRIM bits will effect the ICSOUT frequency if the ICS is in FLL engaged internal (FEI), FLL bypassed internal (FBI), or FLL bypassed internal low power (FBILP) mode. The TRIM and FTRIM value will not be affected by a reset.

Until ICSIRCLK is trimmed, programming low reference divider (RDIV) factors may result in ICSOUT frequencies that exceed the maximum chip-level frequency and violate the chip-level clock timing specifications (see the Device Overview chapter).

If IREFSTEN is set and the IRCLKEN bit is written to 1, the internal reference clock will keep running during stop mode in order to provide a fast recovery upon exiting stop.

All MCU devices are factory programmed with a trim value in a reserved memory location (NVTRIM:NVFTRIM). This value can be copied to the ICSTRM register during reset initialization. The factory trim value includes the FTRIM bit. For finer precision, the user can trim the internal oscillator in the application to take in account small differences between the factory test setup and actual application conditions.

11.4.6 Optional External Reference Clock

The ICS module can support an external reference clock with frequencies between 31.25 kHz to 5 MHz in all modes. When the ERCLKEN is set, the external reference clock signal will be presented as ICSERCLK, which can be used as an additional clock source. When IREFS = 1, the external reference clock will not be used by the FLL and will only be used as ICSERCLK. In these modes, the frequency can be equal to the maximum frequency the chip-level timing specifications will support (see the Device Overview chapter).



Chapter 12 Modulo Timer (S08MTIMV1)

12.3.1 MTIM Status and Control Register (MTIMSC)

MTIMSC contains the overflow status flag and control bits which are used to configure the interrupt enable, reset the counter, and stop the counter.



Figure 12-4. MTIM Status and Control Register

| Table 12-2. MTIM Status and Contro | I Register Field Descriptions |
|------------------------------------|-------------------------------|
|------------------------------------|-------------------------------|

| Field | Description |
|-----------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 7 TOF | MTIM Overflow Flag — This read-only bit is set when the MTIM counter register overflows to \$00 after reaching the value in the MTIM modulo register. Clear TOF by reading the MTIMSC register while TOF is set, then writing a 0 to TOF. TOF is also cleared when TRST is written to a 1 or when any value is written to the MTIMMOD register. 0 MTIM counter has not reached the overflow value in the MTIM modulo register. 1 MTIM counter has reached the overflow value in the MTIM modulo register. |
| 6 TOIE | MTIM Overflow Interrupt Enable — This read/write bit enables MTIM overflow interrupts. If TOIE is set, then an interrupt is generated when TOF = 1. Reset clears TOIE. Do not set TOIE if TOF = 1. Clear TOF first, then set TOIE. 0 TOF interrupts are disabled. Use software polling. 1 TOF interrupts are enabled. |
| 5 TRST | MTIM Counter Reset — When a 1 is written to this write-only bit, the MTIM counter register resets to \$00 and TOF is cleared. Reading this bit always returns 0. 0 No effect. MTIM counter remains at current state. 1 MTIM counter is reset to \$00. |
| 4 TSTP | MTIM Counter Stop — When set, this read/write bit stops the MTIM counter at its current value. Counting resumes from the current value when TSTP is cleared. Reset sets TSTP to prevent the MTIM from counting. 0 MTIM counter is active. 1 MTIM counter is stopped. |
| 3:0 | Unused register bits, always read 0. |



13.1.1 Features

Features of the RTC module include:

- 8-bit up-counter
 - 8-bit modulo match limit
 - Software controllable periodic interrupt on match
- Three software selectable clock sources for input to prescaler with selectable binary-based and decimal-based divider values
 - 1-kHz internal low-power oscillator (LPO)
 - External clock (ERCLK)
 - 32-kHz internal clock (IRCLK)

13.1.2 Modes of Operation

This section defines the operation in stop, wait and background debug modes.

13.1.2.1 Wait Mode

The RTC continues to run in wait mode if enabled before executing the appropriate instruction. Therefore, the RTC can bring the MCU out of wait mode if the real-time interrupt is enabled. For lowest possible current consumption, the RTC should be stopped by software if not needed as an interrupt source during wait mode.

13.1.2.2 Stop Modes

The RTC continues to run in stop2 or stop3 mode if the RTC is enabled before executing the STOP instruction. Therefore, the RTC can bring the MCU out of stop modes with no external components, if the real-time interrupt is enabled.

The LPO clock can be used in stop2 and stop3 modes. ERCLK and IRCLK clocks are only available in stop3 mode.

Power consumption is lower when all clock sources are disabled, but in that case, the real-time interrupt cannot wake up the MCU from stop modes.

13.1.2.3 Active Background Mode

The RTC suspends all counting during active background mode until the microcontroller returns to normal user operating mode. Counting resumes from the suspended value as long as the RTCMOD register is not written and the RTCPS and RTCLKS bits are not altered.



}

```
RTCSC.byte = RTCSC.byte | 0x80;
/* RTC interrupts every 1 Second */
Seconds++;
/* 60 seconds in a minute */
if (Seconds > 59){
Minutes++;
Seconds = 0;
}
/* 60 minutes in an hour */
if (Minutes > 59){
Hours++;
Minutes = 0;
}
/* 24 hours in a day */
if (Hours > 23){
Days ++;
Hours = 0;
}
```





Figure 14-5. SCI Baud Rate Register (SCIBDL)

Table 14-2. SCIBDL Field Descriptions

| Field | Description |
|-----------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 7:0 SBR[7:0] | Baud Rate Modulo Divisor — These 13 bits in SBR[12:0] are referred to collectively as BR, and they set the modulo divide rate for the SCI baud rate generator. When BR = 0, the SCI baud rate generator is disabled to reduce supply current. When BR = 1 to 8191, the SCI baud rate = BUSCLK/(16×BR). See also BR bits in Table 14-1. |

14.2.2 SCI Control Register 1 (SCIC1)

This read/write register is used to control various optional features of the SCI system.

| | 7 | 6 | 5 | 4 | 3 | 2 | 1 | 0 |
|--------|-------|---------|------|---|------|-----|----|----|
| R W | LOOPS | SCISWAI | RSRC | М | WAKE | ILT | PE | PT |
| Reset | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |

Figure 14-6. SCI Control Register 1 (SCIC1)

Table 14-3. SCIC1 Field Descriptions

| Field | Description |
|--------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 7 LOOPS | Loop Mode Select — Selects between loop back modes and normal 2-pin full-duplex modes. When LOOPS = 1, the transmitter output is internally connected to the receiver input. 0 Normal operation — RxD and TxD use separate pins. 1 Loop mode or single-wire mode where transmitter outputs are internally connected to receiver input. (See RSRC bit.) RxD pin is not used by SCI. |
| 6 SCISWAI | SCI Stops in Wait Mode 0 SCI clocks continue to run in wait mode so the SCI can be the source of an interrupt that wakes up the CPU. 1 SCI clocks freeze while CPU is in wait mode. |
| 5 RSRC | Receiver Source Select — This bit has no meaning or effect unless the LOOPS bit is set to 1. When LOOPS = 1, the receiver input is internally connected to the TxD pin and RSRC determines whether this connection is also connected to the transmitter output. Provided LOOPS = 1, RSRC = 0 selects internal loop back mode and the SCI does not use the RxD pins. Single-wire SCI mode where the TxD pin is connected to the transmitter output. |
| 4 M | 9-Bit or 8-Bit Mode Select 0 Normal — start + 8 data bits (LSB first) + stop. 1 Receiver and transmitter use 9-bit data characters start + 8 data bits (LSB first) + 9th data bit + stop. |



Chapter 15 Serial Peripheral Interface (S08SPIV3)



Figure 15-3. SPI Module Block Diagram

15.1.3 SPI Baud Rate Generation

As shown in Figure 15-4, the clock source for the SPI baud rate generator is the bus clock. The three prescale bits (SPPR2:SPPR1:SPPR0) choose a prescale divisor of 1, 2, 3, 4, 5, 6, 7, or 8. The three rate select bits (SPR2:SPR1:SPR0) divide the output of the prescaler stage by 2, 4, 8, 16, 32, 64, 128, or 256 to get the internal SPI master mode bit-rate clock.



Chapter 16 Timer Pulse-Width Modulator (S08TPMV3)

16.1 Introduction

The TPM uses one input/output (I/O) pin per channel, TPMxCHn where x is the TPM number (for example, 1 or 2) and n is the channel number (for example, 0–1). The TPM shares its I/O pins with general-purpose I/O port pins (refer to the Pins and Connections chapter for more information).

All MC9S08SG32 Series MCUs have two TPM modules.

Figure 16-1 shows the MC9S08SG32 Series block diagram with the TPM modules highlighted.

16.1.1 TPM Configuration Information

The external clock for the MTIM module, TCLK, is selected by setting CLKS = 1:1 or 1:0 in MTIMCLK, which selects the TCLK pin input. The TCLK input can be enabled as external clock inputs to both the MTIM and TPM modules simultaneously.

16.1.2 TPM Pin Repositioning

The TPM modules pins, TPM1CHx and TPM2CHx can be repositioned under software control using TxCHnPS bits in SOPT2 as shown in Table 16-1.

| TxCHxPS in SOPT2 | Port Pin for TPM2CH1 | Port Pin for TPM2CH0 | Port Pin for TPM1CH1 | Port Pin for TPM1CH0 |
|------------------|----------------------|----------------------|----------------------|----------------------|
| 0 (default) | PTB4 | PTA1 | PTB5 | PTA0 |
| 1 | PTA7 | PTA6 | PTC1 | PTC0 |

Table 16-1. TPM Position Options



Chapter 17 Development Support

17.1 Introduction

Development support systems in the HCS08 include the background debug controller (BDC) and the on-chip debug module (DBG). The BDC provides a single-wire debug interface to the target MCU that provides a convenient interface for programming the on-chip FLASH and other nonvolatile memories. The BDC is also the primary debug interface for development and allows non-intrusive access to memory data and traditional debug features such as CPU register modify, breakpoints, and single instruction trace commands.

In the HCS08 Family, address and data bus signals are not available on external pins (not even in test modes). Debug is done through commands fed into the target MCU via the single-wire background debug interface. The debug module provides a means to selectively trigger and capture bus information so an external development system can reconstruct what happened inside the MCU on a cycle-by-cycle basis without having external access to the address and data signals.

17.1.1 Forcing Active Background

The method for forcing active background mode depends on the specific HCS08 derivative. For the MC9S08SG32 Series, you can force active background after a power-on reset by holding the BKGD pin low as the device exits the reset condition. You can also force active background by driving BKGD low immediately after a serial background command that writes a one to the BDFR bit in the SBDFR register. Other causes of reset including an external pin reset or an internally generated error reset ignore the state of the BKGD pin and reset into normal user mode. If no debug pod is connected to the BKGD pin, the MCU will always reset into normal operating mode.



17.3 On-Chip Debug System (DBG)

Because HCS08 devices do not have external address and data buses, the most important functions of an in-circuit emulator have been built onto the chip with the MCU. The debug system consists of an 8-stage FIFO that can store address or data bus information, and a flexible trigger system to decide when to capture bus information and what information to capture. The system relies on the single-wire background debug system to access debug control registers and to read results out of the eight stage FIFO.

The debug module includes control and status registers that are accessible in the user's memory map. These registers are located in the high register space to avoid using valuable direct page memory space.

Most of the debug module's functions are used during development, and user programs rarely access any of the control and status registers for the debug module. The one exception is that the debug system can provide the means to implement a form of ROM patching. This topic is discussed in greater detail in Section 17.3.6, "Hardware Breakpoints."

17.3.1 Comparators A and B

Two 16-bit comparators (A and B) can optionally be qualified with the R/W signal and an opcode tracking circuit. Separate control bits allow you to ignore R/W for each comparator. The opcode tracking circuitry optionally allows you to specify that a trigger will occur only if the opcode at the specified address is actually executed as opposed to only being read from memory into the instruction queue. The comparators are also capable of magnitude comparisons to support the inside range and outside range trigger modes. Comparators are disabled temporarily during all BDC accesses.

The A comparator is always associated with the 16-bit CPU address. The B comparator compares to the CPU address or the 8-bit CPU data bus, depending on the trigger mode selected. Because the CPU data bus is separated into a read data bus and a write data bus, the RWAEN and RWA control bits have an additional purpose, in full address plus data comparisons they are used to decide which of these buses to use in the comparator B data bus comparisons. If RWAEN = 1 (enabled) and RWA = 0 (write), the CPU's write data bus is used. Otherwise, the CPU's read data bus is used.

The currently selected trigger mode determines what the debugger logic does when a comparator detects a qualified match condition. A match can cause:

- Generation of a breakpoint to the CPU
- Storage of data bus values into the FIFO
- Starting to store change-of-flow addresses into the FIFO (begin type trace)
- Stopping the storage of change-of-flow addresses into the FIFO (end type trace)

17.3.2 Bus Capture Information and FIFO Operation

The usual way to use the FIFO is to setup the trigger mode and other control options, then arm the debugger. When the FIFO has filled or the debugger has stopped storing data into the FIFO, you would read the information out of it in the order it was stored into the FIFO. Status bits indicate the number of words of valid information that are in the FIFO as data is stored into it. If a trace run is manually halted by writing 0 to ARM before the FIFO is full (CNT = 1:0:0:0), the information is shifted by one position and