## E · K Hat lice Semiconductor Corporation - LCMX02-1200HC-6TG144I Datasheet



Welcome to E-XFL.COM

#### Understanding <u>Embedded - FPGAs (Field</u> <u>Programmable Gate Array)</u>

Embedded - FPGAs, or Field Programmable Gate Arrays, are advanced integrated circuits that offer unparalleled flexibility and performance for digital systems. Unlike traditional fixed-function logic devices, FPGAs can be programmed and reprogrammed to execute a wide array of logical operations, enabling customized functionality tailored to specific applications. This reprogrammability allows developers to iterate designs quickly and implement complex functions without the need for custom hardware.

#### **Applications of Embedded - FPGAs**

The versatility of Embedded - FPGAs makes them indispensable in numerous fields. In telecommunications.

#### Details

Product Status	Active
Number of LABs/CLBs	160
Number of Logic Elements/Cells	1280
Total RAM Bits	65536
Number of I/O	107
Number of Gates	-
Voltage - Supply	2.375V ~ 3.465V
Mounting Type	Surface Mount
Operating Temperature	-40°C ~ 100°C (TJ)
Package / Case	144-LQFP
Supplier Device Package	144-TQFP (20x20)
Purchase URL	https://www.e-xfl.com/product-detail/lattice-semiconductor/lcmxo2-1200hc-6tg144i

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong



## MachXO2 Family Data Sheet Architecture

#### March 2016

Data Sheet DS1035

### **Architecture Overview**

The MachXO2 family architecture contains an array of logic blocks surrounded by Programmable I/O (PIO). The larger logic density devices in this family have sysCLOCK<sup>™</sup> PLLs and blocks of sysMEM Embedded Block RAM (EBRs). Figure 2-1 and Figure 2-2 show the block diagrams of the various family members.





Note: MachXO2-256, and MachXO2-640/U are similar to MachXO2-1200. MachXO2-256 has a lower LUT count and no PLL or EBR blocks. MachXO2-640 has no PLL, a lower LUT count and two EBR blocks. MachXO2-640U has a lower LUT count, one PLL and seven EBR blocks.

Figure 2-2. Top View of the MachXO2-4000 Device



Note: MachXO2-1200U, MachXO2-2000/U and MachXO2-7000 are similar to MachXO2-4000. MachXO2-1200U and MachXO2-2000 have a lower LUT count, one PLL, and eight EBR blocks. MachXO2-2000U has a lower LUT count, two PLLs, and 10 EBR blocks. MachXO2-7000 has a higher LUT count, two PLLs, and 26 EBR blocks.

© 2016 Lattice Semiconductor Corp. All Lattice trademarks, registered trademarks, patents, and disclaimers are as listed at www.latticesemi.com/legal. All other brand or product names are trademarks or registered trademarks of their respective holders. The specifications and information herein are subject to change without notice.



#### Modes of Operation

Each slice has up to four potential modes of operation: Logic, Ripple, RAM and ROM.

#### Logic Mode

In this mode, the LUTs in each slice are configured as 4-input combinatorial lookup tables. A LUT4 can have 16 possible input combinations. Any four input logic functions can be generated by programming this lookup table. Since there are two LUT4s per slice, a LUT5 can be constructed within one slice. Larger look-up tables such as LUT6, LUT7 and LUT8 can be constructed by concatenating other slices. Note LUT8 requires more than four slices.

#### **Ripple Mode**

Ripple mode supports the efficient implementation of small arithmetic functions. In Ripple mode, the following functions can be implemented by each slice:

- Addition 2-bit
- Subtraction 2-bit
- Add/subtract 2-bit using dynamic control
- Up counter 2-bit
- Down counter 2-bit
- Up/down counter with asynchronous clear
- Up/down counter with preload (sync)
- Ripple mode multiplier building block
- Multiplier support
- Comparator functions of A and B inputs
  - A greater-than-or-equal-to B
  - A not-equal-to B
  - A less-than-or-equal-to B

Ripple mode includes an optional configuration that performs arithmetic using fast carry chain methods. In this configuration (also referred to as CCU2 mode) two additional signals, Carry Generate and Carry Propagate, are generated on a per-slice basis to allow fast arithmetic functions to be constructed by concatenating slices.

#### **RAM Mode**

In this mode, a 16x4-bit distributed single port RAM (SPR) can be constructed by using each LUT block in Slice 0 and Slice 1 as a 16x1-bit memory. Slice 2 is used to provide memory address and control signals.

MachXO2 devices support distributed memory initialization.

The Lattice design tools support the creation of a variety of different size memories. Where appropriate, the software will construct these using distributed memory primitives that represent the capabilities of the PFU. Table 2-3 shows the number of slices required to implement different distributed RAM primitives. For more information about using RAM in MachXO2 devices, please see TN1201, Memory Usage Guide for MachXO2 Devices.

#### Table 2-3. Number of Slices Required For Implementing Distributed RAM

	SPR 16x4	PDPR 16x4			
Number of slices	3	3			
Note: SPB = Single Port BAM_PDPB = Pseudo Dual Port BAM					

ote: SPR = Single Port RAM, PDPR = Pseudo Dual



This phase shift can be either programmed during configuration or can be adjusted dynamically. In dynamic mode, the PLL may lose lock after a phase adjustment on the output used as the feedback source and not relock until the  $t_{I,OCK}$  parameter has been satisfied.

The MachXO2 also has a feature that allows the user to select between two different reference clock sources dynamically. This feature is implemented using the PLLREFCS primitive. The timing parameters for the PLL are shown in the sysCLOCK PLL Timing table.

The MachXO2 PLL contains a WISHBONE port feature that allows the PLL settings, including divider values, to be dynamically changed from the user logic. When using this feature the EFB block must also be instantiated in the design to allow access to the WISHBONE ports. Similar to the dynamic phase adjustment, when PLL settings are updated through the WISHBONE port the PLL may lose lock and not relock until the t<sub>LOCK</sub> parameter has been satisfied. The timing parameters for the PLL are shown in the sysCLOCK PLL Timing table.

For more details on the PLL and the WISHBONE interface, see TN1199, MachXO2 sysCLOCK PLL Design and Usage Guide.



#### Figure 2-7. PLL Diagram

Table 2-4 provides signal descriptions of the PLL block.

Port Name	I/O	Description
CLKI	I	Input clock to PLL
CLKFB	I	Feedback clock
PHASESEL[1:0]	I	Select which output is affected by Dynamic Phase adjustment ports
PHASEDIR	I	Dynamic Phase adjustment direction
PHASESTEP	I	Dynamic Phase step – toggle shifts VCO phase adjust by one step.



## Programmable I/O Cells (PIC)

The programmable logic associated with an I/O is called a PIO. The individual PIO are connected to their respective sysIO buffers and pads. On the MachXO2 devices, the PIO cells are assembled into groups of four PIO cells called a Programmable I/O Cell or PIC. The PICs are placed on all four sides of the device.

On all the MachXO2 devices, two adjacent PIOs can be combined to provide a complementary output driver pair.

The MachXO2-640U, MachXO2-1200/U and higher density devices contain enhanced I/O capability. All PIO pairs on these larger devices can implement differential receivers. Half of the PIO pairs on the top edge of these devices can be configured as true LVDS transmit pairs. The PIO pairs on the bottom edge of these higher density devices have on-chip differential termination and also provide PCI support.



#### **Output Register Block**

The output register block registers signals from the core of the device before they are passed to the sysIO buffers.

#### Left, Top, Bottom Edges

In SDR mode, D0 feeds one of the flip-flops that then feeds the output. The flip-flop can be configured as a D-type register or latch.

In DDR generic mode, D0 and D1 inputs are fed into registers on the positive edge of the clock. At the next falling edge the registered D1 input is registered into the register Q1. A multiplexer running off the same clock is used to switch the mux between the outputs of registers Q0 and Q1 that will then feed the output.

Figure 2-14 shows the output register block on the left, top and bottom edges.

Figure 2-14. MachXO2 Output Register Block Diagram (PIO on the Left, Top and Bottom Edges)



#### **Right Edge**

The output register block on the right edge is a superset of the output register on left, top and bottom edges of the device. In addition to supporting SDR and Generic DDR modes, the output register blocks for PIOs on the right edge include additional logic to support DDR-memory interfaces. Operation of this block is similar to that of the output register block on other edges.

In DDR memory mode, D0 and D1 inputs are fed into registers on the positive edge of the clock. At the next falling edge the registered D1 input is registered into the register Q1. A multiplexer running off the DQSW90 signal is used to switch the mux between the outputs of registers Q0 and Q1 that will then feed the output.

Figure 2-15 shows the output register block on the right edge.



## **DDR Memory Support**

Certain PICs on the right edge of MachXO2-640U, MachXO2-1200/U and larger devices, have additional circuitry to allow the implementation of DDR memory interfaces. There are two groups of 14 or 12 PIOs each on the right edge with additional circuitry to implement DDR memory interfaces. This capability allows the implementation of up to 16-bit wide memory interfaces. One PIO from each group contains a control element, the DQS Read/Write Block, to facilitate the generation of clock and control signals (DQSR90, DQSW90, DDRCLKPOL and DATAVALID). These clock and control signals are distributed to the other PIO in the group through dedicated low skew routing.

## **DQS Read Write Block**

Source synchronous interfaces generally require the input clock to be adjusted in order to correctly capture data at the input register. For most interfaces a PLL is used for this adjustment. However, in DDR memories the clock (referred to as DQS) is not free-running so this approach cannot be used. The DQS Read Write block provides the required clock alignment for DDR memory interfaces. DQSR90 and DQSW90 signals are generated by the DQS Read Write block from the DQS input.

In a typical DDR memory interface design, the phase relationship between the incoming delayed DQS strobe and the internal system clock (during the read cycle) is unknown. The MachXO2 family contains dedicated circuits to transfer data between these domains. To prevent set-up and hold violations, at the domain transfer between DQS (delayed) and the system clock, a clock polarity selector is used. This circuit changes the edge on which the data is registered in the synchronizing registers in the input register block. This requires evaluation at the start of each read cycle for the correct clock polarity. Prior to the read operation in DDR memories, DQS is in tri-state (pulled by termination). The DDR memory device drives DQS low at the start of the preamble state. A dedicated circuit in the DQS Read Write block detects the first DQS rising edge after the preamble state and generates the DDRCLKPOL signal. This signal is used to control the polarity of the clock to the synchronizing registers.

The temperature, voltage and process variations of the DQS delay block are compensated by a set of calibration signals (6-bit bus) from a DLL on the right edge of the device. The DLL loop is compensated for temperature, voltage and process variations by the system clock and feedback loop.

## sysIO Buffer

Each I/O is associated with a flexible buffer referred to as a sysIO buffer. These buffers are arranged around the periphery of the device in groups referred to as banks. The sysIO buffers allow users to implement a wide variety of standards that are found in today's systems including LVCMOS, TTL, PCI, SSTL, HSTL, LVDS, BLVDS, MLVDS and LVPECL.

Each bank is capable of supporting multiple I/O standards. In the MachXO2 devices, single-ended output buffers, ratioed input buffers (LVTTL, LVCMOS and PCI), differential (LVDS) and referenced input buffers (SSTL and HSTL) are powered using I/O supply voltage ( $V_{CCIO}$ ). Each sysIO bank has its own  $V_{CCIO}$ . In addition, each bank has a voltage reference,  $V_{REF}$  which allows the use of referenced input buffers independent of the bank  $V_{CCIO}$ .

MachXO2-256 and MachXO2-640 devices contain single-ended ratioed input buffers and single-ended output buffers with complementary outputs on all the I/O banks. Note that the single-ended input buffers on these devices do not contain PCI clamps. In addition to the single-ended I/O buffers these two devices also have differential and referenced input buffers on all I/Os. The I/Os are arranged in pairs, the two pads in the pair are described as "T" and "C", where the true pad is associated with the positive side of the differential input buffer and the comp (complementary) pad is associated with the negative side of the differential input buffer.



#### Table 2-13. Supported Output Standards

Output Standard	V <sub>CCIO</sub> (Typ.)				
Single-Ended Interfaces					
LVTTL	3.3				
LVCMOS33	3.3				
LVCMOS25	2.5				
LVCMOS18	1.8				
LVCMOS15	1.5				
LVCMOS12	1.2				
LVCMOS33, Open Drain	—				
LVCMOS25, Open Drain	—				
LVCMOS18, Open Drain	—				
LVCMOS15, Open Drain	—				
LVCMOS12, Open Drain	—				
PCI33	3.3				
SSTL25 (Class I)	2.5				
SSTL18 (Class I)	1.8				
HSTL18(Class I)	1.8				
Differential Interfaces					
LVDS <sup>1, 2</sup>	2.5, 3.3				
BLVDS, MLVDS, RSDS <sup>2</sup>	2.5				
LVPECL <sup>2</sup>	3.3				
MIPI <sup>2</sup>	2.5				
Differential SSTL18	1.8				
Differential SSTL25	2.5				
Differential HSTL18	1.8				

1. MachXO2-640U, MachXO2-1200/U and larger devices have dedicated LVDS buffers. 2. These interfaces can be emulated with external resistors in all devices.

#### sysIO Buffer Banks

The numbers of banks vary between the devices of this family. MachXO2-1200U, MachXO2-2000/U and higher density devices have six I/O banks (one bank on the top, right and bottom side and three banks on the left side). The MachXO2-1200 and lower density devices have four banks (one bank per side). Figures 2-18 and 2-19 show the sysIO banks and their associated supplies for all devices.



## Hot Socketing

The MachXO2 devices have been carefully designed to ensure predictable behavior during power-up and powerdown. Leakage into I/O pins is controlled to within specified limits. This allows for easy integration with the rest of the system. These capabilities make the MachXO2 ideal for many multiple power supply and hot-swap applications.

## **On-chip Oscillator**

Every MachXO2 device has an internal CMOS oscillator. The oscillator output can be routed as a clock to the clock tree or as a reference clock to the sysCLOCK PLL using general routing resources. The oscillator frequency can be divided by internal logic. There is a dedicated programming bit and a user input to enable/disable the oscillator. The oscillator frequency ranges from 2.08 MHz to 133 MHz. The software default value of the Master Clock (MCLK) is nominally 2.08 MHz. When a different MCLK is selected during the design process, the following sequence takes place:

- 1. Device powers up with a nominal MCLK frequency of 2.08 MHz.
- 2. During configuration, users select a different master clock frequency.
- 3. The MCLK frequency changes to the selected frequency once the clock configuration bits are received.
- 4. If the user does not select a master clock frequency, then the configuration bitstream defaults to the MCLK frequency of 2.08 MHz.

Table 2-14 lists all the available MCLK frequencies.

Table 2-14. Available MCLK Frequencies

MCLK (MHz, Nominal)	MCLK (MHz, Nominal)	MCLK (MHz, Nominal)
2.08 (default)	9.17	33.25
2.46	10.23	38
3.17	13.3	44.33
4.29	14.78	53.2
5.54	20.46	66.5
7	26.6	88.67
8.31	29.56	133

## Embedded Hardened IP Functions and User Flash Memory

All MachXO2 devices provide embedded hardened functions such as SPI, I<sup>2</sup>C and Timer/Counter. MachXO2-640/U and higher density devices also provide User Flash Memory (UFM). These embedded blocks interface through the WISHBONE interface with routing as shown in Figure 2-20.



There are some limitations on the use of the hardened user SPI. These are defined in the following technical notes:

- TN1087, Minimizing System Interruption During Configuration Using TransFR Technology (Appendix B)
- TN1205, Using User Flash Memory and Hardened Control Functions in MachXO2 Devices

#### Figure 2-22. SPI Core Block Diagram



Table 2-16 describes the signals interfacing with the SPI cores.

Table 2-16. SPI Core Signal Description

Signal Name	I/O	Master/Slave	Description	
spi_csn[0]	0	Master	SPI master chip-select output	
spi_csn[17]	0	Master	Additional SPI chip-select outputs (total up to eight slaves)	
spi_scsn	I	Slave	SPI slave chip-select input	
spi_irq	0	Master/Slave	Interrupt request	
spi_clk	I/O	Master/Slave	SPI clock. Output in master mode. Input in slave mode.	
spi_miso	I/O	Master/Slave	SPI data. Input in master mode. Output in slave mode.	
spi_mosi	I/O	Master/Slave	SPI data. Output in master mode. Input in slave mode.	
ufm_sn	I	Slave	Configuration Slave Chip Select (active low), dedicated for selecting the User Flash Memory (UFM).	
cfg_stdby	0	Master/Slave	Stand-by signal – To be connected only to the power module of the MachXO2 device. The signal is enabled only if the "Wakeup Enable" feature has been set within the EFB GUI, SPI Tab.	
cfg_wake	0	Master/Slave	Wake-up signal – To be connected only to the power module of the MachXO2 device. The signal is enabled only if the "Wakeup Enable" feature has been set within the EFB GUI, SPI Tab.	



## **Configuration and Testing**

This section describes the configuration and testing features of the MachXO2 family.

#### IEEE 1149.1-Compliant Boundary Scan Testability

All MachXO2 devices have boundary scan cells that are accessed through an IEEE 1149.1 compliant test access port (TAP). This allows functional testing of the circuit board, on which the device is mounted, through a serial scan path that can access all critical logic nodes. Internal registers are linked internally, allowing test data to be shifted in and loaded directly onto test nodes, or test data to be captured and shifted out for verification. The test access port consists of dedicated I/Os: TDI, TDO, TCK and TMS. The test access port shares its power supply with V<sub>CCIO</sub> Bank 0 and can operate with LVCMOS3.3, 2.5, 1.8, 1.5, and 1.2 standards.

For more details on boundary scan test, see AN8066, Boundary Scan Testability with Lattice sysIO Capability and TN1087, Minimizing System Interruption During Configuration Using TransFR Technology.

#### **Device Configuration**

All MachXO2 devices contain two ports that can be used for device configuration. The Test Access Port (TAP), which supports bit-wide configuration and the sysCONFIG port which supports serial configuration through I<sup>2</sup>C or SPI. The TAP supports both the IEEE Standard 1149.1 Boundary Scan specification and the IEEE Standard 1532 In-System Configuration specification. There are various ways to configure a MachXO2 device:

- 1. Internal Flash Download
- 2. JTAG
- 3. Standard Serial Peripheral Interface (Master SPI mode) interface to boot PROM memory
- 4. System microprocessor to drive a serial slave SPI port (SSPI mode)
- 5. Standard I<sup>2</sup>C Interface to system microprocessor

Upon power-up, the configuration SRAM is ready to be configured using the selected sysCONFIG port. Once a configuration port is selected, it will remain active throughout that configuration cycle. The IEEE 1149.1 port can be activated any time after power-up by sending the appropriate command through the TAP port. Optionally the device can run a CRC check upon entering the user mode. This will ensure that the device was configured correctly.

The sysCONFIG port has 10 dual-function pins which can be used as general purpose I/Os if they are not required for configuration. See TN1204, MachXO2 Programming and Configuration Usage Guide for more information about using the dual-use pins as general purpose I/Os.

Lattice design software uses proprietary compression technology to compress bit-streams for use in MachXO2 devices. Use of this technology allows Lattice to provide a lower cost solution. In the unlikely event that this technology is unable to compress bitstreams to fit into the amount of on-chip Flash memory, there are a variety of techniques that can be utilized to allow the bitstream to fit in the on-chip Flash memory. For more details, refer to TN1204, MachXO2 Programming and Configuration Usage Guide.

The Test Access Port (TAP) has five dual purpose pins (TDI, TDO, TMS, TCK and JTAGENB). These pins are dual function pins - TDI, TDO, TMS and TCK can be used as general purpose I/O if desired. For more details, refer to TN1204, MachXO2 Programming and Configuration Usage Guide.

#### TransFR (Transparent Field Reconfiguration)

TransFR is a unique Lattice technology that allows users to update their logic in the field without interrupting system operation using a simple push-button solution. For more details refer to TN1087, Minimizing System Interruption During Configuration Using TransFR Technology for details.



# MachXO2 Family Data Sheet DC and Switching Characteristics

#### March 2017

#### Data Sheet DS1035

## Absolute Maximum Ratings<sup>1, 2, 3</sup>

	MachXO2 ZE/HE (1.2 V)	MachXO2 HC (2.5 V / 3.3 V)
Supply Voltage V <sub>CC</sub>	–0.5 V to 1.32 V	0.5 V to 3.75 V
Output Supply Voltage V <sub>CCIO</sub>	–0.5 V to 3.75 V	0.5 V to 3.75 V
I/O Tri-state Voltage Applied <sup>4, 5</sup>	–0.5 V to 3.75 V	0.5 V to 3.75 V
Dedicated Input Voltage Applied <sup>4</sup>	–0.5 V to 3.75 V	0.5 V to 3.75 V
Storage Temperature (Ambient)	–55 °C to 125 °C	–55 °C to 125 °C
Junction Temperature $(T_1)$	–40 °C to 125 °C	–40 °C to 125 °C

1. Stress above those listed under the "Absolute Maximum Ratings" may cause permanent damage to the device. Functional operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied.

2. Compliance with the Lattice Thermal Management document is required.

3. All voltages referenced to GND.

4. Overshoot and undershoot of -2 V to (V<sub>IHMAX</sub> + 2) volts is permitted for a duration of <20 ns.

5. The dual function  $I^2C$  pins SCL and SDA are limited to -0.25 V to 3.75 V or to -0.3 V with a duration of <20 ns.

## **Recommended Operating Conditions**<sup>1</sup>

Symbol	Parameter		Max.	Units
V = = <sup>1</sup>	Core Supply Voltage for 1.2 V Devices	1.14	1.26	V
VCC	Core Supply Voltage for 2.5 V / 3.3 V Devices	2.375	3.6	V
V <sub>CCIO</sub> <sup>1, 2, 3</sup>	I/O Driver Supply Voltage	1.14	3.6	V
t <sub>JCOM</sub>	Junction Temperature Commercial Operation	0	85	°C
t <sub>JIND</sub>	Junction Temperature Industrial Operation	-40	100	°C

1. Like power supplies must be tied together. For example, if  $V_{CCIO}$  and  $V_{CC}$  are both the same voltage, they must also be the same supply.

2. See recommended voltages by I/O standard in subsequent table.

3. V<sub>CCIO</sub> pins of unused I/O banks should be connected to the V<sub>CC</sub> power supply on boards.

## Power Supply Ramp Rates<sup>1</sup>

Symbol	Parameter	Min.	Тур.	Max.	Units
t <sub>RAMP</sub>	Power supply ramp rates for all power supplies.	0.01		100	V/ms

1. Assumes monotonic ramp rates.

<sup>© 2017</sup> Lattice Semiconductor Corp. All Lattice trademarks, registered trademarks, patents, and disclaimers are as listed at www.latticesemi.com/legal. All other brand or product names are trademarks or registered trademarks of their respective holders. The specifications and information herein are subject to change without notice.



## **DC Electrical Characteristics**

Symbol	Parameter	Condition	Min.	Тур.	Max.	Units
	Input or I/O Leakage	Clamp OFF and $V_{CCIO} < V_{IN} < V_{IH}$ (MAX)			+175	μΑ
		Clamp OFF and $V_{IN} = V_{CCIO}$	-10	—	10	μΑ
I <sub>II</sub> , I <sub>IH</sub> <sup>1, 4</sup>		Clamp OFF and V <sub>CCIO</sub> –0.97 V < V <sub>IN</sub> < V <sub>CCIO</sub>	-175	—	—	μA
		Clamp OFF and 0 V < $V_{IN}$ < $V_{CCIO}$ –0.97 V			10	μΑ
		Clamp OFF and V <sub>IN</sub> = GND			10	μA
		Clamp ON and 0 V < V <sub>IN</sub> < V <sub>CCIO</sub>			10	μA
I <sub>PU</sub>	I/O Active Pull-up Current	0 < V <sub>IN</sub> < 0.7 V <sub>CCIO</sub>	-30		-309	μΑ
I <sub>PD</sub>	I/O Active Pull-down Current	$V_{IL}$ (MAX) < $V_{IN}$ < $V_{CCIO}$	30	_	305	μA
I <sub>BHLS</sub>	Bus Hold Low sustaining current	$V_{IN} = V_{IL} (MAX)$	30	—	—	μΑ
I <sub>BHHS</sub>	Bus Hold High sustaining current	$V_{IN} = 0.7 V_{CCIO}$	-30	_	_	μΑ
I <sub>BHLO</sub>	Bus Hold Low Overdrive current	$0 \leq V_{IN} \leq V_{CCIO}$	—	_	305	μΑ
I <sub>BHHO</sub>	Bus Hold High Overdrive current	$0 \leq V_{IN} \leq V_{CCIO}$	—	_	-309	μΑ
V <sub>BHT</sub> <sup>3</sup>	Bus Hold Trip Points		V <sub>IL</sub> (MAX)	_	V <sub>IH</sub> (MIN)	v
C1	I/O Capacitance <sup>2</sup>	$V_{CCIO} = 3.3 V, 2.5 V, 1.8 V, 1.5 V, 1.2 V, V_{CC} = Typ., V_{IO} = 0 \text{ to } V_{IH} \text{ (MAX)}$	3	5	9	pF
C2	Dedicated Input Capacitance <sup>2</sup>	$V_{CCIO} = 3.3 \text{ V}, 2.5 \text{ V}, 1.8 \text{ V}, 1.5 \text{ V}, 1.2 \text{ V}, V_{CC} = Typ., V_{IO} = 0 \text{ to } V_{IH} \text{ (MAX)}$	3	5.5	7	pF
	Hysteresis for Schmitt Trigger Inputs⁵	V <sub>CCIO</sub> = 3.3 V, Hysteresis = Large		450		mV
		V <sub>CCIO</sub> = 2.5 V, Hysteresis = Large		250		mV
		V <sub>CCIO</sub> = 1.8 V, Hysteresis = Large		125		mV
M		V <sub>CCIO</sub> = 1.5 V, Hysteresis = Large		100		mV
VHYST		V <sub>CCIO</sub> = 3.3 V, Hysteresis = Small		250		mV
		V <sub>CCIO</sub> = 2.5 V, Hysteresis = Small		150		mV
		V <sub>CCIO</sub> = 1.8 V, Hysteresis = Small		60		mV
		V <sub>CCIO</sub> = 1.5 V, Hysteresis = Small	_	40	_	mV

1. Input or I/O leakage current is measured with the pin configured as an input or as an I/O with the output driver tri-stated. It is not measured with the output driver active. Bus maintenance circuits are disabled.

2. T<sub>A</sub> 25 °C, f = 1.0 MHz.

3. Please refer to  $V_{IL}$  and  $V_{IH}$  in the sysIO Single-Ended DC Electrical Characteristics table of this document.

4. When V<sub>IH</sub> is higher than V<sub>CCIO</sub>, a transient current typically of 30 ns in duration or less with a peak current of 6 mA can occur on the high-to-low transition. For true LVDS output pins in MachXO2-640U, MachXO2-1200/U and larger devices, V<sub>IH</sub> must be less than or equal to V<sub>CCIO</sub>.

5. With bus keeper circuit turned on. For more details, refer to TN1202, MachXO2 sysIO Usage Guide.



			-6		-6 -5		-	4	
Parameter	Description	Device	Min.	Max.	Min.	Max.	Min.	Max.	Units
Generic DDF	R4 Inputs with Clock and Data	ligned at Pin Using PC	LK Pin f	or Clock	Input –	GDDRX	4_RX.E	CLK.Ali	gned <sup>9, 12</sup>
t <sub>DVA</sub>	Input Data Valid After ECLK		—	0.290	_	0.320	—	0.345	UI
t <sub>DVE</sub>	Input Data Hold After ECLK	MachXO2-640U.	0.739	—	0.699	—	0.703	—	UI
f <sub>DATA</sub>	DDRX4 Serial Input Data Speed	MachXO2-1200/U and larger devices,	_	756	_	630	—	524	Mbps
f <sub>DDRX4</sub>	DDRX4 ECLK Frequency	bottom side only.11	—	378	_	315	—	262	MHz
f <sub>SCLK</sub>	SCLK Frequency		_	95	_	79	—	66	MHz
Generic DDF	R4 Inputs with Clock and Data C	entered at Pin Using PCI	_K Pin fo	or Clock	Input –	GDDRX4	4_RX.EC	LK.Cen	tered <sup>9, 12</sup>
t <sub>SU</sub>	Input Data Setup Before ECLK		0.233	—	0.219	—	0.198		ns
t <sub>HO</sub>	Input Data Hold After ECLK	MachXO2-640U,	0.287	—	0.287	—	0.344	—	ns
f <sub>DATA</sub>	DDRX4 Serial Input Data Speed	MachXO2-1200/U and larger devices,		756		630	—	524	Mbps
f <sub>DDRX4</sub>	DDRX4 ECLK Frequency	bottom side only.11	_	378	_	315	—	262	MHz
f <sub>SCLK</sub>	SCLK Frequency		_	95	_	79	—	66	MHz
7:1 LVDS In	puts (GDDR71_RX.ECLK.7:1) <sup>9,</sup>	12							
t <sub>DVA</sub>	Input Data Valid After ECLK			0.290		0.320	—	0.345	UI
t <sub>DVE</sub>	Input Data Hold After ECLK	-	0.739	—	0.699	—	0.703	—	UI
f <sub>DATA</sub>	DDR71 Serial Input Data Speed	MachXO2-640U, MachXO2-1200/U and		756		630		524	Mbps
f <sub>DDR71</sub>	DDR71 ECLK Frequency	larger devices, bottom	_	378		315	—	262	MHz
f <sub>CLKIN</sub>	7:1 Input Clock Frequency (SCLK) (minimum limited by PLL)	Side Only.	-	108	_	90	_	75	MHz
Generic DDF	R Outputs with Clock and Data	Aligned at Pin Using PC	LK Pin f	for Cloci	c Input –	GDDR	(1_TX.S	CLK.Ali	gned <sup>9, 12</sup>
t <sub>DIA</sub>	Output Data Invalid After CLK Output		_	0.520	_	0.550	_	0.580	ns
t <sub>DIB</sub>	Output Data Invalid Before CLK Output	All MachXO2 devices, all sides.	_	0.520	_	0.550	_	0.580	ns
f <sub>DATA</sub>	DDRX1 Output Data Speed		_	300	_	250		208	Mbps
f <sub>DDBX1</sub>	DDRX1 SCLK frequency			150	_	125		104	MHz
Generic DDF	Outputs with Clock and Data C	entered at Pin Using PC	LK Pin f	or Clock	Input –	GDDRX	1_TX.SC	LK.Cen	tered <sup>9, 12</sup>
t <sub>DVB</sub>	Output Data Valid Before CLK Output		1.210	_	1.510	_	1.870	_	ns
t <sub>DVA</sub>	Output Data Valid After CLK Output	All MachXO2 devices,	1.210	_	1.510	_	1.870	_	ns
f <sub>DATA</sub>	DDRX1 Output Data Speed	all sides.	_	300	_	250	_	208	Mbps
f <sub>DDRX1</sub>	DDRX1 SCLK Frequency (minimum limited by PLL)		_	150	_	125	_	104	MHz
Generic DDF	X2 Outputs with Clock and Data	Aligned at Pin Using P	CLK Pin	for Cloc	k Input	- GDDR	X2_TX.E	CLK.Ali	gned <sup>9, 12</sup>
t <sub>DIA</sub>	Output Data Invalid After CLK Output		_	0.200	_	0.215	_	0.230	ns
t <sub>DIB</sub>	Output Data Invalid Before CLK Output	MachXO2-640U, MachXO2-1200/LL and		0.200		0.215		0.230	ns
f <sub>DATA</sub>	DDRX2 Serial Output Data Speed	larger devices, top side only.	_	664	_	554	_	462	Mbps
f <sub>DDRX2</sub>	DDRX2 ECLK frequency	1	—	332	_	277	—	231	MHz
f <sub>SCLK</sub>	SCLK Frequency	1	—	166	—	139	—	116	MHz



			-3		-2		1		
Parameter	Description	Device	Min.	Max.	Min.	Max.	Min.	Max.	Units
		MachXO2-1200ZE	0.66	—	0.68		0.80		ns
+	Clock to Data Hold – PIO Input	MachXO2-2000ZE	0.68	—	0.70		0.83		ns
<sup>I</sup> HPLL	Register	MachXO2-4000ZE	0.68	—	0.71		0.84		ns
		MachXO2-7000ZE	0.73	—	0.74	—	0.87	—	ns
		MachXO2-1200ZE	5.14	—	5.69	—	6.20	—	ns
	Clock to Data Setup – PIO	MachXO2-2000ZE	5.11	—	5.67	—	6.17	—	ns
<sup>I</sup> SU_DELPLL	Delav	MachXO2-4000ZE	5.27	—	5.84		6.35	—	ns
		MachXO2-7000ZE	5.15	—	5.71	—	6.23	—	ns
		MachXO2-1200ZE	-1.36	—	-1.36	—	-1.36	—	ns
	Clock to Data Hold – PIO Input	MachXO2-2000ZE	-1.35	—	-1.35		-1.35	—	ns
<sup>I</sup> H_DELPLL	Register with Input Data Delay	MachXO2-4000ZE	-1.43	—	-1.43	—	-1.43	—	ns
		MachXO2-7000ZE	-1.41	—	-1.41	—	-1.41	—	ns
Generic DDR	X1 Inputs with Clock and Data A	ligned at Pin Using PO	LK Pin	for Cloc	k Input -	GDDR	(1_RX.S	CLK.Ali	gned <sup>9, 12</sup>
t <sub>DVA</sub>	Input Data Valid After CLK		_	0.382		0.401		0.417	UI
t <sub>DVE</sub>	Input Data Hold After CLK	All MachXO2	0.670	—	0.684		0.693	—	UI
f <sub>DATA</sub>	DDRX1 Input Data Speed	devices, all sides	_	140		116	—	98	Mbps
f <sub>DDRX1</sub>	DDRX1 SCLK Frequency		_	70		58	—	49	MHz
Generic DDR	Generic DDRX1 Inputs with Clock and Data Centered at Pin Using PCLK Pin for Clock Input – GDDRX1_RX.SCLK.Centered <sup>9,</sup>								tered <sup>9, 12</sup>
t <sub>SU</sub>	Input Data Setup Before CLK		1.319	—	1.412		1.462	—	ns
t <sub>HO</sub>	Input Data Hold After CLK	All MachXO2	0.717	—	1.010	—	1.340	—	ns
f <sub>DATA</sub>	DDRX1 Input Data Speed	devices, all sides	—	140	—	116	—	98	Mbps
f <sub>DDRX1</sub>	DDRX1 SCLK Frequency		—	70	—	58	—	49	MHz
Generic DDR	X2 Inputs with Clock and Data A	ligned at Pin Using PO	CLK Pin	for Cloc	k Input -	GDDR)	(2_RX.E	CLK.Ali	gned <sup>9, 12</sup>
t <sub>DVA</sub>	Input Data Valid After CLK		_	0.361		0.346	_	0.334	UI
t <sub>DVE</sub>	Input Data Hold After CLK	MachXO2-640U,	0.602	—	0.625		0.648	—	UI
f <sub>DATA</sub>	DDRX2 Serial Input Data Speed	MachXO2-1200/U and larger devices,	—	280	—	234	—	194	Mbps
f <sub>DDRX2</sub>	DDRX2 ECLK Frequency	bottom side only <sup>11</sup>		140	—	117		97	MHz
f <sub>SCLK</sub>	SCLK Frequency			70		59		49	MHz
Generic DDR	X2 Inputs with Clock and Data Ce	entered at Pin Using PC	LK Pin f	for Clock	Input –	GDDRX	2_RX.EC	LK.Cen	tered <sup>9, 12</sup>
t <sub>SU</sub>	Input Data Setup Before CLK		0.472	—	0.672		0.865		ns
t <sub>HO</sub>	Input Data Hold After CLK	MachXO2-640U,	0.363	—	0.501	—	0.743	—	ns
f <sub>DATA</sub>	DDRX2 Serial Input Data Speed	MachXO2-1200/U and larger devices,	_	280	_	234	_	194	Mbps
f <sub>DDRX2</sub>	DDRX2 ECLK Frequency	bottom side only"		140	—	117		97	MHz
f <sub>SCLK</sub>	SCLK Frequency			70		59		49	MHz
Generic DDR	4 Inputs with Clock and Data A	ligned at Pin Using PC	LK Pin	for Cloc	k Input -	GDDRX	4_RX.E	CLK.Ali	gned <sup>9, 12</sup>
t <sub>DVA</sub>	Input Data Valid After ECLK		—	0.307		0.316		0.326	UI
t <sub>DVE</sub>	Input Data Hold After ECLK	MachXO2-640U.	0.662	—	0.650		0.649		UI
f <sub>DATA</sub>	DDRX4 Serial Input Data Speed	MachXO2-1200/U and larger devices,	_	420	_	352	_	292	Mbps
f <sub>DDRX4</sub>	DDRX4 ECLK Frequency	bottom side only <sup>11</sup>	—	210	—	176	—	146	MHz
f <sub>SCLK</sub>	SCLK Frequency	1	—	53	—	44	—	37	MHz



			-3		-2		1		
Parameter	Description	Device	Min.	Max.	Min.	Max.	Min.	Max.	Units
LPDDR <sup>9, 12</sup>			1						
t <sub>DVADQ</sub>	Input Data Valid After DQS Input			0.349	_	0.381	_	0.396	UI
t <sub>DVEDQ</sub>	Input Data Hold After DQS Input		0.665	_	0.630		0.613	_	UI
t <sub>DQVBS</sub>	Output Data Invalid Before DQS Output	MachXO2-1200/U	0.25	_	0.25		0.25	_	UI
t <sub>DQVAS</sub>	Output Data Invalid After DQS Output	and larger devices, right side only. <sup>13</sup>	0.25	_	0.25	_	0.25	_	UI
f <sub>DATA</sub>	MEM LPDDR Serial Data Speed		_	120	_	110	_	96	Mbps
f <sub>SCLK</sub>	SCLK Frequency			60	—	55	_	48	MHz
f <sub>LPDDR</sub>	LPDDR Data Transfer Rate		0	120	0	110	0	96	Mbps
DDR <sup>9, 12</sup>	•	•							
t <sub>DVADQ</sub>	Input Data Valid After DQS Input			0.347	_	0.374	_	0.393	UI
t <sub>DVEDQ</sub>	Input Data Hold After DQS Input	-	0.665	_	0.637		0.616	_	UI
t <sub>DQVBS</sub>	Output Data Invalid Before DQS Output	MachXO2-1200/U	0.25	_	0.25		0.25	_	UI
t <sub>DQVAS</sub>	Output Data Invalid After DQS Output	right side only. <sup>13</sup>	0.25	_	0.25	_	0.25	_	UI
f <sub>DATA</sub>	MEM DDR Serial Data Speed			140		116		98	Mbps
f <sub>SCLK</sub>	SCLK Frequency		—	70	—	58	—	49	MHz
f <sub>MEM_DDR</sub>	MEM DDR Data Transfer Rate		N/A	140	N/A	116	N/A	98	Mbps
DDR2 <sup>9, 12</sup>		•							
t <sub>DVADQ</sub>	Input Data Valid After DQS Input		_	0.372	_	0.394	_	0.410	UI
t <sub>DVEDQ</sub>	Input Data Hold After DQS Input		0.690	_	0.658	_	0.618	_	UI
t <sub>DQVBS</sub>	Output Data Invalid Before DQS Output	MachXO2-1200/U	0.25	_	0.25	_	0.25	_	UI
t <sub>DQVAS</sub>	Output Data Invalid After DQS Output	and larger devices, right side only. <sup>13</sup>	0.25	_	0.25	_	0.25	_	UI
f <sub>DATA</sub>	MEM DDR Serial Data Speed	1	—	140	—	116	—	98	Mbps
f <sub>SCLK</sub>	SCLK Frequency	1	—	70	—	58	—	49	MHz
f <sub>MEM_DDR2</sub>	MEM DDR2 Data Transfer Rate		N/A	140	N/A	116	N/A	98	Mbps

1. Exact performance may vary with device and design implementation. Commercial timing numbers are shown at 85 °C and 1.14 V. Other operating conditions, including industrial, can be extracted from the Diamond software.

2. General I/O timing numbers based on LVCMOS 2.5, 8 mA, 0 pf load, fast slew rate.

3. Generic DDR timing numbers based on LVDS I/O (for input, output, and clock ports).

4. DDR timing numbers based on SSTL25. DDR2 timing numbers based on SSTL18. LPDDR timing numbers based in LVCMOS18.

5. 7:1 LVDS (GDDR71) uses the LVDS I/O standard (for input, output, and clock ports).

6. For Generic DDRX1 mode  $t_{SU} = t_{HO} = (t_{DVE} - t_{DVA} - 0.03 \text{ ns})/2$ .

7. The  $t_{SU_{DEL}}$  and  $t_{H_{DEL}}$  values use the SCLK\_ZERHOLD default step size. Each step is 167 ps (-3), 182 ps (-2), 195 ps (-1).

8. This number for general purpose usage. Duty cycle tolerance is +/-10%.

9. Duty cycle is +/-5% for system usage.

10. The above timing numbers are generated using the Diamond design tool. Exact performance may vary with the device selected.

11. High-speed DDR and LVDS not supported in SG32 (32-Pin QFN) packages.

12. Advance information for MachXO2 devices in 48 QFN packages.

13. DDR memory interface not supported in QN84 (84 QFN) and SG32 (32 QFN) packages.



## **Pinout Information Summary**

	MachXO2-256				MachXO2-640			MachXO2-640U	
	32 QFN <sup>1</sup>	48 QFN <sup>3</sup>	64 ucBGA	100 TQFP	132 csBGA	48 QFN <sup>3</sup>	100 TQFP	132 csBGA	144 TQFP
General Purpose I/O per Bank	•							•	
Bank 0	8	10	9	13	13	10	18	19	27
Bank 1	2	10	12	14	14	10	20	20	26
Bank 2	9	10	11	14	14	10	20	20	28
Bank 3	2	10	12	14	14	10	20	20	26
Bank 4	0	0	0	0	0	0	0	0	0
Bank 5	0	0	0	0	0	0	0	0	0
Total General Purpose Single Ended I/O	21	40	44	55	55	40	78	79	107
Differential I/O per Bank									
Bank 0	4	5	5	7	7	5	9	10	14
Bank 1	1	5	6	7	7	5	10	10	13
Bank 2	4	5	5	7	7	5	10	10	10
Bank 3	1	5	6	7	7	5	10	10	13
Bank 4	0	0	0	0	0	0	0	0	0
Bank 5	0	0	0	0	0	0	0	0	0
Total General Purpose Differential I/O	10	20	22	28	28	20	39	40	54
				_	-	-			-
Dual Function I/O	22	25	27	29	29	25	29	29	33
High-speed Differential I/O	•							•	
Bank 0	0	0	0	0	0	0	0	0	7
Gearboxes									
Number of 7:1 or 8:1 Output Gearbox Available (Bank 0)	0	0	0	0	0	0	0	0	7
Number of 7:1 or 8:1 Input Gearbox Available (Bank 2)	0	0	0	0	0	0	0	0	7
DQS Groups								•	•
Bank 1	0	0	0	0	0	0	0	0	2
VCCIO Pins									
Bank 0	2	2	2	2	2	2	2	2	3
Bank 1	1	1	2	2	2	1	2	2	3
Bank 2	2	2	2	2	2	2	2	2	3
Bank 3	1	1	2	2	2	1	2	2	3
Bank 4	0	0	0	0	0	0	0	0	0
Bank 5	0	0	0	0	0	0	0	0	0
	T	n	1		1				1
VCC	2	2	2	2	2	2	2	2	4
GND <sup>2</sup>	2	1	8	8	8	1	8	10	12
NC	0	0	1	26	58	0	3	32	8
Reserved for Configuration	1	1	1	1	1	1	1	1	1
Total Count of Bonded Pins	32	49	64	100	132	49	100	132	144

1. Lattice recommends soldering the central thermal pad onto the top PCB ground for improved thermal resistance.

2. For 48 QFN package, exposed die pad is the device ground.

3. 48-pin QFN information is 'Advanced'.



## **Ordering Information**

MachXO2 devices have top-side markings, for commercial and industrial grades, as shown below:



Notes:

- 1. Markings are abbreviated for small packages.
- 2. See PCN 05A-12 for information regarding a change to the top-side mark logo.



Part Number	LUTs	Supply Voltage	Grade	Package	Leads	Temp.
LCMXO2-7000ZE-1TG144C	6864	1.2 V	-1	Halogen-Free TQFP	144	COM
LCMXO2-7000ZE-2TG144C	6864	1.2 V	-2	Halogen-Free TQFP	144	COM
LCMXO2-7000ZE-3TG144C	6864	1.2 V	-3	Halogen-Free TQFP	144	COM
LCMXO2-7000ZE-1BG256C	6864	1.2 V	-1	Halogen-Free caBGA	256	COM
LCMXO2-7000ZE-2BG256C	6864	1.2 V	-2	Halogen-Free caBGA	256	COM
LCMXO2-7000ZE-3BG256C	6864	1.2 V	-3	Halogen-Free caBGA	256	COM
LCMXO2-7000ZE-1FTG256C	6864	1.2 V	-1	Halogen-Free ftBGA	256	COM
LCMXO2-7000ZE-2FTG256C	6864	1.2 V	-2	Halogen-Free ftBGA	256	COM
LCMXO2-7000ZE-3FTG256C	6864	1.2 V	-3	Halogen-Free ftBGA	256	COM
LCMXO2-7000ZE-1BG332C	6864	1.2 V	-1	Halogen-Free caBGA	332	COM
LCMXO2-7000ZE-2BG332C	6864	1.2 V	-2	Halogen-Free caBGA	332	COM
LCMXO2-7000ZE-3BG332C	6864	1.2 V	-3	Halogen-Free caBGA	332	COM
LCMXO2-7000ZE-1FG484C	6864	1.2 V	-1	Halogen-Free fpBGA	484	COM
LCMXO2-7000ZE-2FG484C	6864	1.2 V	-2	Halogen-Free fpBGA	484	COM
LCMXO2-7000ZE-3FG484C	6864	1.2 V	-3	Halogen-Free fpBGA	484	COM

Part Number	LUTs	Supply Voltage	Grade	Package	Leads	Temp.
LCMXO2-1200ZE-1TG100CR11	1280	1.2 V	-1	Halogen-Free TQFP	100	COM
LCMXO2-1200ZE-2TG100CR11	1280	1.2 V	-2	Halogen-Free TQFP	100	COM
LCMXO2-1200ZE-3TG100CR11	1280	1.2 V	-3	Halogen-Free TQFP	100	COM
LCMXO2-1200ZE-1MG132CR1 <sup>1</sup>	1280	1.2 V	-1	Halogen-Free csBGA	132	COM
LCMXO2-1200ZE-2MG132CR11	1280	1.2 V	-2	Halogen-Free csBGA	132	COM
LCMXO2-1200ZE-3MG132CR1 <sup>1</sup>	1280	1.2 V	-3	Halogen-Free csBGA	132	COM
LCMXO2-1200ZE-1TG144CR1 <sup>1</sup>	1280	1.2 V	-1	Halogen-Free TQFP	144	COM
LCMXO2-1200ZE-2TG144CR1 <sup>1</sup>	1280	1.2 V	-2	Halogen-Free TQFP	144	COM
LCMXO2-1200ZE-3TG144CR1 <sup>1</sup>	1280	1.2 V	-3	Halogen-Free TQFP	144	COM

1. Specifications for the "LCMXO2-1200ZE-speed package CR1" are the same as the "LCMXO2-1200ZE-speed package C" devices respectively, except as specified in the R1 Device Specifications section of this data sheet.



Part Number	LUTs	Supply Voltage	Grade	Package	Leads	Temp.
LCMXO2-7000HC-4TG144C	6864	2.5 V / 3.3 V	-4	Halogen-Free TQFP	144	COM
LCMXO2-7000HC-5TG144C	6864	2.5 V / 3.3 V	-5	Halogen-Free TQFP	144	COM
LCMXO2-7000HC-6TG144C	6864	2.5 V / 3.3 V	-6	Halogen-Free TQFP	144	COM
LCMXO2-7000HC-4BG256C	6864	2.5 V / 3.3 V	-4	Halogen-Free caBGA	256	COM
LCMXO2-7000HC-5BG256C	6864	2.5 V / 3.3 V	-5	Halogen-Free caBGA	256	COM
LCMXO2-7000HC-6BG256C	6864	2.5 V / 3.3 V	-6	Halogen-Free caBGA	256	COM
LCMXO2-7000HC-4FTG256C	6864	2.5 V / 3.3 V	-4	Halogen-Free ftBGA	256	COM
LCMXO2-7000HC-5FTG256C	6864	2.5 V / 3.3 V	-5	Halogen-Free ftBGA	256	COM
LCMXO2-7000HC-6FTG256C	6864	2.5 V / 3.3 V	-6	Halogen-Free ftBGA	256	COM
LCMXO2-7000HC-4BG332C	6864	2.5 V / 3.3 V	-4	Halogen-Free caBGA	332	COM
LCMXO2-7000HC-5BG332C	6864	2.5 V / 3.3 V	-5	Halogen-Free caBGA	332	COM
LCMXO2-7000HC-6BG332C	6864	2.5 V / 3.3 V	-6	Halogen-Free caBGA	332	COM
LCMXO2-7000HC-4FG400C	6864	2.5 V / 3.3 V	-4	Halogen-Free fpBGA	400	COM
LCMXO2-7000HC-5FG400C	6864	2.5 V / 3.3 V	-5	Halogen-Free fpBGA	400	COM
LCMXO2-7000HC-6FG400C	6864	2.5 V / 3.3 V	-6	Halogen-Free fpBGA	400	COM
LCMXO2-7000HC-4FG484C	6864	2.5 V / 3.3 V	-4	Halogen-Free fpBGA	484	COM
LCMXO2-7000HC-5FG484C	6864	2.5 V / 3.3 V	-5	Halogen-Free fpBGA	484	COM
LCMXO2-7000HC-6FG484C	6864	2.5 V / 3.3 V	-6	Halogen-Free fpBGA	484	COM

Part Number	LUTs	Supply Voltage	Grade	Package	Leads	Temp.
LCMXO2-1200HC-4TG100CR1 <sup>1</sup>	1280	2.5 V / 3.3 V	-4	Halogen-Free TQFP	100	COM
LCMXO2-1200HC-5TG100CR1 <sup>1</sup>	1280	2.5 V / 3.3 V	-5	Halogen-Free TQFP	100	COM
LCMXO2-1200HC-6TG100CR1 <sup>1</sup>	1280	2.5 V / 3.3 V	-6	Halogen-Free TQFP	100	COM
LCMXO2-1200HC-4MG132CR11	1280	2.5 V / 3.3 V	-4	Halogen-Free csBGA	132	COM
LCMXO2-1200HC-5MG132CR11	1280	2.5 V / 3.3 V	-5	Halogen-Free csBGA	132	COM
LCMXO2-1200HC-6MG132CR11	1280	2.5 V / 3.3 V	-6	Halogen-Free csBGA	132	COM
LCMXO2-1200HC-4TG144CR1 <sup>1</sup>	1280	2.5 V / 3.3 V	-4	Halogen-Free TQFP	144	COM
LCMXO2-1200HC-5TG144CR1 <sup>1</sup>	1280	2.5 V / 3.3 V	-5	Halogen-Free TQFP	144	COM
LCMXO2-1200HC-6TG144CR11	1280	2.5 V / 3.3 V	-6	Halogen-Free TQFP	144	COM

1. Specifications for the "LCMXO2-1200HC-speed package CR1" are the same as the "LCMXO2-1200HC-speed package C" devices respectively, except as specified in the R1 Device Specifications section of this data sheet.



Date	Version	Section	Change Summary					
May 2016	3.2	All	Moved designation for 84 QFN package information from 'Advanced' to 'Final'.					
		Introduction	Updated the Features section. Revised Table 1-1, MachXO2 Family Selection Guide. — Added 'Advanced' 48 QFN package. — Revised footnote 6. — Added footnote 9.					
		DC and Switching Characteristics	Updated the MachXO2 External Switching Characteristics – HC/HE Devices section. Added footnote 12.					
			Updated the MachXO2 External Switching Characteristics – ZE Devices section. Added footnote 12.					
		Pinout Information	Updated the Signal Descriptions section. Added information on GND signal.					
			Updated the Pinout Information Summary section. — Added 'Advanced' MachXO2-256 48 QFN values. — Added 'Advanced' MachXO2-640 48 QFN values. — Added footnote to GND. — Added footnotes 2 and 3.					
		Ordering Information	Updated the MachXO2 Part Number Description section. Added 'Advanced' SG48 package and revised footnote.					
			Updated the Ordering Information section. — Added part numbers for 'Advanced' QFN 48 package.					
March 2016	March 2016 3.1	Introduction	Updated the Features section. Revised Table 1-1, MachXO2 Family Selection Guide. — Added 32 QFN value for XO2-1200. — Added 84 QFN (7 mm x 7 mm, 0.5 mm) package. — Modified package name to 100-pin TQFP. — Modified package name to 144-pin TQFP. — Added footnote.					
		Architecture	Updated the Typical I/O Behavior During Power-up section. Removed reference to TN1202.					
		DC and Switching Characteristics	Updated the sysCONFIG Port Timing Specifications section. Revised t <sub>DPPDONE</sub> and t <sub>DPPINIT</sub> Max. values per PCN 03A-16, released March 2016.					
		Pinout Information	Updated the Pinout Information Summary section. — Added MachXO2-1200 32 QFN values. — Added 'Advanced' MachXO2-4000 84 QFN values.					
		Ordering Information	Updated the MachXO2 Part Number Description section. Added 'Advanced' QN84 package and footnote.					
			Updated the Ordering Information section. — Added part numbers for 1280 LUTs QFN 32 package. — Added part numbers for 4320 LUTs QFN 84 package.					
March 2015	3.0	Introduction	Updated the Features section. Revised Table 1-1, MachXO2 Family Selection Guide. — Changed 64-ball ucBGA dimension.					
		Architecture	Updated the Device Configuration section. Added JTAGENB to TAP dual purpose pins.					