



Welcome to E-XFL.COM

What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

Details

| Product Status | Obsolete |
|----------------------------|--|
| Core Processor | AVR |
| Core Size | 8-Bit |
| Speed | 8MHz |
| Connectivity | EBI/EMI, SPI, UART/USART |
| Peripherals | Brown-out Detect/Reset, POR, PWM, WDT |
| Number of I/O | 35 |
| Program Memory Size | 16KB (8K × 16) |
| Program Memory Type | FLASH |
| EEPROM Size | 512 x 8 |
| RAM Size | 1K x 8 |
| Voltage - Supply (Vcc/Vdd) | 2.7V ~ 5.5V |
| Data Converters | - |
| Oscillator Type | Internal |
| Operating Temperature | -40°C ~ 85°C |
| Mounting Type | Through Hole |
| Package / Case | 40-DIP (0.600", 15.24mm) |
| Supplier Device Package | 40-PDIP |
| Purchase URL | https://www.e-xfl.com/product-detail/microchip-technology/atmega162l-8pi |

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

Features

- High-performance, Low-power AVR[®] 8-bit Microcontroller
- Advanced RISC Architecture
 - 131 Powerful Instructions Most Single-clock Cycle Execution
 - 32 x 8 General Purpose Working Registers
 - Fully Static Operation
 - Up to 16 MIPS Throughput at 16 MHz
 - On-chip 2-cycle Multiplier
- Non-volatile Program and Data Memories
 - 16K Bytes of In-System Self-programmable Flash Endurance: 1,000 Write/Erase Cycles Endurance: 10.000 Write/Erase Cycles for ATmega162U
 - Optional Boot Code Section with Independent Lock Bits In-System Programming by On-chip Boot Program
 - True Read-While-Write Operation
 - 512 Bytes EEPROM Endurance: 100.000 Write/Erase Cycles
 - 1K Bytes Internal SRAM
 - Up to 64K Bytes Optional External Memory Space
 - Programming Lock for Software Security
- JTAG (IEEE std. 1149.1 Compliant) Interface
 - Boundary-scan Capabilities According to the JTAG Standard
 - Extensive On-chip Debug Support
 - Programming of Flash, EEPROM, Fuses, and Lock Bits through the JTAG Interface
- Peripheral Features
 - Two 8-bit Timer/Counters with Separate Prescalers and Compare Modes
 - Two 16-bit Timer/Counters with Separate Prescalers, Compare Modes, and Capture Modes
 - Real Time Counter with Separate Oscillator
 - Six PWM Channels
 - Dual Programmable Serial USARTs
 - Master/Slave SPI Serial Interface
 - Programmable Watchdog Timer with Separate On-chip Oscillator
 - On-chip Analog Comparator
- Special Microcontroller Features
 - Power-on Reset and Programmable Brown-out Detection
 - Internal Calibrated RC Oscillator
 - External and Internal Interrupt Sources
 - Five Sleep Modes: Idle, Power-save, Power-down, Standby, and Extended Standby
- I/O and Packages
 - 35 Programmable I/O Lines
 - 40-pin PDIP, 44-lead TQFP, and 44-pad MLF
- Operating Voltages
 - 1.8 3.6V for ATmega162V
 - 2.4 4.0V for ATmega162U
 - 2.7 5.5V for ATmega162L
 - 4.5 5.5V for ATmega162
- Speed Grades
 - 0 1 MHz for ATmega162V
 - 0 8 MHz for ATmega162L/U
 - 0 16 MHz for ATmega162





ATmega162 ATmega162V ATmega162U ATmega162L

Advance Information

Summary



Rev. 2513CS-AVR-09/02



Pin Configurations

Figure 1. Pinout ATmega162



Disclaimer

Typical values contained in this data sheet are based on simulations and characterization of other AVR microcontrollers manufactured on the same process technology. Min and Max values will be available after the device is characterized.

Overview

Block Diagram

The ATmega162 is a low-power CMOS 8-bit microcontroller based on the AVR enhanced RISC architecture. By executing powerful instructions in a single clock cycle, the ATmega162 achieves throughputs approaching 1 MIPS per MHz allowing the system designer to optimize power consumption versus processing speed.







The AVR core combines a rich instruction set with 32 general purpose working registers. All the 32 registers are directly connected to the Arithmetic Logic Unit (ALU), allowing two independent registers to be accessed in one single instruction executed in one clock cycle. The resulting architecture is more code efficient while achieving throughputs up to ten times faster than conventional CISC microcontrollers.

The ATmega162 provides the following features: 16K bytes of In-System Programmable Flash with Read-While-Write capabilities, 512 bytes EEPROM, 1K bytes SRAM, an external memory interface, 35 general purpose I/O lines, 32 general purpose working registers, a JTAG interface for Boundary-scan, On-chip Debugging support and programming, four flexible Timer/Counters with compare modes, internal and external interrupts, two serial programmable USARTs, a programmable Watchdog Timer with Internal Oscillator, an SPI serial port, and five software selectable power saving modes. The Idle mode stops the CPU while allowing the SRAM, Timer/Counters, SPI port, and interrupt system to continue functioning. The Power-down mode saves the register contents but freezes the Oscillator, disabling all other chip functions until the next interrupt or Hardware Reset. In Power-save mode, the Asynchronous Timer continues to run, allowing the user to maintain a timer base while the rest of the device is sleeping. In Standby mode, the crystal/resonator Oscillator is running while the rest of the device is sleeping. This allows very fast start-up combined with low-power consumption. In Extended Standby mode, both the main Oscillator and the Asynchronous Timer continue to run.

The device is manufactured using Atmel's high density non-volatile memory technology. The On-chip ISP Flash allows the program memory to be reprogrammed In-System through an SPI serial interface, by a conventional non-volatile memory programmer, or by an On-chip Boot Program running on the AVR core. The Boot Program can use any interface to download the Application Program in the Application Flash memory. Software in the Boot Flash section will continue to run while the Application Flash section is updated, providing true Read-While-Write operation. By combining an 8-bit RISC CPU with In-System Self-Programmable Flash on a monolithic chip, the Atmel ATmega162 is a powerful microcontroller that provides a highly flexible and cost effective solution to many embedded control applications.

The ATmega162 AVR is supported with a full suite of program and system development tools including: C compilers, macro assemblers, program debugger/simulators, In-Circuit Emulators, and evaluation kits.

ATmega161 and ATmega162 Compatibility

The ATmega162 is a highly complex microcontroller where the number of I/O locations supersedes the 64 I/O locations reserved in the AVR instruction set. To ensure backward compatibility with the ATmega161, all I/O locations present in ATmega161 have the same locations in ATmega162. Some additional I/O locations are added in an Extended I/O space starting from 0x60 to 0xFF, (i.e., in the ATmega162 internal RAM space). These locations can be reached by using LD/LDS/LDD and ST/STS/STD instructions only, not by using IN and OUT instructions. The relocation of the internal RAM space may still be a problem for ATmega161 users. Also, the increased number of Interrupt Vectors might be a problem if the code uses absolute addresses. To solve these problems, an ATmega161 compatibility mode can be selected by programming the fuse M161C. In this mode, none of the functions in the Extended I/O space are in use, so the internal RAM is located as in ATmega161. Also, the Extended Interrupt Vectors are removed. The ATmega162 is 100% pin compatible with ATmega161, and can replace the ATmega161 on current Printed Circuit Boards. However, the location of Fuse bits and the electrical characteristics differs between the two devices.

| ATmega161 Compatibility Mode | Programming the M161C will change the following functionality: The extended I/O map will be configured as internal RAM once the M161C Fuse is |
|---------------------------------|---|
| | The timed sequence for changing the Watchdog Time-out period is disabled. See "Timed Sequences for Changing the Configuration of the Watchdog Timer" on page 55 for details. |
| | The double buffering of the USART Receive Registers is disabled. See "AVR USART vs. AVR UART – Compatibility" on page 166 for details. |
| | Pin change interrupts are not supported (Contol Registers are located in Extended I/O). |
| | • One 16 bits Timer/Counter (Timer/Counter1) only. Timer/Counter3 is not accessible. |
| | Note that the shared UBRRHI Register in ATmega161 is split into two separate registers in ATmega162, UBRR0H and UBRR1H. The location of these registers will not be affected by the ATmega161 compatibility fuse. |
| Pin Descriptions | |
| vcc | Digital supply voltage |
| GND | Ground |
| Port A (PA7PA0) | Port A is an 8-bit bi-directional I/O port with internal pull-up resistors (selected for each bit). The Port A output buffers have symmetrical drive characteristics with both high sink and source capability. When pins PA0 to PA7 are used as inputs and are externally pulled low, they will source current if the internal pull-up resistors are activated. The Port A pins are tri-stated when a reset condition becomes active, even if the clock is not running. |
| | Port A also serves the functions of various special features of the ATmega162 as listed on page 71. |
| Port B (PB7PB0) | Port B is an 8-bit bi-directional I/O port with internal pull-up resistors (selected for each bit). The Port B output buffers have symmetrical drive characteristics with both high sink and source capability. As inputs, Port B pins that are externally pulled low will source current if the pull-up resistors are activated. The Port B pins are tri-stated when a reset condition becomes active, even if the clock is not running. |
| | Port B also serves the functions of various special features of the ATmega162 as listed on page 71. |
| Port C (PC7PC0) | Port C is an 8-bit bi-directional I/O port with internal pull-up resistors (selected for each bit). The Port C output buffers have symmetrical drive characteristics with both high sink and source capability. As inputs, Port C pins that are externally pulled low will source current if the pull-up resistors are activated. The Port C pins are tri-stated when a reset condition becomes active, even if the clock is not running. If the JTAG interface is enabled, the pull-up resistors on pins PC7(TDI), PC5(TMS) and PC4(TCK) will be activated even if a Reset occurs. |
| | Port C also serves the functions of the JTAG interface and other special features of the ATmega162 as listed on page 74. |



| | · · · · · · · · · · · · · · · · · · · |
|---------------------|---|
| Port D (PD7PD0) | Port D is an 8-bit bi-directional I/O port with internal pull-up resistors (selected for each bit). The Port D output buffers have symmetrical drive characteristics with both high sink and source capability. As inputs, Port D pins that are externally pulled low will source current if the pull-up resistors are activated. The Port D pins are tri-stated when a reset condition becomes active, even if the clock is not running. |
| | Port D also serves the functions of various special features of the ATmega162 as listed on page 77. |
| Port E(PE2PE0) | Port E is an 3-bit bi-directional I/O port with internal pull-up resistors (selected for each bit). The Port E output buffers have symmetrical drive characteristics with both high sink and source capability. As inputs, Port E pins that are externally pulled low will source current if the pull-up resistors are activated. The Port E pins are tri-stated when a reset condition becomes active, even if the clock is not running. |
| | Port E also serves the functions of various special features of the ATmega162 as listed on page 80. |
| RESET | Reset input. A low level on this pin for longer than the minimum pulse length will gener- ate a Reset, even if the clock is not running. The minimum pulse length is given in Table 18 on page 47. Shorter pulses are not guaranteed to generate a reset. |
| XTAL1 | Input to the Inverting Oscillator amplifier and input to the internal clock operating circuit. |
| XTAL2 | Output from the Inverting Oscillator amplifier. |
| About Code Examples | This documentation contains simple code examples that briefly show how to use various parts of the device. These code examples assume that the part specific header file is included before compilation. Be aware that not all C compiler vendors include bit definitions in the header files and interrupt handling in C is compiler dependent. Please confirm with the C compiler documentation for more details. |

AIMEL

ATmega162 Typical Characteristics – Preliminary Data

The following charts show typical behavior. These figures are not tested during manufacturing. All current consumption measurements are performed with all I/O pins configured as inputs and with internal pull-ups enabled. A sine wave generator with railto-rail output is used as clock source. The CKSEL Fuses are programmed to select external clock.

The power consumption in Power-down mode is independent of clock selection.

The current consumption is a function of several factors such as: Operating voltage, operating frequency, loading of I/O pins, switching rate of I/O pins, code executed and ambient temperature. The dominating factors are operating voltage and frequency.

The current drawn from capacitive loaded pins may be estimated (for one pin) as $C_L^*V_{CC}^*f$ where C_L = load capacitance, V_{CC} = operating voltage and f = average switching frequency of I/O pin.

The parts are characterized at frequencies higher than test limits. Parts are not guaranteed to function properly at frequencies higher than the ordering code indicates.

The difference between current consumption in Power-down mode with Watchdog Timer enabled and Power-down mode with Watchdog Timer disabled represents the differential current drawn by the Watchdog Timer.





| Address | Name | Bit 7 | Bit 6 | Bit 5 | Bit 4 | Bit 3 | Bit 2 | Bit 1 | Bit 0 | Page |
|---------|----------|--------|---------|----------|-------------------|--------------------|-------------|--------|---------|----------|
| (0xFF) | Reserved | - | - | _ | - | - | - | _ | - | |
| | Reserved | _ | _ | _ | _ | - | _ | _ | _ | |
| (0x9E) | Reserved | - | - | _ | - | - | - | - | - | |
| (0x9D) | Reserved | - | - | _ | _ | - | - | _ | - | |
| (0x9C) | Reserved | - | - | _ | - | - | - | - | - | |
| (0x9B) | Reserved | - | - | - | - | - | - | - | - | |
| (0x9A) | Reserved | - | - | - | - | - | - | - | - | |
| (0x99) | Reserved | - | - | - | - | - | - | - | - | |
| (0x98) | Reserved | - | - | - | - | - | - | - | - | |
| (0x97) | Reserved | - | - | - | - | - | - | - | - | |
| (0x96) | Reserved | - | - | - | - | - | - | - | - | |
| (0x95) | Reserved | - | - | - | - | - | - | - | - | |
| (0x94) | Reserved | - | - | - | - | - | - | - | - | |
| (0x93) | Reserved | - | - | - | - | - | - | - | - | |
| (0x92) | Reserved | - | - | - | - | - | - | - | - | |
| (0x91) | Reserved | - | - | - | - | - | - | - | - | |
| (0x90) | Reserved | - | - | - | - | - | - | - | - | |
| (0x8F) | Reserved | - | - | - | - | - | - | - | - | |
| (0x8E) | Reserved | - | - | - | - | - | - | - | - | |
| (0x8D) | Reserved | - | - | - | - | - | - | - | - | |
| (0x8C) | Reserved | - | - | - | - | - | - | - | - | 400 |
| (0x8B) | TCCR3A | COM3A1 | LOMISAU | COM3B1 | COM3BU | FUC3A | FUC3B | WGM31 | WGM30 | 130 |
| (0x8A) | TCCR3B | ICNC3 | ICES3 | | WGM33 | WGM32 | US32 | 6831 | 0530 | 127 |
| (0x89) | | | | Time | er/Counter3 - Co | unter Register Hig | JII Byle | | | 132 |
| (0x00) | | | | Timor/Co | untor? Output C | amporo Register Lu | | | | 132 |
| (0x87) | OCR3AI | | | Timer/Co | unter3 – Output C | Compare Register | | | | 132 |
| (0x85) | OCR3BH | | | Timer/Co | unter3 – Output C | Compare Register | B High Byte | | | 132 |
| (0x84) | OCR3BI | | | Timer/Co | unter3 – Output C | Compare Register | B Low Byte | | | 132 |
| (0x83) | Reserved | _ | _ | - | _ | _ | - | _ | _ | TOL |
| (0x82) | Reserved | _ | _ | _ | _ | _ | _ | _ | _ | |
| (0x81) | ICR3H | | | Timer/0 | Counter3 – Input | Capture Register | High Byte | | | 133 |
| (0x80) | ICR3L | | | Timer/ | Counter3 – Input | Capture Register | Low Byte | | | 133 |
| (0x7F) | Reserved | - | - | _ | - | - | - | - | - | |
| (0x7E) | Reserved | - | - | _ | - | - | - | - | - | |
| (0x7D) | ETIMSK | - | - | TICIE3 | OCIE3A | OCIE3B | TOIE3 | _ | - | 134 |
| (0x7C) | ETIFR | _ | - | ICF3 | OCF3A | OCF3B | TOV3 | - | - | 135 |
| (0x7B) | Reserved | - | - | - | - | - | - | - | - | |
| (0x7A) | Reserved | - | - | - | - | - | - | - | - | |
| (0x79) | Reserved | - | - | - | - | - | - | - | - | |
| (0x78) | Reserved | - | - | - | - | - | - | - | - | |
| (0x77) | Reserved | - | - | - | - | - | - | - | - | |
| (0x76) | Reserved | - | - | - | - | - | - | - | - | |
| (0x75) | Reserved | - | - | - | - | - | - | - | - | |
| (0x74) | Reserved | - | - | - | - | - | - | - | - | |
| (0x73) | Reserved | - | - | - | - | - | - | - | - | |
| (0x72) | Reserved | - | - | - | - | - | - | - | - | |
| (0x71) | Reserved | - | - | - | - | - | - | - | - | |
| (0x70) | Reserved | - | - | - | - | - | - | - | - | |
| (0x6F) | Reserved | - | - | - | - | - | - | - | - | |
| (0x6E) | Reserved | _ | - | _ | - | _ | _ | _ | _ | |
| (0x6D) | Reserved | | | | | | | | | 07 |
| | PONSKI | | | | | | | PCINT9 | | 0/ 07 |
| | POMSKU | PGIN17 | PUINT6 | PUINT5 | PGIN14 | PCIN13 | PCIN12 | PCINT1 | PCINTO | 8/ |
| (UXDA) | Reserved | - | - | _ | _ | - | _ | - | - | |
| (0x69) | Reserved | _ | _ | _ | _ | _ | _ | _ | - | |
| (0x08) | Reserved | _ | _ | _ | _ | _ | _ | _ | - | |
| (0x67) | Reserved | _ | _ | _ | _ | _ | _ | _ | _ | |
| (0x00) | Reserved | _ | _ | _ | _ | _ | _ | _ | _ | |
| (0x63) | Reserved | _ | | _ | _ | _ | | _ | _ | |
| (0x63) | Reserved | _ | | _ | _ | | | _ | | |
| (0x62) | Reserved | _ | _ | _ | _ | _ | _ | _ | _ | |
| (0x61) | CLKPR | | _ | _ | _ | CLKPS3 | CLKPS2 | CLKPS1 | CI KPS0 | 40 |
| (0,01) | | 01.000 | | | | 01.000 | 01.002 | 02.001 | 02.000 | ~~~~ |

Register Summary



| Addross | Namo | Bit 7 | Rit 6 | Rit 5 | Rit 4 | Rit 2 | Bit 2 | Bit 1 | Rit 0 | Pago |
|---|----------|-------------|-------------------------|---------------|--|-------------------------|-------------|------------------|--------|---------------|
| (0×60) | Reconved | Dit 7 | Dit U | Dit 5 | DIL 4 | Bit 5 | DICZ | DICT | Dit U | i age |
| 0x3F (0x5F) | SREG | - | T | H | S | V | N | Z | C | 8 |
| 0x3E (0x5E) | SPH | SP15 | SP14 | SP13 | SP12 | SP11 | SP10 | SP9 | SP8 | 11 |
| 0x3D (0x5D) | SPL | SP7 | SP6 | SP5 | SP4 | SP3 | SP2 | SP1 | SP0 | 11 |
| 0x3C ⁽²⁾ (0x5C) ⁽²⁾ | UBRR1H | URSEL1 | | | UDMA | 110504 | UBRE | 1[11:8] | | 188 |
| 0x3B (0x5B) | GICR | URSEL1 | UMSEL1 | UPM11 INT2 | PCIE1 | DSBS1 PCIE0 | UCS211 | UCS210 | UCPOL1 | 187 |
| 0x3A (0x5A) | GIFR | INTF1 | INTF0 | INTF2 | PCIF1 | PCIF0 | - | - | - | 86 |
| 0x39 (0x59) | TIMSK | TOIE1 | OCIE1A | OCIE1B | OCIE2 | TICIE1 | TOIE2 | TOIE0 | OCIE0 | 101, 133, 153 |
| 0x38 (0x58) | TIFR | TOV1 | OCF1A | OCF1B | OCF2 | ICF1 | TOV2 | TOV0 | OCF0 | 102, 135, 154 |
| 0x37 (0x57) | SPMCR | SPMIE | RWWSB | - SPI 1 | RWWSRE | SBW01 | PGWRT | PGERS SDW/11 | SPMEN | 219 |
| 0x35 (0x55) | MCUCR | SRE | SRW10 | SE | SM1 | ISC11 | ISC10 | ISC01 | ISC00 | 28,42,83 |
| 0x34 (0x54) | MCUCSR | JTD | - | SM2 | JTRF | WDRF | BORF | EXTRF | PORF | 42,50,205 |
| 0x33 (0x53) | TCCR0 | FOC0 | WGM00 | COM01 | COM00 | WGM01 | CS02 | CS01 | CS00 | 99 |
| 0x32 (0x52) | TCNT0 | | Timer/Counter0 (8 Bits) | | | | | 101 | | |
| 0x30 (0x50) | SFIOR | TSM | XMBK | XMM2 | XMM1 | XMM0 | PUD | PSR2 | PSR310 | 31.69.104.155 |
| 0x2F (0x4F) | TCCR1A | COM1A1 | COM1A0 | COM1B1 | COM1B0 | FOC1A | FOC1B | WGM11 | WGM10 | 127 |
| 0x2E (0x4E) | TCCR1B | ICNC1 | ICES1 | - | WGM13 | WGM12 | CS12 | CS11 | CS10 | 130 |
| 0x2D (0x4D) | TCNT1H | | | Time | er/Counter1 – Cou | unter Register Hig | gh Byte | | | 132 |
| 0x2C (0x4C) 0x2B (0x4B) | OCR1AH | | | Timer/Cou | er/Counter1 – Cou Inter1 – Output C | unter Register Lo | A High Byte | | | 132 |
| 0x2A (0x4A) | OCR1AL | | | Timer/Cou | unter1 – Output C | ompare Register | A Low Byte | | | 132 |
| 0x29 (0x49) | OCR1BH | | | Timer/Cou | unter1 – Output C | ompare Register | B High Byte | | | 132 |
| 0x28 (0x48) | OCR1BL | | | Timer/Cou | unter1 – Output C | compare Register | B Low Byte | | | 132 |
| 0x27 (0x47) | TCCR2 | FOC2 | WGM20 | COM21 | COM20 | WGM21 | CS22 | CS21 | CS20 | 148 |
| 0x25 (0x45) | ICR1H | - | - | – Timer/C | Counter1 – Input (| AS2 Capture Register | High Byte | UCK20B | TCR20B | 133 |
| 0x24 (0x44) | ICR1L | | | Timer/0 | Counter1 – Input (| Capture Register | Low Byte | | | 133 |
| 0x23 (0x43) | TCNT2 | | | | Timer/Cou | nter2 (8 Bits) | | | | 150 |
| 0x22 (0x42) | OCR2 | | | Tin | ner/Counter2 Out | put Compare Reg | gister | | MORO | 150 |
| 0x21 (0x41) | UBRROH | - URSEL0 | | | - | WDE | WDP2 | WDP1 20[11:8] | WDP0 | 52 |
| 0x20 ⁽²⁾ (0x40) ⁽²⁾ | UCSR0C | URSEL0 | UMSEL0 | UPM01 | UPM00 | USBS0 | UCSZ01 | UCSZ00 | UCPOL0 | 187 |
| 0x1F (0x3F) | EEARH | - | - | - | - | - | - | - | EEAR8 | 18 |
| 0x1E (0x3E) | EEARL | | | E | EEPROM Addres | s Register Low B | yte | | | 18 |
| 0x1D (0x3D) 0x1C (0x3C) | EEDR | _ | - | _ | EEPROM I | Jata Register FFRIF | FFMWF | FFWF | FFRF | 19 |
| 0x1B (0x3B) | PORTA | PORTA7 | PORTA6 | PORTA5 | PORTA4 | PORTA3 | PORTA2 | PORTA1 | PORTA0 | 81 |
| 0x1A (0x3A) | DDRA | DDA7 | DDA6 | DDA5 | DDA4 | DDA3 | DDA2 | DDA1 | DDA0 | 81 |
| 0x19 (0x39) | PINA | PINA7 | PINA6 | PINA5 | PINA4 | PINA3 | PINA2 | PINA1 | PINA0 | 81 |
| 0x18 (0x38) | PORTB | PORTB7 | PORTB6 | PORTB5 | PORTB4 | PORTB3 | PORTB2 | PORTB1 | PORTB0 | 81 |
| 0x16 (0x36) | PINB | PINB7 | PINB6 | PINB5 | PINB4 | PINB3 | PINB2 | PINB1 | PINB0 | 81 |
| 0x15 (0x35) | PORTC | PORTC7 | PORTC6 | PORTC5 | PORTC4 | PORTC3 | PORTC2 | PORTC1 | PORTC0 | 81 |
| 0x14 (0x34) | DDRC | DDC7 | DDC6 | DDC5 | DDC4 | DDC3 | DDC2 | DDC1 | DDC0 | 81 |
| 0x13 (0x33) | PINC | PINC7 | PINC6 | PINC5 | PINC4 | PINC3 | PINC2 | PINC1 | PINC0 | 82 |
| 0x12 (0x32) 0x11 (0x31) | DDRD | DDD7 | DDD6 | DDD5 | DDD4 | DDD3 | DDD2 | DDD1 | DDD0 | 82 |
| 0x10 (0x30) | PIND | PIND7 | PIND6 | PIND5 | PIND4 | PIND3 | PIND2 | PIND1 | PIND0 | 82 |
| 0x0F (0x2F) | SPDR | | | | SPI Dat | a Register | | | 1 | 162 |
| 0x0E (0x2E) | SPSR | SPIF | WCOL | - | - | - | - | - | SPI2X | 162 |
| 0x0D (0x2D) | | SPIE | SPE | DORD | MSTR USARTO I/C | CPOL | СРНА | SPR1 | SPR0 | 160 |
| 0x0B (0x2B) | UCSR0A | RXC0 | TXC0 | UDRE0 | FE0 | DOR0 | UPE0 | U2X0 | MPCM0 | 184 |
| 0x0A (0x2A) | UCSR0B | RXCIE0 | TXCIE0 | UDRIE0 | RXEN0 | TXEN0 | UCSZ02 | RXB80 | TXB80 | 185 |
| 0x09 (0x29) | UBRR0L | | | L | JSART0 Baud Ra | te Register Low I | Byte | | | 188 |
| 0x08 (0x28) | ACSR | ACD | ACBG | ACO | ACI | ACIE | ACIC | ACIS1 | ACIS0 | 193 |
| 0x07 (0x27) 0x06 (0x26) | DDRE | _ | _ | _ | _ | _ | DDE2 | DDE1 | DDE0 | 82 |
| 0x05 (0x25) | PINE | - | - | - | - | - | PINE2 | PINE1 | PINE0 | 82 |
| $0x04^{(1)}(0x24)^{(1)}$ | OSCCAL | | | | Oscillator Cali | bration Register | | | | 38 |
| | OCDR | | | | On-chip De | bug Register | | | | 200 |
| 0x03 (0x23) | | RXC1 | TYC1 | | USART1 I/O | DOP1 | | 11211 | MPCM1 | 184 |
| 0102 (0122) | JUDINIA | 10.01 | 1701 | ODILLI | 1 | DONT | ULL | 02/1 | | 104 |





| Address | Name | Bit 7 | Bit 6 | Bit 5 | Bit 4 | Bit 3 | Bit 2 | Bit 1 | Bit 0 | Page |
|-------------|--------|--------|------------------------------------|--------|-------|-------|--------|-------|-------|------|
| 0x01 (0x21) | UCSR1B | RXCIE1 | TXCIE1 | UDRIE1 | RXEN1 | TXEN1 | UCSZ12 | RXB81 | TXB81 | 185 |
| 0x00 (0x20) | UBRR1L | | USART1 Baud Rate Register Low Byte | | | | | 188 | | |

Notes: 1. When the OCDEN Fuse is unprogrammed, the OSCCAL Register is always accessed on this address. Refer to the debugger specific documentation for details on how to use the OCDR Register.

2. Refer to the USART description for details on how to access UBRRH and UCSRC.

3. For compatibility with future devices, reserved bits should be written to zero if accessed. Reserved I/O memory addresses should never be written.

4. Some of the status flags are cleared by writing a logical one to them. Note that the CBI and SBI instructions will operate on all bits in the I/O Register, writing a one back into any flag read as set, thus clearing the flag. The CBI and SBI instructions work with registers 0x00 to 0x1F only.

Instruction Set Summary

| Mnemonics | Operands | Description | Operation | Flags | #Clocks |
|------------------|------------------|--|---|------------|---------|
| ARITHMETIC AND L | OGIC INSTRUCTION | S | | | |
| ADD | Rd, Rr | Add two Registers | $Rd \leftarrow Rd + Rr$ | Z,C,N,V,H | 1 |
| ADC | Rd, Rr | Add with Carry two Registers | $Rd \leftarrow Rd + Rr + C$ | Z,C,N,V,H | 1 |
| ADIW | Rdl,K | Add Immediate to Word | Rdh:RdI ← Rdh:RdI + K | Z,C,N,V,S | 2 |
| SUB | Rd, Rr | Subtract two Registers | $Rd \leftarrow Rd - Rr$ | Z,C,N,V,H | 1 |
| SUBI | Rd, K | Subtract Constant from Register | $Rd \gets Rd - K$ | Z,C,N,V,H | 1 |
| SBC | Rd, Rr | Subtract with Carry two Registers | $Rd \gets Rd - Rr - C$ | Z,C,N,V,H | 1 |
| SBCI | Rd, K | Subtract with Carry Constant from Reg. | $Rd \leftarrow Rd - K - C$ | Z,C,N,V,H | 1 |
| SBIW | Rdl,K | Subtract Immediate from Word | $Rdh:\!Rdl \gets Rdh:\!Rdl \text{ - }K$ | Z,C,N,V,S | 2 |
| AND | Rd, Rr | Logical AND Registers | $Rd \gets Rd \bullet Rr$ | Z,N,V | 1 |
| ANDI | Rd, K | Logical AND Register and Constant | $Rd \gets Rd \bullet K$ | Z,N,V | 1 |
| OR | Rd, Rr | Logical OR Registers | $Rd \leftarrow Rd v Rr$ | Z,N,V | 1 |
| ORI | Rd, K | Logical OR Register and Constant | $Rd \gets Rd \lor K$ | Z,N,V | 1 |
| EOR | Rd, Rr | Exclusive OR Registers | $Rd \gets Rd \oplus Rr$ | Z,N,V | 1 |
| COM | Rd | One's Complement | $Rd \leftarrow 0xFF - Rd$ | Z,C,N,V | 1 |
| NEG | Rd | Two's Complement | $Rd \leftarrow 0x00 - Rd$ | Z,C,N,V,H | 1 |
| SBR | Rd,K | Set Bit(s) in Register | $Rd \gets Rd \lor K$ | Z,N,V | 1 |
| CBR | Rd,K | Clear Bit(s) in Register | $Rd \gets Rd \bullet (0xFF -K)$ | Z,N,V | 1 |
| INC | Rd | Increment | $Rd \leftarrow Rd + 1$ | Z,N,V | 1 |
| DEC | Rd | Decrement | $Rd \leftarrow Rd - 1$ | Z,N,V | 1 |
| TST | Rd | Test for Zero or Minus | $Rd \gets Rd \bullet Rd$ | Z,N,V | 1 |
| CLR | Rd | Clear Register | $Rd \leftarrow Rd \oplus Rd$ | Z,N,V | 1 |
| SER | Rd | Set Register | $Rd \gets 0xFF$ | None | 1 |
| MUL | Rd, Rr | Multiply Unsigned | $R1:R0 \leftarrow Rd x Rr$ | Z,C | 2 |
| MULS | Rd, Rr | Multiply Signed | $R1:R0 \leftarrow Rd x Rr$ | Z,C | 2 |
| MULSU | Rd, Rr | Multiply Signed with Unsigned | $R1:R0 \leftarrow Rd x Rr$ | Z,C | 2 |
| FMUL | Rd, Rr | Fractional Multiply Unsigned | $R1:R0 \leftarrow (Rd \times Rr) << 1$ | Z,C | 2 |
| FMULS | Rd, Rr | Fractional Multiply Signed | $R1:R0 \leftarrow (Rd \times Rr) << 1$ | Z,C | 2 |
| FMULSU | Rd, Rr | Fractional Multiply Signed with Unsigned | R1:R0 ← (Rd x Rr) << 1 | Z,C | 2 |
| BRANCH INSTRUCT | TIONS | | | | |
| RJMP | k | Relative Jump | $PC \leftarrow PC + k + 1$ | None | 2 |
| IJMP | | Indirect Jump to (Z) | $PC \leftarrow Z$ | None | 2 |
| JMP | k | Direct Jump | $PC \leftarrow k$ | None | 3 |
| RCALL | k | Relative Subroutine Call | $PC \leftarrow PC + k + 1$ | None | 3 |
| ICALL | | Indirect Call to (Z) | $PC \leftarrow Z$ | None | 3 |
| CALL | k | Direct Subroutine Call | $PC \leftarrow k$ | None | 4 |
| RET | | Subroutine Return | $PC \leftarrow STACK$ | None | 4 |
| RETI | | Interrupt Return | $PC \leftarrow STACK$ | Ι | 4 |
| CPSE | Rd,Rr | Compare, Skip if Equal | if $(Rd = Rr) PC \leftarrow PC + 2 \text{ or } 3$ | None | 1/2/3 |
| CP | Rd,Rr | Compare | Rd – Rr | Z, N,V,C,H | 1 |
| CPC | Rd,Rr | Compare with Carry | Rd – Rr – C | Z, N,V,C,H | 1 |
| CPI | Rd,K | Compare Register with Immediate | Rd – K | Z, N,V,C,H | 1 |
| SBRC | Rr, b | Skip if Bit in Register Cleared | if (Rr(b)=0) PC \leftarrow PC + 2 or 3 | None | 1/2/3 |
| SBRS | Rr, b | Skip if Bit in Register is Set | if (Rr(b)=1) PC \leftarrow PC + 2 or 3 | None | 1/2/3 |
| SBIC | P, b | Skip if Bit in I/O Register Cleared | if (P(b)=0) PC \leftarrow PC + 2 or 3 | None | 1/2/3 |
| SBIS | P, b | Skip if Bit in I/O Register is Set | if (P(b)=1) PC \leftarrow PC + 2 or 3 | None | 1/2/3 |
| BRBS | s, k | Branch if Status Flag Set | if (SREG(s) = 1) then $PC \leftarrow PC+k + 1$ | None | 1/2 |
| BRBC | s, k | Branch it Status Flag Cleared | If (SREG(s) = 0) then $PC \leftarrow PC+k+1$ | None | 1/2 |
| BREQ | k | Branch if Equal | if (Z = 1) then PC \leftarrow PC + k + 1 | None | 1/2 |
| BRNE | k | Branch if Not Equal | If $(Z = 0)$ then PC \leftarrow PC + k + 1 | None | 1/2 |
| BRCS | k | Branch if Carry Set | if (C = 1) then PC \leftarrow PC + k + 1 | None | 1/2 |
| BRCC | k | Branch if Carry Cleared | if (C = 0) then PC \leftarrow PC + k + 1 | None | 1/2 |
| BRSH | k | Branch if Same or Higher | if (C = 0) then PC \leftarrow PC + k + 1 | None | 1/2 |
| BRLO | k | Branch if Lower | if (C = 1) then PC \leftarrow PC + k + 1 | None | 1/2 |
| BRMI | ĸ | Branch if Minus | If $(N = 1)$ then PC \leftarrow PC + k + 1 | None | 1/2 |
| BRPL | ĸ | Branch if Plus | If $(N = 0)$ then PC \leftarrow PC + k + 1 | None | 1/2 |
| BRGE | ĸ | Branch if Greater or Equal, Signed | If $(N \oplus V = 0)$ then $PC \leftarrow PC + k + 1$ | None | 1/2 |
| BRLI | ĸ | Branch if Less Than Zero, Signed | If $(N \oplus V = 1)$ then $PC \leftarrow PC + k + 1$ | None | 1/2 |
| BRHS | ĸ | Branch if Half Carry Flag Set | If (H = 1) then PC \leftarrow PC + k + 1 | None | 1/2 |
| BRHC | ĸ | Branch it Half Carry Flag Cleared | If (H = 0) then PC \leftarrow PC + k + 1 | None | 1/2 |
| BRIS | K | Branch If I Hag Set | If $(1 = 1)$ then PC \leftarrow PC + k + 1 | None | 1/2 |
| BRIC | ĸ | Dranch if Augustian Flag is Oct | $ (1 = 0) \text{ then } PC \leftarrow PC + K + 1$ | None | 1/2 |
| DRVS | ĸ | Dranch if Overflow Flag is Clear - | $ (v = 1) \text{ then } PC \leftarrow PC + K + 1$ | None | 1/2 |
| DRVU | I K | Diange in Overnow Flag is Gleared | I = I = I = I = I = I = I = I = I = I = | NODE | 1/2 |





| Mnemonics | Operands | Description | Operation | Flags | #Clocks |
|--------------------|-------------|-----------------------------------|--|---------|---------|
| BRIE | k | Branch if Interrupt Enabled | if (I = 1) then PC \leftarrow PC + k + 1 | None | 1/2 |
| BRID | k | Branch if Interrupt Disabled | if (I = 0) then PC \leftarrow PC + k + 1 | None | 1/2 |
| DATA TRANSFER IN | ISTRUCTIONS | | | | |
| MOV | Rd, Rr | Move Between Registers | $Rd \leftarrow Rr$ | None | 1 |
| MOVW | Rd, Rr | Copy Register Word | $Rd+1:Rd \leftarrow Rr+1:Rr$ | None | 1 |
| LDI | Rd, K | Load Immediate | $Rd \leftarrow K$ | None | 1 |
| LD | Rd, X | Load Indirect | $Rd \leftarrow (X)$ | None | 2 |
| LD | Rd, X+ | Load Indirect and Post-Inc. | $Rd \leftarrow (X), X \leftarrow X + 1$ | None | 2 |
| LD | Rd, - X | Load Indirect and Pre-Dec. | $X \leftarrow X - 1, Rd \leftarrow (X)$ | None | 2 |
| LD | Rd, Y | Load Indirect | $Rd \leftarrow (Y)$ | None | 2 |
| LD | Rd, Y+ | Load Indirect and Post-Inc. | $Rd \leftarrow (Y), Y \leftarrow Y + 1$ | None | 2 |
| LD | Rd, - Y | Load Indirect and Pre-Dec. | $Y \leftarrow Y - 1, Rd \leftarrow (Y)$ | None | 2 |
| LDD | Rd,Y+q | Load Indirect with Displacement | $Rd \leftarrow (Y + q)$ | None | 2 |
| LD | Rd, Z | Load Indirect | $Rd \leftarrow (Z)$ | None | 2 |
| LD | Rd, Z+ | Load Indirect and Post-Inc. | $Rd \leftarrow (Z), Z \leftarrow Z+1$ | None | 2 |
| LD | Rd, -Z | Load Indirect and Pre-Dec. | $Z \leftarrow Z - 1, Rd \leftarrow (Z)$ | None | 2 |
| LDD | Rd, Z+q | Load Indirect with Displacement | $Rd \leftarrow (Z + q)$ | None | 2 |
| LDS | Rd, k | Load Direct from SRAM | $Rd \leftarrow (k)$ | None | 2 |
| SI | X, Rr | Store Indirect | $(X) \leftarrow Rr$ | None | 2 |
| 51 | X+, Rr | Store Indirect and Post-Inc. | $(X) \leftarrow \operatorname{Rr}, X \leftarrow X + 1$ | None | 2 |
| SI | - X, Rr | Store Indirect and Pre-Dec. | $X \leftarrow X - 1, (X) \leftarrow Rr$ | None | 2 |
| SI | Y, Rr | Store Indirect | $(Y) \leftarrow Rr$ | None | 2 |
| SI | Y+, Rr | Store Indirect and Post-Inc. | $(Y) \leftarrow Rr, Y \leftarrow Y + 1$ | None | 2 |
| SI | - Y, Rr | Store Indirect and Pre-Dec. | $Y \leftarrow Y - 1, (Y) \leftarrow Rr$ | None | 2 |
| SID | Y+q,Rr | Store Indirect with Displacement | $(Y + q) \leftarrow Rr$ | None | 2 |
| 51 | Z, Rr | Store Indirect | $(2) \leftarrow \operatorname{Rr}$ | None | 2 |
| SI | Z+, Rr | Store Indirect and Post-Inc. | $(Z) \leftarrow \operatorname{Rr}, Z \leftarrow Z + 1$ | None | 2 |
| SI | -Z, Kr | Store Indirect and Pre-Dec. | $Z \leftarrow Z - 1, (Z) \leftarrow Rr$ | None | 2 |
| STD | Z+q,Rr | Store Indirect with Displacement | $(2+q) \leftarrow Rr$ | None | 2 |
| 515 | к, кі | | $(R) \leftarrow RI$ | None | 2 |
| | Dd 7 | Load Program Memory | $RU \leftarrow (Z)$ | None | 3 |
| | RU, Z | Load Program Memory and Post Inc. | $Ru \leftarrow (Z)$ | None | 3 |
| SDM | KU, Z+ | Store Program Momony | $Ru \leftarrow (Z), Z \leftarrow Z + I$ | None | 3 |
| IN IN | Rd P | | $(2) \leftarrow R(1,R0)$ | None | - 1 |
| OUT | P Rr | Out Port | P ← Br | None | 1 |
| PUSH | Rr | Push Register on Stack | $STACK \leftarrow Br$ | None | 2 |
| POP | Rd | Pop Register from Stack | | None | 2 |
| BIT AND BIT-TEST I | NSTRUCTIONS | | | Hono | - |
| SBI | P.b | Set Bit in I/O Register | $I/O(P,b) \leftarrow 1$ | None | 2 |
| CBI | P.b | Clear Bit in I/O Register | $VO(P,b) \leftarrow 0$ | None | 2 |
| LSL | Rd | Logical Shift Left | $Rd(n+1) \leftarrow Rd(n), Rd(0) \leftarrow 0$ | Z,C,N,V | 1 |
| LSR | Rd | Logical Shift Right | $Rd(n) \leftarrow Rd(n+1), Rd(7) \leftarrow 0$ | Z.C.N.V | 1 |
| ROL | Rd | Rotate Left Through Carry | $Rd(0) \leftarrow C, Rd(n+1) \leftarrow Rd(n), C \leftarrow Rd(7)$ | Z,C,N,V | 1 |
| ROR | Rd | Rotate Right Through Carry | $Rd(7) \leftarrow C, Rd(n) \leftarrow Rd(n+1), C \leftarrow Rd(0)$ | Z,C,N,V | 1 |
| ASR | Rd | Arithmetic Shift Right | $Rd(n) \leftarrow Rd(n+1), n=06$ | Z,C,N,V | 1 |
| SWAP | Rd | Swap Nibbles | Rd(30)←Rd(74),Rd(74)←Rd(30) | None | 1 |
| BSET | s | Flag Set | $SREG(s) \leftarrow 1$ | SREG(s) | 1 |
| BCLR | S | Flag Clear | $SREG(s) \leftarrow 0$ | SREG(s) | 1 |
| BST | Rr, b | Bit Store from Register to T | $T \leftarrow Rr(b)$ | Т | 1 |
| BLD | Rd, b | Bit load from T to Register | Rd(b) ← T | None | 1 |
| SEC | | Set Carry | C ← 1 | С | 1 |
| CLC | | Clear Carry | $C \leftarrow 0$ | С | 1 |
| SEN | | Set Negative Flag | $N \leftarrow 1$ | Ν | 1 |
| CLN | | Clear Negative Flag | $N \leftarrow 0$ | N | 1 |
| SEZ | | Set Zero Flag | Z ← 1 | Z | 1 |
| CLZ | | Clear Zero Flag | $Z \leftarrow 0$ | Z | 1 |
| SEI | | Global Interrupt Enable | l ← 1 | Ι | 1 |
| CLI | | Global Interrupt Disable | l ← 0 | Ι | 1 |
| SES | | Set Signed Test Flag | S ← 1 | S | 1 |
| CLS | | Clear Signed Test Flag | S ← 0 | S | 1 |
| SEV | | Set Twos Complement Overflow. | V ← 1 | V | 1 |
| CLV | | Clear Twos Complement Overflow | $V \leftarrow 0$ | V | 1 |
| SET | | Set T in SREG | T ← 1 | Т | 1 |
| CLT | | Clear T in SREG | T ← 0 | Т | 1 |
| SEH | | Set Half Carry Flag in SREG | H ← 1 | Н | 1 |

| Mnemonics | Operands | Description | Operation | Flags | #Clocks |
|-----------------|-----------|-------------------------------|--|-------|---------|
| CLH | | Clear Half Carry Flag in SREG | $H \leftarrow 0$ | Н | 1 |
| MCU CONTROL INS | TRUCTIONS | | | | |
| NOP | | No Operation | | None | 1 |
| SLEEP | | Sleep | (see specific descr. for Sleep function) | None | 1 |
| WDR | | Watchdog Reset | (see specific descr. for WDR/Timer) | None | 1 |
| BREAK | | Break | For On-chip Debug Only | None | N/A |





Ordering Information

| Speed (MHz) | Power Supply | Ordering Code | Package | Operation Range |
|-------------|--------------|--|---------------------|-------------------------------|
| 1 | 1.8 - 3.6V | ATmega162V-1AC ATmega162V-1PC ATmega162V-1MC | 44A 40P6 44M1 | Commercial (0°C to 70°C) |
| 8 | 2.4 - 4.0V | ATmega162U-8AC ATmega162U-8PC ATmega162U-8MC | 44A 40P6 44M1 | Commercial (0°C to 70°C) |
| 8 | 2.7 - 5.5V | ATmega162L-8AC ATmega162L-8PC ATmega162L-8MC | 44A 40P6 44M1 | Commercial (0°C to 70°C) |
| | | ATmega162L-8AI ATmega162L-8PI ATmega162L-8MI | 44A 40P6 44M1 | Industrial (-40°C to 85°C) |
| 16 | 4.5 - 5.5V | ATmega162-16AC ATmega162-16PC ATmega162-16MC | 44A 40P6 44M1 | Commercial (0°C to 70°C) |
| | | ATmega162-16AI ATmega162-16PI ATmega162-16MI | 44A 40P6 44M1 | Industrial (-40°C to 85°C) |

Note: 1. This device can also be supplied in wafer form. Please contact your local Atmel sales office for detailed ordering information and minimum quantities.

| | Package Type |
|------|---|
| 44A | 44-lead, Thin (1.0 mm) Plastic Gull Wing Quad Flat Package (TQFP) |
| 40P6 | 40-pin, 0.600" Wide, Plastic Dual Inline Package (PDIP) |
| 44M1 | 44-pad, 7 x 7 x 1.0 mm body, lead pitch 0.50 mm, Micro Lead Frame Package (MLF) |

Packaging Information

44A

44-lead, Thin (1.0mm) Plastic Quad Flat Package (TQFP), 10x10mm body, 2.0mm footprint, 0.8mm pitch. Dimension in Millimeters and (Inches)* JEDEC STANDARD MS-026 ACB



*Controlling dimension: millimeter







40P6

40-lead, Plastic Dual Inline Package (PDIP), 0.600" wide Dimension in Millimeters and (Inches)* JEDEC STANDARD MS-011 AC



*Controlling dimension: Inches

REV. A 04/11/2001









Data Sheet Change Log for ATmega162

Changes from Rev. 2513A-05/02 to Rev. 2513B-09/02

Changes from Rev. 2513B-09/02 to Rev. 2513C-09/02 Please note that the referring page numbers in this section are referred to this document. The referring revision in this section are referring to the document revision.

1. Added information for ATmega162U.

Information about ATmega162U included in "Features" on page 1, Table 19, "BODLEVEL Fuse Coding," on page 49, and "Ordering Information" on page 14.

1. Canged the Endurance on the Flash to 10,000 Write/Erase Cycles.



Atmel Headquarters

Corporate Headquarters 2325 Orchard Parkway San Jose, CA 95131 TEL 1(408) 441-0311 FAX 1(408) 487-2600

Europe

Atmel Sarl Route des Arsenaux 41 Case Postale 80 CH-1705 Fribourg Switzerland TEL (41) 26-426-5555 FAX (41) 26-426-5500

Asia

Room 1219 Chinachem Golden Plaza 77 Mody Road Tsimhatsui East Kowloon Hong Kong TEL (852) 2721-9778 FAX (852) 2722-1369

Japan

9F, Tonetsu Shinkawa Bldg. 1-24-8 Shinkawa Chuo-ku, Tokyo 104-0033 Japan TEL (81) 3-3523-3551 FAX (81) 3-3523-7581

Atmel Operations

Memory

2325 Orchard Parkway San Jose, CA 95131 TEL 1(408) 441-0311 FAX 1(408) 436-4314

Microcontrollers

2325 Orchard Parkway San Jose, CA 95131 TEL 1(408) 441-0311 FAX 1(408) 436-4314

La Chantrerie BP 70602 44306 Nantes Cedex 3, France TEL (33) 2-40-18-18-18 FAX (33) 2-40-18-19-60

ASIC/ASSP/Smart Cards

Zone Industrielle 13106 Rousset Cedex, France TEL (33) 4-42-53-60-00 FAX (33) 4-42-53-60-01

1150 East Cheyenne Mtn. Blvd. Colorado Springs, CO 80906 TEL 1(719) 576-3300 FAX 1(719) 540-1759

Scottish Enterprise Technology Park Maxwell Building East Kilbride G75 0QR, Scotland TEL (44) 1355-803-000 FAX (44) 1355-242-743 **RF**/Automotive

Theresienstrasse 2 Postfach 3535 74025 Heilbronn, Germany TEL (49) 71-31-67-0 FAX (49) 71-31-67-2340

1150 East Cheyenne Mtn. Blvd. Colorado Springs, CO 80906 TEL 1(719) 576-3300 FAX 1(719) 540-1759

Biometrics/Imaging/Hi-Rel MPU/ High Speed Converters/RF Datacom Avenue de Rochepleine BP 123 38521 Saint-Egreve Cedex, France TEL (33) 4-76-58-30-00 FAX (33) 4-76-58-34-80

e-mail literature@atmel.com

Web Site http://www.atmel.com

© Atmel Corporation 2002.

Atmel Corporation makes no warranty for the use of its products, other than those expressly contained in the Company's standard warranty which is detailed in Atmel's Terms and Conditions located on the Company's web site. The Company assumes no responsibility for any errors which may appear in this document, reserves the right to change devices or specifications detailed herein at any time without notice, and does not make any commitment to update the information contained herein. No licenses to patents or other intellectual property of Atmel are granted by the Company in connection with the sale of Atmel products, expressly or by implication. Atmel's products are not authorized for use as critical components in life support devices or systems.

ATMEL®, AVR®, and AVR Studio® are the registered trademarks of Atmel.

Microsoft[®], Windows[®], and Windows NT[®] are trademarks of Microsoft Corporation.



Other terms and product names may be the trademarks of others.

0M