# E·XFL



#### Welcome to E-XFL.COM

#### **Understanding Embedded - Microprocessors**

Embedded microprocessors are specialized computing chips designed to perform specific tasks within an embedded system. Unlike general-purpose microprocessors found in personal computers, embedded microprocessors are tailored for dedicated functions within larger systems, offering optimized performance, efficiency, and reliability. These microprocessors are integral to the operation of countless electronic devices, providing the computational power necessary for controlling processes, handling data, and managing communications.

#### Applications of **Embedded - Microprocessors**

Embedded microprocessors are utilized across a broad spectrum of applications, making them indispensable in

#### Details

Product Status	Obsolete
Core Processor	PowerPC e500
Number of Cores/Bus Width	1 Core, 32-Bit
Speed	1.2GHz
Co-Processors/DSP	Signal Processing; SPE, Security; SEC
RAM Controllers	DDR, DDR2, SDRAM
Graphics Acceleration	No
Display & Interface Controllers	-
Ethernet	10/100/1000Mbps (4)
SATA	-
USB	-
Voltage - I/O	1.8V, 2.5V, 3.3V
Operating Temperature	0°C ~ 105°C (TA)
Security Features	Cryptography, Random Number Generator
Package / Case	783-BBGA, FCBGA
Supplier Device Package	783-FCPBGA (29x29)
Purchase URL	https://www.e-xfl.com/product-detail/nxp-semiconductors/mpc8545evtatgd

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

Characteristic	Symbol	Recommended Value	Unit	Notes
Junction temperature range	Tj	0 to 105	°C	_

### Table 2. Recommended Operating Conditions (continued)

#### Notes:

1. This voltage is the input to the filter discussed in Section 22.2, "PLL Power Supply Filtering," and not necessarily the voltage at the AV<sub>DD</sub> pin, which may be reduced from V<sub>DD</sub> by the filter.

- Caution: MV<sub>IN</sub> must not exceed GV<sub>DD</sub> by more than 0.3 V. This limit may be exceeded for a maximum of 20 ms during power-on reset and power-down sequences.
- 3. Caution: OV<sub>IN</sub> must not exceed OV<sub>DD</sub> by more than 0.3 V. This limit may be exceeded for a maximum of 20 ms during power-on reset and power-down sequences.
- 4. Caution: L/TV<sub>IN</sub> must not exceed L/TV<sub>DD</sub> by more than 0.3 V. This limit may be exceeded for a maximum of 20 ms during power-on reset and power-down sequences.

The following figure shows the undershoot and overshoot voltages at the interfaces of this device.



The core voltage must always be provided at nominal 1.1 V. Voltage to the processor interface I/Os are provided through separate sets of supply pins and must be provided at the voltages shown in Table 2. The input voltage threshold scales with respect to the associated I/O supply voltage.  $OV_{DD}$  and  $LV_{DD}$  based receivers are simple CMOS I/O circuits and satisfy appropriate LVCMOS type specifications. The DDR SDRAM interface uses a single-ended differential receiver referenced the externally supplied  $MV_{REF}$  signal (nominally set to  $GV_{DD}/2$ ) as is appropriate for the SSTL2 electrical signaling standard.

Figure 8 shows the GMII transmit AC timing diagram.



Figure 8. GMII Transmit AC Timing Diagram

# 8.2.2.2 GMII Receive AC Timing Specifications

This table provides the GMII receive AC timing specifications.

Parameter/Condition	Symbol <sup>1</sup>	Min	Тур	Max	Unit
RX_CLK clock period	t <sub>GRX</sub>	_	8.0	_	ns
RX_CLK duty cycle	t <sub>GRXH</sub> /t <sub>GRX</sub>	35	_	75	ns
RXD[7:0], RX_DV, RX_ER setup time to RX_CLK	t <sub>GRDVKH</sub>	2.0	_	—	ns
RXD[7:0], RX_DV, RX_ER hold time to RX_CLK	t <sub>GRDXKH</sub>	0	_	—	ns
RX_CLK clock rise (20%-80%)	t <sub>GRXR</sub> 2	—	_	1.0	ns
RX_CLK clock fall time (80%-20%)	t <sub>GRXF</sub> 2	—		1.0	ns

#### Notes:

1. The symbols used for timing specifications follow the pattern of t<sub>(first two letters of functional block)(signal)(state)(reference)(state) for inputs and t<sub>(first two letters of functional block)(reference)(state)(signal)(state)</sub> for outputs. For example, t<sub>GRDVKH</sub> symbolizes GMII receive timing (GR) with respect to the time data input signals (D) reaching the valid state (V) relative to the t<sub>RX</sub> clock reference (K) going to the high state (H) or setup time. Also, t<sub>GRDXKL</sub> symbolizes GMII receive timing (GR) with respect to the time data input signals (D) went invalid (X) relative to the t<sub>GRX</sub> clock reference (K) going to the low (L) state or hold time. Note that, in general, the clock reference symbol representation is based on three letters representing the clock of a particular functional. For example, the subscript of t<sub>GRX</sub> represents the GMII (G) receive (RX) clock. For rise and fall times, the latter convention is used with the appropriate letter: R (rise) or F (fall).</sub>

2. Guaranteed by design.

Figure 9 provides the AC test load for eTSEC.



Table 34. RMII Transmit A	C Timing	Specifications	(continued)
---------------------------	----------	----------------	-------------

Parameter/Condition	Symbol <sup>1</sup>	Min	Тур	Мах	Unit
TSEC <i>n_</i> TX_CLK to RMII data TXD[1:0], TX_EN delay	t <sub>RMTDX</sub>	1.0		10.0	ns

Note:

The symbols used for timing specifications follow the pattern of t<sub>(first two letters of functional block)(signal)(state)(reference)(state) for inputs and t<sub>(first two letters of functional block)(reference)(state)(signal)(state) for outputs. For example, t<sub>MTKHDX</sub> symbolizes MII transmit timing (MT) for the time t<sub>MTX</sub> clock reference (K) going high (H) until data outputs (D) are invalid (X). Note that, in general, the clock reference symbol representation is based on two to three letters representing the clock of a particular functional. For example, the subscript of t<sub>MTX</sub> represents the MII(M) transmit (TX) clock. For rise and fall times, the latter convention is used with the appropriate letter: R (rise) or F (fall).
</sub></sub>

### Figure 18 shows the RMII transmit AC timing diagram.



Figure 18. RMII Transmit AC Timing Diagram

# 8.2.7.2 RMII Receive AC Timing Specifications

### Table 35. RMII Receive AC Timing Specifications

Parameter/Condition	Symbol <sup>1</sup>	Min	Тур	Max	Unit
TSEC <i>n</i> _TX_CLK clock period	t <sub>RMR</sub>	15.0	20.0	25.0	ns
TSEC <i>n</i> _TX_CLK duty cycle	t <sub>RMRH</sub>	35	50	65	%
TSEC <i>n</i> _TX_CLK peak-to-peak jitter	t <sub>RMRJ</sub>	—	_	250	ps
Rise time TSEC <i>n</i> _TX_CLK(20%–80%)	t <sub>RMRR</sub>	1.0	_	2.0	ns
Fall time TSEC <i>n</i> _TX_CLK (80%–20%)	t <sub>RMRF</sub>	1.0	_	2.0	ns
RXD[1:0], CRS_DV, RX_ER setup time to REF_CLK rising edge	t <sub>RMRDV</sub>	4.0	_	—	ns
RXD[1:0], CRS_DV, RX_ER hold time to REF_CLK rising edge	t <sub>RMRDX</sub>	2.0	_	—	ns

Note:

1. The symbols used for timing specifications follow the pattern of t<sub>(first two letters of functional block)(signal)(state)(reference)(state) for inputs and t<sub>(first two letters of functional block)(reference)(state)(signal)(state) for outputs. For example, t<sub>MRDVKH</sub> symbolizes MII receive timing (MR) with respect to the time data input signals (D) reach the valid state (V) relative to the t<sub>MRX</sub> clock reference (K) going to the high (H) state or setup time. Also, t<sub>MRDXKL</sub> symbolizes MII receive timing (GR) with respect to the time data input signals (D) went invalid (X) relative to the t<sub>MRX</sub> clock reference (K) going to the low (L) state or hold time. Note that, in general, the clock reference symbol representation is based on three letters representing the clock of a particular functional. For example, the subscript of t<sub>MRX</sub> represents the MII (M) receive (RX) clock. For rise and fall times, the latter convention is used with the appropriate letter: R (rise) or F (fall).</sub></sub>

Parameter	Symbol <sup>1</sup>	Min	Max	Unit	Notes
LGTA/LUPWAIT input hold from local bus clock	t <sub>LBIXKL2</sub>	-1.3		ns	4, 5
LALE output transition to LAD/LDP output transition (LATCH hold time)	t <sub>LBOTOT</sub>	1.5		ns	6
Local bus clock to output valid (except LAD/LDP and LALE)	t <sub>LBKLOV1</sub>	_	-0.3	ns	
Local bus clock to data valid for LAD/LDP	t <sub>LBKLOV2</sub>	_	-0.1	ns	4
Local bus clock to address valid for LAD	t <sub>LBKLOV3</sub>	_	0	ns	4
Local bus clock to LALE assertion	t <sub>LBKLOV4</sub>	_	0	ns	4
Output hold from local bus clock (except LAD/LDP and LALE)	t <sub>LBKLOX1</sub>	-3.7	_	ns	4
Output hold from local bus clock for LAD/LDP	t <sub>LBKLOX2</sub>	-3.7	_	ns	4
Local bus clock to output high Impedance (except LAD/LDP and LALE)	t <sub>LBKLOZ1</sub>	_	0.2	ns	7
Local bus clock to output high impedance for LAD/LDP	t <sub>LBKLOZ2</sub>		0.2	ns	7

### Table 42. Local Bus Timing Parameters—PLL Bypassed (continued)

#### Notes:

The symbols used for timing specifications follow the pattern of t<sub>(first two letters of functional block)(signal)(state)(reference)(state) for inputs and t<sub>(first two letters of functional block)(reference)(state)(signal)(state)</sub> for outputs. For example, t<sub>LBIXKH1</sub> symbolizes local bus timing (LB) for the input (I) to go invalid (X) with respect to the time the t<sub>LBK</sub> clock reference (K) goes high (H), in this case for clock one (1). Also, t<sub>LBKH0X</sub> symbolizes local bus timing (LB) for the t<sub>LBK</sub> clock reference (K) to go high (H), with respect to the output (O) going invalid (X) or output hold time.
</sub>

 All timings are in reference to local bus clock for PLL bypass mode. Timings may be negative with respect to the local bus clock because the actual launch and capture of signals is done with the internal launch/capture clock, which precedes LCLK by t<sub>LBKHKT</sub>.

3. Maximum possible clock skew between a clock LCLK[m] and a relative clock LCLK[n]. Skew measured between complementary signals at BV<sub>DD</sub>/2.

4. All signals are measured from  $BV_{DD}/2$  of the rising edge of local bus clock for PLL bypass mode to  $0.4 \times BV_{DD}$  of the signal in question for 3.3-V signaling levels.

5. Input timings are measured at the pin.

6. The value of t<sub>LBOTOT</sub> is the measurement of the minimum time between the negation of LALE and any change in LAD.

7. For purposes of active/float timing measurements, the Hi-Z or off state is defined to be when the total current delivered through the component pin is less than or equal to the leakage current specification.

- 8. Guaranteed by characterization.
- 9. Guaranteed by design.



Figure 34 shows the AC timing diagram for the  $I^2C$  bus.



Figure 34. I<sup>2</sup>C Bus AC Timing Diagram

of a balanced interchange circuit and ground. In this example, for SerDes output,  $V_{cm_out} = V_{SD_TX} + V_{\overline{SD}_TX} = (A + B)/2$ , which is the arithmetic mean of the two complimentary output voltages within a differential pair. In a system, the common mode voltage may often differ from one component's output to the other's input. Sometimes, it may be even different between the receiver input and driver output circuits within the same component. It is also referred to as the DC offset.



To illustrate these definitions using real values, consider the case of a CML (current mode logic) transmitter that has a common mode voltage of 2.25 V and each of its outputs, TD and TD, has a swing that goes between 2.5 and 2.0 V. Using these values, the peak-to-peak voltage swing of each signal (TD or TD) is 500 mVp-p, which is referred as the single-ended swing for each signal. In this example, since the differential signaling environment is fully symmetrical, the transmitter output's differential swing (V<sub>OD</sub>) has the same amplitude as each signal's single-ended swing. The differential output signal ranges between 500 and -500 mV, in other words, V<sub>OD</sub> is 500 mV in one phase and -500 mV in the other phase. The peak differential voltage (V<sub>DIFFp</sub>) is 500 mV. The peak-to-peak differential voltage (V<sub>DIFFp</sub>) is 1000 mVp-p.

# 16.2 SerDes Reference Clocks

The SerDes reference clock inputs are applied to an internal PLL whose output creates the clock used by the corresponding SerDes lanes. The SerDes reference clocks inputs are SD\_REF\_CLK and SD\_REF\_CLK for PCI Express and serial RapidIO.

The following sections describe the SerDes reference clock requirements and some application information.

# 16.2.1 SerDes Reference Clock Receiver Characteristics

Figure 39 shows a receiver reference diagram of the SerDes reference clocks.

- The supply voltage requirements for  $XV_{DD SRDS2}$  are specified in Table 1 and Table 2.
- SerDes Reference clock receiver reference circuit structure:

- The SD\_REF\_CLK and SD\_REF\_CLK are internally AC-coupled differential inputs as shown in Figure 39. Each differential clock input (SD\_REF\_CLK or SD\_REF\_CLK) has a 50-Ω termination to SGND\_SRDSn (xcorevss) followed by on-chip AC-coupling.
- The external reference clock driver must be able to drive this termination.
- The SerDes reference clock input can be either differential or single-ended. See the differential mode and single-ended mode description below for further detailed requirements.
- The maximum average current requirement that also determines the common mode voltage range:
  - When the SerDes reference clock differential inputs are DC coupled externally with the clock driver chip, the maximum average current allowed for each input pin is 8 mA. In this case, the exact common mode input voltage is not critical as long as it is within the range allowed by the maximum average current of 8 mA (see the following bullet for more detail), since the input is AC-coupled on-chip.
  - This current limitation sets the maximum common mode input voltage to be less than 0.4 V (0.4 V/50 = 8 mA) while the minimum common mode input level is 0.1 V above SGND\_SRDS*n* (xcorevss). For example, a clock with a 50/50 duty cycle can be produced by a clock driver with output driven by its current source from 0 to 16 mA (0–0.8 V), such that each phase of the differential input has a single-ended swing from 0 V to 800 mV with the common mode voltage at 400 mV.
  - If the device driving the SD\_REF\_CLK and  $\overline{\text{SD}_{\text{REF}_{\text{CLK}}}}$  inputs cannot drive 50  $\Omega$  to SGND\_SRDS*n* (xcorevss) DC, or it exceeds the maximum input current limitations, then it must be AC-coupled off-chip.
- The input amplitude requirement:
  - This requirement is described in detail in the following sections.



Figure 39. Receiver of SerDes Reference Clocks

# 16.2.2 DC Level Requirement for SerDes Reference Clocks

The DC level requirement for the SerDes reference clock inputs is different depending on the signaling mode used to connect the clock driver chip and SerDes reference clock inputs as described below:

• Differential mode

#### High-Speed Serial Interfaces (HSSI)

- The input amplitude of the differential clock must be between 400 and 1600 mV differential peak-peak (or between 200 and 800 mV differential peak). In other words, each signal wire of the differential pair must have a single-ended swing less than 800 mV and greater than 200 mV. This requirement is the same for both external DC- or AC-coupled connection.
- For external DC-coupled connection, as described in Section 16.2.1, "SerDes Reference Clock Receiver Characteristics," the maximum average current requirements sets the requirement for average voltage (common mode voltage) to be between 100 and 400 mV. Figure 40 shows the SerDes reference clock input requirement for DC-coupled connection scheme.
- For external AC-coupled connection, there is no common mode voltage requirement for the clock driver. Since the external AC-coupling capacitor blocks the DC level, the clock driver and the SerDes reference clock receiver operate in different command mode voltages. The SerDes reference clock receiver in this connection scheme has its common mode voltage set to SGND\_SRDSn. Each signal wire of the differential inputs is allowed to swing below and above the command mode voltage (SGND\_SRDSn). Figure 41 shows the SerDes reference clock input requirement for AC-coupled connection scheme.
- Single-ended mode
  - The reference clock can also be single-ended. The SD\_REF\_CLK input amplitude (single-ended swing) must be between 400 and 800 mV peak-to-peak (from  $V_{min}$  to  $V_{max}$ ) with SD\_REF\_CLK either left unconnected or tied to ground.
  - The SD\_REF\_CLK input average voltage must be between 200 and 400 mV. Figure 42 shows the SerDes reference clock input requirement for single-ended signaling mode.
  - To meet the input amplitude requirement, the reference clock inputs might need to be DC- or AC-coupled externally. For the best noise performance, the reference of the clock could be DCor AC-coupled into the unused phase (SD\_REF\_CLK) through the same source impedance as the clock input (SD\_REF\_CLK) in use.



Figure 40. Differential Reference Clock Input DC Requirements (External DC-Coupled)

# 16.2.4 AC Requirements for SerDes Reference Clocks

The clock driver selected must provide a high quality reference clock with low phase noise and cycle-to-cycle jitter. Phase noise less than 100 kHz can be tracked by the PLL and data recovery loops and is less of a problem. Phase noise above 15 MHz is filtered by the PLL. The most problematic phase noise occurs in the 1–15 MHz range. The source impedance of the clock driver must be 50  $\Omega$  to match the transmission line and reduce reflections which are a source of noise to the system.

The detailed AC requirements of the SerDes reference clocks are defined by each interface protocol based on application usage. See the following sections for detailed information:

- Section 17.2, "AC Requirements for PCI Express SerDes Clocks"
- Section 18.2, "AC Requirements for Serial RapidIO SD\_REF\_CLK and SD\_REF\_CLK"

# 16.2.4.1 Spread Spectrum Clock

SD\_REF\_CLK/SD\_REF\_CLK are designed to work with a spread spectrum clock (+0% to -0.5% spreading at 30–33 kHz rate is allowed), assuming both ends have same reference clock. For better results, a source without significant unintended modulation must be used.

# 16.3 SerDes Transmitter and Receiver Reference Circuits

Figure 47 shows the reference circuits for SerDes data lane's transmitter and receiver.



Figure 47. SerDes Transmitter and Receiver Reference Circuits

The DC and AC specification of SerDes data lanes are defined in each interface protocol section below (PCI Express, Serial Rapid IO, or SGMII) in this document based on the application usage:

- Section 17, "PCI Express"
- Section 18, "Serial RapidIO"

Note that external an AC coupling capacitor is required for the above three serial transmission protocols with the capacitor value defined in the specification of each protocol section.

#### PCI Express

The eye diagram must be valid for any 250 consecutive UIs.

A recovered TX UI is calculated over 3500 consecutive unit intervals of sample data. The eye diagram is created using all edges of the 250 consecutive UI in the center of the 3500 UI used for calculating the TX UI.

# NOTE

The reference impedance for return loss measurements is 50. to ground for both the D+ and D– line (that is, as measured by a vector network analyzer with 50- $\Omega$  probes—see Figure 50). Note that the series capacitors, CTX, are optional for the return loss measurement.



Figure 49. Minimum Receiver Eye Timing and Voltage Compliance Specification

# 17.5.1 Compliance Test and Measurement Load

The AC timing and voltage parameters must be verified at the measurement point, as specified within 0.2 inches of the package pins, into a test/measurement load shown in Figure 50.

# NOTE

The allowance of the measurement point to be within 0.2 inches of the package pins is meant to acknowledge that package/board routing may benefit from D+ and D- not being exactly matched in length at the package pin boundary.



Figure 50. Compliance Test/Measurement Load

Table 71	. MPC8548E	<b>Pinout Listing</b>	(continued)
----------	------------	-----------------------	-------------

Signal	Package Pin Number	Pin Type	Power Supply	Notes	
	Clock				
RTC	AF16	I	OV <sub>DD</sub>	—	
SYSCLK	AH17	I	OV <sub>DD</sub>	—	
	JTAG				
ТСК	AG28	I	OV <sub>DD</sub>	—	
TDI	AH28	I	OV <sub>DD</sub>	12	
TDO	AF28	0	OV <sub>DD</sub>	—	
TMS	AH27	ļ	OV <sub>DD</sub>	12	
TRST	AH23	I	OV <sub>DD</sub>	12	
	DFT				
L1_TSTCLK	AC25	I	OV <sub>DD</sub>	25	
L2_TSTCLK	AE22	I	OV <sub>DD</sub>	25	
LSSD_MODE	AH20	I	OV <sub>DD</sub>	25	
TEST_SEL	AH14	I	OV <sub>DD</sub>	25	
Thermal Management					
THERM0	AG1	—	—	14	
THERM1	AH1	—	_	14	
	Power Management				
ASLEEP	AH18	0	OV <sub>DD</sub>	9, 19, 29	
	Power and Ground Signals				
GND	<ul> <li>A11, B7, B24, C1, C3, C5, C12, C15, C26, D8, D11, D16, D20, D22, E1, E5, E9, E12, E15, E17,</li> <li>F4, F26, G12, G15, G18, G21, G24, H2, H6, H8, H28, J4, J12, J15, J17, J27, K7, K9, K11, K27,</li> <li>L3, L5, L12, L16, N11, N13, N15, N17, N19, P4, P9, P12, P14, P16, P18, R11, R13, R15, R17, R19, T4, T12, T14, T16, T18, U8, U11, U13,</li> <li>U15, U17, U19, V4, V12, V18, W6, W19, Y4, Y9, Y11, Y19, AA6, AA14, AA17, AA22, AA23, AB4, AC2, AC11, AC19, AC26, AD5, AD9, AD22, AE3, AE14, AF6, AF10, AF13, AG8, AG27,</li> <li>K28, L24, L26, N24, N27, P25, R28, T24, T26,</li> <li>U24, V25, W28, Y24, Y26, AA24, AA27, AB25,</li> <li>AC28, L21, L23, N22, P20, R23, T21, U22, V20, W23, Y21, U27</li> </ul>		_	_	
OV <sub>DD</sub>	V16, W11, W14, Y18, AA13, AA21, AB11, AB17, AB24, AC4, AC9, AC21, AD6, AD13, AD17, AD19, AE10, AE8, AE24, AF4, AF12, AF22, AF27, AG26	Power for PCI and other standards (3.3 V)	OV <sub>DD</sub>	—	

Package Description

Signal	Package Pin Number	Pin Type	Power Supply	Notes
LV <sub>DD</sub>	N8, R7, T9, U6	Power for TSEC1 and TSEC2 (2.5 V, 3.3 V)	LV <sub>DD</sub>	_
TV <sub>DD</sub>	W9, Y6	Power for TSEC3 and TSEC4 (2,5 V, 3.3 V)	TV <sub>DD</sub>	_
GV <sub>DD</sub>	B3, B11, C7, C9, C14, C17, D4, D6, D10, D15, E2, E8, E11, E18, F5, F12, F16, G3, G7, G9, G11, H5, H12, H15, H17, J10, K3, K12, K16, K18, L6, M4, M8, M13	Power for DDR1 and DDR2 DRAM I/O voltage (1.8 V, 2.5)	GV <sub>DD</sub>	
BV <sub>DD</sub>	C21, C24, C27, E20, E25, G19, G23, H26, J20	Power for local bus (1.8 V, 2.5 V, 3.3 V)	BV <sub>DD</sub>	_
V <sub>DD</sub>	M19, N12, N14, N16, N18, P11, P13, P15, P17, P19, R12, R14, R16, R18, T11, T13, T15, T17, T19, U12, U14, U16, U18, V17, V19	Power for core (1.1 V)	V <sub>DD</sub>	_
SV <sub>DD</sub>	L25, L27, M24, N28, P24, P26, R24, R27, T25, V24, V26, W24, W27, Y25, AA28, AC27	Core Power for SerDes transceivers (1.1 V)	SV <sub>DD</sub>	
XV <sub>DD</sub>	L20, L22, N23, P21, R22, T20, U23, V21, W22, Y20	Pad Power for SerDes transceivers (1.1 V)	XV <sub>DD</sub>	_
AVDD_LBIU	J28	Power for local bus PLL (1.1 V)	—	26
AVDD_PCI1	AH21	Power for PCI1 PLL (1.1 V)	_	26
AVDD_PCI2	AH22	Power for PCI2 PLL (1.1 V)	_	26
AVDD_CORE	AH15	Power for e500 PLL (1.1 V)	—	26
AVDD_PLAT	AH19	Powerfor CCB PLL (1.1 V)		26
AVDD_SRDS	U25	Power for SRDSPLL (1.1 V)		26
SENSEVDD	M14	0	V <sub>DD</sub>	13

# Table 71. MPC8548E Pinout Listing (continued)

#### Package Description

# Table 71. MPC8548E Pinout Listing (continued)

Signal	Package Pin Number	Pin Type	Power Supply	Notes
25.These are test signals for factory u	ise only and must be pulled up (100 $\Omega$ –1 k $\Omega$ ) to (	OV <sub>DD</sub> for normal	machine opera	ation.
26.Independent supplies derived from	n board V <sub>DD</sub> .			
27.Recommend a pull-up resistor (~1	$k\Omega$ ) be placed on this pin to OV <sub>DD</sub> .			
29. The following pins must NOT be p HRESET_REQ, TRIG_OUT/READ	oul <u>led down du</u> ring power-on reset: TSEC3_TXD  Y/QUIESCE, MSRCID[2:4], ASLEEP.	[3], TSEC4_TXD	3/TSEC3_TXE	07,
30. This pin requires an external 4.7-k driven.	2 pull-down resistor to prevent PHY from seeing a	valid transmit en	able before it is	actively
31. This pin is only an output in eTSE	C3 FIFO mode when used as Rx flow control.			
32. These pins must be connected to 2	XV <sub>DD</sub> .			
33.TSEC2_TXD1, TSEC2_TX_ER an HRESET assertion.	e multiplexed as cfg_dram_type[0:1]. They must	be valid at powe	r-up, even befo	ore
34. These pins must be pulled to group	nd through a 300- $\Omega$ (±10%) resistor.			
35.When a PCI block is disabled, eith down to select external arbiter if the connect' or terminated through 2–1 connected to any other PCI device. POR config pins—irrespective of w any other PCI device connected or	er the POR config pin that selects between interrere is any other PCI device connected on the PCI 0 k $\Omega$ pull-up resistors with the default of internal. The PCI block drives the PCI <i>n_</i> AD pins if it is context. The block drives the DEVDISR register or the bus.	hal and external a l bus, or leave th arbiter if the PCI nfigured to be th not. It may caus	arbiter must be e PCI <i>n_</i> AD pir <i>n_</i> AD pins are e PCI arbiter— e contention if	e pulled ns as 'no not through there is
36.MDIC0 is grounded through an 18. 1% resistor. These pins are used for	2- $\Omega$ precision 1% resistor and MDIC1 is connected or automatic calibration of the DDR IOs.	ed to GV <sub>DD</sub> throu	gh an 18.2-Ω p	recision
38. These pins must be left floating.				
39. If PCI1 or PCI2 is configured as P Otherwise the processor will not be	CI asynchronous mode, a valid clock must be pro oot up.	ovided on pin PC	I1_CLK or PC	I2_CLK.
40.These pins must be connected to	GND.			
101.This pin requires an external 4.7-	kΩ resistor to GND.			
102.For Rev. 2.x silicon, DMA_DACK POR configuration are don't care.	[0:1] must be 0b11 during POR configuration; for	rev. 1.x silicon, t	he pin values o	during
103.If these pins are not used as GPI $2-10 \text{ k}\Omega$ resistors.	Nn (general-purpose input), they must be pulled	low (to GND) or	high (to LV <sub>DD</sub> )	through
104.These must be pulled low to GNE	D through 2–10 k $\Omega$ resistors if they are not used.			
105.These must be pulled low or high	to $\text{LV}_{\text{DD}}$ through 2–10 k $\Omega$ resistors if they are no	ot used.		
106.For rev. 2.x silicon, DMA_DACK[0 configuration are don't care.	):1] must be 0b10 during POR configuration; for re	v. 1.x silicon, the	pin values duri	ng POR
107.For rev. 2.x silicon, DMA_DACK[C configuration are don't care.	):1] must be 0b01 during POR configuration; for re	v. 1.x silicon, the	pin values duri	ng POR
108.For rev. 2.x silicon, DMA_DACK[C configuration are don't care.	):1] must be 0b11 during POR configuration; for re	v. 1.x silicon, the	pin values duri	ng POR
109. This is a test signal for factory us	e only and must be pulled down (100 $\Omega$ – 1 k $\Omega$ ) t	o GND for norma	al machine ope	eration.
111. If these pins are not used as GPI	Nn (general-purpose input), they must be pulled I	ow (to GND) or h	nigh (to OV <sub>DD</sub> )	through
2-10 K22 HESISIUIS.	during DOP configuration			
112. This pin must not be pulled down	$\alpha$ $\alpha$ $\beta$			
	$\int \int \nabla \nabla D = \int \nabla \nabla \nabla \nabla D = \int \nabla \nabla \nabla \nabla \nabla \nabla D = \int \nabla \nabla$			

Signal	Package Pin Number	Pin Type	Power Supply	<b>Notes</b> 5, 9, 33	
TSEC2_TX_ER	R10	0	LV <sub>DD</sub>		
Three	e-Speed Ethernet Controller (Gigabit Eth	ernet 3)			
TSEC3_TXD[3:0]	TSEC3_TXD[3:0] V8, W10, Y10, W7				
TSEC3_RXD[3:0]	Y1, W3, W5, W4	I	TV <sub>DD</sub>	_	
TSEC3_GTX_CLK	W8	0	TV <sub>DD</sub>	_	
TSEC3_RX_CLK	W2	I	TV <sub>DD</sub>	_	
TSEC3_RX_DV	W1	I	TV <sub>DD</sub>	_	
TSEC3_RX_ER	Y2	I	TV <sub>DD</sub>	_	
TSEC3_TX_CLK	V10	I	TV <sub>DD</sub>	_	
TSEC3_TX_EN	V9	0	TV <sub>DD</sub>	30	
Three	e-Speed Ethernet Controller (Gigabit Eth	ernet 4)			
TSEC4_TXD[3:0]/TSEC3_TXD[7:4]	AB8, Y7, AA7, Y8	0	TV <sub>DD</sub>	1, 5, 9, 29	
TSEC4_RXD[3:0]/TSEC3_RXD[7:4]	AA1, Y3, AA2, AA4	I	TV <sub>DD</sub>	1	
TSEC4_GTX_CLK	AA5	0	TV <sub>DD</sub>		
TSEC4_RX_CLK/TSEC3_COL	Y5	I	TV <sub>DD</sub>	1	
TSEC4_RX_DV/TSEC3_CRS	AA3	I/O	TV <sub>DD</sub>	1, 31	
TSEC4_TX_EN/TSEC3_TX_ER	AB6	0	TV <sub>DD</sub>	1, 30	
· · ·	DUART			•	
UART_CTS[0:1]	AB3, AC5	I	OV <sub>DD</sub>	—	
UART_RTS[0:1]	AC6, AD7	0	OV <sub>DD</sub>	—	
UART_SIN[0:1]	AB5, AC7	I	OV <sub>DD</sub>	—	
UART_SOUT[0:1]	AB7, AD8	0	OV <sub>DD</sub>	_	
· · ·	I <sup>2</sup> C Interface			•	
IIC1_SCL	AG22	I/O	OV <sub>DD</sub>	4, 27	
IIC1_SDA	AG21	I/O	OV <sub>DD</sub>	4, 27	
IIC2_SCL	AG15	I/O	OV <sub>DD</sub>	4, 27	
IIC2_SDA	AG14	AG14 I/O OV <sub>DI</sub>			
· · ·	SerDes				
SD_RX[0:3]	M28, N26, P28, R26	I	XV <sub>DD</sub>	—	
SD_RX[0:3]	M27, N25, P27, R25	I	XV <sub>DD</sub>	—	
SD_TX[0:3]	M22, N20, P22, R20	0	XV <sub>DD</sub>	—	
SD_TX[0:3]	M23, N21, P23, R21	0	XV <sub>DD</sub>	<b>—</b>	
Reserved	W26, Y28, AA26, AB28	—	— —	40	
Reserved	W25, Y27, AA25, AB27	—	_	40	

# Table 72. MPC8547E Pinout Listing (continued)

Package Description

# Table 73. MPC8545E Pinout Listing (continued)

Signal	Package Pin Number	Pin Type	Power Supply	Notes
PCI1_FRAME	AE11	I/O	OV <sub>DD</sub>	2
PCI1_IDSEL	AG9	I	OV <sub>DD</sub>	_
PCI1_REQ64/PCI2_FRAME	AF14	I/O	OV <sub>DD</sub>	2, 5, 10
PCI1_ACK64/PCI2_DEVSEL	V15	I/O	OV <sub>DD</sub>	2
PCI2_CLK	AE28	I	OV <sub>DD</sub>	39
PCI2_IRDY	AD26	I/O	OV <sub>DD</sub>	2
PCI2_PERR	AD25	I/O	OV <sub>DD</sub>	2
PCI2_GNT[4:1]	AE26, AG24, AF25, AE25	0	OV <sub>DD</sub>	5, 9, 35
PCI2_GNT0	AG25	I/O	OV <sub>DD</sub>	_
PCI2_SERR	AD24	I/O	OV <sub>DD</sub>	2,4
PCI2_STOP	AF24	I/O	OV <sub>DD</sub>	2
PCI2_TRDY	AD27	I/O	OV <sub>DD</sub>	2
PCI2_REQ[4:1]	AD28, AE27, W17, AF26	I	OV <sub>DD</sub>	_
PCI2_REQ0	AH25	I/O	OV <sub>DD</sub>	_
	DDR SDRAM Memory Interface			
MDQ[0:63]	L18, J18, K14, L13, L19, M18, L15, L14, A17, B17, A13, B12, C18, B18, B13, A12, H18, F18, J14, F15, K19, J19, H16, K15, D17, G16, K13, D14, D18, F17, F14, E14, A7, A6, D5, A4, C8, D7, B5, B4, A2, B1, D1, E4, A3, B2, D2, E3, F3, G4, J5, K5, F6, G5, J6, K4, J1, K2, M5, M3, J3, J2, L1, M6	I/O	GV <sub>DD</sub>	
MECC[0:7]	H13, F13, F11, C11, J13, G13, D12, M12	I/O	GV <sub>DD</sub>	—
MDM[0:8]	M17, C16, K17, E16, B6, C4, H4, K1, E13	0	GV <sub>DD</sub>	_
MDQS[0:8]	M15, A16, G17, G14, A5, D3, H1, L2, C13	I/O	GV <sub>DD</sub>	_
MDQS[0:8]	L17, B16, J16, H14, C6, C2, H3, L4, D13	I/O	GV <sub>DD</sub>	_
MA[0:15]	A8, F9, D9, B9, A9, L10, M10, H10, K10, G10, B8, E10, B10, G6, A10, L11	Ο	GV <sub>DD</sub>	—
MBA[0:2]	F7, J7, M11	0	GV <sub>DD</sub>	_
MWE	E7	0	GV <sub>DD</sub>	_
MCAS	H7	0	GV <sub>DD</sub>	_
MRAS	L8	0	GV <sub>DD</sub>	_
MCKE[0:3]	F10, C10, J11, H11	0	GV <sub>DD</sub>	11
MCS[0:3]	K8, J8, G8, F8	0	GV <sub>DD</sub>	_
MCK[0:5]	H9, B15, G2, M9, A14, F1	0	GV <sub>DD</sub>	_
MCK[0:5]	J9, A15, G1, L9, B14, F2	0	GV <sub>DD</sub>	_
MODT[0:3]	E6, K6, L7, M7	0	GV <sub>DD</sub>	—

### Package Description

Signal	Package Pin Number	Pin Type	Power Supply	Notes
SENSEVSS	M16	—	—	13
	Analog Signals			
MVREF	A18	l Reference voltage signal for DDR	MVREF	
SD_IMP_CAL_RX	L28	I	200 Ω (±1%) to GND	_
SD_IMP_CAL_TX	AB26	I	100 Ω (±1%) to GND	—
SD_PLL_TPA	U26	0	AVDD_SRDS	24

### Table 74. MPC8543E Pinout Listing (continued)

**Note:** All note references in this table use the same numbers as those for Table 71. See Table 71 for the meanings of these notes.

	Maximum Process	Unit	Notes	
Characteristic	800, 10			
	Min	Мах		
Memory bus clock speed	166	200	MHz	1, 2

### Table 80. Memory Bus Clocking Specifications (MPC8543E)

Notes:

1. **Caution:** The CCB clock to SYSCLK ratio and e500 core to CCB clock ratio settings must be chosen such that the resulting SYSCLK frequency, e500 (core) frequency, and CCB clock frequency do not exceed their respective maximum or minimum operating frequencies. See Section 20.2, "CCB/SYSCLK PLL Ratio," and Section 20.3, "e500 Core PLL Ratio," for ratio settings.

2. The memory bus speed is half of the DDR/DDR2 data rate, hence, half of the platform clock frequency.

# 20.2 CCB/SYSCLK PLL Ratio

The CCB clock is the clock that drives the e500 core complex bus (CCB), and is also called the platform clock. The frequency of the CCB is set using the following reset signals, as shown in Table 81:

- SYSCLK input signal
- Binary value on LA[28:31] at power up

Note that there is no default for this PLL ratio; these signals must be pulled to the desired values. Also note that the DDR data rate is the determining factor in selecting the CCB bus frequency, since the CCB frequency must equal the DDR data rate.

For specifications on the PCI\_CLK, see the PCI 2.2 Specification.

Binary Value of LA[28:31] Signals CCB:SYSCLK Ratio		Binary Value of LA[28:31] Signals	CCB:SYSCLK Ratio	
0000	16:1	1000	8:1	
0001	Reserved	1001	9:1	
0010	2:1	1010	10:1	
0011	3:1	1011	Reserved	
0100	4:1	1100	12:1	
0101	5:1	1101	20:1	
0110	6:1	1110	Reserved	
0111	Reserved	1111	Reserved	

### Table 81. CCB Clock Ratio

# 20.3 e500 Core PLL Ratio

This table describes the clock ratio between the e500 core complex bus (CCB) and the e500 core clock. This ratio is determined by the binary value of LBCTL, LALE, and LGPL2 at power up, as shown in this table.

Binary Value of LBCTL, LALE, LGPL2 Signals	e500 core:CCB Clock Ratio	Binary Value of LBCTL, LALE, LGPL2 Signals	e500 core:CCB Clock Ratio	
000	4:1	100	2:1	
001	9:2	101	5:2	
010	Reserved	110	3:1	
011	3:2	111	7:2	

Table 82. e500 Core to	<b>CCB Clock Ratio</b>
------------------------	------------------------

# 20.4 Frequency Options

Table 83This table shows the expected frequency values for the platform frequency when using a CCB clock to SYSCLK ratio in comparison to the memory bus clock speed.

CCB to SYSCLK Ratio	SYSCLK (MHz)								
	16.66	25	33.33	41.66	66.66	83	100	111	133.33
			ļ	Platform/C	CB Freque	ency (MHz	)		
2									
3								333	400
4						333	400	445	533
5					333	415	500		
6					400	500		-	
8				333	533				
9				375					
10			333	417					
12			400	500					
16		400	533		-				
20	333	500		-					

Table 83. Frequency Options of SYSCLK with Respect to Memory Bus Speeds

**Note:** Due to errata Gen 13 the max sys clk frequency must not exceed 100 MHz if the core clk frequency is below 1200 MHz.

System Design Information

# 22.10 Guidelines for High-Speed Interface Termination

This section provides the guidelines for high-speed interface termination when the SerDes interface is entirely unused and when it is partly unused.

# 22.10.1 SerDes Interface Entirely Unused

If the high-speed SerDes interface is not used at all, the unused pin must be terminated as described in this section.

The following pins must be left unconnected (float):

- SD\_TX[7:0]
- $\overline{\text{SD}}_{\text{TX}}[7:0]$
- Reserved pins T22, T23, M20, M21

The following pins must be connected to GND:

- SD\_RX[7:0]
- <u>SD\_RX</u>[7:0]
- SD\_REF\_CLK
- SD\_REF\_CLK

# NOTE

It is recommended to power down the unused lane through SRDSCR1[0:7] register (offset =  $0xE_0F08$ ) (This prevents the oscillations and holds the receiver output in a fixed state.) that maps to SERDES lane 0 to lane 7 accordingly.

Pins V28 and M26 must be tied to  $XV_{DD}$ . Pins V27 and M25 must be tied to GND through a 300- $\Omega$  resistor.

In Rev 2.0 silicon, POR configuration pin cfg\_srds\_en on TSEC4\_TXD[2]/TSEC3\_TXD[6] can be used to power down SerDes block.

# 22.10.2 SerDes Interface Partly Unused

If only part of the high-speed SerDes interface pins are used, the remaining high-speed serial I/O pins must be terminated as described in this section.

The following pins must be left unconnected (float) if not used:

- SD\_TX[7:0]
- <u>SD\_TX</u>[7:0]
- Reserved pins: T22, T23, M20, M21

The following pins must be connected to GND if not used:

- SD\_RX[7:0]
- $\overline{\text{SD}_{RX}}[7:0]$
- SD\_REF\_CLK

# 23.2 Part Marking

Parts are marked as the example shown in Figure 64.



### Notes:

TWLYYWW is final test traceability code. MMMMM is 5 digit mask number. CCCCC is the country of assembly. This space is left blank if parts are assembled in the United States. YWWLAZ is assembly traceability code.

### Figure 64. Part Marking for CBGA and PBGA Device