

Welcome to E-XFL.COM

What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

Details

E-XF

Product Status	Active
Core Processor	PIC
Core Size	8-Bit
Speed	4MHz
Connectivity	-
Peripherals	Brown-out Detect/Reset, POR, WDT
Number of I/O	13
Program Memory Size	3.5KB (2K x 14)
Program Memory Type	ОТР
EEPROM Size	128 x 8
RAM Size	128 x 8
Voltage - Supply (Vcc/Vdd)	3V ~ 5.5V
Data Converters	-
Oscillator Type	External
Operating Temperature	-40°C ~ 85°C (TA)
Mounting Type	Surface Mount
Package / Case	18-SOIC (0.295", 7.50mm Width)
Supplier Device Package	18-SOIC
Purchase URL	https://www.e-xfl.com/product-detail/microchip-technology/pic16ce625-04i-so

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

2.0 PIC16CE62X DEVICE VARIETIES

A variety of frequency ranges and packaging options are available. Depending on application and production requirements the proper device option can be selected using the information in the PIC16CE62X Product Identification System section at the end of this data sheet. When placing orders, please use this page of the data sheet to specify the correct part number.

2.1 UV Erasable Devices

The UV erasable version, offered in the CERDIP package is optimal for prototype development and pilot programs. This version can be erased and reprogrammed to any of the oscillator modes.

Microchip's PICSTART[®] and PRO MATE[®] programmers both support programming of the PIC16CE62X.

2.2 <u>One-Time-Programmable (OTP)</u> <u>Devices</u>

The availability of OTP devices is especially useful for customers who need the flexibility for frequent code updates and small volume applications. In addition to the program memory, the configuration bits must also be programmed.

2.3 <u>Quick-Turn-Programming (QTP)</u> <u>Devices</u>

Microchip offers a QTP Programming Service for factory production orders. This service is made available for users who chose not to program a medium to high quantity of units and whose code patterns have stabilized. The devices are identical to the OTP devices but with all EPROM locations and configuration options already programmed by the factory. Certain code and prototype verification procedures apply before production shipments are available. Please contact your Microchip Technology sales office for more details.

2.4 <u>Serialized Quick-Turn-Programming</u> (SQTPSM) Devices

Microchip offers a unique programming service where a few user-defined locations in each device are programmed with different serial numbers. The serial numbers may be random, pseudo-random or sequential.

Serial programming allows each device to have a unique number which can serve as an entry-code, password or ID number.

Name	DIP/ SOIC Pin #	SSOP Pin #	I/O/P Type	Buffer Type	Description
OSC1/CLKIN	16	18	I	ST/CMOS	Oscillator crystal input/external clock source input.
OSC2/CLKOUT	15	17	0	_	Oscillator crystal output. Connects to crystal or resonator in crystal oscillator mode. In RC mode, OSC2 pin outputs CLKOUT which has 1/4 the frequency of OSC1, and denotes the instruction cycle rate.
MCLR/VPP	4	4	I/P	ST	Master clear (reset) input/programming voltage input. This pin is an active low reset to the device.
					PORTA is a bi-directional I/O port.
RA0/AN0	17	19	I/O	ST	Analog comparator input
RA1/AN1	18	20	I/O	ST	Analog comparator input
RA2/AN2/VREF	1	1	I/O	ST	Analog comparator input or VREF output
RA3/AN3	2	2	I/O	ST	Analog comparator input /output
RA4/T0CKI	3	3	I/O	ST	Can be selected to be the clock input to the Timer0 timer/counter or a comparator output. Output is open drain type.
					PORTB is a bi-directional I/O port. PORTB can be software programmed for internal weak pull-up on all inputs.
RB0/INT	6	7	I/O	TTL/ST ⁽¹⁾	RB0/INT can also be selected as an external interrupt pin.
RB1	7	8	I/O	TTL	
RB2	8	9	I/O	TTL	
RB3	9	10	I/O	TTL	
RB4	10	11	I/O	TTL	Interrupt on change pin.
RB5	11	12	I/O	TTL	Interrupt on change pin.
RB6	12	13	I/O	TTL/ST ⁽²⁾	Interrupt on change pin. Serial programming clock.
RB7	13	14	I/O	TTL/ST ⁽²⁾	Interrupt on change pin. Serial programming data.
Vss	5	5,6	Р	—	Ground reference for logic and I/O pins.
Vdd	14	15,16	Р	—	Positive supply for logic and I/O pins.
Legend:	0 = 0 	utput Not used = TTL inpu	I/C I = It	D = input/ou = Input	utput P = power ST = Schmitt Trigger input

TABLE 3-1: PIC16CE62X PINOUT DESCRIPTION

Note 1: This buffer is a Schmitt Trigger input when configured as the external interrupt. **Note 2:** This buffer is a Schmitt Trigger input when used in serial programming mode.

FIGURE 4-4: DATA MEMORY MAP FOR THE PIC16CE623/624

File Address	3		File Address			
00h	INDF ⁽¹⁾	INDF ⁽¹⁾	80h			
01h	TMR0	OPTION	81h			
02h	PCL	PCL	82h			
03h	STATUS	STATUS	83h			
04h	FSR	FSR	84h			
05h	PORTA	TRISA	85h			
06h	PORTB	TRISB	86h			
07h			87h			
08h			88h			
09h			89h			
0Ah	PCLATH	PCLATH	8Ah			
0Bh	INTCON	INTCON	8Bh			
0Ch	PIR1	PIE1	8Ch			
0Dh			8Dh			
0Eh		PCON	8Eh			
0Fh			8Fh			
10h		EEINTF	90h			
11h		_	91h			
12h			92h			
13h			93h			
14h			94h			
15h			95h			
16h			96h			
17h			97h			
18h			98h			
19h			99h			
1Ah			9Ah			
1Bh			9Bh			
1Ch			9Ch			
1Dh			9Dh			
1Eh			9Eh			
1Fh	CMCON	VRCON	9Fh			
20h			A0h			
			7.011			
	General					
	Purpose Register					
	riogiotor					
			FEb			
		Accesses				
7Eb		/UN-/FN	FFh			
7 - 11 -	Bank 0	Bank 1				
Unimplemented data memory locations, read as '0'. Note 1: Not a physical register.						

FIGURE 4-5: DATA MEMORY MAP FOR THE PIC16CE625

File Address	6		File Address
00h	INDE(1)		80h
01h	TMB0	OPTION	81h
02h	PCI	PCI	- 82h
02h	STATUS	STATUS	- 83h
04h	FSB	FSB	84h
05h	PORTA	TRISA	- 0-11 85h
05h		TRISA	0011
0011 07h	ТОПТВ	THISD	87h
0711			- 0711 - 00h
001			90h
0.00			0.00
0Bn			8BN
	PIRI	PIET	
		DOON	8Dn
0En		PCON	8En
0⊢h			8Fh
10h		EEINTE	90h
11h			91h
12h			92h
13h			93h
14h			94h
15h			95h
16h			96h
17h			97h
18h			98h
19h			99h
1Ah			9Ah
1Bh			9Bh
1Ch			9Ch
1Dh			9Dh
1Eh			9Eh
1Fh	CMCON	VRCON	9Fh
20h			A0h
	General	General	
	Register	Register	
			BFh
			C0h
		•	F0h
		ACCESSES	
756		7011-7711	FEh
7 - 11 -	Bank 0	Bank 1	
	lomontad data	monulocotions	
	Not a physical region	mory locations, fo	eau as 'U'.
NOLE I.	voi a priysical regis	DIG1.	

4.2.2.2 OPTION REGISTER

The OPTION register is a readable and writable register which contains various control bits to configure the TMR0/WDT prescaler, the external RB0/INT interrupt, TMR0 and the weak pull-ups on PORTB.

Note: To achieve a 1:1 prescaler assignment for TMR0, assign the prescaler to the WDT (PSA = 1).

REGISTER 4-2: OPTION REGISTER (ADDRESS 81H)

R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	
RBPU	INTEDG	TOCS	T0SE	PSA	PS2	PS1	PS0	R = Readable bit
bit7				•		•	bit0	W = Writable bit
								U = Unimplemented bit,
								read as '0'
								-n = Value at POR reset
								-x = Unknown at POR reset
bit 7:	RBPU: PC	RTB Pull	-up Enab	le bit				
	1 = PORTI	B pull-ups	are disa	bled				
	0 = PORTI	B pull-ups	are enat	oled by ind	ividual port	latch valu	es	
bit 6:	INTEDG: I	nterrupt E	Edge Sele	ct bit				
	1 = Interru	pt on risir	ng edge o	f RB0/INT	pin			
	0 = Interru	pt on falliı	ng edge c	of RB0/INT	pin			
hit 5.		BA Clock	Source S	alact hit	•			
DIL 5.		ion on D/						
	$\perp = 11ansit$	linetruoti		pin dook (CLk				
	0 = Interna		on cycle		(001)			
bit 4:	TOSE: TM	R0 Source	e Edge S	elect bit				
	1 = Increm	ent on hig	gh-to-low	transition	on RA4/T00	CKI pin		
	0 = Increm	ent on lo	w-to-high	transition	on RA4/T00	CKI pin		
bit 3:	PSA: Pres	caler Ass	ianment k	oit				
	1 = Presca	ler is ass	igned to t	he WDT				
	0 = Presca	ler is ass	igned to t	he Timer0	module			
bit 2-0 [.]	PS<2:0>	Prescaler	- Rate Sel	ect bits				
	Bit Value	IMR0 R	ate WD	I Rate				
	000	1:2	1	:1				
	001	1:4	1:	: 2				
	010	1:8	1:	: 4				
	011	1:16		0 16				
	101	1 . 32	1	. 10 . 32				
	110	1:12	8 1	: 64				
	111	1:25	6 1	128				

4.2.2.4 PIE1 REGISTER

This register contains the individual enable bit for the comparator interrupt.

REGISTER 4-4: PIE1 REGISTER (ADDRESS 8CH)



4.2.2.5 PIR1 REGISTER

This register contains the individual flag bit for the comparator interrupt.

Note:	Interrupt flag bits get set when an interru								
	condition occurs, regardless of the state of								
	its corresponding enable bit or the global								
	enable bit, GIE (INTCON<7>). User								
	software should ensure the appropriate								
	interrupt flag bits are clear prior to enabling								
	an interrupt.								

REGISTER 4-5: PIR1 REGISTER (ADDRESS 0CH)







FIGURE 7-4: TIMER0 INTERRUPT TIMING



The code example in Example 8-1 depicts the steps required to configure the comparator module. RA3 and RA4 are configured as digital output. RA0 and RA1 are configured as the V- inputs and RA2 as the V+ input to both comparators.

EXAMPLE 8-1: INITIALIZING COMPARATOR MODULE

FLAG_REG	EQU	0X20
CLRF	FLAG_REG	;Init flag register
CLRF	PORTA	;Init PORTA
MOVF	CMCON,W	;Move comparator contents to W
ANDLW	0xC0	;Mask comparator bits
IORWF	FLAG_REG,F	;Store bits in flag register
MOVLW	0x03	;Init comparator mode
MOVWF	CMCON	;CM<2:0> = 011
BSF	STATUS, RPO	;Select Bank1
MOVLW	0x07	;Initialize data direction
MOVWF	TRISA	;Set RA<2:0> as inputs
		;RA<4:3> as outputs
		;TRISA<7:5> always read `0'
BCF	STATUS, RPO	;Select Bank 0
CALL	DELAY 10	;10µs delay
MOVF	CMCON, F	;Read CMCONtoend change condition
BCF	PIR1,CMIF	;Clear pending interrupts
BSF	STATUS, RPO	;Select Bank 1
BSF	PIE1,CMIE	;Enable comparator interrupts
BCF	STATUS, RPO	;Select Bank 0
BSF	INTCON, PEIE	;Enable peripheral interrupts
BSF	INTCON,GIE	;Global interrupt enable

8.2 Comparator Operation

A single comparator is shown in Figure 8-2 along with the relationship between the analog input levels and the digital output. When the analog input at VIN+ is less than the analog input VIN–, the output of the comparator is a digital low level. When the analog input at VIN+ is greater than the analog input VIN–, the output of the comparator is a digital high level. The shaded areas of the output of the comparator in Figure 8-2 represent the uncertainty due to input offsets and response time.

8.3 <u>Comparator Reference</u>

An external or internal reference signal may be used depending on the comparator operating mode. The analog signal that is present at VIN– is compared to the signal at VIN+, and the digital output of the comparator is adjusted accordingly (Figure 8-2).

FIGURE 8-2: SINGLE COMPARATOR



8.3.1 EXTERNAL REFERENCE SIGNAL

When external voltage references are used, the comparator module can be configured to have the comparators operate from the same or different reference sources. However, threshold detector applications may require the same reference. The reference signal must be between VSS and VDD and can be applied to either pin of the comparator(s).

8.3.2 INTERNAL REFERENCE SIGNAL

The comparator module also allows the selection of an internally generated voltage reference for the comparators. Section 13, Instruction Sets, contains a detailed description of the Voltage Reference Module that provides this signal. The internal reference signal is used when the comparators are in mode CM<2:0>=010 (Figure 8-1). In this mode, the internal voltage reference is applied to the VIN+ pin of both comparators.

8.4 Comparator Response Time

Response time is the minimum time, after selecting a new reference voltage or input source, before the comparator output has a valid level. If the internal reference is changed, the maximum delay of the internal voltage reference must be considered when using the comparator outputs, otherwise the maximum delay of the comparators should be used (Table 13-1).

8.5 <u>Comparator Outputs</u>

The comparator outputs are read through the CMCON register. These bits are read only. The comparator outputs may also be directly output to the RA3 and RA4 I/O pins. When the CM<2:0> = 110, multiplexors in the output path of the RA3 and RA4 pins will switch and the output of each pin will be the unsynchronized output of the comparator. The uncertainty of each of the comparators is related to the input offset voltage and the response time given in the specifications. Figure 8-3 shows the comparator output block diagram.

The TRISA bits will still function as an output enable/disable for the RA3 and RA4 pins while in this mode.

- Note 1: When reading the PORT register, all pins configured as analog inputs will read as a '0'. Pins configured as digital inputs will convert an analog input according to the Schmitt Trigger input specification.
 - 2: Analog levels on any pin that is defined as a digital input may cause the input buffer to consume more current than is specified.

FIGURE 8-3: COMPARATOR OUTPUT BLOCK DIAGRAM



Address	Name	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0	Value on: POR	Value on All Other Resets
1Fh	CMCON	C2OUT	C1OUT	_	—	CIS	CM2	CM1	CM0	00 0000	00 0000
9Fh	VRCON	VREN	VROE	VRR	—	VR3	VR2	VR1	VR0	000- 0000	000- 0000
0Bh	INTCON	GIE	PEIE	TOIE	INTE	RBIE	T0IF	INTF	RBIF	0000 000x	0000 000u
0Ch	PIR1	—	CMIF	_	—	—	_	—	—	-0	-0
8Ch	PIE1	—	CMIE	_	—	—	_	—	—	-0	-0
85h	TRISA		_	_	TRISA4	TRISA3	TRISA2	TRISA1	TRISA0	1 1111	1 1111
Logond	_ Unimn	lomontor	h rood oo	"0"	Linknown		hongod				

TABLE 8-1: REGISTERS ASSOCIATED WITH COMPARATOR MODULE

Legend: - = Unimplemented, read as "0", x = Unknown, u = unchanged





FIGURE 10-9: TIME-OUT SEQUENCE ON POWER-UP (MCLR NOT TIED TO VDD): CASE 2



FIGURE 10-10: TIME-OUT SEQUENCE ON POWER-UP (MCLR TIED TO VDD)



^{© 1998-2013} Microchip Technology Inc.

10.6 Context Saving During Interrupts

During an interrupt, only the return PC value is saved on the stack. Typically, users may wish to save key registers during an interrupt (i.e. W register and STATUS register). This will have to be implemented in software.

Example 10-1 stores and restores the STATUS and W registers. The user register, W_TEMP, must be defined in both banks and must be defined at the same offset from the bank base address (i.e., W_TEMP is defined at 0x70 in Bank 0 and it must also be defined at 0xF0 in Bank 1). The user register, STATUS_TEMP, must be defined in Bank 0. The Example 10-1:

- Stores the W register
- Stores the STATUS register in Bank 0
- Executes the ISR code
- Restores the STATUS (and bank select bit register)
- · Restores the W register

EXAMPLE 10-1: SAVING THE STATUS AND W REGISTERS IN RAM

MOVWF	W_TEMP	;copy W to temp register, ;could be in either bank
SWAPF	STATUS,W	;swap status to be saved into $\ensuremath{\mathtt{W}}$
BCF	STATUS, RPO	;change to bank 0 regardless ;of current bank
MOVWF	STATUS_TEMP	;save status to bank 0 ;register
:		
:	(ISR)	
:		
SWAPF	STATUS_TEMP,W	;swap STATUS_TEMP register ;into W, sets bank to original ;state
MOVWF	STATUS	;move W into STATUS register
SWAPF	W_TEMP,F	;swap W_TEMP
SWAPF	W_TEMP,W	;swap W_TEMP into W

10.7 <u>Watchdog Timer (WDT)</u>

The Watchdog Timer is a free running on-chip RC oscillator which does not require any external components. This RC oscillator is separate from the RC oscillator of the CLKIN pin. That means that the WDT will run, even if the clock on the OSC1 and OSC2 pins of the device have been stopped, for example, by execution of a SLEEP instruction. During normal operation, a WDT time-out generates a device RESET. If the device is in SLEEP mode, a WDT time-out causes the device to wake-up and continue with normal operation. The WDT can be permanently disabled by programming the configuration bit WDTE as clear (Section 10.1).

10.7.1 WDT PERIOD

The WDT has a nominal time-out period of 18 ms, (with no prescaler). The time-out periods vary with temperature, VDD and process variations from part to part (see DC specs). If longer time-out periods are desired, a prescaler with a division ratio of up to 1:128 can be assigned to the WDT under software control by writing to the OPTION register. Thus, time-out periods up to 2.3 seconds can be realized.

The CLRWDT and SLEEP instructions clear the WDT and the postscaler, if assigned to the WDT, and prevent it from timing out and generating a device RESET.

The $\overline{\text{TO}}$ bit in the STATUS register will be cleared upon a Watchdog Timer time-out.

10.7.2 WDT PROGRAMMING CONSIDERATIONS

It should also be taken in account that under worst case conditions (VDD = Min., Temperature = Max., max. WDT prescaler), it may take several seconds before a WDT time-out occurs.

10.8 Power-Down Mode (SLEEP)

The Power-down mode is entered by executing a SLEEP instruction.

If enabled, the Watchdog Timer will be cleared but keeps running, the \overline{PD} bit in the STATUS register is cleared, the \overline{TO} bit is set and the oscillator driver is turned off. The I/O ports maintain the status they had before SLEEP was executed (driving high, low, or hi-impedance).

For lowest current consumption in this mode, all I/O pins should be either at VDD or VSS, with no external circuitry drawing current from the I/O pin, and the comparators and VREF should be disabled. I/O pins that are hi-impedance inputs should be pulled high or low externally to avoid switching currents caused by floating inputs. The TOCKI input should also be at VDD or VSS for lowest current consumption. The contribution from on chip pull-ups on PORTB should be considered.

The MCLR pin must be at a logic high level (VIHMC).

Note:	It should be noted that a RESET generated
	by a WDT time-out does not drive MCLR
	pin low.

10.8.1 WAKE-UP FROM SLEEP

The device can wake-up from SLEEP through one of the following events:

- 1. External reset input on MCLR pin
- 2. Watchdog Timer Wake-up (if WDT was enabled)
- 3. Interrupt from RB0/INT pin, RB Port change, or the Peripheral Interrupt (Comparator).

The first event will cause a device reset. The two latter events are considered a continuation of program execution. The \overline{TO} and \overline{PD} bits in the STATUS register can be used to determine the cause of device reset. \overline{PD} bit, which is set on power-up is cleared when SLEEP is invoked. \overline{TO} bit is cleared if WDT wake-up occurred.

When the SLEEP instruction is being executed, the next instruction (PC + 1) is pre-fetched. For the device to wake-up through an interrupt event, the corresponding interrupt enable bit must be set (enabled). Wake-up is regardless of the state of the GIE bit. If the GIE bit is clear (disabled), the device continues execution at the instruction after the SLEEP instruction. If the GIE bit is set (enabled), the device executes the instruction after the SLEEP instruction after the SLEEP instruction after the instruction and then branches to the interrupt address (0004h). In cases where the execution of the instruction following SLEEP is not desirable, the user should have an NOP after the SLEEP instruction.

If the global interrupts are disabled (GIE is
cleared), but any interrupt source has both
its interrupt enable bit and the correspond-
ing interrupt flag bits set, the device will
immediately wake-up from sleep. The
sleep instruction is completely executed.

The WDT is cleared when the device wakes-up from sleep, regardless of the source of wake-up.

; a1 a2 a3 a4 ; a1 a2 a3 a osc1////////////////////////////////////	4 Q1	a1 a2 a3 a4	a1 a2 a3 a4	; a1 a2 a3 a4 /~	; a1 a2 a3 a4; ////////////////////////////////////
CLKOUT(4)	Tost(2)		\/	<u>\</u> /	\ł
INT pin INTF flag (INTCON<1>) GIE bit (INTCON<7>)	Processor in SLEEP		Interrupt Latency		
INSTRUCTION FLOW			I I	I I	
PC PC PC+1	PC+2	X PC+2	X PC + 2	X 0004h	X 0005h
$\begin{array}{l} \text{Instruction} \\ \text{fetched} \end{array} \left\{ \begin{array}{l} \text{Inst(PC)} = \text{SLEEP} & \text{Inst(PC + 1)} \end{array} \right.$		Inst(PC + 2)	1 1 1	Inst(0004h)	Inst(0005h)
Instruction { Inst(PC - 1) SLEEP	1 1 1	Inst(PC + 1)	Dummy cycle	Dummy cycle	Inst(0004h)

FIGURE 10-19: WAKE-UP FROM SLEEP THROUGH INTERRUPT

Note 1: XT, HS or LP oscillator mode assumed.

2: TOST = 1024TOSC (drawing not to scale) This delay does not occur for RC osc mode.

3: GIE = '1' assumed. In this case after wake- up, the processor jumps to the interrupt routine. If GIE = '0', execution will continue in-line.

4: CLKOUT is not available in these osc modes, but shown here for timing reference.

10.9 <u>Code Protection</u>

If the code protection bit(s) have not been programmed, the on-chip program memory can be read out for verification purposes.

Note:	Microchip	does	not	recommend	code
	protecting	windov	ved d	evices.	

10.10 ID Locations

Four memory locations (2000h-2003h) are designated as ID locations where the user can store checksum or other code-identification numbers. These locations are not accessible during normal execution but are readable and writable during program/verify. Only the least significant 4 bits of the ID locations are used.

10.11 In-Circuit Serial Programming

The PIC16CE62X microcontrollers can be serially programmed while in the end application circuit. This is simply done with two lines for clock and data, and three other lines for power, ground, and the programming voltage. This allows customers to manufacture boards with unprogrammed devices, and then program the microcontroller just before shipping the product. This also allows the most recent firmware or a custom firmware to be programmed.

The device is placed into a program/verify mode by holding the RB6 and RB7 pins low, while raising the MCLR (VPP) pin from VIL to VIHH (see programming specification). RB6 becomes the programming clock and RB7 becomes the programming data. Both RB6 and RB7 are Schmitt Trigger inputs in this mode.

After reset, to place the device into programming/verify mode, the program counter (PC) is at location 00h. A 6-bit command is then supplied to the device. Depending on the command, 14-bits of program data are then supplied to or from the device, depending if the command was a load or a read. For complete details of serial programming, please refer to the PIC16C6X/7X/9XX Programming Specifications (Literature #DS30228).

A typical in-circuit serial programming connection is shown in Figure 10-20.

FIGURE 10-20: TYPICAL IN-CIRCUIT SERIAL PROGRAMMING CONNECTION



11.0 INSTRUCTION SET SUMMARY

Each PIC16CE62X instruction is a 14-bit word divided into an OPCODE which specifies the instruction type and one or more operands which further specify the operation of the instruction. The PIC16CE62X instruction set summary in Table 11-2 lists **byte-oriented**, **bit-oriented**, and **literal and control** operations. Table 11-1 shows the opcode field descriptions.

For **byte-oriented** instructions, 'f' represents a file register designator and 'd' represents a destination designator. The file register designator specifies which file register is to be used by the instruction.

The destination designator specifies where the result of the operation is to be placed. If 'd' is zero, the result is placed in the W register. If 'd' is one, the result is placed in the file register specified in the instruction.

For **bit-oriented** instructions, 'b' represents a bit field designator which selects the number of the bit affected by the operation, while 'f' represents the number of the file in which the bit is located.

For **literal and control** operations, 'k' represents an eight or eleven bit constant or literal value.

TABLE 11-1: OPCODE FIELD DESCRIPTIONS

Field	Description
f	Register file address (0x00 to 0x7F)
W	Working register (accumulator)
b	Bit address within an 8-bit file register
k	Literal field, constant data or label
x	Don't care location (= 0 or 1) The assembler will generate code with $x = 0$. It is the recommended form of use for compatibility with all Microchip software tools.
d	Destination select; d = 0: store result in W, d = 1: store result in file register f. Default is d = 1
label	Label name
TOS	Top of Stack
PC	Program Counter
PCLATH	Program Counter High Latch
GIE	Global Interrupt Enable bit
WDT	Watchdog Timer/Counter
TO	Time-out bit
PD	Power-down bit
dest	Destination either the W register or the specified register file location
[]	Options
()	Contents
\rightarrow	Assigned to
<>	Register bit field
∈	In the set of
italics	User defined term (font is courier)

The instruction set is highly orthogonal and is grouped into three basic categories:

- Byte-oriented operations
- Bit-oriented operations
- Literal and control operations

All instructions are executed within one single instruction cycle, unless a conditional test is true or the program counter is changed as a result of an instruction. In this case, the execution takes two instruction cycles with the second cycle executed as a NOP. One instruction cycle consists of four oscillator periods. Thus, for an oscillator frequency of 4 MHz, the normal instruction execution time is 1 μ s. If a conditional test is true or the program counter is changed as a result of an instruction, the instruction execution time is 2 μ s.

Table 11-1 lists the instructions recognized by the MPASM assembler.

Figure 11-1 shows the three general formats that the instructions can have.

Note:	То	maintain	upward	compatibility	with
	futu	ire PIC [®] M	ICU produ	ucts, <u>do not us</u>	<u>e</u> the
	OP	TION and 1	TRIS inst	ructions.	

All examples use the following format to represent a hexadecimal number:

0xhh

where h signifies a hexadecimal digit.

FIGURE 11-1: GENERAL FORMAT FOR INSTRUCTIONS



 <sup>13
 11
 10
 0</sup> OPCODE
 k (literal)
 k
 11-bit immediate value

^{© 1998-2013} Microchip Technology Inc.

TABLE 11-2: PIC16CE62X INSTRUCTION SET

Mnemonic,		Description	Cycles		14-Bit	Opcode	•	Status	Notes
Operands				MSb			LSb	Affected	
BYTE-ORIE	NTED	FILE REGISTER OPERATIONS							
ADDWF	f, d	Add W and f	1	00	0111	dfff	ffff	C,DC,Z	1,2
ANDWF	f, d	AND W with f	1	00	0101	dfff	ffff	Z	1,2
CLRF	f	Clear f	1	00	0001	lfff	ffff	Z	2
CLRW	-	Clear W	1	00	0001	0000	0011	Z	
COMF	f, d	Complement f	1	00	1001	dfff	ffff	Z	1,2
DECF	f, d	Decrement f	1	00	0011	dfff	ffff	Z	1,2
DECFSZ	f, d	Decrement f, Skip if 0	1(2)	00	1011	dfff	ffff		1,2,3
INCF	f, d	Increment f	1	00	1010	dfff	ffff	Z	1,2
INCFSZ	f, d	Increment f, Skip if 0	1(2)	00	1111	dfff	ffff		1,2,3
IORWF	f, d	Inclusive OR W with f	1	00	0100	dfff	ffff	Z	1,2
MOVF	f, d	Move f	1	00	1000	dfff	ffff	Z	1,2
MOVWF	f	Move W to f	1	00	0000	lfff	ffff		
NOP	-	No Operation	1	00	0000	0xx0	0000		
RLF	f, d	Rotate Left f through Carry	1	00	1101	dfff	ffff	С	1,2
RRF	f, d	Rotate Right f through Carry	1	00	1100	dfff	ffff	С	1,2
SUBWF	f, d	Subtract W from f	1	00	0010	dfff	ffff	C,DC,Z	1,2
SWAPF	f, d	Swap nibbles in f	1	00	1110	dfff	ffff		1,2
XORWF	f, d	Exclusive OR W with f	1	00	0110	dfff	ffff	Z	1,2
BIT-ORIENT	ED FIL	E REGISTER OPERATIONS							
BCF	f, b	Bit Clear f	1	01	00bb	bfff	ffff		1,2
BSF	f, b	Bit Set f	1	01	01bb	bfff	ffff		1,2
BTFSC	f, b	Bit Test f, Skip if Clear	1 (2)	01	10bb	bfff	ffff		3
BTFSS	f, b	Bit Test f, Skip if Set	1 (2)	01	11bb	bfff	ffff		3
LITERAL AND CONTROL OPERATIONS									
ADDLW	k	Add literal and W	1	11	111x	kkkk	kkkk	C,DC,Z	
ANDLW	k	AND literal with W	1	11	1001	kkkk	kkkk	Z	
CALL	k	Call subroutine	2	10	0kkk	kkkk	kkkk		
CLRWDT	-	Clear Watchdog Timer	1	00	0000	0110	0100	TO,PD	
GOTO	k	Go to address	2	10	1kkk	kkkk	kkkk		
IORLW	k	Inclusive OR literal with W	1	11	1000	kkkk	kkkk	Z	
MOVLW	k	Move literal to W	1	11	00xx	kkkk	kkkk		
RETFIE	-	Return from interrupt	2	00	0000	0000	1001		
RETLW	k	Return with literal in W	2	11	01xx	kkkk	kkkk		
RETURN	-	Return from Subroutine	2	00	0000	0000	1000		
SLEEP	-	Go into standby mode	1	00	0000	0110	0011	TO,PD	
SUBLW	k	Subtract W from literal	1	11	110x	kkkk	kkkk	C,DC,Z	
XORLW	k	Exclusive OR literal with W	1	11	1010	kkkk	kkkk	Z	

Note 1: When an I/O register is modified as a function of itself (e.g., MOVF PORTB, 1), the value used will be that value present on the pins themselves. For example, if the data latch is '1' for a pin configured as input and is driven low by an external device, the data will be written back with a '0'.

2: If this instruction is executed on the TMR0 register (and, where applicable, d = 1), the prescaler will be cleared if assigned to the Timer0 Module.

3: If Program Counter (PC) is modified or a conditional test is true, the instruction requires two cycles. The second cycle is executed as a NOP.

TABLE 12-1: DEVELOPMENT TOOLS FROM MICROCHIP

Metallicity (Metallicity) Metallicity (Metallicity) Me		PIC12CXXX	PIC14000	PIC16C5X	PIC16C6X	PIC16CXXX	PIC16F62X	X7281519	XX7Oðfolg	PIC16C8X	PIC16F8XX	PIC16C9XX	X4071019	XX7371319	PIC18CXX2	83CXX 52CXX/ 54CXX/	хххээн	MCRFXXX	MCP2510
Bit Add C 17 Complex Source in the contraction of the control of the co	MPLAB [®] Integrated Development Environment	~	~	>	>	>	>	>	>	>	>	>	>	>	>				
MAME Complex Image Complex Complex <th>MPLAB[®] C17 Compiler</th> <th></th> <th>></th> <th>></th> <th></th> <th></th> <th></th> <th></th> <th></th>	MPLAB [®] C17 Compiler												>	>					
Mediatricity × <t< th=""><th>MPLAB[®] C18 Compiler</th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th>></th><th></th><th></th><th></th><th></th></t<>	MPLAB [®] C18 Compiler														>				
MPAR8 ¹⁶ -LE V <t< td=""><td>MPASM/MPLINK</td><td>></td><td>></td><td>></td><td>></td><td>></td><td>></td><td>></td><td>></td><td>></td><td>></td><td>></td><td>></td><td>></td><td>></td><td>></td><td>></td><td></td><td></td></t<>	MPASM/MPLINK	>	>	>	>	>	>	>	>	>	>	>	>	>	>	>	>		
PICHARGE /<	2 MPLAB [®] -ICE	~	>	>	>	>	** ^	>	>	>	>	>	>	>	>				
Closette funder Image: Closete funder Image: Closefunder	PICMASTER/PICMASTER-CE	~	>	>	>	>		>	>	>		>	>	>					
MetaBolic Statisticati Not Statist	ICEPIC™ Low-Cost In-Circuit Emulator	~		~	>	>		>	>	>		`							
PICSTART® Plus. V	0 99 MPLAB [®] -ICD In-Circuit Debugger				*>			* >			>								
PRIONATE® IL Contract Programmer Contended Programer ContrendeProgrammer	PICSTART®Plus Low-Cost Universal Dev. Kit	>	~	~	`	>	**>	`	>	`	>	>	>	`	>				
Since v <td>BRO MATE® II Universal Programmer</td> <td>></td> <td>></td> <td>></td> <td>></td> <td>></td> <td>** ></td> <td>></td> <td></td> <td></td>	BRO MATE® II Universal Programmer	>	>	>	>	>	** >	>	>	>	>	>	>	>	>	>	>		
PICDEM-1 ·<	SIMICE	~		>															
PICDEM-3 PICDEM-3 ···· ···· ···· ···· ···· ···· ···· ···· ···· ···· ···· ···· ···· ···· ···· ···· ····· ····· ····· ····· ····· ····· ····· ······ ······ ······· ·······	PICDEM-1			>		>		<+ <		>			>						
PICDEM-3 PICDEM-1 ·	PICDEM-2				+∽			↓							>				
PICDEM:14 (PICDEM-3											>							
Pictore Defendent	PICDEM-14A		>																
KEELO0® Evaluation Kit Image: market in the image: ma	PICDEM-17													~					
KEELOO Transponder Kit Image: market in the image: ma	KEELoo® Evaluation Kit																~		
IndecolD1 ^{rm} Programmer's Kit Indecol	KEELoo Transponder Kit																~		
125 kHz microID Developer's Kit 125 kHz microID Developer's Kit 1 125 kHz Anticollision microID 1 1 125 kHz Anticollision microID 1 1 13.56 MHz Anticollision microID 1 1 1 13.56 MHz Anticollision microID 1 1 1 1	microlD™ Programmer's Kit																	~	
125 KHz Anticollision microlD 125 KHz Anticollision microlD Developer's Klt 13.56 MHz Anticollision microlD 13.56 MHz Anticollision microlD 13.56 MHz Anticollision microlD Developer's Klt 1	125 kHz microID Developer's Kit																	~	
13.56 MHz Anticollision microlD 13.56 MHz Anticollision microlD Developer's Kit MCP2510 CAN Developer's Kit	7 125 kHz Anticollision microlD Developer's Kit																	>	
MCP2510 CAN Developer's Kit	13.56 MHz Anticollision microID Developer's Kit																	~	
	MCP2510 CAN Developer's Kit																		`

** Contact Microchip Technology Inc. for availability [†] Development tool is available on select devices.

13.2 DC CHARACTERISTICS: F

PIC16LCE62X-04 (Commercial, Industrial)

				Standard Operating Conditions (unless otherwise stated)					
DC CH		STICS	Operating temperature $-40^{\circ}C \le TA \le +85^{\circ}C$ for industrial and $0^{\circ}C \le TA \le +70^{\circ}C$ for commercial and						
				-40° C \leq TA \leq +125°C for extende					
Param	Sym	Characteristic	Min	Typ†	Max	Units	Conditions		
No.									
D001	Vdd	Supply Voltage	2.5	-	5.5	V	See Figure 13-1 through Figure 13-3		
D002	Vdr	RAM Data Retention Voltage (Note 1)	-	1.5*	-	V	Device in SLEEP mode		
D003	VPOR	VDD start voltage to ensure Power-on Reset	-	Vss	-	V	See section on power-on reset for details		
D004	SVDD	VDD rise rate to ensure Power-on Reset	.05*	-	-	V/ms	See section on power-on reset for details		
D005	VBOR	Brown-out Detect Voltage	3.7	4.0	4.35	V	BOREN configuration bit is cleared		
D010	IDD	Supply Current (Note 2)	-	1.2	2.0	mA	Fosc = 4 MHz, VDD = 5.5V, WDT disabled,		
							XT osc mode, (Note 4)*		
			-	_	1.1	mA	FOSC = 4 MHZ, $VDD = 2.5V$, WDT disabled, XT osc mode (Note 4)		
			_	35	70	μA	Fosc = 32 kHz , VDD = 2.5V, WDT disabled,		
						•	LP osc mode		
D020	IPD	Power Down Current (Note 3)	-	-	2.0	μA	VDD = 2.5V		
			-	-	2.2	μA	VDD = 3.0V*		
			-	-	9.0	μA	VDD = 5.5V		
Dooo	Alwor		_	-	10	μΑ			
D022	AIWDT	WDT Current (Note 5)	-	6.0	10	μΑ	VDD=4.0V (125°C)		
D022A	AIBOB	Brown-out Beset Current	_	75	125	μΑ	$\frac{(123)}{BOD}$ enabled, VDD = 5.0V		
	2.001	(Note 5)			0	po t			
D023	Δ ICOMP	Comparator Current for each	-	30	60	μA	VDD = 4.0V		
00004		Comparator (Note 5)		80	105	A	$V_{DD} = 4.0 V_{c}$		
DUZSA		Operating Current	_	80	135	μA mA	$V_{DD} = 4.0V$		
		Operating Current	_		3 1	mA	VCC = 5.5V, SCL = 400 KHZ		
		Standby Current	_		30	uА	$V_{CC} = 3.0V$. EE VDD = VCC		
	ΔIEE	Standby Current	-		100	μA	VCC = 3.0V, EE VDD = VCC		
1A	Fosc	LP Oscillator Operating Frequency	0		200	kHz	All temperatures		
		RC Oscillator Operating Frequency	0	—	4	MHz	All temperatures		
		XT Oscillator Operating Frequency	0	—	4	MHz	All temperatures		
		HS Oscillator Operating Frequency	0	—	20	MHz	All temperatures		

* These parameters are characterized but not tested.

† Data in "Typ" column is at 5.0V, 25°C, unless otherwise stated. These parameters are for design guidance only and are not tested.

Note 1: This is the limit to which VDD can be lowered in SLEEP mode without losing RAM data.

2: The supply current is mainly a function of the operating voltage and frequency. Other factors such as I/O pin loading and switching rate, oscillator type, internal code execution pattern, and temperature also have an impact on the current consumption.

The test conditions for all IDD measurements in active operation mode are:

OSC1 = external square wave, from rail to rail; all I/O pins tri-stated, pulled to VDD,

MCLR = VDD; WDT enabled/disabled as specified.

3: The power down current in SLEEP mode does not depend on the oscillator type. Power down current is measured with the part in SLEEP mode, with all I/O pins in hi-impedance state and tied to VDD or Vss.

4: For RC osc configuration, current through Rext is not included. The current through the resistor can be estimated by the formula Ir = VDD/2Rext (mA) with Rext in k Ω .

5: The Δ current is the additional current consumed when this peripheral is enabled. This current should be added to the base IDD or IPD measurement.

6: Commercial temperature range only.

INDEX

Α	
ADDLW Instruction	
ADDWF Instruction	
ANDLW Instruction	
ANDWF Instruction	
Architectural Overview	7
Assembler	
MPASM Assembler	77
в	

В

BCF Instruction	
Block Diagram	
TIMER0	35
TMR0/WDT PRESCALER	
Brown-Out Detect (BOD)	
BSF Instruction	68
BTFSC Instruction	
BTFSS Instruction	
С	

CALL Instruction	
Clocking Scheme/Instruction Cycle	10
CLRF Instruction	69
CLRW Instruction	69
CLRWDT Instruction	70
CMCON Register	
Code Protection	64
COMF Instruction	
Comparator Configuration	42
Comparator Interrupts	45
Comparator Module	41
Comparator Operation	
Comparator Reference	
Configuration Bits	50
Configuring the Voltage Reference	47
Crystal Operation	51
_	

D

Data Memory Organization	12
DECF Instruction	70
DECFSZ Instruction	70
Development Support	77
E	

Е

EEPROM Peripheral Operation	29
Errata	2
External Crystal Oscillator Circuit	52

G

General purpose Register File	12
GOTO Instruction	71

L

I/O Ports	23
I/O Programming Considerations	
ID Locations	64
INCF Instruction	71
INCFSZ Instruction	71
In-Circuit Serial Programming	64
Indirect Addressing, INDF and FSR Registers	21
Instruction Flow/Pipelining	10
Instruction Set	
ADDLW	67
ADDWF	67
ANDLW	67
ANDWF	67
BCF	68
BSF	
-	

BTFSC	68
BTFSS	69
CALL	69
	69
	09 70
COMF	70
DECF	70
DECFSZ	70
GOTO	71
	71
	/1 71
IORWE	72
MOVF	72
MOVLW	72
MOVWF	72
NOP	73
OPTION	73
	73
BETURN	74
RLF	74
RRF	74
SLEEP	74
SUBLW	75
SUBWF	75
TRIS	76
	76
XORLW	76
XORUW	76 65
XORLW XORWF Instruction Set Summary INT Interrupt	76 65 60
XORUW XORWF Instruction Set Summary INT Interrupt INTCON Register	76 65 60 17
XORUWXORWF Instruction Set Summary INT Interrupt INTCON Register Interrupts	76 65 60 17 59 71
XORLW XORWF Instruction Set Summary INT Interrupt INTCON Register. Interrupts IORLW Instruction IORWF Instruction	76 65 60 17 59 71 72
XORUF Instruction Set Summary INT Interrupt INTCON Register Interrupts IORLW Instruction IORWF Instruction K	76 65 60 17 59 71 72
XORWF	76 65 60 17 59 71 72 80
XORWF	76 65 60 17 59 71 72 80
XORWF	76 65 60 17 59 71 72 80
XORWF	76 65 60 17 59 71 72 80 72 72
XORWF	 76 65 60 17 59 71 72 80 72 72 72 72 72 72 72 72
XORWF	76 65 60 17 59 71 72 80 72 72 72 72 72
XORUF XORWF Instruction Set Summary INT Interrupt INTCON Register Interrupts IORLW Instruction IORWF Instruction IORWF Instruction K KeeLoq® Evaluation and Programming Tools M MOVF Instruction MOVLW Instruction MOVLW Instruction MOVLW Instruction MOVLW Instruction MOVWF Instruction MOVWF Instruction MOVWF Instruction MOVWF Instruction MOVWF Instruction MOVWF Instruction MOVWF Instruction MOVAB Integrated Development Environment Software N	76 65 60 17 59 71 72 80 72 72 72 77
XORUFXORWF	76 65 60 17 59 71 72 80 72 72 72 72 77 73
XORUFXORWF Instruction Set Summary INT Interrupt INTCON Register INTCON	76 65 60 17 59 71 72 80 72 72 72 77 73
XORWF	76 65 60 17 59 71 72 80 72 72 77 73 . 5
XORWF	76 65 60 17 59 71 72 80 72 72 72 77 73 . 5 73
XORUF	76 65 60 17 59 71 72 80 72 72 72 77 73 . 5 73 16
XORUF	76 65 60 17 59 71 80 72 72 73 .5 73 .5 73 .5 73 .5 73 .5 73
XORWF	76 65 60 17 59 71 72 80 72 77 73 .5 73 .5 51 54
XORWF	76 65 60 17 59 71 72 80 72 72 77 73 . 5 73 16 51 54
XORUFXORWFXORWFXORWFXORWFXORWFXORWFXORWFXORWFXORWFXORWFXORWFXORWFXORWFXORWFXORWFXORWFXORWF INSTRUCTIONXORWF InstructionXORVF INSTRUCTIONX	76 60 65 60 17 59 71 72 80 722 77 73 . 53 16 51 54 01 54
XORUF	76 660 17 59 71 72 80 7272 73 .53 16 51 54 01 97 20
XORUFXORWF .	76 660 17 59 72 72 77 73 .53 16 54 01 97 20 197 20
XORUFXORWF INSTRUCTIONXORWF INSTRUCTIONXORVF INSTRUCTIONYORVF INSTRUCTIONYORV	76 60 60 179 70 77 70 77 71 73 73 16 10 10 70 73 71 10 71 73 73 16 74 10 75 10 76 10 77 73 73 10 74 10 75 10 76 10 77 73 73 10 74 10 75 10 76 10 77 73 73 10 74 10 75 10 76 10 77 10 77 10 77 10 77 10 77 10 77 10 77 10 77 10
XORWF	76560175972 80727277 73.531651 9720197979

PICSTART® Plus Entry Level Development System 79 PIE1 Register 18 PIR1 Register 18

Note the following details of the code protection feature on Microchip devices:

- Microchip products meet the specification contained in their particular Microchip Data Sheet.
- Microchip believes that its family of products is one of the most secure families of its kind on the market today, when used in the intended manner and under normal conditions.
- There are dishonest and possibly illegal methods used to breach the code protection feature. All of these methods, to our knowledge, require using the Microchip products in a manner outside the operating specifications contained in Microchip's Data Sheets. Most likely, the person doing so is engaged in theft of intellectual property.
- Microchip is willing to work with the customer who is concerned about the integrity of their code.
- Neither Microchip nor any other semiconductor manufacturer can guarantee the security of their code. Code protection does not mean that we are guaranteeing the product as "unbreakable."

Code protection is constantly evolving. We at Microchip are committed to continuously improving the code protection features of our products. Attempts to break Microchip's code protection feature may be a violation of the Digital Millennium Copyright Act. If such acts allow unauthorized access to your software or other copyrighted work, you may have a right to sue for relief under that Act.

Information contained in this publication regarding device applications and the like is provided only for your convenience and may be superseded by updates. It is your responsibility to ensure that your application meets with your specifications. MICROCHIP MAKES NO REPRESENTATIONS OR WARRANTIES OF ANY KIND WHETHER EXPRESS OR IMPLIED, WRITTEN OR ORAL, STATUTORY OR OTHERWISE, RELATED TO THE INFORMATION, INCLUDING BUT NOT LIMITED TO ITS CONDITION, QUALITY, PERFORMANCE, MERCHANTABILITY OR FITNESS FOR PURPOSE. Microchip disclaims all liability arising from this information and its use. Use of Microchip devices in life support and/or safety applications is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless Microchip from any and all damages, claims, suits, or expenses resulting from such use. No licenses are conveyed, implicitly or otherwise, under any Microchip intellectual property rights.

QUALITY MANAGEMENT SYSTEM CERTIFIED BY DNV = ISO/TS 16949=

Trademarks

The Microchip name and logo, the Microchip logo, dsPIC, FlashFlex, KEELOQ, KEELOQ logo, MPLAB, PIC, PICmicro, PICSTART, PIC³² logo, rfPIC, SST, SST Logo, SuperFlash and UNI/O are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

FilterLab, Hampshire, HI-TECH C, Linear Active Thermistor, MTP, SEEVAL and The Embedded Control Solutions Company are registered trademarks of Microchip Technology Incorporated in the U.S.A.

Silicon Storage Technology is a registered trademark of Microchip Technology Inc. in other countries.

Analog-for-the-Digital Age, Application Maestro, BodyCom, chipKIT, chipKIT logo, CodeGuard, dsPICDEM, dsPICDEM.net, dsPICworks, dsSPEAK, ECAN, ECONOMONITOR, FanSense, HI-TIDE, In-Circuit Serial Programming, ICSP, Mindi, MiWi, MPASM, MPF, MPLAB Certified logo, MPLIB, MPLINK, mTouch, Omniscient Code Generation, PICC, PICC-18, PICDEM, PICDEM.net, PICkit, PICtail, REAL ICE, rfLAB, Select Mode, SQI, Serial Quad I/O, Total Endurance, TSHARC, UniWinDriver, WiperLock, ZENA and Z-Scale are trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

SQTP is a service mark of Microchip Technology Incorporated in the U.S.A.

GestIC and ULPP are registered trademarks of Microchip Technology Germany II GmbH & Co. & KG, a subsidiary of Microchip Technology Inc., in other countries.

All other trademarks mentioned herein are property of their respective companies.

© 1998-2013, Microchip Technology Incorporated, Printed in the U.S.A., All Rights Reserved.

Printed on recycled paper.

ISBN: 9781620769768

Microchip received ISO/TS-16949:2009 certification for its worldwide headquarters, design and wafer fabrication facilities in Chandler and Tempe, Arizona; Gresham, Oregon and design centers in California and India. The Company's quality system processes and procedures are for its PIC® MCUs and dsPIC® DSCs, KEEL0Q® code hopping devices, Serial EEPROMs, microperipherals, nonvolatile memory and analog products. In addition, Microchip's quality system for the design and mulfacture of development systems is ISO 9001:2000 certified.

Worldwide Sales and Service

AMERICAS

Corporate Office 2355 West Chandler Blvd. Chandler, AZ 85224-6199 Tel: 480-792-7200 Fax: 480-792-7277 Technical Support: http://www.microchip.com/ support Web Address: www.microchip.com

Atlanta Duluth, GA Tel: 678-957-9614 Fax: 678-957-1455

Boston Westborough, MA Tel: 774-760-0087 Fax: 774-760-0088

Chicago Itasca, IL Tel: 630-285-0071 Fax: 630-285-0075

Cleveland Independence, OH Tel: 216-447-0464 Fax: 216-447-0643

Dallas Addison, TX Tel: 972-818-7423 Fax: 972-818-2924

Detroit Farmington Hills, MI Tel: 248-538-2250 Fax: 248-538-2260

Indianapolis Noblesville, IN Tel: 317-773-8323 Fax: 317-773-5453

Los Angeles Mission Viejo, CA Tel: 949-462-9523 Fax: 949-462-9608

Santa Clara Santa Clara, CA Tel: 408-961-6444 Fax: 408-961-6445

Toronto Mississauga, Ontario, Canada Tel: 905-673-0699 Fax: 905-673-6509

ASIA/PACIFIC

Asia Pacific Office Suites 3707-14, 37th Floor Tower 6, The Gateway Harbour City, Kowloon Hong Kong Tel: 852-2401-1200 Fax: 852-2401-3431 Australia - Sydney Tel: 61-2-9868-6733

Fax: 61-2-9868-6755 China - Beijing

Tel: 86-10-8569-7000 Fax: 86-10-8528-2104

China - Chengdu Tel: 86-28-8665-5511 Fax: 86-28-8665-7889

China - Chongqing Tel: 86-23-8980-9588 Fax: 86-23-8980-9500

China - Hangzhou Tel: 86-571-2819-3187 Fax: 86-571-2819-3189

China - Hong Kong SAR Tel: 852-2943-5100 Fax: 852-2401-3431

China - Nanjing Tel: 86-25-8473-2460 Fax: 86-25-8473-2470

China - Qingdao Tel: 86-532-8502-7355 Fax: 86-532-8502-7205

China - Shanghai Tel: 86-21-5407-5533 Fax: 86-21-5407-5066

China - Shenyang Tel: 86-24-2334-2829 Fax: 86-24-2334-2393

China - Shenzhen Tel: 86-755-8864-2200 Fax: 86-755-8203-1760

China - Wuhan Tel: 86-27-5980-5300 Fax: 86-27-5980-5118

China - Xian Tel: 86-29-8833-7252 Fax: 86-29-8833-7256

China - Xiamen Tel: 86-592-2388138 Fax: 86-592-2388130

China - Zhuhai Tel: 86-756-3210040 Fax: 86-756-3210049

ASIA/PACIFIC

India - Bangalore Tel: 91-80-3090-4444 Fax: 91-80-3090-4123

India - New Delhi Tel: 91-11-4160-8631 Fax: 91-11-4160-8632

India - Pune Tel: 91-20-2566-1512 Fax: 91-20-2566-1513

Japan - Osaka Tel: 81-6-6152-7160 Fax: 81-6-6152-9310

Japan - Tokyo Tel: 81-3-6880- 3770 Fax: 81-3-6880-3771

Korea - Daegu Tel: 82-53-744-4301 Fax: 82-53-744-4302

Korea - Seoul Tel: 82-2-554-7200 Fax: 82-2-558-5932 or 82-2-558-5934

Malaysia - Kuala Lumpur Tel: 60-3-6201-9857 Fax: 60-3-6201-9859

Malaysia - Penang Tel: 60-4-227-8870 Fax: 60-4-227-4068

Philippines - Manila Tel: 63-2-634-9065 Fax: 63-2-634-9069

Singapore Tel: 65-6334-8870 Fax: 65-6334-8850

Taiwan - Hsin Chu Tel: 886-3-5778-366 Fax: 886-3-5770-955

Taiwan - Kaohsiung Tel: 886-7-213-7828 Fax: 886-7-330-9305

Taiwan - Taipei Tel: 886-2-2508-8600 Fax: 886-2-2508-0102

Thailand - Bangkok Tel: 66-2-694-1351 Fax: 66-2-694-1350

EUROPE

Austria - Wels Tel: 43-7242-2244-39 Fax: 43-7242-2244-393 Denmark - Copenhagen Tel: 45-4450-2828

Fax: 45-4485-2829 France - Paris Tel: 33-1-69-53-63-20 Fax: 33-1-69-30-90-79

Germany - Munich Tel: 49-89-627-144-0 Fax: 49-89-627-144-44

Italy - Milan Tel: 39-0331-742611 Fax: 39-0331-466781

Netherlands - Drunen Tel: 31-416-690399 Fax: 31-416-690340

Spain - Madrid Tel: 34-91-708-08-90 Fax: 34-91-708-08-91

UK - Wokingham Tel: 44-118-921-5869 Fax: 44-118-921-5820