



Welcome to E-XFL.COM

#### What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

#### Details

Product Status	Obsolete
Core Processor	80C51
Core Size	8-Bit
Speed	40/20MHz
Connectivity	UART/USART
Peripherals	POR, PWM, WDT
Number of I/O	32
Program Memory Size	-
Program Memory Type	ROMIess
EEPROM Size	-
RAM Size	768 x 8
Voltage - Supply (Vcc/Vdd)	4.5V ~ 5.5V
Data Converters	-
Oscillator Type	Internal
Operating Temperature	0°C ~ 70°C (TA)
Mounting Type	Surface Mount
Package / Case	44-LCC (J-Lead)
Supplier Device Package	44-PLCC (16.6x16.6)
Purchase URL	https://www.e-xfl.com/product-detail/microchip-technology/ts80c51rd2-mcb

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong



## **5. Pin Configuration**



\*NIC: No Internal Connection







Reset	9	10	4	Ι	Reset: A high on this pin for two machine cycles while the oscillator is running,
					resets the device. An internal diffused resistor to $V_{\mbox{\scriptsize SS}}$ permits a power-on reset
					using only an external capacitor to $V_{CC}$ . If the hardware watchdog reaches its
					time-out, the reset pin becomes an output during the time the internal reset is
					activated.



Mnemonic	Pin Number			Туре	Name And Function
ALE/PROG	30	33	27	O (I)	Address Latch Enable/Program Pulse: Output pulse for latching the low byte of the address during an access to external memory. In normal operation, ALE is emitted at a constant rate of 1/6 (1/3 in X2 mode) the oscillator frequency, and can be used for external timing or clocking. Note that one ALE pulse is skipped during each access to external data memory. This pin is also the program pulse input (PROG) during EPROM programming. ALE can be disabled by setting SFR's AUXR.0 bit. With this bit set, ALE will be inactive during internal fetches.
PSEN	29	32	26	0	<b>Program Store ENable:</b> The read strobe to external program memory. When executing code from the external program memory, $\overrightarrow{PSEN}$ is activated twice each machine cycle, except that two $\overrightarrow{PSEN}$ activations are skipped during each access to external data memory. $\overrightarrow{PSEN}$ is not activated during fetches from internal program memory.
EA/V <sub>pp</sub>	31	35	29	I	<b>External Access Enable/Programming Supply Voltage:</b> $\overline{\text{EA}}$ must be externally held low to enable the device to fetch code from external program memory locations 0000H and 3FFFH (RB) or 7FFFH (RC), or FFFFH (RD). If EA is held high, the device executes from internal program memory unless the program counter contains an address greater than 3FFFH (RB) or 7FFFH (RC) $\overline{\text{EA}}$ must be held low for ROMless devices. This pin also receives the 12.75V programming supply voltage (V <sub>PP</sub> ) during EPROM programming. If security level 1 is programmed, $\overline{\text{EA}}$ will be internally latched on Reset.
XTAL1	19	21	15	Ι	<b>Crystal 1:</b> Input to the inverting oscillator amplifier and input to the internal clock generator circuits.
XTAL2	18	20	14	0	Crystal 2: Output from the inverting oscillator amplifier



	PLCC68	SQUARE VQFP64 1.4
P3.2	40	29
P3.3	41	30
P3.4	42	31
P3.5	43	32
P3.6	45	34
P3.7	47	36
RESET	30	21
ALE/PROG	68	56
PSEN	67	55
EA/VPP	2	58
XTAL1	49	38
XTAL2	48	37
P4.0	20	11
P4.1	24	15
P4.2	26	17
P4.3	44	33
P4.4	46	35
P4.5	50	39
P4.6	53	42
P4.7	57	46
P5.0	60	49
P5.1	62	51
P5.2	63	52
P5.3	7	62
P5.4	8	63
P5.5	10	1
P5.6	13	4
P5.7	16	7



### 6.3. Expanded RAM (XRAM)

The TS80C51Rx2 provide additional Bytes of ramdom access memory (RAM) space for increased data parameter handling and high level language usage.

RA2, RB2 and RC2 devices have 256 bytes of expanded RAM, from 00H to FFH in external data space; RD2 devices have 768 bytes of expanded RAM, from 00H to 2FFH in external data space.

The TS80C51Rx2 has internal data memory that is mapped into four separate segments.

The four segments are:

- 1. The Lower 128 bytes of RAM (addresses 00H to 7FH) are directly and indirectly addressable.
- 2. The Upper 128 bytes of RAM (addresses 80H to FFH) are indirectly addressable only.
- 3. The Special Function Registers, SFRs, (addresses 80H to FFH) are directly addressable only.
- 4. The expanded RAM bytes are indirectly accessed by MOVX instructions, and with the EXTRAM bit cleared in the AUXR register. (See Table 5.)

The Lower 128 bytes can be accessed by either direct or indirect addressing. The Upper 128 bytes can be accessed by indirect addressing only. The Upper 128 bytes occupy the same address space as the SFR. That means they have the same address, but are physically separate from SFR space.

When an instruction accesses an internal location above address 7FH, the CPU knows whether the access is to the upper 128 bytes of data RAM or to SFR space by the addressing mode used in the instruction.

- Instructions that use direct addressing access SFR space. For example: MOV 0A0H, # data ,accesses the SFR at location 0A0H (which is P2).
- Instructions that use indirect addressing access the Upper 128 bytes of data RAM. For example: MOV @R0, # data where R0 contains 0A0H, accesses the data byte at address 0A0H, rather than P2 (whose address is 0A0H).
- The 256 or 768 XRAM bytes can be accessed by indirect addressing, with EXTRAM bit cleared and MOVX instructions. This part of memory which is physically located on-chip, logically occupies the first 256 or 768 bytes of external data memory.
- With <u>EXTRAM = 0</u>, the XRAM is indirectly addressed, using the MOVX instruction in combination with any of the registers R0, R1 of the selected bank or DPTR. An access to XRAM will not affect ports P0, P2, P3.6 ( $\overline{WR}$ ) and P3.7 ( $\overline{RD}$ ). For example, with EXTRAM = 0, MOVX @R0, # data where R0 contains 0A0H, accesses the XRAM at address 0A0H rather than external memory. An access to external data memory locations higher than FFH (i.e. 0100H to FFFFH) (higher than 2FFH (i.e. 0300H to FFFFH for RD devices) will be performed with the MOVX DPTR instructions in the same way as in the standard 80C51, so with P0 and P2 as data/address busses, and P3.6 and P3.7 as write and read timing signals. Refer to Figure . For RD devices, accesses to expanded RAM from 100H to 2FFH can only be done thanks to the use of DPTR.
- With <u>EXTRAM = 1</u>, MOVX @Ri and MOVX @DPTR will be similar to the standard 80C51. MOVX @ Ri will provide an eight-bit address multiplexed with data on Port0 and any output port pins can be used to output higher order address bits. This is to provide the external paging capability. MOVX @DPTR will generate a sixteen-bit address. Port2 outputs the high-order eight address bits (the contents of DPH) while Port0 multiplexes the low-order eight address bits (DPL) with data. MOVX @ Ri and MOVX @DPTR will generate either read or write signals on P3.6 (WR) and P3.7 (RD).

The stack pointer (SP) may be located anywhere in the 256 bytes RAM (lower and upper RAM) internal data memory. The stack may not be located in the XRAM.





Figure 5. Auto-Reload Mode Up/Down Counter (DCEN = 1)

#### 6.4.2. Programmable Clock-Output

In the clock-out mode, timer 2 operates as a 50%-duty-cycle, programmable clock generator (See Figure 6) . The input clock increments TL2 at frequency  $F_{OSC}/2$ . The timer repeatedly counts to overflow from a loaded value. At overflow, the contents of RCAP2H and RCAP2L registers are loaded into TH2 and TL2. In this mode, timer 2 overflows do not generate interrupts. The formula gives the clock-out frequency as a function of the system oscillator frequency and the value in the RCAP2H and RCAP2L registers :

$$Clock - OutFrequency = \frac{F_{osc}}{4 \times (65536 - RCAP2H/RCAP2L)}$$

For a 16 MHz system clock, timer 2 has a programmable frequency range of 61 Hz  $(F_{OSC}/2^{16})$  to 4 MHz  $(F_{OSC}/4)$ . The generated clock signal is brought out to T2 pin (P1.0).

Timer 2 is programmed for the clock-out mode as follows:

- Set T2OE bit in T2MOD register.
- Clear C/T2 bit in T2CON register.
- Determine the 16-bit reload value from the formula and enter it in RCAP2H/RCAP2L registers.
- Enter a 16-bit initial value in timer registers TH2/TL2. It can be the same as the reload value or a different one depending on the application.
- To start the timer, set TR2 run control bit in T2CON register.



It is possible to use timer 2 as a baud rate generator and a clock generator simultaneously. For this configuration, the baud rates and clock frequencies are not independent since both functions use the values in the RCAP2H and RCAP2L registers.



Figure 6. Clock-Out Mode  $C/\overline{T2} = 0$ 



• The ECF bit which when set causes an interrupt and the PCA overflow flag CF (in the CCON SFR) to be set when the PCA timer overflows.





Figure 8. PCA Interrupt System

PCA Modules: each one of the five compare/capture modules has six possible functions. It can perform:

- 16-bit Capture, positive-edge triggered,
- 16-bit Capture, negative-edge triggered,
- 16-bit Capture, both positive and negative-edge triggered,
- 16-bit Software Timer,
- 16-bit High Speed Output,
- 8-bit Pulse Width Modulator.

In addition, module 4 can be used as a Watchdog Timer.

Each module in the PCA has a special function register associated with it. These registers are: CCAPM0 for module 0, CCAPM1 for module 1, etc. (See Table 10). The registers contain the bits that control the mode that each module will operate in.

- The ECCF bit (CCAPMn.0 where n=0, 1, 2, 3, or 4 depending on the module) enables the CCF flag in the CCON SFR to generate an interrupt when a match or compare occurs in the associated module.
- PWM (CCAPMn.1) enables the pulse width modulation mode.
- The TOG bit (CCAPMn.2) when set causes the CEX output associated with the module to toggle when there is a match between the PCA counter and the module's capture/compare register.
- The match bit MAT (CCAPMn.3) when set will cause the CCFn bit in the CCON register to be set when there is a match between the PCA counter and the module's capture/compare register.
- The next two bits CAPN (CCAPMn.4) and CAPP (CCAPMn.5) determine the edge that a capture input will be active on. The CAPN bit enables the negative edge, and the CAPP bit enables the positive edge. If both bits are set both edges will be enabled and a capture will occur for either transition.
- The last bit in the register ECOM (CCAPMn.6) when set enables the comparator function.

Table 11 shows the CCAPMn settings for the various PCA functions.



### Table 16. SCON Register

#### SCON - Serial Control Register (98h)

7	6	5	4	3	2	1	0			
FE/SM0	SM1	SM2	REN	TB8	RB8	TI	RI			
Bit Number	Bit Mnemonic			Descrip	tion					
7	FE	Framing Error bit Clear to reset the Set by hardware SMOD0 must be	raming Error bit (SMOD0=1) Clear to reset the error state, not cleared by a valid stop bit. Set by hardware when an invalid stop bit is detected. SMOD0 must be set to enable access to the FE bit							
	SM0	Serial port Mode bi Refer to SM1 fo SMOD0 must be	rial port Mode bit 0 Refer to SM1 for serial port mode selection. SMOD0 must be cleared to enable access to the SM0 bit							
	6141	Serial port Mode bi SM0 SM	t 1 11 <u>Mode</u>	Description	on Baud Rate	2 2 (/( := <b>X</b> 2 === 1=)				
6	SMI	$ \begin{array}{cccccccccccccccccccccccccccccccccccc$	1 2 3	8-bit UAI 9-bit UAI 9-bit UAI	RT F <sub>XTAL</sub> /I RT Variable RT F <sub>XTAL</sub> /6 RT Variable	2 (/6 in X2 mode) 4 or F <sub>XTAL</sub> /32 (/32	2,/16 in X2 mode)			
5	SM2	Serial port Mod Clear to disable Set to enable mu be cleared in mo	e 2 bit / Multipro multiprocessor cor ltiprocessor comm de 0.	cessor Communic nmunication featur unication feature in	ation Enable bit e. mode 2 and 3, and	eventually mode	1. This bit should			
4	REN	Reception Enable b Clear to disable Set to enable ser	it serial reception. ial reception.							
3	TB8	Transmitter Bit 8 / Clear to transmi Set to transmit a	Ninth bit to trans t a logic 0 in the 9t logic 1 in the 9th b	<b>mit in modes 2 an</b> h bit. bit.	d 3.					
2	RB8	Receiver Bit 8 / Nin Cleared by hard Set by hardware In mode 1, if SM	th bit received in a ware if 9th bit received if 9th bit received $12 = 0$ , RB8 is the particular to the second s	modes 2 and 3 ived is a logic 0. is a logic 1. received stop bit. In	n mode 0 RB8 is n	ot used.				
1	TI	Transmit Interrupt Clear to acknow Set by hardware modes.	flag ledge interrupt. at the end of the 8	th bit time in mode	0 or at the beginn	ing of the stop bit	in the other			
0	RI	Receive Interrupt fl Clear to acknow Set by hardware	<b>ag</b> ledge interrupt. at the end of the 8	th bit time in mode	0, see Figure 14.	and Figure 15. in	the other modes.			

Reset Value = 0000 0000b Bit addressable



### 6.10. Hardware Watchdog Timer

The WDT is intended as a recovery method in situations where the CPU may be subjected to software upset. The WDT consists of a 14-bit counter and the WatchDog Timer ReSeT (WDTRST) SFR. The WDT is by default disabled from exiting reset. To enable the WDT, user must write 01EH and 0E1H in sequence to the WDTRST, SFR location 0A6H. When WDT is enabled, it will increment every machine cycle while the oscillator is running and there is no way to disable the WDT except through reset (either hardware reset or WDT overflow reset). When WDT overflows, it will drive an output RESET HIGH pulse at the RST-pin.

### 6.10.1. Using the WDT

To enable the WDT, user must write 01EH and 0E1H in sequence to the WDTRST, SFR location 0A6H. When WDT is enabled, the user needs to service it by writing to 01EH and 0E1H to WDTRST to avoid WDT overflow. The 14-bit counter overflows when it reaches 16383 (3FFFH) and this will reset the device. When WDT is enabled, it will increment every machine cycle while the oscillator is running. This means the user must reset the WDT at least every 16383 machine cycle. To reset the WDT the user must write 01EH and 0E1H to WDTRST. WDTRST is a write only register. The WDT counter cannot be read or written. When WDT overflows, it will generate an output RESET pulse at the RST-pin. The RESET pulse duration is 96 x  $T_{OSC}$ , where  $T_{OSC} = 1/F_{OSC}$ . To make the best use of the WDT, it should be serviced in those sections of code that will periodically be executed within the time required to prevent a WDT reset.

To have a more powerful WDT, a  $2^7$  counter has been added to extend the Time-out capability, ranking from 16ms to 2s @  $F_{OSC} = 12$ MHz. To manage this feature, refer to WDTPRG register description, Table 24. (SFR0A7h).

#### Table 23. WDTRST Register

#### WDTRST Address (0A6h)

	7	6	5	4	3	2	1
Reset value	Х	Х	Х	Х	Х	Х	Х

Write only, this SFR is used to reset/enable the WDT by writing 01EH then 0E1H in sequence.



### 6.12. Power-Off Flag

The power-off flag allows the user to distinguish between a "cold start" reset and a "warm start" reset.

A cold start reset is the one induced by  $V_{CC}$  switch-on. A warm start reset occurs while  $V_{CC}$  is still applied to the device and could be generated for example by an exit from power-down.

The power-off flag (POF) is located in PCON register (See Table 26.). POF is set by hardware when  $V_{CC}$  rises from 0 to its nominal voltage. The POF can be set or cleared by software allowing the user to determine the type of reset.

The POF value is only relevant with a Vcc range from 4.5V to 5.5V. For lower Vcc value, reading POF bit will return indeterminate value.

#### Table 26. PCON Register

#### PCON - Power Control Register (87h)

7	6	5	4	3	2	1	0		
SMOD1	SMOD	-	- POF GF1 GF0 PD				IDL		
Bit Number	Bit Mnemonic		Description						
7	SMOD1	Serial port Mode bit Set to select dou	erial port Mode bit 1 Set to select double baud rate in mode 1, 2 or 3.						
6	SMOD0	Serial port Mode bit Clear to select SI Set to to select F	erial port Mode bit 0 Clear to select SM0 bit in SCON register. Set to to select FE bit in SCON register.						
5	-	<b>Reserved</b> The value read fr	Reserved The value read from this bit is indeterminate. Do not set this bit.						
4	POF	Power-Off Flag Clear to recogniz Set by hardware	e next reset type. when V <sub>CC</sub> rises fr	om 0 to its nomina	l voltage. Can also	be set by software	·.		
3	GF1	General purpose Fla Cleared by user f Set by user for g	<b>g</b> or general purpose eneral purpose usa	e usage. ge.					
2	GF0	General purpose Fla Cleared by user f Set by user for g	General purpose Flag Cleared by user for general purpose usage. Set by user for general purpose usage.						
1	PD	Power-Down mode I Cleared by hardw Set to enter powe	Power-Down mode bit Cleared by hardware when reset occurs. Set to enter power-down mode.						
0	IDL	Idle mode bit Clear by hardwar Set to enter idle r	e when interrupt on ode.	or reset occurs.					

Reset Value = 00X1 0000b Not bit addressable



### **8.3. EPROM Programming**

### 8.3.1. Set-up modes

In order to program and verify the EPROM or to read the signature bytes, the TS87C51RB2/RC2/RD2 is placed in specific set-up modes (See Figure 18.).

Control and program signals must be held at the levels indicated in Table 30.

### **8.3.2.** Definition of terms

Address Lines: P1.0-P1.7, P2.0-P2.5, P3.4, P3.5 respectively for A0-A15 (P2.5 (A13) for RB, P3.4 (A14) for RC, P3.5 (A15) for RD)

Data Lines: P0.0-P0.7 for D0-D7

**Control Signals:** RST, <u>PSEN</u>, P2.6, P2.7, P3.3, P3.6, P3.7.

Program Signals: ALE/PROG, EA/VPP.

Mode	RST	PSEN	ALE/ PROG	<b>EA</b> /VPP	P2.6	P2.7	P3.3	P3.6	P3.7
Program Code data	1	0	Г	12.75V	0	1	1	1	1
Verify Code data	1	0	1	1	0		0	1	1
Program Encryption Array Address 0-3Fh	1	0	Г	12.75V	0	1	1	0	1
Read Signature Bytes	1	0	1	1	0		0	0	0
Program Lock bit 1	1	0	Г	12.75V	1	1	1	1	1
Program Lock bit 2	1	0	Г	12.75V	1	1	1	0	0
Program Lock bit 3	1	0	Г	12.75V	1	0	1	1	0

Table 30. EPROM Set-Up Modes



## 9. Signature Bytes

The TS83/87C51RB2/RC2/RD2 has four signature bytes in location 30h, 31h, 60h and 61h. To read these bytes follow the procedure for EPROM verify but activate the control lines provided in Table 31. for Read Signature Bytes. Table 31. shows the content of the signature byte for the TS87C51RB2/RC2/RD2.

Location	Contents	Comment
30h	58h	Manufacturer Code: Atmel Wireless & Microcontrollers
31h	57h	Family Code: C51 X2
60h	7Ch	Product name: TS83C51RD2
60h	FCh	Product name: TS87C51RD2
60h	37h	Product name: TS83C51RC2
60h	B7h	Product name: TS87C51RC2
60h	3Bh	Product name: TS83C51RB2
60h	BBh	Product name: TS87C51RB2
61h	FFh	Product revision number

#### Table 31. Signature Bytes Content



Symbol	Parameter	Min	Тур	Max	Unit	Test Conditions
I <sub>CC</sub> operating	Power Supply Current Maximum values, X1 mode: <sup>(7)</sup>			3 + 0.6 Freq (MHz) @12MHz 10.2 @16MHz 12.6	mA	$V_{CC} = 5.5 V^{(8)}$
I <sub>CC</sub> idle	Power Supply Current Maximum values, X1 mode: <sup>(7)</sup>			0.25+0.3Freq (MHz) @12MHz 3.9 @16MHz 5.1	mA	$V_{CC} = 5.5 V^{(2)}$

### **10.4. DC Parameters for Low Voltage**

TA = 0°C to +70°C; V<sub>SS</sub> = 0 V; V<sub>CC</sub> = 2.7 V to 5.5 V  $\pm$  10%; F = 0 to 30 MHz. TA = -40°C to +85°C; V<sub>SS</sub> = 0 V; V<sub>CC</sub> = 2.7 V to 5.5 V  $\pm$  10%; F = 0 to 30 MHz.

Table 33	. DC	<b>Parameters</b>	for	Low	Voltage
----------	------	-------------------	-----	-----	---------

Symbol	Parameter	Min	Тур	Max	Unit	Test Conditions
V <sub>IL</sub>	Input Low Voltage	-0.5		0.2 V <sub>CC</sub> - 0.1	v	
V <sub>IH</sub>	Input High Voltage except XTAL1, RST	$0.2 V_{CC} + 0.9$		V <sub>CC</sub> + 0.5	v	
V <sub>IH1</sub>	Input High Voltage, XTAL1, RST	0.7 V <sub>CC</sub>		V <sub>CC</sub> + 0.5	v	
V <sub>OL</sub>	Output Low Voltage, ports 1, 2, 3, 4, 5 <sup>(6)</sup>			0.45	v	$I_{OL} = 0.8 \text{ mA}^{(4)}$
V <sub>OL1</sub>	Output Low Voltage, port 0, ALE, PSEN (6)			0.45	v	$I_{OL} = 1.6 \text{ mA}^{(4)}$
V <sub>OH</sub>	Output High Voltage, ports 1, 2, 3, 4, 5	0.9 V <sub>CC</sub>			V	$I_{OH} = -10 \ \mu A$
V <sub>OH1</sub>	Output High Voltage, port 0, ALE, PSEN	0.9 V <sub>CC</sub>			v	$I_{OH} = -40 \ \mu A$
I <sub>IL</sub>	Logical 0 Input Current ports 1, 2, 3, 4, 5			-50	μΑ	Vin = 0.45 V
I <sub>LI</sub>	Input Leakage Current			±10	μΑ	0.45 V < Vin < V <sub>CC</sub>
I <sub>TL</sub>	Logical 1 to 0 Transition Current, ports 1, 2, 3, 4, 5			-650	μΑ	Vin = 2.0 V
R <sub>RST</sub>	RST Pulldown Resistor	50	90 <sup>(5)</sup>	200	kΩ	
CIO	Capacitance of I/O Buffer			10	pF	$    Fc = 1 MHz  TA = 25^{\circ}C $
I <sub>PD</sub>	Power Down Current		20 <sup>(5)</sup>	50	μΑ	$V_{CC} = 2.0 \text{ V to } 5.5 \text{ V}^{(3)}$
			10 <sup>(5)</sup>	30		$V_{\rm CC} = 2.0 \text{ V to } 3.3 \text{ V}^{(3)}$
I <sub>CC</sub> under RESET	Power Supply Current Maximum values, X1 mode: <sup>(7)</sup>			1 + 0.2 Freq (MHz) @12MHz 3.4 @16MHz 4.2	mA	$V_{CC} = 3.3 V^{(1)}$
I <sub>CC</sub> operating	Power Supply Current Maximum values, X1 mode: <sup>(7)</sup>			1 + 0.3 Freq (MHz) @12MHz 4.6 @16MHz 5.8	mA	$V_{\rm CC} = 3.3 \ V^{(8)}$





All other pins are disconnected.





All other pins are disconnected.

Figure 22. I<sub>CC</sub> Test Condition, Idle Mode



Figure 23. I<sub>CC</sub> Test Condition, Power-Down Mode



Figure 24. Clock Signal Waveform for  $I_{\mbox{\scriptsize CC}}$  Tests in Active and Idle Modes



Speed	-M 40 MHz		-V X2 mode 30 MHz 60 MHz equiv.		-V standard mode 40 MHz		-L X2 mode 20 MHz 40 MHz equiv.		-L standard mode 30 MHz		Units
Symbol	Min	Max	Min	Max	Min	Max	Min	Max	Min	Max	
T <sub>RLRH</sub>	130		85		135		125		175		ns
T <sub>WLWH</sub>	130		85		135		125		175		ns
T <sub>RLDV</sub>		100		60		102		95		137	ns
T <sub>RHDX</sub>	0		0		0		0		0		ns
T <sub>RHDZ</sub>		30		18		35		25		42	ns
T <sub>LLDV</sub>		160		98		165		155		222	ns
T <sub>AVDV</sub>		165		100		175		160		235	ns
T <sub>LLWL</sub>	50	100	30	70	55	95	45	105	70	130	ns
T <sub>AVWL</sub>	75		47		80		70		103		ns
T <sub>QVWX</sub>	10		7		15		5		13		ns
T <sub>QVWH</sub>	160		107		165		155		213		ns
T <sub>WHQX</sub>	15		9		17		10		18		ns
T <sub>RLAZ</sub>		0		0		0		0		0	ns
T <sub>WHLH</sub>	10	40	7	27	15	35	5	45	13	53	ns

Table 40. AC Parameters for a Fix Clock



Symbol	Туре	Standard Clock	X2 Clock	-M	-V	-L	Units
T <sub>RLRH</sub>	Min	6 T - x	3 T - x	20	15	25	ns
T <sub>WLWH</sub>	Min	6 T - x	3 T - x	20	15	25	ns
T <sub>RLDV</sub>	Max	5 T - x	2.5 T - x	25	23	30	ns
T <sub>RHDX</sub>	Min	x	X	0	0	0	ns
T <sub>RHDZ</sub>	Max	2 T - x	T - x	20	15	25	ns
T <sub>LLDV</sub>	Max	8 T - x	4T -x	40	35	45	ns
T <sub>AVDV</sub>	Max	9 T - x	4.5 T - x	60	50	65	ns
T <sub>LLWL</sub>	Min	3 T - x	1.5 T - x	25	20	30	ns
T <sub>LLWL</sub>	Max	3 T + x	1.5 T + x	25	20	30	ns
T <sub>AVWL</sub>	Min	4 T - x	2 T - x	25	20	30	ns
T <sub>QVWX</sub>	Min	T - x	0.5 T - x	15	10	20	ns
T <sub>QVWH</sub>	Min	7 T - x	3.5 T - x	15	10	20	ns
T <sub>WHQX</sub>	Min	T - x	0.5 T - x	10	8	15	ns
T <sub>RLAZ</sub>	Max	x	х	0	0	0	ns
T <sub>WHLH</sub>	Min	T - x	0.5 T - x	15	10	20	ns
T <sub>WHLH</sub>	Max	T + x	0.5 T + x	15	10	20	ns

Table 41. AC Parameters	for	a	Variable	<b>Clock:</b>	derating	formula
-------------------------	-----	---	----------	---------------	----------	---------

### 10.5.5. External Data Memory Write Cycle



Figure 26. External Data Memory Write Cycle



### **10.5.9. EPROM Programming and Verification Characteristics**

TA = 21°C to 27°C;  $V_{SS} = 0V$ ;  $V_{CC} = 5V \pm 10\%$  while programming.  $V_{CC}$  = operating range while verifying

Symbol	Parameter	Min	Max	Units
V <sub>PP</sub>	Programming Supply Voltage	12.5	13	V
I <sub>PP</sub>	Programming Supply Current		75	mA
1/T <sub>CLCL</sub>	Oscillator Frquency	4	6	MHz
T <sub>AVGL</sub>	Address Setup to PROG Low	48 T <sub>CLCL</sub>		
T <sub>GHAX</sub>	Adress Hold after PROG	48 T <sub>CLCL</sub>		
T <sub>DVGL</sub>	Data Setup to PROG Low	48 T <sub>CLCL</sub>		
T <sub>GHDX</sub>	Data Hold after PROG	48 T <sub>CLCL</sub>		
T <sub>EHSH</sub>	(Enable) High to V <sub>PP</sub>	48 T <sub>CLCL</sub>		
T <sub>SHGL</sub>	V <sub>PP</sub> Setup to PROG Low	10		μs
T <sub>GHSL</sub>	V <sub>PP</sub> Hold after PROG	10		μs
T <sub>GLGH</sub>	PROG Width	90	110	μs
T <sub>AVQV</sub>	Address to Valid Data		48 T <sub>CLCL</sub>	
T <sub>ELQV</sub>	ENABLE Low to Data Valid		48 T <sub>CLCL</sub>	
T <sub>EHQZ</sub>	Data Float after ENABLE	0	48 T <sub>CLCL</sub>	

#### Table 45. EPROM Programming Parameters

### 10.5.10. EPROM Programming and Verification Waveforms



\* 8KB: up to P2.4, 16KB: up to P2.5, 32KB: up to P3.4, 64KB: up to P3.5

#### Figure 29. EPROM Programming and Verification Waveforms