

Welcome to E-XFL.COM

#### What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

#### Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

#### Details

E·XFI

Product Status	Obsolete
Core Processor	XC800
Core Size	8-Bit
Speed	24MHz
Connectivity	CANbus, SSI, UART/USART
Peripherals	Brown-out Detect/Reset, POR, PWM, WDT
Number of I/O	34
Program Memory Size	32KB (32K x 8)
Program Memory Type	FLASH
EEPROM Size	-
RAM Size	1.75К х 8
Voltage - Supply (Vcc/Vdd)	4.5V ~ 5.5V
Data Converters	A/D 8x10b
Oscillator Type	Internal
Operating Temperature	-40°C ~ 125°C (TA)
Mounting Type	Surface Mount
Package / Case	48-LQFP
Supplier Device Package	PG-TQFP-48
Purchase URL	https://www.e-xfl.com/product-detail/infineon-technologies/sak-xc886cm-8ffi-5v-ac

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong



#### **Table of Contents**

4.3.3	Power-on Reset and PLL Timing 126
4.3.4	On-Chip Oscillator Characteristics 128
4.3.5	External Clock Drive XTAL1 129
4.3.6	JTAG Timing
4.3.7	SSC Master Mode Timing 132
5	Package and Quality Declaration
5.1	Package Parameters
5.2	Package Outline
52	Quality Daslandian (100



#### **Summary of Features**

<b>Table 2 Device Frome</b> (cont d)	Table 2	Device Profile (cont'd)
--------------------------------------	---------	-------------------------

Sales Type	Device Type	Program Memory (Kbytes)	Power Supply (V)	Temp- erature (°C)	Quality Profile
SAK-XC886*/888*-8FFA 3V3	Flash	32	3.3	-40 to 125	Automotive
SAK-XC886*/888*-6FFA 3V3	Flash	24	3.3	-40 to 125	Automotive
SAF-XC886*/888*-8FFA 3V3	Flash	32	3.3	-40 to 85	Automotive
SAF-XC886*/888*-6FFA 3V3	Flash	24	3.3	-40 to 85	Automotive
SAF-XC886*/888*-8FFI 3V3	Flash	32	3.3	-40 to 85	Industrial
SAF-XC886*/888*-6FFI 3V3	Flash	24	3.3	-40 to 85	Industrial

- Note: The asterisk (\*) above denotes the device configuration letters from **Table 1**. Corresponding ROM derivatives will be available on request.
- Note: For variants with LIN BSL support, only LIN BSL is available regardless of the availability of the CAN module.

As this document refers to all the derivatives, some description may not apply to a specific product. For simplicity, all versions are referred to by the term XC886/888 throughout this document.

#### **Ordering Information**

The ordering code for Infineon Technologies microcontrollers provides an exact reference to the required product. This ordering code identifies:

- The derivative itself, i.e. its function set, the temperature range, and the supply voltage
- The package and the type of delivery

For the available ordering codes for the XC886/888, please refer to your responsible sales representative or your local distributor.

Note: The ordering codes for the Mask-ROM versions are defined for each product after verification of the respective ROM code.



# XC886/888CLM

# **General Device Information**

Symbol	Pin Number (TQFP-48/64)	Туре	Reset State	Function	
P3		I/O		Port 3 Port 3 is an 8 I/O port. It ca for CCU6, U/	B-bit bidirectional general purpose on be used as alternate functions ART1, Timer 21 and MultiCAN.
P3.0	35/43		Hi-Z	CCPOS1_2 CC60_0 RXDO1_1	CCU6 Hall Input 1 Input/Output of Capture/Compare channel 0 UART1 Transmit Data Output
P3.1	36/44		Hi-Z	CCPOS0_2 CC61_2 COUT60_0	CCU6 Hall Input 0 Input/Output of Capture/Compare channel 1 Output of Capture/Compare
				TXD1_1	UART1 Transmit Data Output/Clock Output
P3.2	37/49		Hi-Z	CCPOS2_2 RXDC1_1 RXD1_1 CC61_0	CCU6 Hall Input 2 MultiCAN Node 1 Receiver Input UART1 Receive Data Input Input/Output of Capture/Compare channel 1
P3.3	38/50		Hi-Z	COUT61_0 TXDC1_1	Output of Capture/Compare channel 1 MultiCAN Node 1 Transmitter Output
P3.4	39/51		Hi-Z	CC62_0 RXDC0_1 T2EX1_0	Input/Output of Capture/Compare channel 2 MultiCAN Node 0 Receiver Input Timer 21 External Trigger Input
P3.5	40/52		Hi-Z	COUT62_0 EXF21_0 TXDC0_1	Output of Capture/Compare channel 2 Timer 21 External Flag Output MultiCAN Node 0 Transmitter Output
P3.6	33/41		PD	CTRAP 0	CCU6 Trap Input

# Table 3Pin Definitions and Functions (cont'd)



# 3.2.2 Special Function Register

The Special Function Registers (SFRs) occupy direct internal data memory space in the range  $80_{H}$  to FF<sub>H</sub>. All registers, except the program counter, reside in the SFR area. The SFRs include pointers and registers that provide an interface between the CPU and the on-chip peripherals. As the 128-SFR range is less than the total number of registers required, address extension mechanisms are required to increase the number of addressable SFRs. The address extension mechanisms include:

- Mapping
- Paging

# 3.2.2.1 Address Extension by Mapping

Address extension is performed at the system level by mapping. The SFR area is extended into two portions: the standard (non-mapped) SFR area and the mapped SFR area. Each portion supports the same address range  $80_H$  to FF<sub>H</sub>, bringing the number of addressable SFRs to 256. The extended address range is not directly controlled by the CPU instruction itself, but is derived from bit RMAP in the system control register SYSCON0 at address  $8F_H$ . To access SFRs in the mapped area, bit RMAP in SFR SYSCON0 must be set. Alternatively, the SFRs in the standard area can be accessed by clearing bit RMAP. The SFR area can be selected as shown in **Figure 8**.

As long as bit RMAP is set, the mapped SFR area can be accessed. This bit is not cleared automatically by hardware. Thus, before standard/mapped registers are accessed, bit RMAP must be cleared/set, respectively, by software.









Address Extension by Mapping



SYSCON0

#### **Functional Description**

#### System Control Register 0 Reset Value: 04 7 5 4 3 2 1 0 6 IMODE 1 RMAP 0 0 0 r r r r rw rw

Field	Bits	Туре	Description
RMAP	0	rw	<ul> <li>Interrupt Node XINTR0 Enable</li> <li>0 The access to the standard SFR area is enabled</li> <li>1 The access to the mapped SFR area is enabled</li> </ul>
1	2	r	<b>Reserved</b> Returns 1 if read; should be written with 1.
0	[7:5], 3,1	r	<b>Reserved</b> Returns 0 if read; should be written with 0.

Note: The RMAP bit should be cleared/set by ANL or ORL instructions.

# 3.2.2.2 Address Extension by Paging

Address extension is further performed at the module level by paging. With the address extension by mapping, the XC886/888 has a 256-SFR address range. However, this is still less than the total number of SFRs needed by the on-chip peripherals. To meet this requirement, some peripherals have a built-in local address extension mechanism for increasing the number of addressable SFRs. The extended address range is not directly controlled by the CPU instruction itself, but is derived from bit field PAGE in the module page register MOD\_PAGE. Hence, the bit field PAGE must be programmed before accessing the SFR of the target module. Each module may contain a different number of pages and a different number of SFRs per page, depending on the specific requirement. Besides setting the correct RMAP bit value to select the SFR area, the user must also ensure that a valid PAGE is selected to target the desired SFR. A page inside the extended address range can be selected as shown in **Figure 9**.



# XC886/888CLM

# **Functional Description**

# Table 10Port Register Overview (cont'd)

Addr	Register Name	Bit	7	6	5	4	3	2	1	0
RMAP =	= 0, PAGE 1									
80 <sub>H</sub>	P0_PUDSEL Reset: FF <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
	P0 Pull-Up/Pull-Down Select Register	Туре	rw							
86 <sub>H</sub>	P0_PUDEN Reset: C4 <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
	P0 Pull-Up/Pull-Down Enable Register	Туре	rw							
90 <sub>H</sub>	P1_PUDSEL Reset: FF <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
	P1 Pull-Up/Pull-Down Select Register	Туре	rw							
91 <sub>H</sub>	P1_PUDEN Reset: FF <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
	P1 Pull-Up/Pull-Down Enable Register	Туре	rw							
92 <sub>H</sub>	P5_PUDSEL Reset: FF <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
	P5 Pull-Up/Pull-Down Select Register	Туре	rw							
93 <sub>H</sub>	P5_PUDEN Reset: FF <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
	P5 Pull-Up/Pull-Down Enable Register	Туре	rw							
A0 <sub>H</sub>	H P2_PUDSEL Reset: FF <sub>H</sub>		P7	P6	P5	P4	P3	P2	P1	P0
	P2 Pull-Up/Pull-Down Select Register	Туре	rw							
A1 <sub>H</sub>	P2_PUDEN Reset: 00 <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
	P2 Pull-Up/Pull-Down Enable Register	Туре	rw							
во <sub>Н</sub>	P3_PUDSEL Reset: BF <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
	P3 Pull-Up/Pull-Down Select Register	Туре	rw							
B1 <sub>H</sub>	P3_PUDEN Reset: 40 <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
	P3 Pull-Up/Pull-Down Enable Register	Туре	rw							
C8 <sub>H</sub>	P4_PUDSEL Reset: FF <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
	P4 Pull-Up/Pull-Down Select Register	Туре	rw							
C9 <sub>H</sub>	P4_PUDEN Reset: 04 <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
	P4 Pull-Up/Pull-Down Enable Register	Туре	rw							
RMAP =	= 0, PAGE 2			•				•		
<sup>80</sup> H	P0_ALTSEL0 Reset: 00 <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
	P0 Alternate Select 0 Register	Туре	rw							
86 <sub>H</sub>	P0_ALTSEL1 Reset: 00 <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
	PU Alternate Select 1 Register	Туре	rw							
90 <sub>H</sub>	P1_ALTSEL0 Reset: 00 <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
	PT Alternate Select 0 Register	Туре	rw							
<sup>91</sup> H	P1_ALTSEL1 Reset: 00 <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
	I Allemale Select I Register	Туре	rw							
92 <sub>H</sub>	P5_ALTSEL0 Reset: 00 <sub>H</sub>	Bit Field	P7	P6	P5	P4	P3	P2	P1	P0
		Туре	rw							



#### Table 13T21 Register Overview (cont'd)

Addr	Register Name	Bit	Bit 7 6 5		5	4	3	2	1	0
C5 <sub>H</sub> T21_T2H Reset: 00 <sub>H</sub>		Bit Field	THL2							
	Timer 2 Register High	Туре	rwh							

# 3.2.4.10 CCU6 Registers

The CCU6 SFRs can be accessed in the standard memory area (RMAP = 0).

#### Table 14 CCU6 Register Overview

Addr	Register Name	Bit	7	6	5	4	3	2	1	0
RMAP =	= 0		I	I		I	I	I	l	
A3 <sub>H</sub>	3 <sub>H</sub> CCU6_PAGE Reset: 00 <sub>H</sub>		C	P	ST	NR	0		PAGE	
	Page Register	Туре	١	N	١	N	r		rw	
RMAP =	0, PAGE 0									
9A <sub>H</sub>	CCU6_CC63SRL Reset: 00 <sub>H</sub>	Bit Field				CC6	3SL			
	for Channel CC63 Low	Туре				r	w			
9B <sub>H</sub>	CCU6_CC63SRH Reset: 00 <sub>H</sub>	Bit Field				CC6	3SH			
	for Channel CC63 High	Туре				r	w			
9CH	CCU6_TCTR4L Reset: 00 <sub>H</sub> Timer Control Register 4 Low	Bit Field	T12 STD	T12 STR	(	0	DT RES	T12 RES	T12R S	T12R R
		Туре	w	w		r	w	w	w	w
9D <sub>H</sub>	DDH CCU6_TCTR4H Reset: 00 <sub>H</sub> Timer Control Register 4 High		T13 STD	T13 STR	0		T13 RES	T13R S	T13R R	
		Туре	w	w	r		w	w	w	
9E <sub>H</sub>	E <sub>H</sub> CCU6_MCMOUTSL Reset: 00 <sub>H</sub> Multi-Channel Mode Output Shadow		STRM CM	0	MCMPS					
	Register Low	Туре	w	r	rw					
9F <sub>H</sub>	CCU6_MCMOUTSH Reset: 00 <sub>H</sub> Multi-Channel Mode Output Shadow	Bit Field	STRH P	0	CURHS EXPHS					
		Туре	w	r	rw			rw		
A4 <sub>H</sub>	CCU6_ISRL Reset: 00 <sub>H</sub> Capture/Compare Interrupt Status	Bit Field	RT12 PM	RT12 OM	RCC6 2F	RCC6 2R	RCC6 1F	RCC6 1R	RCC6 0F	RCC6 0R
		Туре	w	w	w	w	w	w	w	w
A5 <sub>H</sub>	CCU6_ISRH Reset: 00 <sub>H</sub> Capture/Compare Interrupt Status	Bit Field	RSTR	RIDLE	RWH E	RCHE	0	RTRP F	RT13 PM	RT13 CM
Reset Register High	Reset Register High	Туре	w	w	w	w	r	w	w	w
A6 <sub>H</sub>	CCU6_CMPMODIFL Reset: 00 <sub>H</sub> Compare State Modification Register		0	MCC6 3S		0		MCC6 2S	MCC6 1S	MCC6 0S
		Туре	r	w		r		w	w	w
а7 <sub>Н</sub>	CCU6_CMPMODIFH Reset: 00 <sub>H</sub> Compare State Modification Register	Bit Field	0	MCC6 3R		0		MCC6 2R	MCC6 1R	MCC6 0R
	High		r	w		r		w	w	w



# 3.3 Flash Memory

The Flash memory provides an embedded user-programmable non-volatile memory, allowing fast and reliable storage of user code and data. It is operated from a single 2.5 V supply from the Embedded Voltage Regulator (EVR) and does not require additional programming or erasing voltage. The sectorization of the Flash memory allows each sector to be erased independently.

## Features

- In-System Programming (ISP) via UART
- In-Application Programming (IAP)
- Error Correction Code (ECC) for dynamic correction of single-bit errors
- Background program and erase operations for CPU load minimization
- Support for aborting erase operation
- Minimum program width<sup>1)</sup> of 32-byte for D-Flash and 64-byte for P-Flash
- 1-sector minimum erase width
- 1-byte read access
- Flash is delivered in erased state (read all zeros)
- Operating supply voltage: 2.5 V ± 7.5 %
- Read access time:  $3 \times t_{CCLK} = 125 \text{ ns}^{2}$
- Program time: 248256 /  $f_{SYS}^{(3)}$  = 2.6 ms<sup>3)</sup>
- Erase time: 9807360 / f<sub>SYS</sub> = 102 ms<sup>3)</sup>

<sup>1)</sup> P-Flash: 64-byte wordline can only be programmed once, i.e., one gate disturb allowed. D-Flash: 32-byte wordline can be programmed twice, i.e., two gate disturbs allowed.

<sup>2)</sup> Values shown here are typical values.  $f_{sys}$  = 96 MHz ± 7.5% ( $f_{CCLK}$  = 24 MHz ± 7.5 %) is the maximum frequency range for Flash read access.

<sup>3)</sup> Values shown here are typical values.  $f_{sys} = 96 \text{ MHz} \pm 7.5\%$  is the only frequency range for Flash programming and erasing.  $f_{sysmin}$  is used for obtaining the worst case timing.



# 3.4 Interrupt System

The XC800 Core supports one non-maskable interrupt (NMI) and 14 maskable interrupt requests. In addition to the standard interrupt functions supported by the core, e.g., configurable interrupt priority and interrupt masking, the XC886/888 interrupt system provides extended interrupt support capabilities such as the mapping of each interrupt vector to several interrupt sources to increase the number of interrupt sources supported, and additional status registers for detecting and determining the interrupt source.

# 3.4.1 Interrupt Source

**Figure 13** to **Figure 17** give a general overview of the interrupt sources and nodes, and their corresponding control and status flags.



Figure 13 Non-Maskable Interrupt Request Sources



# XC886/888CLM

### **Functional Description**



Figure 14 Interrupt Request Sources (Part 1)



# 3.7 Reset Control

The XC886/888 has five types of reset: power-on reset, hardware reset, watchdog timer reset, power-down wake-up reset, and brownout reset.

When the XC886/888 is first powered up, the status of certain pins (see **Table 23**) must be defined to ensure proper start operation of the device. At the end of a reset sequence, the sampled values are latched to select the desired boot option, which cannot be modified until the next power-on reset or hardware reset. This guarantees stable conditions during the normal operation of the device.

In order to power up the system properly, the external reset pin  $\overrightarrow{\text{RESET}}$  must be asserted until  $V_{\text{DDC}}$  reaches 0.9\* $V_{\text{DDC}}$ . The delay of external reset can be realized by an external capacitor at  $\overrightarrow{\text{RESET}}$  pin. This capacitor value must be selected so that  $V_{\text{RESET}}$  reaches 0.4 V, but not before  $V_{\text{DDC}}$  reaches 0.9\*  $V_{\text{DDC}}$ .

A typical application example is shown in Figure 22. The  $V_{\text{DDP}}$  capacitor value is 100 nF while the  $V_{\text{DDC}}$  capacitor value is 220 nF. The capacitor connected to RESET pin is 100 nF.

Typically, the time taken for  $V_{DDC}$  to reach  $0.9^*V_{DDC}$  is less than 50 µs once  $V_{DDP}$  reaches 2.3V. Hence, based on the condition that 10% to 90%  $V_{DDP}$  (slew rate) is less than 500 µs, the RESET pin should be held low for 500 µs typically. See Figure 23.



Figure 22 Reset Circuitry



# 3.7.1 Module Reset Behavior

**Table 22** lists the functions of the XC886/888 and the various reset types that affect these functions. The symbol "■" signifies that the particular function is reset to its default state.

Module/ Function	Wake-Up Reset	Watchdog Reset	Hardware Reset	Power-On Reset	Brownout Reset
CPU Core					
Peripherals					
On-Chip Static RAM	Not affected, Reliable	Not affected, Reliable	Not affected, Reliable	Affected, un- reliable	Affected, un- reliable
Oscillator, PLL		Not affected			
Port Pins					
EVR	The voltage regulator is switched on	Not affected			
FLASH					
NMI	Disabled	Disabled			

#### Table 22Effect of Reset on Device Functions

# 3.7.2 Booting Scheme

When the XC886/888 is reset, it must identify the type of configuration with which to start the different modes once the reset sequence is complete. Thus, boot configuration information that is required for activation of special modes and conditions needs to be applied by the external world through input pins. After power-on reset or hardware reset, the pins MBC, TMS and P0.0 collectively select the different boot options. Table 23 shows the available boot options in the XC886/888.

MBC	TMS	P0.0	Type of Mode	PC Start Value
1	0	Х	User Mode <sup>1)</sup> ; on-chip OSC/PLL non-bypassed	0000 <sub>H</sub>
0	0	Х	BSL Mode; on-chip OSC/PLL non-bypassed <sup>2)</sup>	0000 <sub>H</sub>
0	1	0	OCDS Mode; on-chip OSC/PLL non- bypassed	0000 <sub>H</sub>
1	1	0	User (JTAG) Mode <sup>3)</sup> ; on-chip OSC/PLL non- bypassed (normal)	0000 <sub>H</sub>

Table 23	XC886/888 Boot Selection



# 3.12 CORDIC Coprocessor

The CORDIC Coprocessor provides CPU with hardware support for the solving of circular (trigonometric), linear (multiply-add, divide-add) and hyperbolic functions.

# Features

- Modes of operation
  - Supports all CORDIC operating modes for solving circular (trigonometric), linear (multiply-add, divide-add) and hyperbolic functions
  - Integrated look-up tables (LUTs) for all operating modes
- Circular vectoring mode: Extended support for values of initial X and Y data up to full range of [-2<sup>15</sup>,(2<sup>15</sup>-1)] for solving angle and magnitude
- Circular rotation mode: Extended support for values of initial Z data up to full range of  $[-2^{15},(2^{15}-1)]$ , representing angles in the range  $[-\pi,((2^{15}-1)/2^{15})\pi]$  for solving trigonometry
- Implementation-dependent operational frequency of up to 80 MHz
- Gated clock input to support disabling of module
- 16-bit accessible data width
  - 24-bit kernel data width plus 2 overflow bits for X and Y each
  - 20-bit kernel data width plus 1 overflow bit for Z
  - With KEEP bit to retain the last value in the kernel register for a new calculation
- 16 iterations per calculation: Approximately 41 clock-cycles or less, from set of start (ST) bit to set of end-of-calculation flag, excluding time taken for write and read access of data bytes.
- Twos complement data processing
- Only exception: X result data with user selectable option for unsigned result
- X and Y data generally accepted as integer or rational number; X and Y must be of the same data form
- Entries of LUTs are 20-bit signed integers
  - Entries of atan and atanh LUTs are integer representations (S19) of angles with the scaling such that  $[-2^{15},(2^{15}-1)]$  represents the range  $[-\pi,((2^{15}-1)/2^{15})\pi]$
  - Accessible Z result data for circular and hyperbolic functions is integer in data form of S15
- Emulated LUT for linear function
  - Data form is 1 integer bit and 15-bit fractional part (1.15)
  - Accessible Z result data for linear function is rational number with fixed data form of S4.11 (signed 4Q16)
- Truncation Error
  - The result of a CORDIC calculation may return an approximation due to truncation of LSBs
  - Good accuracy of the CORDIC calculated result data, especially in circular mode
- Interrupt
  - On completion of a calculation



- Interrupt enabling and corresponding flag

# 3.13 UART and UART1

The XC886/888 provides two Universal Asynchronous Receiver/Transmitter (UART and UART1) modules for full-duplex asynchronous reception/transmission. Both are also receive-buffered, i.e., they can commence reception of a second byte before a previously received byte has been read from the receive register. However, if the first byte still has not been read by the time reception of the second byte is complete, one of the bytes will be lost.

#### Features

- Full-duplex asynchronous modes
  - 8-bit or 9-bit data frames, LSB first
  - Fixed or variable baud rate
- Receive buffered
- Multiprocessor communication
- Interrupt generation on the completion of a data transmission or reception

The UART modules can operate in the four modes shown in **Table 29**.

Operating Mode	Baud Rate
Mode 0: 8-bit shift register	f <sub>PCLK</sub> /2
Mode 1: 8-bit shift UART	Variable
Mode 2: 9-bit shift UART	$f_{\rm PCLK}/32 \text{ or } f_{\rm PCLK}/64^{1)}$
Mode 3: 9-bit shift UART	Variable

#### Table 29UART Modes

1) For UART1 module, the baud rate is fixed at  $f_{PCLK}/64$ .

There are several ways to generate the baud rate clock for the serial port, depending on the mode in which it is operating. In mode 0, the baud rate for the transfer is fixed at  $f_{\rm PCLK}/2$ . In mode 2, the baud rate is generated internally based on the UART input clock and can be configured to either  $f_{\rm PCLK}/32$  or  $f_{\rm PCLK}/64$ . For UART1 module, only  $f_{\rm PCLK}/64$  is available. The variable baud rate is set by the underflow rate on the dedicated baud-rate generator. For UART module, the variable baud rate alternatively can be set by the overflow rate on Timer 1.

# 3.13.1 Baud-Rate Generator

Both UART modules have their own dedicated baud-rate generator, which is based on a programmable 8-bit reload value, and includes divider stages (i.e., prescaler and



# XC886/888CLM

**Functional Description** 



Figure 32 SSC Block Diagram



#### Table 40ADC Characteristics (Operating Conditions apply; $V_{DDP}$ = 5V Range)

Parameter	Symbol		Limit Values			Unit	Test Conditions/
			min.	typ.	max.		Remarks
Overload current coupling factor for digital I/O pins	K <sub>OVD</sub>	CC	-	_	5.0 x 10 <sup>-3</sup>	-	$I_{\rm OV} > 0^{1)3)}$
			_	_	1.0 x 10 <sup>-2</sup>	_	$I_{\rm OV} < 0^{1)3)}$
Switched capacitance at the reference voltage input	$C_{\sf AREFSW}$	CC	_	10	20	pF	1)4)
Switched capacitance at the analog voltage inputs	C <sub>AINSW</sub>	CC	_	5	7	pF	1)5)
Input resistance of the reference input	R <sub>AREF</sub>	CC	_	1	2	kΩ	1)
Input resistance of the selected analog channel	R <sub>AIN</sub>	CC	_	1	1.5	kΩ	1)

1) Not subjected to production test, verified by design/characterization

2) TUE is tested at  $V_{\text{AREF}}$  = 5.0 V,  $V_{\text{AGND}}$  = 0 V,  $V_{\text{DDP}}$  = 5.0 V.

- 3) An overload current  $(I_{OV})$  through a pin injects a certain error current  $(I_{INJ})$  into the adjacent pins. This error current adds to the respective pin's leakage current  $(I_{OZ})$ . The amount of error current depends on the overload current and is defined by the overload coupling factor  $K_{OV}$ . The polarity of the injected error current is inverse compared to the polarity of the overload current that produces it. The total current through a pin is  $|I_{TOT}| = |I_{OZ1}| + (|I_{OV}| \times K_{OV})$ . The additional error current may distort the input voltage on analog inputs.
- 4) This represents an equivalent switched capacitance. This capacitance is not switched to the reference voltage at once. Instead of this, smaller capacitances are successively switched to the reference voltage.
- 5) The sampling capacity of the conversion C-Network is pre-charged to  $V_{AREF}/2$  before connecting the input to the C-Network. Because of the parasitic elements, the voltage measured at ANx is lower than  $V_{AREF}/2$ .





Figure 39 ADC Input Circuits



# 4.3.4 On-Chip Oscillator Characteristics

 Table 47 provides the characteristics of the on-chip oscillator in the XC886/888.

Table 47	On-chip Oscillator Characteristics (Operating Conditions apply)
----------	---

Parameter	Symbol		Limit Values			Unit	Test Conditions	
			min.	typ.	max.			
Nominal frequency	f <sub>nom</sub>	CC	9.36	9.6	9.84	MHz	under nominal conditions <sup>1)</sup>	
Long term frequency deviation	Δf <sub>LT</sub>	CC	-5.0	-	5.0	%	with respect to $f_{\text{NOM}}$ , over lifetime and temperature (-10°C to 125°C), for one given device after trimming	
			-6.0	_	0	%	with respect to $f_{NOM}$ , over lifetime and temperature (-40°C to -10°C), for one given device after trimming	
Short term frequency deviation	$\Delta f_{\rm ST}$	CC	-1.0	-	1.0	%	within one LIN message (<10 ms 100 ms)	

1) Nominal condition:  $V_{\text{DDC}}$  = 2.5 V,  $T_{\text{A}}$  = + 25°C.



# 4.3.7 SSC Master Mode Timing

Table 51 provides the characteristics of the SSC timing in the XC886/888.

Table 51	SSC Master Mode Timing	(Operating Conditions	apply; $CL = 50  pF$ )
	J		

Parameter	Symbol		Limi	t Values	Unit	Test
			min.	max.		Conditions
SCLK clock period	t <sub>0</sub>	CC	2*T <sub>SSC</sub>	_	ns	1)2)
MTSR delay from SCLK	t <sub>1</sub>	CC	0	8	ns	2)
MRST setup to SCLK	<i>t</i> <sub>2</sub>	SR	24	-	ns	2)
MRST hold from SCLK	<i>t</i> <sub>3</sub>	SR	0	-	ns	2)

1)  $T_{SSCmin} = T_{CPU} = 1/f_{CPU}$ . When  $f_{CPU} = 24$  MHz,  $t_0 = 83.3$  ns.  $T_{CPU}$  is the CPU clock period.

2) Not all parameters are 100% tested, but are verified by design/characterization and test correlation.



Figure 52 SSC Master Mode Timing