



Welcome to E-XFL.COM

What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

Details

Product Status	Active
Core Processor	PIC
Core Size	8-Bit
Speed	25MHz
Connectivity	I ² C, SPI, UART/USART
Peripherals	Brown-out Detect/Reset, LVD, POR, PWM, WDT
Number of I/O	52
Program Memory Size	128KB (64K x 16)
Program Memory Type	FLASH
EEPROM Size	1K x 8
RAM Size	3.75K x 8
Voltage - Supply (Vcc/Vdd)	2V ~ 5.5V
Data Converters	A/D 12x10b
Oscillator Type	External
Operating Temperature	-40°C ~ 85°C (TA)
Mounting Type	Surface Mount
Package / Case	64-TQFP
Supplier Device Package	64-TQFP (10x10)
Purchase URL	https://www.e-xfl.com/product-detail/microchip-technology/pic18lf6720-i-pt

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

Din Nome	Pin N	Pin	Buffer	Description	
	PIC18F6X20	PIC18F8X20	Туре	Туре	Description
MCLR/Vpp	7	9			Master Clear (input) or programming
MCLR			I	ST	Master Clear (Reset) input. This pin is
Vpp			Р		an active-low Reset to the device. Programming voltage input.
OSC1/CLKI OSC1	39	49	I	CMOS/ST	Oscillator crystal or external clock input. Oscillator crystal input or external clock source input. ST buffer when configured
CLKI			I	CMOS	in RC mode; otherwise CMOS. External clock source input. Always associated with pin function OSC1 (see OSC1/CLKI, OSC2/CLKO pins).
OSC2/CLKO/RA6 OSC2	40	50	0	_	Oscillator crystal or clock output. Oscillator crystal output. Connects to crystal or resonator in
CLKO			0	—	In RC mode, OSC2 pin outputs CLKO, which has 1/4 the frequency of OSC1
RA6			I/O	TTL	and denotes the instruction cycle rate. General purpose I/O pin.
Legend: TTL = TTL ST = Schr	compatible inpunitt Trigger inpu	ut ut with CMOS le	evels	CMOS = Analog =	CMOS compatible input or output Analog input

TABLE 1-2: PIC18FXX20 PINOUT I/O DESCRIPTIONS

=	TTL compatible input	CMOS	=	CMOS compatible input or output
=	Schmitt Trigger input with CMOS levels	Analog	=	Analog input
=	Input	0	=	Output
=	Power	OD	=	Open-Drain (no P diode to VDD)

Note 1: Alternate assignment for CCP2 when CCP2MX is not selected (all operating modes except Microcontroller).

2: Default assignment when CCP2MX is set.

Т

Ρ

3: External memory interface functions are only available on PIC18F8X20 devices.

4: CCP2 is multiplexed with this pin by default when configured in Microcontroller mode. Otherwise, it is multiplexed with either RB3 or RC1.

5: PORTH and PORTJ are only available on PIC18F8X20 (80-pin) devices.

6: AVDD must be connected to a positive supply and AVss must be connected to a ground reference for proper operation of the part in user or ICSP modes. See parameter D001A for details.



FIGURE 4-6: DATA MEMORY MAP FOR PIC18FX520 DEVICES

4.12 Indirect Addressing, INDF and FSR Registers

Indirect addressing is a mode of addressing data memory, where the data memory address in the instruction is not fixed. An FSR register is used as a pointer to the data memory location that is to be read or written. Since this pointer is in RAM, the contents can be modified by the program. This can be useful for data tables in the data memory and for software stacks. Figure 4-9 shows the operation of indirect addressing. This shows the moving of the value to the data memory address, specified by the value of the FSR register.

Indirect addressing is possible by using one of the INDF registers. Any instruction using the INDF register actually accesses the register pointed to by the File Select Register, FSR. Reading the INDF register itself, indirectly (FSR = 0), will read 00h. Writing to the INDF register indirectly, results in a no operation. The FSR register contains a 12-bit address, which is shown in Figure 4-10.

The INDFn register is not a physical register. Addressing INDFn actually addresses the register whose address is contained in the FSRn register (FSRn is a pointer). This is indirect addressing.

Example 4-4 shows a simple use of indirect addressing to clear the RAM in Bank 1 (locations 100h-1FFh) in a minimum number of instructions.

EXAMPLE 4-4: HOW TO CLEAR RAM (BANK 1) USING INDIRECT ADDRESSING

	LFSR	FSR0 ,0x100	;	
NEXT	CLRF	POSTINC0	;	Clear INDF
			;	register and
			;	inc pointer
	BTFSS	FSROH, 1	;	All done with
			;	Bank 1?
	GOTO	NEXT	;	NO, clear next
CONTINU	Έ		;	YES, continue

There are three indirect addressing registers. To address the entire data memory space (4096 bytes), these registers are 12 bits wide. To store the 12 bits of addressing information, two 8-bit registers are required. These indirect addressing registers are:

- 1. FSR0: composed of FSR0H:FSR0L
- 2. FSR1: composed of FSR1H:FSR1L
- 3. FSR2: composed of FSR2H:FSR2L

In addition, there are registers INDF0, INDF1 and INDF2, which are not physically implemented. Reading or writing to these registers activates indirect addressing, with the value in the corresponding FSR register being the address of the data. If an instruction writes a value to INDF0, the value will be written to the address pointed to by FSR0H:FSR0L. A read from INDF1 reads

the data from the address pointed to by FSR1H:FSR1L. INDFn can be used in code anywhere an operand can be used.

If INDF0, INDF1 or INDF2 are read indirectly via an FSR, all '0's are read (zero bit is set). Similarly, if INDF0, INDF1 or INDF2 are written to indirectly, the operation will be equivalent to a NOP instruction and the Status bits are not affected.

4.12.1 INDIRECT ADDRESSING OPERATION

Each FSR register has an INDF register associated with it, plus four additional register addresses. Performing an operation on one of these five registers determines how the FSR will be modified during indirect addressing.

When data access is done to one of the five INDFn locations, the address selected will configure the FSRn register to:

- Do nothing to FSRn after an indirect access (no change) INDFn.
- Auto-decrement FSRn after an indirect access (post-decrement) POSTDECn.
- Auto-increment FSRn after an indirect access (post-increment) POSTINCn.
- Auto-increment FSRn before an indirect access (pre-increment) PREINCn.
- Use the value in the WREG register as an offset to FSRn. Do not modify the value of the WREG or the FSRn register after an indirect access (no change) – PLUSWn.

When using the auto-increment or auto-decrement features, the effect on the FSR is not reflected in the Status register. For example, if the indirect address causes the FSR to equal '0', the Z bit will not be set.

Incrementing or decrementing an FSR affects all 12 bits. That is, when FSRnL overflows from an increment, FSRnH will be incremented automatically.

Adding these features allows the FSRn to be used as a stack pointer, in addition to its uses for table operations in data memory.

Each FSR has an address associated with it that performs an indexed indirect access. When a data access to this INDFn location (PLUSWn) occurs, the FSRn is configured to add the signed value in the WREG register and the value in FSR to form the address before an indirect access. The FSR value is not changed.

If an FSR register contains a value that points to one of the INDFn, an indirect read will read 00h (zero bit is set), while an indirect write will be equivalent to a NOP (Status bits are not affected).

If an indirect addressing operation is done where the target address is an FSRnH or FSRnL register, the write operation will dominate over the pre- or post-increment/ decrement functions.

6.2 16-bit Mode

The External Memory Interface implemented in PIC18F8X20 devices operates only in 16-bit mode. The mode selection is not software configurable, but is programmed via the configuration bits.

The WM<1:0> bits in the MEMCON register determine three types of connections in 16-bit mode. They are referred to as:

- 16-bit Byte Write
- 16-bit Word Write
- 16-bit Byte Select

These three different configurations allow the designer maximum flexibility in using 8-bit and 16-bit memory devices.

For all 16-bit modes, the Address Latch Enable (ALE) pin indicates that the address bits A<15:0> are available on the External Memory Interface bus. Following the address latch, the Output Enable signal (\overline{OE}) will enable both bytes of program memory at once to form a 16-bit instruction word. The Chip Enable signal (\overline{CE}) is active at any time that the microcontroller accesses external memory, whether reading or writing; it is inactive (asserted high) whenever the device is in Sleep mode.

In Byte Select mode, JEDEC standard Flash memories will require BA0 for the byte address line and one I/O line to select between Byte and Word mode. The other 16-bit modes do not need BA0. JEDEC standard static RAM memories will use the UB or LB signals for byte selection.

6.2.1 16-BIT BYTE WRITE MODE

Figure 6-1 shows an example of 16-bit Byte Write mode for PIC18F8X20 devices. This mode is used for two separate 8-bit memories connected for 16-bit operation. This generally includes basic EPROM and Flash devices. It allows table writes to byte-wide external memories.

During a TBLWT instruction cycle, the TABLAT data is presented on the upper and <u>lower bytes</u> of the AD15:AD0 bus. The appropriate WRH or WRL control line is strobed on the LSb of the TBLPTR.









FIGURE 10-4: BLOCK DIAGRAM OF RA6 PIN (WHEN ENABLED AS I/O)



TABLE 10-15: PORTH FUNCTIONS

Name	Bit#	Buffer Type	Function
RH0/A16	bit 0	ST/TTL ⁽¹⁾	Input/output port pin or address bit 16 for external memory interface.
RH1/A17	bit 1	ST/TTL ⁽¹⁾	Input/output port pin or address bit 17 for external memory interface.
RH2/A18	bit 2	ST/TTL ⁽¹⁾	Input/output port pin or address bit 18 for external memory interface.
RH3/A19	bit 3	ST/TTL ⁽¹⁾	Input/output port pin or address bit 19 for external memory interface.
RH4/AN12	bit 4	ST	Input/output port pin or analog input channel 12.
RH5/AN13	bit 5	ST	Input/output port pin or analog input channel 13.
RH6/AN14	bit 6	ST	Input/output port pin or analog input channel 14.
RH7/AN15	bit 7	ST	Input/output port pin or analog input channel 15.

Legend: ST = Schmitt Trigger input, TTL = TTL input

Note 1: Input buffers are Schmitt Triggers when in I/O mode and TTL buffers when in System Bus or Parallel Slave Port mode.

TABLE 10-16:	SUMMARY OF	REGISTERS	ASSOCIATED	WITH PORTH
				•••••

Name	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0	Value on POR, BOR	Value on all other Resets
TRISH	PORTH Data Direction Control Register								1111 1111	1111 1111
PORTH	Read PORTH pin/Write PORTH Data Latch								xxxx xxxx	uuuu uuuu
LATH	Read PORTH Data Latch/Write PORTH Data Latch							xxxx xxxx	uuuu uuuu	
ADCON1	—	_	VCFG1	VCFG0	PCFG3	PCFG2	PCFG1	PCFG0	00 0000	00 0000
MEMCON	EBDIS		WAIT1	WAIT0	_	_	WM1	WM0	0-0000	0-0000

Legend: x = unknown, u = unchanged, - = unimplemented. Shaded cells are not used by PORTH.

11.0 TIMER0 MODULE

The Timer0 module has the following features:

- Software selectable as an 8-bit or 16-bit timer/counter
- Readable and writable
- Dedicated 8-bit software programmable prescaler
- · Clock source selectable to be external or internal
- Interrupt-on-overflow from FFh to 00h in 8-bit mode and FFFFh to 0000h in 16-bit mode
- Edge select for external clock

Figure 11-1 shows a simplified block diagram of the Timer0 module in 8-bit mode and Figure 11-2 shows a simplified block diagram of the Timer0 module in 16-bit mode.

The T0CON register (Register 11-1) is a readable and writable register that controls all the aspects of Timer0, including the prescale selection.

REGISTER 11-1:	T0CON: TIMER0 CONTROL REGISTER

R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1
TMR0ON	T08BIT	TOCS	T0SE	PSA	T0PS2	T0PS1	T0PS0
bit 7							bit 0

- bit 7 TMR0ON: Timer0 On/Off Control bit
 - 1 = Enables Timer0
 - 0 = Stops Timer0
- bit 6 **T08BIT:** Timer0 8-bit/16-bit Control bit
 - 1 = Timer0 is configured as an 8-bit timer/counter
 - 0 = Timer0 is configured as a 16-bit timer/counter
- bit 5 **TOCS:** Timer0 Clock Source Select bit
 - 1 = Transition on TOCKI pin
 - 0 = Internal instruction cycle clock (CLKO)
- bit 4 TOSE: Timer0 Source Edge Select bit
 - 1 = Increment on high-to-low transition on T0CKI pin
 - 0 = Increment on low-to-high transition on T0CKI pin
- bit 3 **PSA:** Timer0 Prescaler Assignment bit
 - 1 = TImer0 prescaler is NOT assigned. Timer0 clock input bypasses prescaler.
 - 0 = Timer0 prescaler is assigned. Timer0 clock input comes from prescaler output.
- bit 2-0 TOPS2:TOPS0: Timer0 Prescaler Select bits
 - 111 = 1:256 prescale value
 - 110 = 1:128 prescale value
 - 101 = 1:64 prescale value
 - 100 = 1:32 prescale value
 - 011 = 1:16 prescale value
 - 010 = 1:8 prescale value
 - 001 = 1:4 prescale value
 - 000 = 1:2 prescale value

Legend:					
R = Readable bit	W = Writable bit	U = Unimplemented bit, read as '0'			
- n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown		

17.4.4.5 Clock Synchronization and the CKP bit

When the CKP bit is cleared, the SCL output is forced to '0'. However, clearing the CKP bit will not assert the SCL output low until the SCL output is already sampled low. Therefore, the CKP bit will not assert the SCL line until an external I^2C master device has

already asserted the SCL line. The SCL output will remain low until the CKP bit is set and all other devices on the I^2 C bus have deasserted SCL. This ensures that a write to the CKP bit will not violate the minimum high time requirement for SCL (see Figure 17-12).







17.4.14 SLEEP OPERATION

While in Sleep mode, the I²C module can receive addresses or data and when an address match or complete byte transfer occurs, wake the processor from Sleep (if the MSSP interrupt is enabled).

17.4.15 EFFECT OF A RESET

A Reset disables the MSSP module and terminates the current transfer.

17.4.16 MULTI-MASTER MODE

In Multi-Master mode, the interrupt generation on the detection of the Start and Stop conditions allows the determination of when the bus is free. The Stop (P) and Start (S) bits are cleared from a Reset or when the MSSP module is disabled. Control of the I^2C bus may be taken when the P bit (SSPSTAT<4>) is set, or the bus is idle with both the S and P bits clear. When the bus is busy, enabling the SSP interrupt will generate the interrupt when the Stop condition occurs.

In multi-master operation, the SDA line must be monitored for arbitration, to see if the signal level is the expected output level. This check is performed in hardware, with the result placed in the BCLIF bit.

The states where arbitration can be lost are:

- Address Transfer
- Data Transfer
- A Start Condition
- A Repeated Start Condition
- An Acknowledge Condition

17.4.17 MULTI -MASTER COMMUNICATION, BUS COLLISION AND BUS ARBITRATION

Multi-Master mode support is achieved by bus arbitration. When the master outputs address/data bits onto the SDA pin, arbitration takes place when the master outputs a '1' on SDA, by letting SDA float high and another master asserts a '0'. When the SCL pin floats high, data should be stable. If the expected data on SDA is a '1' and the data sampled on the SDA pin = 0, then a bus collision has taken place. The master will set the Bus Collision Interrupt Flag, BCLIF and reset the I^2C port to its Idle state (Figure 17-25).

If a transmit was in progress when the bus collision occurred, the transmission is halted, the BF flag is cleared, the SDA and SCL lines are deasserted and the SSPBUF can be written to. When the user services the bus collision Interrupt Service Routine and if the I^2C bus is free, the user can resume communication by asserting a Start condition.

If a Start, Repeated Start, Stop, or Acknowledge condition was in progress when the bus collision occurred, the condition is aborted, the SDA and SCL lines are deasserted and the respective control bits in the SSPCON2 register are cleared. When the user services the bus collision Interrupt Service Routine and if the I^2C bus is free, the user can resume communication by asserting a Start condition.

The master will continue to monitor the SDA and SCL pins. If a Stop condition occurs, the SSPIF bit will be set.

A write to the SSPBUF will start the transmission of data at the first data bit, regardless of where the transmitter left off when the bus collision occurred.

In Multi-Master mode, the interrupt generation on the detection of Start and Stop conditions allows the determination of when the bus is free. Control of the I^2C bus can be taken when the P bit is set in the SSPSTAT register, or the bus is Idle and the S and P bits are cleared.

FIGURE 17-25: BUS COLLISION TIMING FOR TRANSMIT AND ACKNOWLEDGE



© 2003-2013 Microchip Technology Inc.

22.1 Control Register

bit 5

The Low-Voltage Detect Control register controls the operation of the Low-Voltage Detect circuitry.

REGISTER 22-1: LVDCON REGISTER

U-0	U-0	R-0	R/W-0	R/W-0	R/W-1	R/W-0	R/W-1
—	—	IRVST	LVDEN	LVDL3	LVDL2	LVDL1	LVDL0
bit 7							bit 0

bit 7-6 Unimplemented: Read as '0'

IRVST: Internal Reference Voltage Stable Flag bit

- 1 = Indicates that the Low-Voltage Detect logic will generate the interrupt flag at the specified voltage range
- 0 = Indicates that the Low-Voltage Detect logic will not generate the interrupt flag at the specified voltage range and the LVD interrupt should not be enabled
- bit 4 LVDEN: Low-Voltage Detect Power Enable bit
 - 1 = Enables LVD, powers up LVD circuit

0 = Disables LVD, powers down LVD circuit

bit 3-0 LVDL3:LVDL0: Low-Voltage Detection Limit bits⁽²⁾

1111 = External analog input is used (input comes from the LVDIN pin)

- 1110 = 4.64V 1101 = 4.33V 1100 = 4.13V 1001 = 3.72V 1001 = 3.61V 1000 = 3.41V 0111 = 3.1V 0110 = 2.89V 0101 = 2.78V 0100 = 2.58V 0011 = 2.47V 0010 = 2.27V 0001 = 2.06V 0000 = Reserved
 - **Note 1:** LVDL3:LVDL0 modes which result in a trip point below the valid operating voltage of the device are not tested.
 - 2: Typical values shown, see parameter D420 in Table 26-3 for more information.

Legend:			
R = Readable bit	W = Writable bit	U = Unimplemented	bit, read as '0'
- n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown

File	Name	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0	Default/ Unprogrammed Value
300001h	CONFIG1H	—	—	OSCSEN	—	_	FOSC2	FOSC1	FOSC0	1111
300002h	CONFIG2L	—	_	_	—	BORV1	BORV0	BODEN	PWRTEN	1111
300003h	CONFIG2H	—	—	_	—	WDTPS2	WDTPS1	WDTPS0	WDTEN	1111
300004h ⁽¹⁾	CONFIG3L	WAIT	_	—	—	—	—	PM1	PM0	111
300005h	CONFIG3H	—	—	_	—	_	—	r(3)	CCP2MX	11
300006h	CONFIG4L	DEBUG	—	_	—	_	LVP	—	STVREN	11-1
300008h	CONFIG5L	CP7 ⁽²⁾	CP6 ⁽²⁾	CP5 ⁽²⁾	CP4 ⁽²⁾	CP3	CP2	CP1	CP0	1111 1111
300009h	CONFIG5H	CPD	CPB	_	—	_	—	_	—	11
30000Ah	CONFIG6L	WRT7 ⁽²⁾	WRT6 ⁽²⁾	WRT5 ⁽²⁾	WRT4 ⁽²⁾	WRT3	WRT2	WRT1	WRT0	1111 1111
30000Bh	CONFIG6H	WRTD	WRTB	WRTC	—	—	—	—	—	111
30000Ch	CONFIG7L	EBTR7 ⁽²⁾	EBTR6 ⁽²⁾	EBTR5 ⁽²⁾	EBTR4 ⁽²⁾	EBTR3	EBTR2	EBTR1	EBTR0	1111 1111
30000Dh	CONFIG7H	—	EBTRB	_	—	_	—	—	—	-1
3FFFFEh	DEVID1	DEV2	DEV1	DEV0	REV4	REV3	REV2	REV1	REV0	(4)
3FFFFFh	DEVID2	DEV10	DEV9	DEV8	DEV7	DEV6	DEV5	DEV4	DEV3	0000 0110

TABLE 23-1: CONFIGURATION BITS AND DEVICE IDS

Legend: x = unknown, u = unchanged, -= unimplemented, q = value depends on condition, r = reserved. Shaded cells are unimplemented, read as '0'.

Note 1: Unimplemented in PIC18F6X20 devices; maintain this bit set.

2: Unimplemented in PIC18FX520 and PIC18FX620 devices; maintain this bit set.

3: Unimplemented in PIC18FX620 and PIC18FX720 devices; maintain this bit set.

4: See Register 23-13 for DEVID1 values.

REGISTER 23-1: CONFIG1H: CONFIGURATION REGISTER 1 HIGH (BYTE ADDRESS 300001h)

U-0	U-0	R/P-1	U-0	U-0	R/P-1	R/P-1	R/P-1
_	_	OSCSEN	—	—	FOSC2	FOSC1	FOSC0
bit 7							bit 0

bit 7-6 Unimplemented: Read as '0'

bit 5 **OSCSEN**: Oscillator System Clock Switch Enable bit

1 = Oscillator system clock switch option is disabled (main oscillator is source)

0 = Timer1 Oscillator system clock switch option is enabled (oscillator switching is enabled)

bit 4-3 Unimplemented: Read as '0'

bit 2-0 FOSC2:FOSC0: Oscillator Selection bits

111 = RC oscillator w/ OSC2 configured as RA6

- 110 = HS oscillator with PLL enabled; clock frequency = (4 x FOSC)
- 101 = EC oscillator w/ OSC2 configured as RA6
- 100 = EC oscillator w/ OSC2 configured as divide-by-4 clock output
- 011 = RC oscillator w/ OSC2 configured as divide-by-4 clock output
- 010 = HS oscillator
- 001 = XT oscillator
- 000 = LP oscillator

Legend:

R = Readable bit	P = Programmable bit	U = Unimplemented bit, read as '0'
- n = Value when device	e is unprogrammed	u = Unchanged from programmed state

REGISTER 23-12: CONFIG7H: CONFIGURATION REGISTER 7 HIGH (BYTE ADDRESS 30000Dh)

U-0	R/P-1	U-0	U-0	U-0	U-0	U-0	U-0
—	EBTRB	—	—	—	—	—	—
bit 7							bit 0

- bit 7 Unimplemented: Read as '0'
- bit 6 **EBTRB:** Boot Block Table Read Protection bit

For PIC18FX520 devices:

- 1 = Boot Block (000000-0007FFh) not protected from table reads executed in other blocks
- 0 = Boot Block (000000-0007FFh) protected from table reads executed in other blocks
- For PIC18FX620 and PIC18FX720 devices:
- 1 = Boot Block (000000-0001FFh) not protected from table reads executed in other blocks
- 0 = Boot Block (000000-0001FFh) protected from table reads executed in other blocks
- bit 5-0 Unimplemented: Read as '0'

Legend:		
R = Readable bit	P = Programmable bit	U = Unimplemented bit, read as '0'
- n = Value when device	e is unprogrammed	u = Unchanged from programmed state

REGISTER 23-13: DEVICE ID REGISTER 1 FOR PIC18FXX20 DEVICES (ADDRESS 3FFFFEh)

R	R	R	R	R	R	R	R
DEV2	DEV1	DEV0	REV4	REV3	REV2	REV1	REV0
bit 7							bit 0

bit 7-5 **DEV2:DEV0:** Device ID bits

000	=	PIC18F8720
001	=	PIC18F6720
010	=	PIC18F8620
011	=	PIC18F6620

bit 4-0 REV4:REV0: Revision ID bits

These bits are used to indicate the device revision.

Legend:		
R = Readable bit	P = Programmable bit	U = Unimplemented bit, read as '0'
- n = Value when devic	e is unprogrammed	u = Unchanged from programmed state

REGISTER 23-14: DEVICE ID REGISTER 2 FOR PIC18FXX20 DEVICES (ADDRESS 3FFFFFh)

R	R	R	R	R	R	R	R
DEV10	DEV9	DEV8	DEV7	DEV6	DEV5	DEV4	DEV3
bit 7							bit 0

bit 7-0 DEV10:DEV3: Device ID bits

These bits are used with the DEV2:DEV0 bits in the Device ID Register 1 to identify the part number.

Legend:		
R = Readable bit	P = Programmable bit	U = Unimplemented bit, read as '0'
- n = Value when device	e is unprogrammed	u = Unchanged from programmed state

23.4.2 DATA EEPROM CODE PROTECTION

The entire data EEPROM is protected from external reads and writes by two bits: CPD and WRTD. CPD inhibits external reads and writes of data EEPROM. WRTD inhibits external writes to data EEPROM. The CPU can continue to read and write data EEPROM, regardless of the protection bit settings.

23.4.3 CONFIGURATION REGISTER PROTECTION

The configuration registers can be write-protected. The WRTC bit controls protection of the configuration registers. In user mode, the WRTC bit is readable only. WRTC can only be written via ICSP or an external programmer.

23.5 ID Locations

Eight memory locations (200000h-200007h) are designated as ID locations, where the user can store checksum or other code identification numbers. These locations are accessible during normal execution through the TBLRD and TBLWT instructions or during program/verify. The ID locations can be read when the device is code-protected.

23.6 In-Circuit Serial Programming

PIC18FX520/X620/X720 microcontrollers can be serially programmed while in the end application circuit. This is simply done with two lines for clock and data and three other lines for power, ground and the programming voltage. This allows customers to manufacture boards with unprogrammed devices and then program the microcontroller just before shipping the product. This also allows the most recent firmware or a custom firmware to be programmed.

Note:	When	performing	In-Circuit	Serial	
	Progran	nming, verify	that power	is con-	
	nected	to all VDD an	id AVDD pins	of the	
	microcontroller and that all Vss and AVss				
	pins are	grounded.			

23.7 In-Circuit Debugger

When the DEBUG bit in the CONFIG4L Configuration register is programmed to a '0', the In-Circuit Debugger functionality is enabled. This function allows simple debugging functions when used with MPLAB[®] IDE. When the microcontroller has this feature enabled, some of the resources are not available for general use. Table 23-4 shows which features are consumed by the background debugger.

TABLE 23-4: DEBUGGER RESOURCES

I/O pins	RB6, RB7
Stack	2 levels
Program Memory	Last 576 bytes
Data Memory	Last 10 bytes

To use the In-Circuit Debugger function of the microcontroller, the design must implement In-Circuit Serial Programming connections to MCLR/VPP, VDD, GND, RB7 and RB6. This will interface to the In-Circuit Debugger module available from Microchip or one of the third party development tool companies.

23.8 Low-Voltage ICSP Programming

The LVP bit in the CONFIG4L Configuration register enables Low-Voltage ICSP Programming. This mode allows the microcontroller to be programmed via ICSP using a VDD source in the operating voltage range. This only means that VPP does not have to be brought to VIHH, but can instead be left at the normal operating voltage. In this mode, the RB5/PGM pin is dedicated to the programming function and ceases to be a general purpose I/O pin. During programming, VDD is applied to the MCLR/VPP pin. To enter Programming mode, VDD must be applied to the RB5/PGM pin, provided the LVP bit is set. The LVP bit defaults to a '1' from the factory.

- Note 1: The High-Voltage Programming mode is always available, regardless of the state of the LVP bit, by applying VIHH to the MCLR pin.
 - 2: While in Low-Voltage ICSP mode, the RB5 pin can no longer be used as a general purpose I/O pin and should be held low during normal operation.
 - 3: When using Low-Voltage ICSP Programming (LVP) and the pull-ups on PORTB are enabled, bit 5 in the TRISB register must be cleared to disable the pull-up on RB5 and ensure the proper operation of the device.

If Low-Voltage Programming mode is not used, the LVP bit can be programmed to a '0' and RB5/PGM becomes a digital I/O pin. However, the LVP bit may only be programmed when programming is entered with VIHH on MCLR/VPP.

It should be noted that once the LVP bit is programmed to '0', only the High-Voltage Programming mode is available and only High-Voltage Programming mode can be used to program the device.

When using Low-Voltage ICSP Programming, the part must be supplied 4.5V to 5.5V if a bulk erase will be executed. This includes reprogramming of the codeprotect bits from an on state to an off state. For all other cases of Low-Voltage ICSP, the part may be programmed at the normal operating voltage. This means unique user IDs or user code can be reprogrammed or added.

MULLW	Multiply Lit	teral with V	N	MULWF	Multiply	W with f	
Syntax:	[label] M	IULLW k		Syntax:	[label]	MULWF f	[,a]
Operands:	$0 \leq k \leq 255$			Operands:	$0 \le f \le 25$	5	
Operation:	(W) x k \rightarrow F	PRODH:PR	ODL		a ∈ [0,1]		
Status Affected:	None			Operation:	(W) x (f) -	→ PRODH:PI	RODL
Encoding:	0000 1	1101 kk	kk kkkk	Status Affecte	ed: None		
Description:	An unsigned	d multiplica	tion is	Encoding:	0000	001a fff	f ffff
	carried out b of W and the 16-bit result PRODH:PR PRODH cor W is unchar None of the affected. Note that ne carry is pose operation. A possible but	between the e 8-bit litera t is placed i RODL regist ntains the h nged. e status flag either overf sible in this A zero resul t not detect	e contents al 'k'. The n ier pair. iigh byte. s are low nor s t is red.	Description	An unsigr carried ou of W and 'f'. The 16 the PROE pair. PRO byte. Both W an None of th affected. Note that carry is po	ned multiplica it between the the register fi 3-bit result is : DH:PRODL re DH contains and 'f' are unc the status flag neither overf possible in this	tion is e contents le location stored in egister the high hanged. s are low nor
Words:	1				operation	. A zero resu	It is
Cycles:	1				'0', the Ac	cess Bank w	vill be
Q Cycle Activity:					selected,	overriding the	e BSR
Q1	Q2	Q3	Q4		value. If 'a	a' = 1, then the	e bank will
Decode	Read literal 'k'	Process Data	Write registers PRODH: PRODL	Words: Cycles:	value (dei 1	fault).	DOR
				Q Cycle Acti	vitv [.]		
Example:	MULLW 0x	¢C4		Q1	Q2	Q3	Q4
Before Instru W PRODH PRODL After Instruct	ction = 0xE2 = ? = ? ion	2		Decode	e Read register 'f'	Process Data	Write registers PRODH: PRODL
W PRODH PRODL	= 0xE2 = 0xAE = 0x08	2 D 3		Example: Before Ir W REG PRO PRO After Inst W REG PRO PRO	MULWF astruction = 0x = 0x DH = ? DL = ? truction = 0x DH = 0x DH = 0x DL = 0x	REG, 1 C4 B5 C4 B5 8A 94	

TSTFSZ	Test f, ski	Test f, skip if 0					
Syntax:	[label] T	[<i>label</i>] TSTFSZ f[,a]					
Operands:	0 ≤ f ≤ 255 a ∈ [0,1]	0 ≤ f ≤ 255 a ∈ [0.1]					
Operation:	skip if f = (skip if $f = 0$					
Status Affected:	None						
Encodina:	0110	011a fff	f ffff				
Description:	If 'f' = 0, the fetched du instruction and a NOP a two-cycle the Access overriding '1', then the as per the	If 'f' = 0, the next instruction, fetched during the current instruction execution is discarded and a NOP is executed, making this a two-cycle instruction. If 'a' is '0', the Access Bank will be selected, overriding the BSR value. If 'a' is '1', then the bank will be selected as per the BSR value (default).					
Words:	1						
Cycles:	1(2) Note: 3 cy by a	1(2) Note: 3 cycles if skip and followed by a 2-word instruction.					
Q Cycle Activit	y:						
Q1	Q2	Q3	Q4				
Decode	Read	Process Data	No				
If skip:	regiotor r	Data	oporation				
Q1	Q2	Q3	Q4				
No	No	No	No				
operation	operation	operation	operation				
If skip and follo	wed by 2-word	d instruction:	_				
Q1	Q2	Q3	Q4				
No	No	No	No				
No	No	No	No				
operation	operation	operation	operation				
Example:	HERE T NZERO : ZERO :	HERE TSTFSZ CNT, 1 NZERO : ZERO :					
Before Inst	ruction						
PC	= Ad	dress (HERE))				
After Instru	ction	00					
IT CN I PC	= 0x0 = Ad	uu, dress (ZERO))				
If CNT PC	If CNT ≠ 0x00, PC = Address (NZERO)						

XORLW	Exclusiv	Exclusive OR literal with W					
Syntax:	[label])	[label] XORLW k					
Operands:	$0 \le k \le 2k$	$0 \le k \le 255$					
Operation:	(W) .XOF	(W) .XOR. $k \rightarrow W$					
Status Affected:	N, Z						
Encoding:	0000	1010	kkkk	kkkk			
Description:	The cont with the 8 is placed	ents of V 3-bit liter in W.	V are X(al 'k'. Th	OR'ed ne result			
Words:	1						
Cycles:	1						
Q Cycle Activity:							
Q1	Q2	Q3		Q4			
Decode	Read	Proces	ss W	rite to W			

Example: XORLW 0xAF

Before Instruction W = 0xB5 After Instruction

W = 0x1A

XORWF		Exclusiv	Exclusive OR W with f						
Synt	tax:	[label]	XORWF	f [,d [,	a]			
Operands:		$0 \le f \le 25$ $d \in [0,1]$ $a \in [0,1]$	$\begin{array}{l} 0 \leq f \leq 255 \\ d \in [0,1] \\ a \in [0,1] \end{array}$						
Ope	ration:	(W) .XOR	(W) .XOR. (f) \rightarrow dest						
Statu	us Affected:	N, Z	N, Z						
Enco	oding:	0001	10da	fff	f	ffff			
Description:		Exclusive with regis is stored (default). Bank will the BSR bank will BSR valu	Exclusive OR the contents of W with register 'f'. If 'd' is '0', the result is stored in W. If 'd' is '1', the result is stored back in register 'f' (default). If 'a' is '0', the Access Bank will be selected, overriding the BSR value. If 'a' is '1', then the bank will be selected as per the BSR value (default).						
Wor	ds:	1							
Cycl	es:	1							
QC	Cycle Activity:								
	Q1	Q2	Q2 Q3		Q4				
	Decode	Read register 'f'	Read Proce register 'f' Data		W des	/rite to stination			
<u>Exar</u>	<u>mple</u> :	XORWF	REG, 1,	0					
	Before Instru REG W	uction = 0xAF = 0xB5							
	After Instruct REG W	tion = 0x1A = 0xB5							

FIGURE 26-5: LOW-VOLTAGE DETECT CHARACTERISTICS



TABLE 26-3: LOW-VOLTAGE DETECT CHARACTERISTICS

Standard Operating Conditions (unless otherwise stated)

Operating temperature $~-40^\circ C \le TA \le +85^\circ C$ for industrial $-40^\circ C ~\le TA \le +125^\circ C$ for extended

Param No.	Symbol	Characteristic		Min	Тур†	Max	Units	Conditions
D420		LVD Voltage on VDD	LVV = 0001	1.96	2.06	2.16	V	
		Transition high-to-low	LVV = 0010	2.16	2.27	2.38	V	
			LVV = 0011	2.35	2.47	2.59	V	
			LVV = 0100	2.45	2.58	2.71	V	
			LVV = 0101	2.64	2.78	2.92	V	
			LVV = 0110	2.75	2.89	3.03	V	
			LVV = 0111	2.95	3.1	3.26	V	
			LVV = 1000	3.24	3.41	3.58	V	
			LVV = 1001	3.43	3.61	3.79	V	
			LVV = 1010	3.53	3.72	3.91	V	
			LVV = 1011	3.72	3.92	4.12	V	
			LVV = 1100	3.92	4.13	4.34	V	
			LVV = 1101	4.11	4.33	4.55	V	
			LVV = 1110	4.41	4.64	4.87	V	
D423	Vbg	Band Gap Reference Voltage Value			1.22		V	

† Production tested at TAMB = 25°C. Specifications over temperature limits ensured by characterization.

Param No.	Symbol	Characteristic			Min	Max	Units	Conditions
50	TCCL CCPx Input Low		No prescaler		0.5 TCY + 20		ns	
		Time	With	PIC18FXX20	10	—	ns	
			prescaler	PIC18LFXX20	20		ns	
51 TccH		CCPx Input High	No prescaler		0.5 Tcy + 20		ns	
		Time	With	PIC18FXX20	10		ns	
			prescaler	PIC18LFXX20	20	—	ns	
52	TCCP	CCPx Input Period			<u>3 Tcy + 40</u> N		ns	N = prescale value (1, 4 or 16)
53	TCCR CCPx Output Rise Time		PIC18FXX20		25	ns		
				PIC18LFXX20		45	ns	VDD = 2.0V
54	TCCF	CCPx Output Fall Time		PIC18FXX20	_	25	ns	
				PIC18LFXX20		45	ns	VDD = 2.0V

TABLE 26-13: CAPTURE/COMPARE/PWM REQUIREMENTS (ALL CCP MODULES)





27.0 DC AND AC CHARACTERISTICS GRAPHS AND TABLES

Note: The graphs and tables provided following this note are a statistical summary based on a limited number of samples and are provided for informational purposes only. The performance characteristics listed herein are not tested or guaranteed. In some graphs or tables, the data presented may be outside the specified operating range (e.g., outside specified power supply range) and therefore, outside the warranted range.

"Typical" represents the mean of the distribution at 25°C. "Maximum" or "minimum" represents (mean + 3σ) or (mean – 3σ) respectively, where σ is a standard deviation, over the whole temperature range.







MAXIMUM IDD vs. Fosc OVER VDD (HS MODE) INDUSTRIAL

