

Welcome to E-XFL.COM

What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

Details

E·XFI

Product Status	Obsolete
Core Processor	PIC
Core Size	16-Bit
Speed	20 MIPS
Connectivity	I ² C, IrDA, LINbus, SPI, UART/USART
Peripherals	Brown-out Detect/Reset, POR, PWM, WDT
Number of I/O	35
Program Memory Size	32KB (11K x 24)
Program Memory Type	FLASH
EEPROM Size	-
RAM Size	2K x 8
Voltage - Supply (Vcc/Vdd)	3V ~ 3.6V
Data Converters	A/D 13x10b/12b
Oscillator Type	Internal
Operating Temperature	-40°C ~ 150°C (TA)
Mounting Type	Surface Mount
Package / Case	44-TQFP
Supplier Device Package	44-TQFP (10x10)
Purchase URL	https://www.e-xfl.com/product-detail/microchip-technology/pic24hj32gp204-h-pt

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

Pin Diagrams



Table of Contents

		•
1.0	Device Overview	
2.0	Guidelines for Getting Started with 16-bit Microcontrollers	
3.0		
4.0	Memory Organization	
5.0	Final Program Memory	
6.0	Resets	
7.0	Interrupt Controller	
8.0	Oscillator Configuration	
9.0	Power-Saving Features	
10.0	I/O Ports	105
11.0	Timer1	127
12.0	Timer2/3 Feature	131
13.0	Input Capture	137
14.0	Output Compare	141
15.0	Serial Peripheral Interface (SPI)	145
16.0	Inter-Integrated Circuit™ (I ² C [™])	151
17.0	Universal Asynchronous Receiver Transmitter (UART)	159
18.0	10-bit/12-bit Analog-to-Digital Converter (ADC)	165
19.0	Special Features	179
20.0	Instruction Set Summary	187
21.0	Development Support	195
22.0	Electrical Characteristics	199
23.0	High Temperature Electrical Characteristics	245
24.0	DC and AC Device Characteristics Graphs	255
25.0	Packaging Information	259
Appe	ndix A: Revision History	271
Index	٢	281
The N	Vicrochip Web Site	285
Custo	omer Change Notification Service	285
Custo	omer Support	
Read	er Response	
Produ	uct Identification System	

TO OUR VALUED CUSTOMERS

It is our intention to provide our valued customers with the best documentation possible to ensure successful use of your Microchip products. To this end, we will continue to improve our publications to better suit your needs. Our publications will be refined and enhanced as new volumes and updates are introduced.

If you have any questions or comments regarding this publication, please contact the Marketing Communications Department via E-mail at **docerrors@microchip.com** or fax the **Reader Response Form** in the back of this data sheet to (480) 792-4150. We welcome your feedback.

Most Current Data Sheet

To obtain the most up-to-date version of this data sheet, please register at our Worldwide Web site at:

http://www.microchip.com

You can determine the version of a data sheet by examining its literature number found on the bottom outside corner of any page. The last character of the literature number is the version number, (e.g., DS30000A is version A of document DS30000).

Errata

An errata sheet, describing minor operational differences from the data sheet and recommended workarounds, may exist for current devices. As device/documentation issues become known to us, we will publish an errata sheet. The errata will specify the revision of silicon and revision of document to which it applies.

To determine if an errata sheet exists for a particular device, please check with one of the following:

Microchip's Worldwide Web site; http://www.microchip.com

· Your local Microchip sales office (see last page)

When contacting a sales office, please specify which device, revision of silicon and data sheet (include literature number) you are using.

Customer Notification System

Register on our web site at www.microchip.com to receive the most current information on all of our products.

FIGURE 3-2:	PIC24HJ32GP202	2/204 AND PIC24HJ16GP304	PROGRAMMER'S MODEL
		D15 D0	
		W0/WREG	
		W1	
		W2	DO Shadow
		W3	L
		W4	
		W5	
		W6	
		W7	Working Pogistor
		W8	
		W9	
		W10	
		W11	
		W12	
		W13	
		W14/Frame Pointer	
		W15/Stack Pointer	J
		SPLIM	Stack Pointer Limit Register
PC22		PC0	
		0	Program Counter
7	0		
TBLP	AG Data Tabl	le Page Address	
7	0		
PS	VPAG Progra	am Space Visibility Page Address	
<u> </u>			
		RECONT	REPEAT LOOP Counter
		15 0	
		CORCON	Core Configuration Register
		DC IPLZ IPLI IPLO RA N C	JV Z C STATUS Register
<	SRH	SRL SRL	→

	· · · ·		201011		1 0111	1024110		02										
File Name	Addr	Bit 15	Bit 14	Bit 13	Bit 12	Bit 11	Bit 10	Bit 9	Bit 8	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0	All Resets
ADC1BUF0	0300		ADC Data Buffer 0 xx												xxxx			
ADC1BUF1	0302		ADC Data Buffer 1 xxxx										xxxx					
ADC1BUF2	0304		ADC Data Buffer 2 xxxx									xxxx						
ADC1BUF3	0306								ADC Dat	a Buffer 3								xxxx
ADC1BUF4	0308								ADC Dat	a Buffer 4								xxxx
ADC1BUF5	030A								ADC Dat	a Buffer 5								xxxx
ADC1BUF6	030C								ADC Dat	a Buffer 6								xxxx
ADC1BUF7	030E								ADC Dat	a Buffer 7								xxxx
ADC1BUF8	0310								ADC Dat	a Buffer 8								xxxx
ADC1BUF9	0312								ADC Dat	a Buffer 9								xxxx
ADC1BUFA	0314								ADC Data	Buffer 10								xxxx
ADC1BUFB	0316								ADC Data	Buffer 11								xxxx
ADC1BUFC	0318								ADC Data	Buffer 12								xxxx
ADC1BUFD	031A								ADC Data	Buffer 13								xxxx
ADC1BUFE	031C								ADC Data	Buffer 14								xxxx
ADC1BUFF	031E								ADC Data	Buffer 15								xxxx
AD1CON1	0320	ADON	—	ADSIDL	_	—	AD12B	FOR	M<1:0>	5	SSRC<2:0>	>	—	SIMSAM	ASAM	SAMP	DONE	0000
AD1CON2	0322	Ň	VCFG<2:0	>	_	—	CSCNA	CHP	S<1:0>	BUFS			SMPI	<3:0>		BUFM	ALTS	0000
AD1CON3	0324	ADRC	_	—		-	SAMC<4:0	>	_				ADCS	S<7:0>	-		_	0000
AD1CHS123	0326	—	_	—	—	—	CH123N	NB<1:0>	CH123SB	—	_	—	—	—	CH123	NA<1:0>	CH123SA	0000
AD1CHS0	0328	CH0NB	_	—		(CH0SB<4:0)>		CH0NA	_	—			CH0SA<4:	0>		0000
AD1PCFGL	032C		—	—	PCFG12	PCFG11	PCFG10	PCFG9		—		PCFG5	PCFG4	PCFG3	PCFG2	PCFG1	PCFG0	0000
AD1CSSL	0330	-	—	—	CSS12	CSS11	CSS10	CSS9	—	_	—	CSS5	CSS4	CSS3	CSS2	CSS1	CSS0	0000

TABLE 4-15: ADC1 REGISTER MAP FOR PIC24HJ32GP202

Legend: x = unknown value on Reset, — = unimplemented, read as '0'. Reset values are shown in hexadecimal.

IPC0: INTERRUPT PRIORITY CONTROL REGISTER 0 **REGISTER 7-11:** U-0 R/W-1 R/W-0 R/W-0 U-0 R/W-1 R/W-0 R/W-0 T1IP<2:0> OC1IP<2:0> bit 8 bit 15 R/W-1 R/W-0 U-0 R/W-0 R/W-0 U-0 R/W-1 R/W-0 IC1IP<2:0> INT0IP<2:0> bit 7 bit 0 Legend: R = Readable bit W = Writable bit U = Unimplemented bit, read as '0' -n = Value at POR '1' = Bit is set '0' = Bit is cleared x = Bit is unknown bit 15 Unimplemented: Read as '0' bit 14-12 T1IP<2:0>: Timer1 Interrupt Priority bits 111 = Interrupt is priority 7 (highest priority interrupt) 001 = Interrupt is priority 1 000 = Interrupt source is disabled bit 11 Unimplemented: Read as '0' bit 10-8 OC1IP<2:0>: Output Compare Channel 1 Interrupt Priority bits 111 = Interrupt is priority 7 (highest priority interrupt) 001 = Interrupt is priority 1 000 = Interrupt source is disabled bit 7 Unimplemented: Read as '0' bit 6-4 IC1IP<2:0>: Input Capture Channel 1 Interrupt Priority bits 111 = Interrupt is priority 7 (highest priority interrupt) 001 = Interrupt is priority 1 000 = Interrupt source is disabled bit 3 Unimplemented: Read as '0' bit 2-0 INTOIP<2:0>: External Interrupt 0 Priority bits 111 = Interrupt is priority 7 (highest priority interrupt) 001 = Interrupt is priority 1 000 = Interrupt source is disabled

U-0 R/W-1 R/W-0 R/W-0 U-0 R/W-1 R/W-0 R/W-0 U1RXIP<2:0> SPI1IP<2:0> bit 8 bit 15 R/W-0 R/W-0 U-0 R/W-1 R/W-0 R/W-0 U-0 R/W-1 SPI1EIP<2:0> T3IP<2:0> bit 7 bit 0 Legend: R = Readable bit W = Writable bit U = Unimplemented bit, read as '0' -n = Value at POR '1' = Bit is set '0' = Bit is cleared x = Bit is unknown bit 15 Unimplemented: Read as '0' bit 14-12 U1RXIP<2:0>: UART1 Receiver Interrupt Priority bits 111 = Interrupt is priority 7 (highest priority interrupt) 001 = Interrupt is priority 1 000 = Interrupt source is disabled bit 11 Unimplemented: Read as '0' bit 10-8 SPI1IP<2:0>: SPI1 Event Interrupt Priority bits 111 = Interrupt is priority 7 (highest priority interrupt) 001 = Interrupt is priority 1 000 = Interrupt source is disabled bit 7 Unimplemented: Read as '0' bit 6-4 SPI1EIP<2:0>: SPI1 Error Interrupt Priority bits 111 = Interrupt is priority 7 (highest priority interrupt) 001 = Interrupt is priority 1 000 = Interrupt source is disabled bit 3 Unimplemented: Read as '0' bit 2-0 T3IP<2:0>: Timer3 Interrupt Priority bits 111 = Interrupt is priority 7 (highest priority interrupt) 001 = Interrupt is priority 1 000 = Interrupt source is disabled

REGISTER 7-13: IPC2: INTERRUPT PRIORITY CONTROL REGISTER 2

8.1 CPU Clocking System

The PIC24HJ32GP202/204 and PIC24HJ16GP304 devices provide the following seven system clock options.

- Fast RC (FRC) Oscillator
- FRC Oscillator with PLL
- Primary (XT, HS or EC) Oscillator
- · Primary Oscillator with PLL
- Secondary (LP) Oscillator
- Low-Power RC (LPRC) Oscillator
- FRC Oscillator with postscaler

8.1.1 SYSTEM CLOCK SOURCES

8.1.1.1 Fast RC

The Fast RC (FRC) internal oscillator runs at a nominal frequency of 7.37 MHz. User software can tune the FRC frequency. User software can optionally specify a factor (ranging from 1:2 to 1:256) by which the FRC clock frequency is divided. This factor is selected using the FRCDIV<2:0> bits (CLKDIV<10:8>).

8.1.1.2 Primary

The primary oscillator can use one of the following as its clock source:

- Crystal (XT): Crystals and ceramic resonators in the range of 3.5 MHz to 10 MHz. The crystal is connected to the OSC1 and OSC2 pins.
- HS (High-Speed Crystal): Crystals in the range of 10 MHz to 40 MHz. The crystal is connected to the OSC1 and OSC2 pins.
- EC (External Clock): The external clock signal is directly applied to the OSC1 pin.

8.1.1.3 Secondary

The secondary (LP) oscillator is designed for low power and uses a 32.768 kHz crystal or ceramic resonator. The LP oscillator uses SOSCI and SOSCO pins.

8.1.1.4 Low-Power RC

The Low-Power RC (LPRC) internal oscillator runs at a nominal frequency of 32.768 kHz. It is also used as a reference clock by the Watchdog Timer (WDT) and Fail-Safe Clock Monitor (FSCM).

8.1.1.5 FRC

The clock signals generated by the FRC and primary oscillators can be optionally applied to an on-chip Phase-Locked Loop (PLL) to provide a wide range of output frequencies for device operation. PLL configuration is described in **Section 8.1.3 "PLL Configuration**".

The FRC frequency depends on the FRC accuracy (see Table 22-18) and the value of the FRC Oscillator Tuning register (see Register 8-4).

8.1.2 SYSTEM CLOCK SELECTION

The oscillator source used at a device Power-on Reset event is selected using Configuration bit settings. The oscillator Configuration bit settings are located in the Configuration registers in the program memory. (Refer to Section 19.1 "Configuration Bits" for further details.) The Initial Oscillator Selection Configuration bits, FNOSC<2:0> (FOSCSEL<2:0>), and the Primary Mode Configuration Oscillator Select bits. POSCMD<1:0> (FOSC<1:0>), select the oscillator source that is used at a Power-on Reset. The FRC primary oscillator is the default (unprogrammed) selection.

The Configuration bits allow users to choose among 12 different clock modes, shown in Table 8-1.

The output of the oscillator (or the output of the PLL if a PLL mode has been selected) FOSC is divided by 2 to generate the device instruction clock (FCY) and the peripheral clock time base (FP). FCY defines the operating speed of the device, and speeds up to 40 MHz are supported by the PIC24HJ32GP202/204 and PIC24HJ16GP304 architecture.

Instruction execution speed or device operating frequency, FCY, is given by:

EQUATION 8-1: DEVICE OPERATING FREQUENCY

$$FCY = \frac{FOSC}{2}$$

8.1.3 PLL CONFIGURATION

The primary oscillator and internal FRC oscillator can optionally use on-chip PLL to obtain higher speeds of operation. The PLL provides significant flexibility in selecting the device operating speed. A block diagram of the PLL is shown in Figure 8-2.

The output of the primary oscillator or FRC, denoted as 'FIN' is divided down by a prescale factor (N1) of 2, 3, ... or 33 before it is being provided to the PLL's Voltage Controlled Oscillator (VCO). The input to the VCO must be selected in the range of 0.8 MHz to 8 MHz. The prescale factor 'N1' is selected using the PLLPRE<4:0> bits (CLKDIV<4:0>).

The PLL Feedback Divisor, selected using the PLLDIV<8:0> bits (PLLFBD<8:0>), provides a factor 'M', by which the input to the VCO is multiplied. This factor must be selected such that the resulting VCO output frequency is in the range of 100 MHz to 200 MHz.

The VCO output is further divided by a postscale factor 'N2.' This factor is selected using the PLLPOST<1:0> bits (CLKDIV<7:6>). 'N2' can be 2, 4 or 8, and must be selected such that the PLL output frequency (Fosc) is in the range of 12.5 MHz to 80 MHz, which generates device operating speeds of 6.25-40 MIPS.

REGISTER 10-15: RPOR5: PERIPHERAL PIN SELECT OUTPUT REGISTER 5

U-0	U-0	U-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0
	_	—			RP11R<4:0>		
bit 15	·						bit 8
U-0	U-0	U-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0

			I	RP10R<4	:0>		
bit 7	•						bit 0
Legend:							

5			
R = Readable bit	W = Writable bit	U = Unimplemented bit, read	l as '0'
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown

bit 15-13 Unimplemented: Read as '0'

bit 12-8 **RP11R<4:0>:** Peripheral Output Function is Assigned to RP11 Output Pin (see Table 10-2 for peripheral function numbers)

bit 7-5 Unimplemented: Read as '0'

bit 4-0 **RP10R<4:0>:** Peripheral Output Function is Assigned to RP10 Output Pin (see Table 10-2 for peripheral function numbers)

REGISTER 10-16: RPOR6: PERIPHERAL PIN SELECT OUTPUT REGISTER 6

U-0	U-0	U-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	
—	—	—			RP13R<4:0>	>		
bit 15							bit 8	
U-0	U-0	U-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	
_	_	—			RP12R<4:0>	>		
bit 7		•					bit 0	
-								
Legend:								
R = Readable	bit	W = Writable	bit	U = Unimpler	nented bit, rea	d as '0'		
-n = Value at F	POR	'1' = Bit is set	et '0' = Bit is cleared x = Bit is unknown					
bit 15-13	Unimplemen	ted: Read as ')'					
bit 12-8	bit 12-8 RP13R<4:0>: Peripheral Output Function is Assigned to RP13 Output Pin (see Table 10-2 for peripheral function numbers)							

bit 7-5 Unimplemented: Read as '0'

bit 4-0 **RP12R<4:0>:** Peripheral Output Function is Assigned to RP12 Output Pin (see Table 10-2 for peripheral function numbers)

12.0 TIMER2/3 FEATURE

- Note 1: This data sheet summarizes the features of the PIC24HJ32GP202/204 and PIC24HJ16GP304 family of devices. It is not intended to be a comprehensive reference source. To complement the information in this data sheet, refer to "Section 11. Timers" (DS70205) of the "dsPIC33F/PIC24H Family Reference Manual", which is available from the Microchip website (www.microchip.com).
 - 2: Some registers and associated bits described in this section may not be available on all devices. Refer to **Section 4.0 "Memory Organization"** in this data sheet for device-specific register and bit information.

The Timer2/3 feature has 32-bit timers that can also be configured as two independent 16-bit timers with selectable operating modes.

As a 32-bit timer, the Timer2/3 feature permits operation in three modes:

- Two Independent 16-bit timers (Timer2 and Timer3) with all 16-bit operating modes (except Asynchronous Counter mode)
- Single 32-bit timer (Timer2/3)
- Single 32-bit synchronous counter (Timer2/3)

The Timer2/3 feature also supports:

- Timer gate operation
- Selectable Prescaler Settings
- Timer operation during Idle and Sleep modes
- · Interrupt on a 32-bit Period Register Match
- Time Base for Input Capture and Output Compare Modules (Timer2 and Timer3 only)
- ADC1 Event Trigger (Timer2/3 only)

Individually, all eight of the 16-bit timers can function as synchronous timers or counters. They also offer the features that are listed above, except for the event trigger. The operating modes and enabled features are determined by setting the appropriate bit(s) in the T2CON and T3CON registers. T2CON registers are shown in generic form in Register 12-1. T3CON registers are shown in Register 12-2.

For 32-bit timer/counter operation, Timer2 is the least significant word (lsw), and Timer3 is the most significant word (msw) of the 32-bit timers.

Note: For 32-bit operation, T3CON control bits are ignored. Only T2CON control bit is used for setup and control. Timer2 clock and gate inputs are used for the 32-bit timer modules, but an interrupt is generated with the Timer3 interrupt flags.

12.1 32-bit Operation

To configure the Timer2/3 feature for 32-bit operation:

- 1. Set the corresponding T32 control bit.
- 2. Select the prescaler ratio for Timer2 using the TCKPS<1:0> bits.
- 3. Set the Clock and Gating modes using the corresponding TCS and TGATE bits.
- 4. Load the timer period value. PR3 contains the most significant word of the value, while PR2 contains the least significant word.
- 5. Set the interrupt enable bit T3IE, if interrupts are required. Use the priority bits T3IP<2:0> to set the interrupt priority. While Timer2 controls the timer, the interrupt appears as a Timer3 interrupt.
- 6. Set the corresponding TON bit.

The timer value at any point is stored in the register pair TMR3:TMR2. TMR3 always contains the most significant word of the count, while TMR2 contains the least significant word.

To configure any of the timers for individual 16-bit operation:

- 1. Clear the T32 bit corresponding to that timer.
- 2. Select the timer prescaler ratio using the TCKPS<1:0> bits.
- 3. Set the Clock and Gating modes using the TCS and TGATE bits.
- 4. Load the timer period value into the PRx register.
- 5. If interrupts are required, set the interrupt enable bit, TxIE. Use the priority bits, TxIP<2:0>, to set the interrupt priority.
- 6. Set the TON bit.

12.2 Timer2/3 Resources

Many useful resources are provided on the main product page of the Microchip web site for the devices listed in this data sheet. This product page, which can be accessed using this link, contains the latest updates and additional information.

Note:	In the event you are not able to access
	the product page using the link above,
	enter this URL in your browser:
	http://www.microchip.com/wwwproducts/
	Devices.aspx?dDocName=en530271

12.2.1 KEY RESOURCES

- Section 11. "Timers" (DS70205)
- Code Samples
- Application Notes
- Software Libraries
- · Webinars
- All related dsPIC33F/PIC24H Family Reference Manuals Sections
- Development Tools

NOTES:

14.2 Output Compare Resources

Many useful resources are provided on the main product page of the Microchip web site for the devices listed in this data sheet. This product page, which can be accessed using this link, contains the latest updates and additional information.

Note:	In the event you are not able to access
	the product page using the link above,
	enter this URL in your browser:
	http://www.microchip.com/wwwproducts/
	Devices.aspx?dDocName=en530271

14.2.1 KEY RESOURCES

- Section 13. "Output Compare" (DS70209)
- Code Samples
- Application Notes
- Software Libraries
- · Webinars
- All related dsPIC33F/PIC24H Family Reference Manuals Sections
- Development Tools

R/W-0	R/W-0	R/W-0	U-0	U-0	U-0	U-0	U-0
FRMEN	SPIFSD	FRMPOL	—	_	—	—	_
bit 15							bit 8
U-0	U-0	U-0	U-0	U-0	U-0	R/W-0	U-0
		<u> </u>	—			FRMDLY	<u> </u>
bit 7							bit 0
Legend:							
R = Readable	bit	W = Writable	bit	U = Unimpler	mented bit, read	as '0'	
-n = Value at F	POR	'1' = Bit is set		'0' = Bit is cle	eared	x = Bit is unkr	nown
bit 15	FRMEN: Fran	ned SPIx Supp	ort bit				
	1 = Framed S	Plx support en	abled (SSx pi	n used as fran	ne sync pulse in	put/output)	
hit 14	SPIESD: Eror	mo Sync Bulso	Direction Cor	atrol bit			
DIL 14	1 = Frame svi	ne oulse input i	(slave)				
	0 = Frame sy	nc pulse output	t (master)				
bit 13	FRMPOL: Fra	ame Sync Puls	e Polarity bit				
	1 = Frame sy	nc pulse is acti	ve-high				
	0 = Frame sy	nc pulse is acti	ve-low				
bit 12-2	Unimplemen	ted: Read as '	0'				
bit 1	FRMDLY: Fra	ame Sync Pulse	e Edge Select	bit			
	1 = Frame sy	nc pulse coinci	des with first l	bit clock			
	0 = Frame sy	nc pulse prece	des first bit clo	DCK			
bit 0	Unimplemen	ted: This bit m	ust not be set	to '1' by the u	ser application		

REGISTER 15-3: SPIxCON2: SPIx CONTROL REGISTER 2

REGISTER 18-4: AD1CHS123: ADC1 INPUT CHANNEL 1, 2, 3 SELECT REGISTER (CONTINUED)

bit 2-1 CH123NA<1:0>: Channel 1, 2, 3 Negative Input Select for Sample A bits

PIC24HJ32GP202 devices only:

If AD12B = 1:

- 11 = Reserved
- 10 = Reserved
- 01 = Reserved
- 00 = Reserved

If AD12B = 0:

11 = CH1 negative input is AN9, CH2 negative input is AN10, CH3 negative input is AN11 10 = Reserved

10 = Reserved

01 = CH1, CH2, CH3 negative input is VREF-

00 = CH1, CH2, CH3 negative input is VREF-

PIC24HJ32GP204 and PIC24HJ16GP304 devices only:

If AD12B = 1:

- 11 = Reserved
- 10 = Reserved
- 01 = Reserved
- 00 = Reserved

If AD12B = 0:

11 = CH1 negative input is AN9, CH2 negative input is AN10, CH3 negative input is AN11

- 10 = CH1 negative input is AN6, CH2 negative input is AN7, CH3 negative input is AN8
- 01 = CH1, CH2, CH3 negative input is VREF-
- 00 = CH1, CH2, CH3 negative input is VREF-

CH123SA: Channel 1, 2, 3 Positive Input Select for Sample A bit

If AD12B = 1:

bit 0

1 = Reserved

0 = Reserved

If AD12B = 0:

- ${\tt 1}$ = CH1 positive input is AN3, CH2 positive input is AN4, CH3 positive input is AN5
- 0 = CH1 positive input is AN0, CH2 positive input is AN1, CH3 positive input is AN2

19.5 JTAG Interface

PIC24HJ32GP202/204 and PIC24HJ16GP304 devices implement a JTAG interface, which supports boundary scan device testing, as well as in-circuit programming. Detailed information on this interface will be provided in future revisions of the document.

19.6 Code Protection and CodeGuard[™] Security

The PIC24HJ32GP202/204 and PIC24HJ16GP304 product family offers the intermediate implementation of CodeGuard Security. CodeGuard Security allows multiple parties to securely share resources (memory,

TABLE 19-3:CODE FLASH SECURITY
SEGMENT SIZES FOR
32 KBYTE DEVICES

CONFIG BITS		
	VS = 256 IW	0x000000 0x0001FE
BSS<2:0>=x11 0K	GS = 11008 IW	0x000200 0x0007FE 0x000800 0x001FFE 0x002000 0x003FFE 0x004000
		0x0057FE
	VS = 256 IW	0x000000 0x0001FE
BSS<2:0>=x10	BS = 768 IW	0x000200 0x0007FE
256		0x000800 0x001FFE 0x002000 0x003FFE 0x004000
	GS = 10240 IW	0x0057FE
	VS = 256 IW	0x000000 0x0001FE
BSS<2:0>=x01	BS = 3840 IW	0x000200 0x0007FE 0x000800 0x001FFE
768	GS = 7168 IW	0x002000 0x003FFE 0x004000
		_0x0057FE
	VS = 256 IW	0x000000 0x0001FE
BSS<2:0>=x00	BS = 7936 IW	0x0007FE 0x000800 0x001FFE
1792		0x002000 0x003FFE
	GS = 3072 IW	0x004000 0x0057FE

interrupts and peripherals) on a single chip. This feature helps to protect individual Intellectual Property in collaborative system designs.

When coupled with software encryption libraries, CodeGuard Security can be used to securely update Flash even when multiple IPs reside on the single chip.

The code protection features are controlled by the Configuration registers: FBS and FGS. The Secure segment and RAM is not implemented.

Note: Refer to Section 23. "CodeGuard™ Security" (DS70199) in the "dsPIC33F/PIC24H Family Reference Manual" for further information on usage, configuration and operation of CodeGuard Security.

TABLE 19-4: CODE FLASH SECURITY SEGMENT SIZES FOR 16 KBYTE DEVICES

CONFIG BITS				
PSS -12:05	VS = 256 IW	0x000000 0x0001FE 0x000200 0x0007FE		
взз<2:0>=x11 0К	GS = 5376 IW	0x000800 0x001FFE 0x002000		
		0x002BFE		
	VS = 256 IW	0x000000 0x0001FE		
BSS<2:0>=x10	BS = 768 IW	0x000200 0x0007FE		
256		0x001FFE 0x002000		
	GS = 4608 IW	0x002BFE		
	VS = 256 IW	0x000000 0x0001FE		
BSS<2:0>=x01	BS = 3840 IW	0x000200 0x0007FE 0x000800 0x001FFE		
768		0x002000		
	GS = 1536 IW	0x002BFE		
	VS = 256 IW	0x000000 0x0001FE		
BSS<2:0>=x00	BS = 5376 IW	0x000200 0x0007FE 0x000800 0x001FFE		
1792		0x002000		
		0x002BFE		

Base Status Flags Assembly # of # of Instr Assembly Syntax Description Mnemonic Words Cycles Affected # RCALL 47 Relative Call 2 RCALL Expr 1 None RCALL Computed Call 1 2 None Wn 48 REPEAT REPEAT #lit14 Repeat Next Instruction lit14 + 1 times 1 1 None REPEAT Repeat Next Instruction (Wn) + 1 times 1 1 None Wn 49 RESET RESET Software device Reset 1 1 None 50 RETFIE 1 3 (2) RETFIE Return from interrupt None 51 RETLW #lit10,Wn Return with literal in Wn 1 3 (2) None RETLW 52 RETURN Return from Subroutine 1 3 (2) RETURN None 53 RLC f = Rotate Left through Carry f 1 C,N,Z RLC f 1 WREG = Rotate Left through Carry f RLC f.WREG 1 1 C,N,Z RLC Ws,Wd Wd = Rotate Left through Carry Ws 1 1 C,N,Z 1 54 RLNC RLNC f f = Rotate Left (No Carry) f 1 N,Z WREG = Rotate Left (No Carry) f RLNC f,WREG 1 1 N,Z Wd = Rotate Left (No Carry) Ws RLNC Ws,Wd 1 1 N,Z RRC 55 f f = Rotate Right through Carry f 1 1 C,N,Z RRC RRC f,WREG WREG = Rotate Right through Carry f 1 1 C,N,Z RRC Ws,Wd Wd = Rotate Right through Carry Ws 1 1 C,N,Z 56 RRNC RRNC f = Rotate Right (No Carry) f 1 1 N,Z f WREG = Rotate Right (No Carry) f 1 N,Z RRNC 1 f,WREG Wd = Rotate Right (No Carry) Ws 1 1 N,Z RRNC Ws,Wd 57 SE SE Ws,Wnd Wnd = sign-extended Ws 1 1 C,N,Z 58 SETM SETM f f = 0xFFFF1 1 None WREG = 0xFFFF 1 1 SETM WREG None Ws = 0xFFFF SETM 1 1 None Ws SL f = Left Shift f C,N,OV,Z 59 SL f 1 1 SL f,WREG WREG = Left Shift f 1 1 C,N,OV,Z SL Ws,Wd Wd = Left Shift Ws 1 1 C,N,OV,Z Wnd = Left Shift Wb by Wns 1 SL 1 N.Z Wb, Wns, Wnd Wb,#lit5,Wnd Wnd = Left Shift Wb by lit5 1 1 N,Z SL 60 SUB f = f - WREG 1 C,DC,N,OV,Z 1 SUB f SUB f,WREG WREG = f - WREG 1 1 C,DC,N,OV,Z Wn = Wn - lit10SUB #lit.10.Wn 1 1 C,DC,N,OV,Z SUB Wb,Ws,Wd Wd = Wb - Ws 1 1 C,DC,N,OV,Z 1 Wd = Wb - lit5 Wb,#lit5,Wd 1 C,DC,N,OV,Z SUB 61 SUBB $f = f - WREG - (\overline{C})$ 1 1 C,DC,N,OV,Z SUBB f f,WREG WREG = f - WREG - (\overline{C}) 1 1 C,DC,N,OV,Z SUBB $Wn = Wn - lit10 - (\overline{C})$ 1 C,DC,N,OV,Z SUBB #lit10,Wn 1 SUBB $Wd = Wb - Ws - (\overline{C})$ 1 1 C,DC,N,OV,Z Wb,Ws,Wd SUBB Wb,#lit5,Wd $Wd = Wb - lit5 - (\overline{C})$ 1 1 C,DC,N,OV,Z 62 SUBR SUBR f f = WREG - f 1 1 C,DC,N,OV,Z f,WREG WREG = WREG - f 1 1 C,DC,N,OV,Z SUBR Wd = Ws - Wb 1 C,DC,N,OV,Z SUBR Wb,Ws,Wd 1 Wb,#lit5,Wd Wd = lit5 - Wb C,DC,N,OV,Z SUBR 1 1 63 SUBBR SUBBR f $f = WREG - f - (\overline{C})$ 1 1 C,DC,N,OV,Z WREG = WREG - $f - (\overline{C})$ SUBBR 1 1 C,DC,N,OV,Z f,WREG SUBBR Wb,Ws,Wd $Wd = Ws - Wb - (\overline{C})$ 1 1 C,DC,N,OV,Z $Wd = lit5 - Wb - (\overline{C})$ 1 1 C,DC,N,OV,Z SUBBR Wb,#lit5,Wd Wn = nibble swap Wn 64 SWAP 1 SWAP.b Wn 1 None SWAP Wn = byte swap Wn 1 1 None Wn 65 TBLRDH Read Prog<23:16> to Wd<7:0> 1 2 TBLRDH Ws,Wd None

INSTRUCTION SET OVERVIEW (CONTINUED) TABLE 20-2:

21.7 MPLAB SIM Software Simulator

The MPLAB SIM Software Simulator allows code development in a PC-hosted environment by simulating the PIC MCUs and dsPIC[®] DSCs on an instruction level. On any given instruction, the data areas can be examined or modified and stimuli can be applied from a comprehensive stimulus controller. Registers can be logged to files for further run-time analysis. The trace buffer and logic analyzer display extend the power of the simulator to record and track program execution, actions on I/O, most peripherals and internal registers.

The MPLAB SIM Software Simulator fully supports symbolic debugging using the MPLAB C Compilers, and the MPASM and MPLAB Assemblers. The software simulator offers the flexibility to develop and debug code outside of the hardware laboratory environment, making it an excellent, economical software development tool.

21.8 MPLAB REAL ICE In-Circuit Emulator System

MPLAB REAL ICE In-Circuit Emulator System is Microchip's next generation high-speed emulator for Microchip Flash DSC and MCU devices. It debugs and programs PIC[®] Flash MCUs and dsPIC[®] Flash DSCs with the easy-to-use, powerful graphical user interface of the MPLAB Integrated Development Environment (IDE), included with each kit.

The emulator is connected to the design engineer's PC using a high-speed USB 2.0 interface and is connected to the target with either a connector compatible with incircuit debugger systems (RJ11) or with the new high-speed, noise tolerant, Low-Voltage Differential Signal (LVDS) interconnection (CAT5).

The emulator is field upgradable through future firmware downloads in MPLAB IDE. In upcoming releases of MPLAB IDE, new devices will be supported, and new features will be added. MPLAB REAL ICE offers significant advantages over competitive emulators including low-cost, full-speed emulation, run-time variable watches, trace analysis, complex breakpoints, a ruggedized probe interface and long (up to three meters) interconnection cables.

21.9 MPLAB ICD 3 In-Circuit Debugger System

MPLAB ICD 3 In-Circuit Debugger System is Microchip's most cost effective high-speed hardware debugger/programmer for Microchip Flash Digital Signal Controller (DSC) and microcontroller (MCU) devices. It debugs and programs PIC[®] Flash microcontrollers and dsPIC[®] DSCs with the powerful, yet easyto-use graphical user interface of MPLAB Integrated Development Environment (IDE).

The MPLAB ICD 3 In-Circuit Debugger probe is connected to the design engineer's PC using a high-speed USB 2.0 interface and is connected to the target with a connector compatible with the MPLAB ICD 2 or MPLAB REAL ICE systems (RJ-11). MPLAB ICD 3 supports all MPLAB ICD 2 headers.

21.10 PICkit 3 In-Circuit Debugger/ Programmer and PICkit 3 Debug Express

The MPLAB PICkit 3 allows debugging and programming of PIC[®] and dsPIC[®] Flash microcontrollers at a most affordable price point using the powerful graphical user interface of the MPLAB Integrated Development Environment (IDE). The MPLAB PICkit 3 is connected to the design engineer's PC using a full speed USB interface and can be connected to the target via an Microchip debug (RJ-11) connector (compatible with MPLAB ICD 3 and MPLAB REAL ICE). The connector uses two device I/O pins and the reset line to implement in-circuit debugging and In-Circuit Serial Programming[™].

The PICkit 3 Debug Express include the PICkit 3, demo board and microcontroller, hookup cables and CDROM with user's guide, lessons, tutorial, compiler and MPLAB IDE software.

FIGURE 22-14: SPIx SLAVE MODE (FULL-DUPLEX, CKE = 1, CKP = 1, SMP = 0) TIMING CHARACTERISTICS



28-Lead Plastic Quad Flat, No Lead Package (MM) – 6x6x0.9 mm Body [QFN-S] with 0.40 mm Contact Length

Note: For the most current package drawings, please see the Microchip Packaging Specification located at http://www.microchip.com/packaging



	Units	MILLIMETERS		
Dimensio	on Limits	MIN	NOM	MAX
Number of Pins	Ν	28		
Pitch	е	0.65 BSC		
Overall Height	Α	0.80	0.90	1.00
Standoff	A1	0.00	0.02	0.05
Contact Thickness	A3		0.20 REF	
Overall Width	Е	6.00 BSC		
Exposed Pad Width	E2	3.65	3.70	4.70
Overall Length	D	6.00 BSC		
Exposed Pad Length	D2	3.65	3.70	4.70
Contact Width	b	0.23	0.38	0.43
Contact Length	L	0.30	0.40	0.50
Contact-to-Exposed Pad	К	0.20	-	-

Notes:

1. Pin 1 visual index feature may vary, but must be located within the hatched area.

2. Package is saw singulated.

3. Dimensioning and tolerancing per ASME Y14.5M.

BSC: Basic Dimension. Theoretically exact value shown without tolerances.

REF: Reference Dimension, usually without tolerance, for information purposes only.

Microchip Technology Drawing C04-124B

28-Lead Plastic Quad Flat, No Lead Package (MM) – 6x6x0.9 mm Body [QFN-S] with 0.40 mm Contact Length

Note: For the most current package drawings, please see the Microchip Packaging Specification located at http://www.microchip.com/packaging



Units		MILLIMETERS		
Dimension Limits		MIN	NOM	MAX
Contact Pitch	E		0.65 BSC	
Optional Center Pad Width	W2			4.70
Optional Center Pad Length	T2			4.70
Contact Pad Spacing	C1		6.00	
Contact Pad Spacing	C2		6.00	
Contact Pad Width (X28)	X1			0.40
Contact Pad Length (X28)	Y1			0.85
Distance Between Pads	G	0.25		

Notes:

1. Dimensioning and tolerancing per ASME Y14.5M

BSC: Basic Dimension. Theoretically exact value shown without tolerances.

Microchip Technology Drawing No. C04-2124A