

Welcome to E-XFL.COM

Understanding <u>Embedded - FPGAs (Field</u> <u>Programmable Gate Array)</u>

Embedded - FPGAs, or Field Programmable Gate Arrays, are advanced integrated circuits that offer unparalleled flexibility and performance for digital systems. Unlike traditional fixed-function logic devices, FPGAs can be programmed and reprogrammed to execute a wide array of logical operations, enabling customized functionality tailored to specific applications. This reprogrammability allows developers to iterate designs quickly and implement complex functions without the need for custom hardware.

Applications of Embedded - FPGAs

The versatility of Embedded - FPGAs makes them indispensable in numerous fields. In telecommunications.

Details

E·XFI

Product Status	Active
Number of LABs/CLBs	-
Number of Logic Elements/Cells	-
Total RAM Bits	147456
Number of I/O	177
Number of Gates	1000000
Voltage - Supply	1.425V ~ 1.575V
Mounting Type	Surface Mount
Operating Temperature	0°C ~ 85°C (TJ)
Package / Case	256-LBGA
Supplier Device Package	256-FPBGA (17x17)
Purchase URL	https://www.e-xfl.com/product-detail/microchip-technology/a3p1000-2fgg256

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong



ProASIC3 Ordering Information



M1A3P1000 = 1,000,000 System Gates

ProASIC3 Device Status

ProASIC3 Devices	Status	Cortex-M1 Devices	Status
A3P015	Not recommended for new designs.		
A3P030	Production		
A3P060	Production		
A3P125	Production		
A3P250	Production	M1A3P250	Production
A3P400	Production	M1A3P400	Production
A3P600	Production	M1A3P600	Production
A3P1000	Production	M1A3P1000	Production



I/O Power-Up and Supply Voltage Thresholds for Power-On Reset (Commercial and Industrial)

Sophisticated power-up management circuitry is designed into every ProASIC[®]3 device. These circuits ensure easy transition from the powered-off state to the powered-up state of the device. The many different supplies can power up in any sequence with minimized current spikes or surges.

In addition, the I/O will be in a known state through the power-up sequence. The basic principle is shown in Figure 2-2 on page 2-5.

There are five regions to consider during power-up.

ProASIC3 I/Os are activated only if ALL of the following three conditions are met:

- 1. VCC and VCCI are above the minimum specified trip points (Figure 2-2 on page 2-5).
- 2. VCCI > VCC 0.75 V (typical)
- 3. Chip is in the operating mode.

VCCI Trip Point:

```
Ramping up: 0.6 V < trip_point_up < 1.2 V
Ramping down: 0.5 V < trip_point_down < 1.1 V
```

VCC Trip Point:

```
Ramping up: 0.6 V < trip_point_up < 1.1 V
Ramping down: 0.5 V < trip_point_down < 1 V
```

VCC and VCCI ramp-up trip points are about 100 mV higher than ramp-down trip points. This specifically built-in hysteresis prevents undesirable power-up oscillations and current surges. Note the following:

- During programming, I/Os become tristated and weakly pulled up to VCCI.
- JTAG supply, PLL power supplies, and charge pump VPUMP supply have no influence on I/O behavior.

PLL Behavior at Brownout Condition

Microsemi recommends using monotonic power supplies or voltage regulators to ensure proper power-up behavior. Power ramp-up should be monotonic at least until VCC and VCCPLLX exceed brownout activation levels. The VCC activation level is specified as 1.1 V worst-case (see Figure 2-2 on page 2-5 for more details).

When PLL power supply voltage and/or VCC levels drop below the VCC brownout levels (0.75 V \pm 0.25 V), the PLL output lock signal goes low and/or the output clock is lost. Refer to the "Power-Up/Down Behavior of Low Power Flash Devices" chapter of the *ProASIC3 FPGA Fabric User's Guide* for information on clock and lock recovery.

Internal Power-Up Activation Sequence

- 1. Core
- 2. Input buffers

Output buffers, after 200 ns delay from input buffer activation.

Thermal Characteristics

Introduction

The temperature variable in the Microsemi Designer software refers to the junction temperature, not the ambient temperature. This is an important distinction because dynamic and static power consumption cause the chip junction to be higher than the ambient temperature.

EQ can be used to calculate junction temperature.

 T_J = Junction Temperature = $\Delta T + T_A$

where:

T_A = Ambient Temperature

 ΔT = Temperature gradient between junction (silicon) and ambient ΔT = θ_{ia} * P

 θ_{ia} = Junction-to-ambient of the package. θ_{ia} numbers are located in Table 2-5 on page 2-6.

P = Power dissipation



Table 2-9 • Summary of I/O Input Buffer Power (Per Pin) – Default I/O Software Settings Applicable to Standard Plus I/O Banks

	VMV (V)	Static Power PDC2 (mW) ¹	Dynamic Power PAC9 (µW/MHz) ²
2.5 V LVCMOS	2.5	-	5.14
1.8 V LVCMOS	1.8	-	2.13
1.5 V LVCMOS (JESD8-11)	1.5	-	1.48
3.3 V PCI	3.3	-	18.13
3.3 V PCI-X	3.3	-	18.13

Notes:

- 1. PDC2 is the static power (where applicable) measured on VMV.
- 2. PAC9 is the total dynamic power measured on VCC and VMV.
- 3. All LVCMOS 3.3 V software macros support LVCMOS 3.3 V wide range as specified in the JESD8-B specification.

Table 2-10 • Summary of I/O Input Buffer Power (Per Pin) – Default I/O Software Settings Applicable to Standard I/O Banks

	VMV (V)	Static Power PDC2 (mW) ¹	Dynamic Power PAC9 (μW/MHz) ²
Single-Ended			
3.3 V LVTTL / 3.3 V LVCMOS	3.3	-	17.24
3.3 V LVCMOS Wide Range ³	3.3	-	17.24
2.5 V LVCMOS	2.5	-	5.19
1.8 V LVCMOS	1.8	-	2.18
1.5 V LVCMOS (JESD8-11)	1.5	_	1.52

Notes:

1. PDC2 is the static power (where applicable) measured on VMV.

2. PAC9 is the total dynamic power measured on VCC and VMV.

3. All LVCMOS 3.3 V software macros support LVCMOS 3.3 V wide range as specified in the JESD8-B specification.



User I/O Characteristics

Timing Model







I/O DC Characteristics

Table 2-27 • Input Capacitance

Symbol	Definition	Conditions	Min	Мах	Units
C _{IN}	Input capacitance	VIN = 0, f = 1.0 MHz	-	8	pF
CINCLK	Input capacitance on the clock pin	VIN = 0, f = 1.0 MHz	_	8	pF

Table 2-28 • I/O Output Buffer Maximum Resistances¹ Applicable to Advanced I/O Banks

Standard	Drive Strength	R _{PULL-DOWN} (Ω) ²	R _{PULL-UP} (Ω) ³		
3.3 V LVTTL / 3.3 V LVCMOS	2 mA	100	300		
	4 mA	100	300		
	6 mA	50	150		
	8 mA	50	150		
	12 mA	25	75		
	16 mA	17	50		
	24 mA	11	33		
3.3 V LVCMOS Wide Range ⁴	100 µA	Same as regular 3.3 V LVCMOS	Same as regular 3.3 V LVCMOS		
2.5 V LVCMOS	2 mA	100	200		
	4 mA	100	200		
	6 mA	50	100		
	8 mA	50	100		
	12 mA	25	50		
	16 mA	20	40		
	24 mA	11	22		
1.8 V LVCMOS	2 mA	200	225		
	4 mA	100	112		
	6 mA	50	56		
	8 mA	50	56		
	12 mA	20	22		
	16 mA	20	22		
1.5 V LVCMOS	2 mA	200	224		
	4 mA	100	112		
	6 mA	67	75		
	8 mA	33	37		
	12 mA	33	37		
3.3 V PCI/PCI-X	Per PCI/PCI-X specification	25	75		

Notes:

- 2. R_(PULL-DOWN-MAX) = (VOLspec) / IOLspec
- 3. R_(PULL-UP-MAX) = (VCCImax VOHspec) / IOHspec

4. All LVCMOS 3.3 V software macros support LVCMOS 3.3 V wide range as specified in the JESD-8B specification.

^{1.} These maximum values are provided for informational reasons only. Minimum output buffer resistance values depend on VCCI, drive strength selection, temperature, and process. For board design considerations and detailed output buffer resistances, use the corresponding IBIS models located at http://www.microsemi.com/soc/download/ibis/default.aspx.



Drive Strength	Speed Grade	t _{DOUT}	t _{DP}	t _{DIN}	t _{PY}	t _{EOUT}	t _{ZL}	t _{zH}	t _{LZ}	t _{HZ}	t _{ZLS}	t _{zHS}	Units
2 mA	Std.	0.66	9.68	0.04	1.00	0.43	9.86	8.42	2.28	2.21	12.09	10.66	ns
	-1	0.56	8.23	0.04	0.85	0.36	8.39	7.17	1.94	1.88	10.29	9.07	ns
	-2	0.49	7.23	0.03	0.75	0.32	7.36	6.29	1.70	1.65	9.03	7.96	ns
4 mA	Std.	0.66	9.68	0.04	1.00	0.43	9.86	8.42	2.28	2.21	12.09	10.66	ns
	-1	0.56	8.23	0.04	0.85	0.36	8.39	7.17	1.94	1.88	10.29	9.07	ns
	-2	0.49	7.23	0.03	0.75	0.32	7.36	6.29	1.70	1.65	9.03	7.96	ns
6 mA	Std.	0.66	6.70	0.04	1.00	0.43	6.82	5.89	2.58	2.74	9.06	8.12	ns
	-1	0.56	5.70	0.04	0.85	0.36	5.80	5.01	2.20	2.33	7.71	6.91	ns
	-2	0.49	5.00	0.03	0.75	0.32	5.10	4.40	1.93	2.05	6.76	6.06	ns
8 mA	Std.	0.66	6.70	0.04	1.00	0.43	6.82	5.89	2.58	2.74	9.06	8.12	ns
	-1	0.56	5.70	0.04	0.85	0.36	5.80	5.01	2.20	2.33	7.71	6.91	ns
	-2	0.49	5.00	0.03	0.75	0.32	5.10	4.40	1.93	2.05	6.76	6.06	ns
12 mA	Std.	0.66	5.05	0.04	1.00	0.43	5.14	4.51	2.79	3.08	7.38	6.75	ns
	-1	0.56	4.29	0.04	0.85	0.36	4.37	3.84	2.38	2.62	6.28	5.74	ns
	-2	0.49	3.77	0.03	0.75	0.32	3.84	3.37	2.09	2.30	5.51	5.04	ns
16 mA	Std.	0.66	5.05	0.04	1.00	0.43	5.14	4.51	2.79	3.08	7.38	6.75	ns
	-1	0.56	4.29	0.04	0.85	0.36	4.37	3.84	2.38	2.62	6.28	5.74	ns
	-2	0.49	3.77	0.03	0.75	0.32	3.84	3.37	2.09	2.30	5.51	5.04	ns

Table 2-44 • 3.3 V LVTTL / 3.3 V LVCMOS Low Slew

Commercial-Case Conditions: $T_J = 70^{\circ}$ C, Worst-Case VCC = 1.425 V, Worst-Case VCCI = 3.0 V Applicable to Standard Plus I/O Banks

Note: For specific junction temperature and voltage supply levels, refer to Table 2-6 on page 2-6 for derating values.

Table 2-45 • 3.3 V LVTTL / 3.3 V LVCMOS High Slew

Commercial-Case Conditions: T_J = 70°C, Worst-Case VCC = 1.425 V, Worst-Case VCCI = 3.0 V Applicable to Standard I/O Banks

Drive Strength	Speed Grade	t _{DOUT}	t _{DP}	t _{DIN}	t _{PY}	t _{EOUT}	t _{ZL}	t _{zH}	t _{LZ}	t _{HZ}	Units
2 mA	Std.	0.66	7.07	0.04	1.00	0.43	7.20	6.23	2.07	2.15	ns
	–1	0.56	6.01	0.04	0.85	0.36	6.12	5.30	1.76	1.83	ns
	-2	0.49	5.28	0.03	0.75	0.32	5.37	4.65	1.55	1.60	ns
4 mA	Std.	0.66	7.07	0.04	1.00	0.43	7.20	6.23	2.07	2.15	ns
	–1	0.56	6.01	0.04	0.85	0.36	6.12	5.30	1.76	1.83	ns
	-2	0.49	5.28	0.03	0.75	0.32	5.37	4.65	1.55	1.60	ns
6 mA	Std.	0.66	4.41	0.04	1.00	0.43	4.49	3.75	2.39	2.69	ns
	–1	0.56	3.75	0.04	0.85	0.36	3.82	3.19	2.04	2.29	ns
	-2	0.49	3.29	0.03	0.75	0.32	3.36	2.80	1.79	2.01	ns
8 mA	Std.	0.66	4.41	0.04	1.00	0.43	4.49	3.75	2.39	2.69	ns
	-1	0.56	3.75	0.04	0.85	0.36	3.82	3.19	2.04	2.29	ns



Table 2-64 • 2.5 V LVCMOS High Slew

Commercial-Case Conditions: T = 70°C, Worst-Case VCC = 1.425 V, Worst-Case VCCI = 3.0 V
Applicable to Standard I/O Banks

Drive Strength	Speed Grade	t _{DOUT}	t _{DP}	t _{DIN}	t _{PY}	t _{EOUT}	t _{ZL}	t _{zH}	t _{LZ}	t _{HZ}	Units
2 mA	Std.	0.66	8.20	0.04	1.29	0.43	7.24	8.20	2.03	1.91	ns
	-1	0.56	6.98	0.04	1.10	0.36	6.16	6.98	1.73	1.62	ns
	-2	0.49	6.13	0.03	0.96	0.32	5.41	6.13	1.52	1.43	ns
4 mA	Std.	0.66	8.20	0.04	1.29	0.43	7.24	8.20	2.03	1.91	ns
	-1	0.56	6.98	0.04	1.10	0.36	6.16	6.98	1.73	1.62	ns
	-2	0.49	6.13	0.03	0.96	0.32	5.41	6.13	1.52	1.43	ns
6 mA	Std.	0.66	4.77	0.04	1.29	0.43	4.55	4.77	2.38	2.55	ns
	-1	0.56	4.05	0.04	1.10	0.36	3.87	4.05	2.03	2.17	ns
	-2	0.49	3.56	0.03	0.96	0.32	3.40	3.56	1.78	1.91	ns
8 mA	Std.	0.66	4.77	0.04	1.29	0.43	4.55	4.77	2.38	2.55	ns
	-1	0.56	4.05	0.04	1.10	0.36	3.87	4.05	2.03	2.17	ns
	-2	0.49	3.56	0.03	0.96	0.32	3.40	3.56	1.78	1.91	ns

Notes:

1. Software default selection highlighted in gray.

2. For specific junction temperature and voltage supply levels, refer to Table 2-6 on page 2-6 for derating values.

Table 2-65 • 2.5 V LVCMOS Low Slew

Commercial-Case Conditions: T_J = 70°C, Worst-Case VCC = 1.425 V, Worst-Case VCCI = 3.0 V Applicable to Standard I/O Banks

Drive Strength	Speed Grade	t _{DOUT}	t _{DP}	t _{DIN}	t _{PY}	t _{EOUT}	t _{ZL}	t _{zH}	t _{LZ}	t _{HZ}	Units
2 mA	Std.	0.66	11.00	0.04	1.29	0.43	10.37	11.00	2.03	1.83	ns
	-1	0.56	9.35	0.04	1.10	0.36	8.83	9.35	1.73	1.56	ns
	-2	0.49	8.21	0.03	0.96	0.32	7.75	8.21	1.52	1.37	ns
4 mA	Std.	0.66	11.00	0.04	1.29	0.43	10.37	11.00	2.03	1.83	ns
	-1	0.56	9.35	0.04	1.10	0.36	8.83	9.35	1.73	1.56	ns
	-2	0.49	8.21	0.03	0.96	0.32	7.75	8.21	1.52	1.37	ns
6 mA	Std.	0.66	7.50	0.04	1.29	0.43	7.36	7.50	2.39	2.46	ns
	-1	0.56	6.38	0.04	1.10	0.36	6.26	6.38	2.03	2.10	ns
	-2	0.49	5.60	0.03	0.96	0.32	5.49	5.60	1.78	1.84	ns
8 mA	Std.	0.66	7.50	0.04	1.29	0.43	7.36	7.50	2.39	2.46	ns
	-1	0.56	6.38	0.04	1.10	0.36	6.26	6.38	2.03	2.10	ns
	-2	0.49	5.60	0.03	0.96	0.32	5.49	5.60	1.78	1.84	ns

Note: For specific junction temperature and voltage supply levels, refer to Table 2-6 on page 2-6 for derating values.



3.3 V PCI, 3.3 V PCI-X

Peripheral Component Interface for 3.3 V standard specifies support for 33 MHz and 66 MHz PCI Bus applications.

Table 2-86 •	Minimum and	Maximum D	OC Input and	Output Levels
--------------	-------------	-----------	--------------	---------------

3.3 V PCI/PCI-X	V	ΊL	V	IH	VOL	VOH	IOL	IOH	IOSL	IOSH	IIL	IIH
Drive Strength	Min. V	Max. V	Min. V	Max. V	Max,. V	Min. V	mA	mA	Max. mA ¹	Max. mA ¹	μA²	μA²
Per PCI specification					Per PCI	curves					10	10

Notes:

1. Currents are measured at high temperature (100°C junction temperature) and maximum voltage.

2. Currents are measured at 85°C junction temperature.

AC loadings are defined per the PCI/PCI-X specifications for the datapath; Microsemi loadings for enable path characterization are described in Figure 2-11.



Figure 2-11 • AC Loading

AC loadings are defined per PCI/PCI-X specifications for the datapath; Microsemi loading for tristate is described in Table 2-87.

Table 2-87 • AC Waveforms, Measuring Points, and Capacitive Loads

Input Low (V)	Input High (V)	Measuring Point* (V)	C _{LOAD} (pF)
0	3.3	0.285 * VCCI for t _{DP(R)}	10
		0.615 * VCCI for t _{DP(F)}	

Note: *Measuring point = V_{trip} . See Table 2-22 on page 2-22 for a complete table of trip points.



Output Enable Register



Figure 2-19 • Output Enable Register Timing Diagram



Embedded SRAM and FIFO Characteristics

SRAM



Figure 2-30 • RAM Models



Timing Waveforms











Table 2-122 • A3P250 FIFO 2k×2

Worst Commercial-Case Conditions: T_J = 70°C, VCC = 1.425 V

Parameter	Description	-2	-1	Std.	Units
t _{ENS}	REN, WEN Setup Time	4.39	5.00	5.88	ns
t _{ENH}	REN, WEN Hold Time	0.00	0.00	0.00	ns
t _{BKS}	BLK Setup Time	0.19	0.22	0.26	ns
t _{BKH}	BLK Hold Time	0.00	0.00	0.00	ns
t _{DS}	Input Data (WD) Setup Time	0.18	0.21	0.25	ns
t _{DH}	Input Data (WD) Hold Time	0.00	0.00	0.00	ns
t _{CKQ1}	Clock High to New Data Valid on RD (flow-through)	2.36	2.68	3.15	ns
t _{CKQ2}	Clock High to New Data Valid on RD (pipelined)	0.89	1.02	1.20	ns
t _{RCKEF}	RCLK High to Empty Flag Valid	1.72	1.96	2.30	ns
t _{WCKFF}	WCLK High to Full Flag Valid	1.63	1.86	2.18	ns
t _{CKAF}	Clock High to Almost Empty/Full Flag Valid	6.19	7.05	8.29	ns
t _{RSTFG}	RESET Low to Empty/Full Flag Valid	1.69	1.93	2.27	ns
t _{RSTAF}	RESET Low to Almost Empty/Full Flag Valid	6.13	6.98	8.20	ns
t _{RSTBQ}	RESET Low to Data Out Low on RD (flow-through)	0.92	1.05	1.23	ns
	RESET Low to Data Out Low on RD (pipelined)	0.92	1.05	1.23	ns
t _{REMRSTB}	RESET Removal	0.29	0.33	0.38	ns
t _{RECRSTB}	RESET Recovery	1.50	1.71	2.01	ns
t _{MPWRSTB}	RESET Minimum Pulse Width	0.21	0.24	0.29	ns
t _{CYC}	Clock Cycle Time	3.23	3.68	4.32	ns
F _{MAX}	Maximum Frequency for FIFO	310	272	231	MHz

Table 2-123 • A3P250 FIFO 4k×1

Worst Commercial-Case Conditions: T_J = 70°C, VCC = 1.425 V

Parameter	Description	-2	-1	Std.	Units
t _{ENS}	REN, WEN Setup Time	4.86	5.53	6.50	ns
t _{ENH}	REN, WEN Hold Time	0.00	0.00	0.00	ns
t _{BKS}	BLK Setup Time	0.19	0.22	0.26	ns
t _{BKH}	BLK Hold Time	0.00	0.00	0.00	ns
t _{DS}	Input Data (WD) Setup Time	0.18	0.21	0.25	ns
t _{DH}	Input Data (WD) Hold Time	0.00	0.00	0.00	ns
t _{CKQ1}	Clock High to New Data Valid on RD (flow-through)	2.36	2.68	3.15	ns
t _{CKQ2}	Clock High to New Data Valid on RD (pipelined)	0.89	1.02	1.20	ns
t _{RCKEF}	RCLK High to Empty Flag Valid	1.72	1.96	2.30	ns
t _{WCKFF}	WCLK High to Full Flag Valid	1.63	1.86	2.18	ns
t _{CKAF}	Clock High to Almost Empty/Full Flag Valid	6.19	7.05	8.29	ns
t _{RSTFG}	RESET Low to Empty/Full Flag Valid	1.69	1.93	2.27	ns



JTAG 1532 Characteristics

JTAG timing delays do not include JTAG I/Os. To obtain complete JTAG timing, add I/O buffer delays to the corresponding standard selected; refer to the I/O timing characteristics in the "User I/O Characteristics" section on page 2-15 for more details.

Timing Characteristics

Table 2-125 • JTAG 1532

```
Commercial-Case Conditions: T<sub>J</sub> = 70°C, Worst-Case VCC = 1.425 V
```

Parameter	Description	-2	-1	Std.	Units
t _{DISU}	Test Data Input Setup Time	0.50	0.57	0.67	ns
t _{DIHD}	Test Data Input Hold Time	1.00	1.13	1.33	ns
t _{TMSSU}	Test Mode Select Setup Time	0.50	0.57	0.67	ns
t _{TMDHD}	Test Mode Select Hold Time	1.00	1.13	1.33	ns
t _{TCK2Q}	Clock to Q (data out)	6.00	6.80	8.00	ns
t _{RSTB2Q}	Reset to Q (data out)	20.00	22.67	26.67	ns
F _{TCKMAX}	TCK Maximum Frequency	25.00	22.00	19.00	MHz
t _{TRSTREM}	ResetB Removal Time	0.00	0.00	0.00	ns
t _{TRSTREC}	ResetB Recovery Time	0.20	0.23	0.27	ns
t _{TRSTMPW}	ResetB Minimum Pulse	TBD	TBD	TBD	ns

Note: For specific junction temperature and voltage supply levels, refer to Table 2-6 on page 2-6 for derating values.



3 – Pin Descriptions

Supply Pins

Ground

Ground supply voltage to the core, I/O outputs, and I/O logic.

GNDQ Ground (quiet)

Quiet ground supply voltage to input buffers of I/O banks. Within the package, the GNDQ plane is decoupled from the simultaneous switching noise originated from the output buffer ground domain. This minimizes the noise transfer within the package and improves input signal integrity. GNDQ must always be connected to GND on the board.

VCC

GND

Core Supply Voltage

Supply voltage to the FPGA core, nominally 1.5 V. VCC is required for powering the JTAG state machine in addition to VJTAG. Even when a device is in bypass mode in a JTAG chain of interconnected devices, both VCC and VJTAG must remain powered to allow JTAG signals to pass through the device.

VCCIBx I/O Supply Voltage

Supply voltage to the bank's I/O output buffers and I/O logic. Bx is the I/O bank number. There are up to eight I/O banks on low power flash devices plus a dedicated VJTAG bank. Each bank can have a separate VCCI connection. All I/Os in a bank will run off the same VCCIBx supply. VCCI can be 1.5 V, 1.8 V, 2.5 V, or 3.3 V, nominal voltage. In general, unused I/O banks should have their corresponding VCCIX pins tied to GND. If an output pad is terminated to ground through any resistor and if the corresponding VCCIX is left floating, then the leakage current to ground is ~ 0uA. However, if an output pad is terminated to ground is ~ 3 uA. For unused banks the aforementioned behavior is to be taken into account while deciding if it's better to float VCCIX of unused bank or tie it to GND.

VMVx I/O Supply Voltage (quiet)

Quiet supply voltage to the input buffers of each I/O bank. *x* is the bank number. Within the package, the VMV plane biases the input stage of the I/Os in the I/O banks. This minimizes the noise transfer within the package and improves input signal integrity. Each bank must have at least one VMV connection, and no VMV should be left unconnected. All I/Os in a bank run off the same VMVx supply. VMV is used to provide a quiet supply voltage to the input buffers of each I/O bank. VMVx can be 1.5 V, 1.8 V, 2.5 V, or 3.3 V, nominal voltage. Unused I/O banks should have their corresponding VMV pins tied to GND. VMV and VCCI should be at the same voltage within a given I/O bank. Used VMV pins must be connected to the corresponding VCCI pins of the same bank (i.e., VMV0 to VCCIB0, VMV1 to VCCIB1, etc.).

VCCPLA/B/C/D/E/F PLL Supply Voltage

Supply voltage to analog PLL, nominally 1.5 V.

When the PLLs are not used, the Designer place-and-route tool automatically disables the unused PLLs to lower power consumption. The user should tie unused VCCPLx and VCOMPLx pins to ground. Microsemi recommends tying VCCPLx to VCC and using proper filtering circuits to decouple VCC noise from the PLLs. Refer to the PLL Power Supply Decoupling section of the "Clock Conditioning Circuits in IGLOO and ProASIC3 Devices" chapter of the *ProASIC3 FPGA Fabric User's Guide* for a complete board solution for the PLL analog power supply and ground.

There is one VCCPLF pin on ProASIC3 devices.

VCOMPLA/B/C/D/E/F PLL Ground

Ground to analog PLL power supplies. When the PLLs are not used, the Designer place-and-route tool automatically disables the unused PLLs to lower power consumption. The user should tie unused VCCPLx and VCOMPLx pins to ground.

There is one VCOMPLF pin on ProASIC3 devices.

Pin Number A3P125 Function Pin Number A3P125 Function A1 GAB2//OSPRSB1 A37 GBB1//O38RSB0 B25 GND A2 IO130RSB1 A38 GBC0/IO38RSB0 B26 NC A3 VCCIB1 A39 VCCIB0 B27 GCB2/IO58RSB0 A4 GFC1/IO128RSB1 A41 IO22RSB0 B28 GND A5 GFB0/IO123RSB1 A41 IO22RSB0 B29 GCB0/IO54RSB0 A6 VCCPLF A42 IO18RSB0 B31 GB21/O33RSB0 A7 GFA1/IO121RSB1 A43 IO14RSB0 B33 V/V/V A10 VCC A46 VCC B34 GB21/O33RSB0 A11 GEB1//O110RSB1 A44 IO11RSB0 B35 GB21/O33RSB0 A13 GEC2//IO14RSB1 B1 IO68RSB1 B36 GIC1/IO36RSB0 A13 GEC2//IO14RSB1 B2 GAC2//O131RSB1 B37 IO26RSB0 A14 IO909RSB1 B2 GAC2//O131RSB		QN132		QN132	QN132	
A1 GAB2/IO69RSB1 A37 GBB1/IO39RSB0 B25 GND A2 IO130RSB1 A38 GBC0/IO33RSB0 B26 NC A3 VCCIB1 A39 VCCIB0 B27 GCB2/IO58RSB0 A4 GFC1/IO128RSB1 A40 IO28RSB0 B28 GND A5 GFB0/IO123RSB1 A41 IO22RSB0 B29 GCB0/IO54RSB0 A6 VCCPLF A42 IO18RSB0 B30 GCC1/IO51RSB0 A7 GFA1/IO121RSB1 A43 IO14RSB0 B31 GND A8 GFC2/IO14RSB1 A44 IO17RSB0 B33 GWN0 A10 VCC A46 VCC B34 GBA0/IO39RSB0 A11 GE2/IO104RSB1 B41 IO68RSB1 B37 IO26RSB0 A13 GE2/IO104RSB1 B4 GAC2/IO131RSB1 B38 IO21RSB0 A14 IO100RSB1 B4 GFC0/IO125RSB1 B40 IO13RSB0 A15 VCC B3 GND	Pin Number	A3P125 Function	Pin Number	A3P125 Function	Pin Number	A3P125 Function
A2 I0130RSB1 A38 GBC0/I035RSB0 B26 NC A3 VCCIB1 A39 VCCIB0 B27 GCB2/I058RSB0 A4 GFC1/I0126RSB1 A40 I028RSB0 B28 GND A5 GFB0/I0123RSB1 A41 I022RSB0 B29 GCB0/I054RSB0 A6 VCCPLF A42 I018RSB0 B30 GCC1/I051RSB0 A7 GFA1/I0121RSB1 A43 I014RSB0 B31 GND A8 GFC2/I0118RSB1 A44 I011RSB0 B32 GB2/I043RSB0 A9 I0115RSB1 A44 I011RSB0 B33 VMV0 A10 VCC A46 VCC B34 GB2/I043RSB0 A13 GEC2/I014RSB1 B41 I069RSB1 B37 I026RSB0 A14 I0100RSB1 B4 GFC0/I0125RSB1 B40 I013RSB0 A15 VCC B3 GND B42 GND A15 VCC B3 GND B43	A1	GAB2/IO69RSB1	A37	GBB1/IO38RSB0	B25	GND
A3 VCCIB1 A39 VCCIB0 B27 GCB2/IO58RSB0 A4 GFC1/IO126RSB1 A40 IO28RSB0 B28 GND A5 GFB0/IO123RSB1 A41 IO28RSB0 B29 GCB0/IO54RSB0 A6 VCCPLF A42 IO18RSB0 B30 GCC1/IO51RSB0 A7 GFA1/IO121RSB1 A44 IO11RSB0 B31 GND A8 GFC2/IO118RSB1 A44 IO11RSB0 B33 VMV0 A10 VCC A46 VCC B34 GBA0/IO39RSB0 A11 GEB1/IO110RSB1 A47 GAC1/IO05RSB0 B35 GBC1/IO38RSB0 A12 GEA0/IO107RSB1 A48 GAB0/IO28RSB0 B36 GND A14 IO100RSB1 B2 GAC2/IO131RSB1 B38 IO21RSB0 A14 IO109RSB1 B4 GFC0/IO125RSB1 B38 IO21RSB0 A14 IO99RSB1 B5 VCOMPLF B41 IO08RSB1 A20 IO38RSB1 B7	A2	IO130RSB1	A38	GBC0/IO35RSB0	B26	NC
A4 GFC1/I/0126RSB1 A40 IO28RSB0 B28 GND A5 GFB0/0123RSB1 A41 IO22RSB0 B30 GCC1/I/054RSB0 A6 VCCPLF A42 IO18RSB0 B30 GCC1/I/054RSB0 A7 GFA1/I/0121RSB1 A43 IO14RSB0 B31 GB2//043RSB0 A9 IO115RSB1 A44 IO17RSB0 B33 VMV0 A10 VCC A46 VCC B34 GBA//039RSB0 A11 GEB1//0110RSB1 A45 IO07RSB0 B35 GBC1//036RSB0 A11 GEA//0107RSB1 A48 GAD//002RSB0 B36 GND A13 GEC2/0104RSB1 B1 IO668RSB1 B37 IO266RSB0 A15 VCC B3 GND B38 IO218RSB0 A16 IO99RSB1 B4 GFC0//0127SRS1 B40 IO138RS0 A17 IO468RSB1 B5 VCOMPLF B41 IO088RS0 A20 IO35RSB1 B6 GND <td>A3</td> <td>VCCIB1</td> <td>A39</td> <td>VCCIB0</td> <td>B27</td> <td>GCB2/IO58RSB0</td>	A3	VCCIB1	A39	VCCIB0	B27	GCB2/IO58RSB0
A5 GFB0/IO123RSB1 A41 IO22RSB0 B29 GCB0/IO54RSB0 A6 VCCPLF A42 IO18RSB0 B30 GCC1/IO51RSB0 A7 GFA1/0121RSB1 A43 IO14RSB0 B32 GB2/IO43RSB0 A9 IO115RSB1 A44 IO11RSB0 B32 GB2/IO43RSB0 A9 IO115RSB1 A45 IO07RSB0 B33 VMV0 A10 VCC A46 VCC B3 GB2/IO43RSB0 A11 GEB1/IO17RSB1 A45 IO07RSB0 B35 GB2/IO39RSB0 A13 GEC2/IO104RSB1 B1 IO68RSB1 B37 IO26RSB0 A14 IO100RSB1 B2 GAC2/IO131RSB1 B38 IO21RSB0 A15 VCC B3 GND B40 IO13RSB0 A16 IO99RSB1 B4 GFC2/IO19RSB1 B43 GAC0/IO4RSB0 A20 IO68SRS1 B6 GND B44 GNDQ A21 IO79RSB1 B7 GFB2/IO119RSB1 </td <td>A4</td> <td>GFC1/IO126RSB1</td> <td>A40</td> <td>IO28RSB0</td> <td>B28</td> <td>GND</td>	A4	GFC1/IO126RSB1	A40	IO28RSB0	B28	GND
A6 VCCPLF A42 I018RSB0 B30 GCC1/I051RSB0 A7 GFA1/I0121RSB1 A43 I014RSB0 B31 GND A8 GFC2/I0118RSB1 A44 I011RSB0 B32 GBB2/I043RSB0 A9 I0115RSB1 A45 I007RSB0 B33 VMV0 A10 VCC A46 VCC B34 GBA0/I039RSB0 A11 GEB1/I0110RSB1 A47 GAC1/I005RSB0 B35 GBC1/I039RSB0 A13 GEC2/I014RSB1 B1 I068RSB1 B37 I026RSB0 A14 I0100RSB1 B2 GAC2/I0131RSB1 B38 I021RSB0 A15 VCC B3 GND B39 GND A16 I099RSB1 B4 GFC0/I012SRS1 B40 I013RSB0 A18 I094RSB1 B6 GND B41 I008RSB1 A20 I068SRS1 B8 I011RSB1 B44 GNDQ A21 I079RSB1 B11 VMV1 C3	A5	GFB0/IO123RSB1	A41	IO22RSB0	B29	GCB0/IO54RSB0
A7 GFA1/I0121RSB1 A43 I014RSB0 B31 GND A8 GFC2/I0118RSB1 A44 I011RSB0 B32 GBB2/I043RSB0 A9 I0115RSB1 A45 I007RSB0 B33 VMV0 A10 VCC A46 VCC B34 GBA//I039RSB0 A11 GEB1//I010RSB1 A47 GAC1//I005RSB0 B35 GBC1//I036RSB0 A12 GEA0/I0107RSB1 A48 GAC2/I011RSB1 B36 GND A13 GEC2//I014RSB1 B1 I068RSB1 B37 I026RSB0 A14 I0100RSB1 B2 GAC2/I013RSB1 B38 I021RSB0 A16 I099RSB1 B4 GFC0//I012RSB1 B39 GND A16 I099RSB1 B5 VC0MPLF B41 I008RSB0 A20 I085RSB1 B8 I0116RSB1 B44 GNDQ A21 I079RSB1 B11 VMV1 C3 VCC A23 GDB2//071RSB1 B11 VMV1	A6	VCCPLF	A42	IO18RSB0	B30	GCC1/IO51RSB0
A8 GFC2/I0118RSB1 A44 I011RSB0 B32 GBB2/I043RSB0 A9 I0115RSB1 A45 I007RSB0 B33 VMV0 A10 VCC A46 VCC B34 GBA///039RSB0 A11 GEB1/I0110RSB1 A47 GAC1/I005RSB0 B35 GBC1/I036RSB0 A12 GEA0/I0107RSB1 A48 GAB//I02RSB0 B36 GND A13 GEC2/I0104RSB1 B1 I068RSB1 B37 I026RSB0 A14 I0100RSB1 B2 GAC2/I0131RSB1 B38 I021RSB0 A15 VCC B3 GND B39 GND A16 I099RSB1 B4 GFC0//0125RSB1 B40 I013RSB0 A18 I094RSB1 B6 GND B42 GND A20 I085RSB1 B8 I0116RSB1 B44 GNDQ A21 I079RSB1 B10 GEB0//0109RSB1 C2 I0132RSB1 A22 VCC B10 GEB0//0109RSB1	A7	GFA1/IO121RSB1	A43	IO14RSB0	B31	GND
A9 I0115RSB1 A45 I007RSB0 B33 VMV0 A10 VCC A46 VCC B34 GBA0/IO39RSB0 A11 GEB1/IO110RSB1 A47 GAC1/IO05RSB0 B35 GBC1/IO36RSB0 A12 GEA0/IO107RSB1 A48 GAB0/IO2RSB0 B36 GND A13 GEC2/IO14RSB1 B1 IO68RSB1 B37 IO26RS80 A14 IO100RSB1 B2 GAC2/IO131RSB1 B38 IO21RS80 A16 IO99RSB1 B4 GFC0/IO125RSB1 B40 IO13RS80 A17 IO96RSB1 B5 VCOMPLF B41 IO08RS80 A18 IO94RSB1 B6 GND B42 GND A20 I085RSB1 B8 IO116RSB1 B44 GNDQ A21 IO79RSB1 B9 GND C1 GAA2/IO67RSB1 A22 VCC B10 GEB0/IO19RSB1 C2 IO132RSB1 A22 VCC B13 IO116RSB1 G4 <td>A8</td> <td>GFC2/IO118RSB1</td> <td>A44</td> <td>IO11RSB0</td> <td>B32</td> <td>GBB2/IO43RSB0</td>	A8	GFC2/IO118RSB1	A44	IO11RSB0	B32	GBB2/IO43RSB0
A10 VCC A46 VCC B34 GBA0/IO39RSB0 A11 GEB1/IO110RSB1 A47 GAC1/IO05RSB0 B35 GBC1/IO36RSB0 A12 GEA0/IO107RSB1 A48 GAB0/IO2RSB0 B36 GND A13 GEC2/IO104RSB1 B1 IO68RSB1 B37 IO26RSB0 A14 IO100RSB1 B2 GAC2/IO131RSB1 B38 IO21RSB0 A16 IO99RSB1 B4 GFC0/IO125RSB1 B40 IO13RSB0 A17 IO96RSB1 B5 VCOMPLF B41 IO08RSB0 A18 IO94RSB1 B6 GND B42 GND A20 IO85RSB1 B7 GFB2/IO119RSB1 B43 GAC0/IO4RSB0 A21 IO79RSB1 B9 GND C1 GAA2/IO67RSB1 A22 VCC B10 GEB0/IO19RSB1 C2 IO132RSB1 A23 GDB2/IO71RSB1 B11 VMV1 C3 VCC A24 TDI B12 GEB2/IO105RSB1	A9	IO115RSB1	A45	IO07RSB0	B33	VMV0
A11 GEB1/I0110RSB1 A47 GAC1/I005RSB0 B35 GBC1/I036RSB0 A12 GEA0/I0107RSB1 A48 GAB0/I002RSB0 B36 GND A13 GEC2/I0104RSB1 B1 I068RSB1 B37 I026RSB0 A14 I0100RSB1 B2 GAC2/I0131RSB1 B38 I021RSB0 A16 I099RSB1 B4 GFC0/I0125RSB1 B39 GND A17 I096RSB1 B5 VCOMPLF B41 I0088RS0 A18 I094RSB1 B6 GND B42 GND A20 I085RSB1 B8 I0116RSB1 B43 GAC0/I04RSB0 A21 I079RSB1 B9 GND C1 GAA2/I067RSB1 A22 VCC B10 GEB0/I0109RSB1 C2 I0132RSB1 A23 GDB2/I071RSB1 B11 VMV1 C3 VCC A24 TDI B12 GEB2/I0105RSB1 C4 GFB1/I0124RSB1 A25 TRST B13 I0101RSB1	A10	VCC	A46	VCC	B34	GBA0/IO39RSB0
A12 GEA0/IO107RSB1 A48 GAB0/IO02RSB0 B36 GND A13 GEC2/IO104RSB1 B1 IO68RSB1 B37 IO26RSB0 A14 IO100RSB1 B2 GAC2/IO131RSB1 B38 IO21RSB0 A15 VCC B3 GND B39 GND A16 IO99RSB1 B4 GFC0/IO125RSB1 B40 IO13RSB0 A17 IO96RSB1 B5 VCOMPLF B41 IO08RSB0 A18 IO94RSB1 B6 GND B42 GND A19 IO91RSB1 B7 GFB2/IO119RSB1 B43 GAC0/IO4RSB0 A20 IO85RSB1 B8 IO116RSB1 B44 GNDQ A21 IO79RSB1 B9 GND C1 GA2/IO67RSB1 A22 VCC B10 GEB2/IO105RSB1 C2 IO132RSB1 A23 GDB2/IO71RSB1 B11 VMV1 C3 VCC A24 TDI B12 GEB2/IO105RSB1 C4 <	A11	GEB1/IO110RSB1	A47	GAC1/IO05RSB0	B35	GBC1/IO36RSB0
A13 GEC2/IO104RSB1 B1 IO68RSB1 B37 IO26RSB0 A14 IO100RSB1 B2 GAC2/IO131RSB1 B38 IO21RSB0 A15 VCC B3 GND B39 GND A16 IO99RSB1 B4 GFC0/IO125RSB1 B40 IO13RSB0 A17 IO96RSB1 B5 VCOMPLF B41 IO08RSB0 A18 IO94RSB1 B6 GND B42 GND A19 IO91RSB1 B7 GFB2/IO119RSB1 B43 GAC0/IO4RSB0 A20 IO85RSB1 B8 IO116RSB1 B44 GNDQ A21 IO79RSB1 B9 GND C1 GAA2/IO67RSB1 A22 VCC B10 GEB0/IO109RSB1 C2 IO132RSB1 A23 GDB2/IO71RSB1 B11 VMV1 C3 VCC A24 TDI B12 GEB2/IO105RSB1 C4 GFB1/IO124RSB1 A26 GDC1/IO61RSB0 B14 GND C6 <	A12	GEA0/IO107RSB1	A48	GAB0/IO02RSB0	B36	GND
A14 IO100RSB1 B2 GAC2/IO131RSB1 B38 IO21RSB0 A15 VCC B3 GND B39 GND A16 IO99RSB1 B4 GFC0/IO125RSB1 B40 IO13RSB0 A17 IO96RSB1 B5 VCOMPLF B41 IO08RSB0 A18 IO94RSB1 B6 GND B42 GND A19 IO91RSB1 B7 GFB2/IO119RSB1 B43 GAC0/IO04RSB0 A20 IO85RSB1 B8 IO116RSB1 B44 GNDQ A21 IO79RSB1 B9 GND C1 GAA2/IO67RSB1 A22 VCC B10 GEB0/IO109RSB1 C2 IO132RSB1 A23 GDB2/IO71RSB1 B11 VMV1 C3 VCC A24 TDI B12 GEB2/IO105RSB1 C4 GFB1/IO124RSB1 A26 GDC1/IO61RSB0 B14 GND C6 GFA2/IO120RSB1 A27 VCC B15 IO98RSB1 C7 I	A13	GEC2/IO104RSB1	B1	IO68RSB1	B37	IO26RSB0
A15 VCC B3 GND B39 GND A16 IO99RSB1 B4 GFC0/IO125RSB1 B40 IO13RSB0 A17 IO96RSB1 B5 VCOMPLF B41 IO08RSB0 A18 IO94RSB1 B6 GND B42 GND A19 IO91RSB1 B7 GFB2/IO119RSB1 B43 GAC0/IO04RSB0 A20 IO85RSB1 B8 IO116RSB1 B44 GNDQ A21 IO79RSB1 B9 GND C1 GAA2/IO67RSB1 A22 VCC B10 GEB0/IO199RSB1 C2 IO132RSB1 A23 GDB2/IO71RSB1 B11 VMV1 C3 VCC A24 TDI B12 GEB2/IO105RSB1 C4 GFB1/IO124RSB1 A25 TRST B13 IO101RSB1 C5 GFA0/IO122RSB1 A26 GDC1/I/061RSB0 B14 GND C6 GFA2/IO120RSB1 A27 VCC B15 IO98RSB1 C7 IO11	A14	IO100RSB1	B2	GAC2/IO131RSB1	B38	IO21RSB0
A16 IO99RSB1 B4 GFC0/IO125RSB1 B40 IO13RSB0 A17 IO96RSB1 B5 VCOMPLF B41 IO08RSB0 A18 IO94RSB1 B6 GND B42 GND A19 IO91RSB1 B7 GFB2/IO119RSB1 B43 GAC0/IO04RSB0 A20 IO85RSB1 B8 IO116RSB1 B44 GNDQ A21 IO79RSB1 B9 GND C1 GAA2/IO67RSB1 A22 VCC B10 GEB0/IO109RSB1 C2 IO132RSB1 A23 GDB2/IO71RSB1 B11 VMV1 C3 VCC A24 TDI B12 GEB2/IO105RSB1 C4 GFB1/IO124RSB1 A25 TRST B13 IO101RSB1 C5 GFA0/IO122RSB1 A26 GDC1/IO61RSB0 B14 GND C6 GFA2/IO120RSB1 A28 IO60RSB0 B16 IO95RSB1 C3 VCCIB1 A30 GCA2/IO57RSB0 B18 IO87RSB1 C1	A15	VCC	B3	GND	B39	GND
A17 IO96RSB1 B5 VCOMPLF B41 IO08RSB0 A18 IO94RSB1 B6 GND B42 GND A19 IO91RSB1 B7 GFB2/IO119RSB1 B43 GAC0/IO04RSB0 A20 IO85RSB1 B8 IO116RSB1 B44 GNDQ A21 IO79RSB1 B9 GND C1 GAA2/IO67RSB1 A22 VCC B10 GEB0/IO109RSB1 C2 IO132RSB1 A23 GDB2/IO71RSB1 B11 VMV1 C3 VCC A24 TDI B12 GEB2/IO105RSB1 C4 GFB1/IO124RSB1 A25 TRST B13 IO101RSB1 C5 GFA0/IO122RSB1 A26 GDC1/IO61RSB0 B14 GND C6 GFA2/IO120RSB1 A27 VCC B16 IO95RSB1 C8 VCCIB1 A29 GCC2/IO59RSB0 B17 GND C9 GEA1/IO108RSB1 A30 GCA0/IO56RSB0 B19 IO81RSB1 C11 <td>A16</td> <td>IO99RSB1</td> <td>B4</td> <td>GFC0/IO125RSB1</td> <td>B40</td> <td>IO13RSB0</td>	A16	IO99RSB1	B4	GFC0/IO125RSB1	B40	IO13RSB0
A18 IO94RSB1 B6 GND B42 GND A19 IO91RSB1 B7 GFB2/IO119RSB1 B43 GAC0/IO04RSB0 A20 IO85RSB1 B8 IO116RSB1 B44 GND A21 IO79RSB1 B9 GND C1 GAA2/IO67RSB1 A22 VCC B10 GEB0/IO199RSB1 C2 IO132RSB1 A23 GDB2/IO71RSB1 B11 VMV1 C3 VCC A24 TDI B12 GEB2/IO105RSB1 C4 GFB1/IO124RSB1 A25 TRST B13 IO101RSB1 C5 GFA0/IO122RSB1 A26 GDC1/IO61RSB0 B14 GND C6 GFA2/IO120RSB1 A27 VCC B15 IO98RSB1 C7 IO117RSB1 A28 IO60RSB0 B16 IO95RSB1 C8 VCCIB1 A30 GCA2/IO57RSB0 B18 IO87RSB1 C10 GNDQ A31 GCA0/IO56RSB0 B19 IO81RSB1 C11	A17	IO96RSB1	B5	VCOMPLF	B41	IO08RSB0
A19 IO91RSB1 B7 GFB2/IO119RSB1 B43 GAC0/IO04RSB0 A20 IO85RSB1 B8 IO116RSB1 B44 GNDQ A21 IO79RSB1 B9 GND C1 GAA2/IO67RSB1 A22 VCC B10 GEB0/IO109RSB1 C2 IO132RSB1 A23 GDB2/IO71RSB1 B11 VMV1 C3 VCC A24 TDI B12 GEB2/IO105RSB1 C4 GFB1/IO124RSB1 A25 TRST B13 IO101RSB1 C5 GFA0/IO122RSB1 A26 GDC1/IO61RSB0 B14 GND C6 GFA2/IO120RSB1 A27 VCC B15 IO98RSB1 C7 IO117RSB1 A28 IO60RSB0 B16 IO95RSB1 C8 VCCIB1 A30 GCA2/IO57RSB0 B18 IO87RSB1 C10 GNDQ A31 GCA0/IO56RSB0 B19 IO81RSB1 C11 GEA2/IO106RSB1 A33 IO49RSB0 B21 GNDQ	A18	IO94RSB1	B6	GND	B42	GND
A20 IO85RSB1 B8 IO116RSB1 B44 GNDQ A21 IO79RSB1 B9 GND C1 GAA2/IO67RSB1 A22 VCC B10 GEB0/IO109RSB1 C2 IO132RSB1 A23 GDB2/IO71RSB1 B11 VMV1 C3 VCC A24 TDI B12 GEB2/IO105RSB1 C4 GFB1/IO124RSB1 A25 TRST B13 IO101RSB1 C5 GFA0/IO122RSB1 A26 GDC1/IO61RSB0 B14 GND C6 GFA2/IO120RSB1 A27 VCC B15 IO98RSB1 C7 IO117RSB1 A28 IO60RSB0 B16 IO95RSB1 C8 VCCIB1 A29 GCC2/IO59RSB0 B17 GND C9 GEA1/IO108RSB1 A30 GCA2/IO57RSB0 B19 IO81RSB1 C10 GNDQ A31 GCA0/IO56RSB0 B19 IO81RSB1 C11 GEA2/IO106RSB1 A33 IO49RSB0 B21 GNDQ C	A19	IO91RSB1	B7	GFB2/IO119RSB1	B43	GAC0/IO04RSB0
A21 IO79RSB1 B9 GND C1 GAA2/IO67RSB1 A22 VCC B10 GEB0/IO109RSB1 C2 IO132RSB1 A23 GDB2/IO71RSB1 B11 VMV1 C3 VCC A24 TDI B12 GEB2/IO15RSB1 C4 GFB1/IO124RSB1 A25 TRST B13 IO101RSB1 C5 GFA0/IO122RSB1 A26 GDC1/IO61RSB0 B14 GND C6 GFA2/IO120RSB1 A27 VCC B15 IO98RSB1 C7 IO117RSB1 A28 IO60RSB0 B16 IO95RSB1 C8 VCCIB1 A29 GCC2/IO59RSB0 B17 GND C9 GEA1/IO108RSB1 A30 GCA2/IO57RSB0 B19 IO81RSB1 C11 GEA2/IO106RSB1 A32 GCB1/IO53RSB0 B20 GND C12 IO103RSB1 A33 IO49RSB0 B21 GNDQ C13 VCCIB1 A34 VCC B22 TMS C14	A20	IO85RSB1	B8	IO116RSB1	B44	GNDQ
A22 VCC B10 GEB0/IO109RSB1 C2 IO132RSB1 A23 GDB2/IO71RSB1 B11 VMV1 C3 VCC A24 TDI B12 GEB2/IO105RSB1 C4 GFB1/IO124RSB1 A25 TRST B13 IO101RSB1 C5 GFA0/IO122RSB1 A26 GDC1/IO61RSB0 B14 GND C6 GFA2/IO120RSB1 A27 VCC B15 IO98RSB1 C7 IO117RSB1 A28 IO60RSB0 B16 IO95RSB1 C8 VCCIB1 A29 GCC2/IO59RSB0 B17 GND C9 GEA1/IO108RSB1 A30 GCA2/IO57RSB0 B18 IO87RSB1 C10 GNDQ A31 GCA0/IO56RSB0 B19 IO81RSB1 C11 GEA2/IO106RSB1 A33 IO49RSB0 B21 GNDQ C12 IO103RSB1 A33 IO49RSB0 B23 TDO C14 IO97RSB1 A35 IO44RSB0 B24 GDC0/IO62RSB0	A21	IO79RSB1	B9	GND	C1	GAA2/IO67RSB1
A23 GDB2/IO71RSB1 B11 VMV1 C3 VCC A24 TDI B12 GEB2/IO105RSB1 C4 GFB1/IO124RSB1 A25 TRST B13 IO101RSB1 C5 GFA0/IO122RSB1 A26 GDC1/IO61RSB0 B14 GND C6 GFA2/IO120RSB1 A27 VCC B15 IO98RSB1 C7 IO117RSB1 A28 IO60RSB0 B16 IO95RSB1 C8 VCCIB1 A29 GCC2/IO59RSB0 B17 GND C9 GEA1/IO108RSB1 A30 GCA2/IO57RSB0 B19 IO81RSB1 C10 GNDQ A31 GCA0/IO56RSB0 B19 IO81RSB1 C11 GEA2/IO106RSB1 A32 GCB1/IO53RSB0 B20 GND C12 IO103RSB1 A33 IO49RSB0 B21 GNDQ C13 VCCIB1 A34 VCC B22 TMS C14 IO93RSB1 A36 GBA2/IO41RSB0 B24 GDC0/IO62RSB0 <	A22	VCC	B10	GEB0/IO109RSB1	C2	IO132RSB1
A24 TDI B12 GEB2/IO105RSB1 C4 GFB1/IO124RSB1 A25 TRST B13 IO101RSB1 C5 GFA0/IO122RSB1 A26 GDC1/IO61RSB0 B14 GND C6 GFA2/IO120RSB1 A27 VCC B15 IO98RSB1 C7 IO117RSB1 A28 IO60RSB0 B16 IO95RSB1 C8 VCCIB1 A29 GCC2/IO59RSB0 B17 GND C9 GEA1/IO108RSB1 A30 GCA2/IO57RSB0 B18 IO87RSB1 C10 GNDQ A31 GCA0/IO56RSB0 B19 IO81RSB1 C11 GEA2/IO106RSB1 A33 IO49RSB0 B20 GND C12 IO103RSB1 A34 VCC B22 TMS C14 IO97RSB1 A35 IO44RSB0 B23 TDO C15 IO93RSB1 A36 GBA2/IO41RSB0 B24 GDC0/IO62RSB0 C16 IO89RSB1	A23	GDB2/IO71RSB1	B11	VMV1	C3	VCC
A25 TRST B13 IO101RSB1 C5 GFA0/IO122RSB1 A26 GDC1/IO61RSB0 B14 GND C6 GFA2/IO120RSB1 A27 VCC B15 IO98RSB1 C7 IO117RSB1 A28 IO60RSB0 B16 IO95RSB1 C8 VCCIB1 A29 GCC2/IO59RSB0 B17 GND C9 GEA1/IO108RSB1 A30 GCA2/IO57RSB0 B18 IO87RSB1 C10 GNDQ A31 GCA0/IO56RSB0 B19 IO81RSB1 C11 GEA2/IO106RSB1 A32 GCB1/IO53RSB0 B20 GND C12 IO103RSB1 A33 IO49RSB0 B21 GNDQ C13 VCCIB1 A34 VCC B22 TMS C14 IO97RSB1 A35 IO44RSB0 B24 GDC0/IO62RSB0 C16 IO89RSB1	A24	TDI	B12	GEB2/IO105RSB1	C4	GFB1/IO124RSB1
A26 GDC1/IO61RSB0 B14 GND C6 GFA2/IO120RSB1 A27 VCC B15 IO98RSB1 C7 IO117RSB1 A28 IO60RSB0 B16 IO95RSB1 C8 VCCIB1 A29 GCC2/IO59RSB0 B17 GND C9 GEA1/IO108RSB1 A30 GCA2/IO57RSB0 B18 IO87RSB1 C10 GNDQ A31 GCA0/IO56RSB0 B19 IO81RSB1 C11 GEA2/IO106RSB1 A32 GCB1/IO53RSB0 B20 GND C12 IO103RSB1 A33 IO49RSB0 B21 GNDQ C13 VCCIB1 A34 VCC B22 TMS C14 IO97RSB1 A35 IO44RSB0 B23 TDO C15 IO93RSB1 A36 GBA2/IO41RSB0 B24 GDC0/IO62RSB0 C16 IO89RSB1	A25	TRST	B13	IO101RSB1	C5	GFA0/IO122RSB1
A27 VCC B15 IO98RSB1 C7 IO117RSB1 A28 IO60RSB0 B16 IO95RSB1 C8 VCCIB1 A29 GCC2/IO59RSB0 B17 GND C9 GEA1/IO108RSB1 A30 GCA2/IO57RSB0 B18 IO87RSB1 C10 GNDQ A31 GCA0/IO56RSB0 B19 IO81RSB1 C11 GEA2/IO106RSB1 A32 GCB1/IO53RSB0 B20 GND C12 IO103RSB1 A33 IO49RSB0 B21 GNDQ C14 IO97RSB1 A34 VCC B23 TDO C15 IO93RSB1 A36 GBA2/IO41RSB0 B24 GDC0/IO62RSB0 C16 IO89RSB1	A26	GDC1/IO61RSB0	B14	GND	C6	GFA2/IO120RSB1
A28 IO60RSB0 B16 IO95RSB1 C8 VCCIB1 A29 GCC2/IO59RSB0 B17 GND C9 GEA1/IO108RSB1 A30 GCA2/IO57RSB0 B18 IO87RSB1 C10 GNDQ A31 GCA0/IO56RSB0 B19 IO81RSB1 C11 GEA2/IO106RSB1 A32 GCB1/IO53RSB0 B20 GND C12 IO103RSB1 A33 IO49RSB0 B21 GNDQ C13 VCCIB1 A34 VCC B22 TMS C14 IO97RSB1 A35 IO44RSB0 B24 GDC0/IO62RSB0 C16 IO89RSB1	A27	VCC	B15	IO98RSB1	C7	IO117RSB1
A29 GCC2/IO59RSB0 B17 GND C9 GEA1/IO108RSB1 A30 GCA2/IO57RSB0 B18 IO87RSB1 C10 GNDQ A31 GCA0/IO56RSB0 B19 IO81RSB1 C11 GEA2/IO106RSB1 A32 GCB1/IO53RSB0 B20 GND C12 IO103RSB1 A33 IO49RSB0 B21 GNDQ C13 VCCIB1 A35 IO44RSB0 B23 TDO C15 IO93RSB1 A36 GBA2/IO41RSB0 B24 GDC0/IO62RSB0 C16 IO89RSB1	A28	IO60RSB0	B16	IO95RSB1	C8	VCCIB1
A30 GCA2/IO57RSB0 B18 IO87RSB1 C10 GNDQ A31 GCA0/IO56RSB0 B19 IO81RSB1 C11 GEA2/IO106RSB1 A32 GCB1/IO53RSB0 B20 GND C12 IO103RSB1 A33 IO49RSB0 B21 GNDQ C13 VCCIB1 A34 VCC B22 TMS C14 IO97RSB1 A35 IO44RSB0 B23 TDO C15 IO89RSB1 A36 GBA2/IO41RSB0 B24 GDC0/IO62RSB0 C16 IO89RSB1	A29	GCC2/IO59RSB0	B17	GND	C9	GEA1/IO108RSB1
A31 GCA0/IO56RSB0 B19 IO81RSB1 C11 GEA2/IO106RSB1 A32 GCB1/IO53RSB0 B20 GND C12 IO103RSB1 A33 IO49RSB0 B21 GNDQ C13 VCCIB1 A34 VCC B22 TMS C14 IO97RSB1 A35 IO44RSB0 B23 TDO C15 IO93RSB1 A36 GBA2/IO41RSB0 B24 GDC0/IO62RSB0 C16 IO89RSB1	A30	GCA2/IO57RSB0	B18	IO87RSB1	C10	GNDQ
A32 GCB1/IO53RSB0 B20 GND C12 IO103RSB1 A33 IO49RSB0 B21 GNDQ C13 VCCIB1 A34 VCC B22 TMS C14 IO97RSB1 A35 IO44RSB0 B23 TDO C15 IO93RSB1 A36 GBA2/IO41RSB0 B24 GDC0/IO62RSB0 C16 IO89RSB1	A31	GCA0/IO56RSB0	B19	IO81RSB1	C11	GEA2/IO106RSB1
A33 IO49RSB0 B21 GNDQ C13 VCCIB1 A34 VCC B22 TMS C14 IO97RSB1 A35 IO44RSB0 B23 TDO C15 IO93RSB1 A36 GBA2/IO41RSB0 B24 GDC0/IO62RSB0 C16 IO89RSB1	A32	GCB1/IO53RSB0	B20	GND	C12	IO103RSB1
A34 VCC B22 TMS C14 IO97RSB1 A35 IO44RSB0 B23 TDO C15 IO93RSB1 A36 GBA2/IO41RSB0 B24 GDC0/IO62RSB0 C16 IO89RSB1	A33	IO49RSB0	B21	GNDQ	C13	VCCIB1
A35 IO44RSB0 B23 TDO C15 IO93RSB1 A36 GBA2/IO41RSB0 B24 GDC0/IO62RSB0 C16 IO89RSB1	A34	VCC	B22	TMS	C14	IO97RSB1
A36 GBA2/IO41RSB0 B24 GDC0/IO62RSB0 C16 IO89RSB1	A35	IO44RSB0	B23	TDO	C15	IO93RSB1
	A36	GBA2/IO41RSB0	B24	GDC0/IO62RSB0	C16	IO89RSB1



Package Pin Assignments

QN132					
Pin Number	A3P125 Function				
C17	IO83RSB1				
C18	VCCIB1				
C19	ТСК				
C20	VMV1				
C21	VPUMP				
C22	VJTAG				
C23	VCCIB0				
C24	NC				
C25	NC				
C26	GCA1/IO55RSB0				
C27	GCC0/IO52RSB0				
C28	VCCIB0				
C29	IO42RSB0				
C30	GNDQ				
C31	GBA1/IO40RSB0				
C32	GBB0/IO37RSB0				
C33	VCC				
C34	IO24RSB0				
C35	IO19RSB0				
C36	IO16RSB0				
C37	IO10RSB0				
C38	VCCIB0				
C39	GAB1/IO03RSB0				
C40	VMV0				
D1	GND				
D2	GND				
D3	GND				
D4	GND				



TQ144					
Pin Number	A3P125 Function				
109	GBA1/IO40RSB0				
110	GBA0/IO39RSB0				
111	GBB1/IO38RSB0				
112	GBB0/IO37RSB0				
113	GBC1/IO36RSB0				
114	GBC0/IO35RSB0				
115	IO34RSB0				
116	IO33RSB0				
117	VCCIB0				
118	GND				
119	VCC				
120	IO29RSB0				
121	IO28RSB0				
122	IO27RSB0				
123	IO25RSB0				
124	IO23RSB0				
125	IO21RSB0				
126	IO19RSB0				
127	IO17RSB0				
128	IO16RSB0				
129	IO14RSB0				
130	IO12RSB0				
131	IO10RSB0				
132	IO08RSB0				
133	IO06RSB0				
134	VCCIB0				
135	GND				
136	VCC				
137	GAC1/IO05RSB0				
138	GAC0/IO04RSB0				
139	GAB1/IO03RSB0				
140	GAB0/IO02RSB0				
141	GAA1/IO01RSB0				
142	GAA0/IO00RSB0				
143	GNDQ				
144	VMV0				

Microsemi

Package Pin Assignments

FG484					
Pin Number	A3P400 Function				
Y15	VCC				
Y16	NC				
Y17	NC				
Y18	GND				
Y19	NC				
Y20	NC				
Y21	NC				
Y22	VCCIB1				
AA1	GND				
AA2	VCCIB3				
AA3	NC				
AA4	NC				
AA5	NC				
AA6	NC				
AA7	NC				
AA8	NC				
AA9	NC				
AA10	NC				
AA11	NC				
AA12	NC				
AA13	NC				
AA14	NC				
AA15	NC				
AA16	NC				
AA17	NC				
AA18	NC				
AA19	NC				
AA20	NC				
AA21	VCCIB1				
AA22	GND				
AB1	GND				
AB2	GND				
AB3	VCCIB2				
AB4	NC				
AB5	NC				
AB6	IO121RSB2				

FG484					
Pin Number	A3P400 Function				
AB7	IO119RSB2				
AB8	IO114RSB2				
AB9	IO109RSB2				
AB10	NC				
AB11	NC				
AB12	IO104RSB2				
AB13	IO103RSB2				
AB14	NC				
AB15	NC				
AB16	IO91RSB2				
AB17	IO90RSB2				
AB18	NC				
AB19	NC				
AB20	VCCIB2				
AB21	GND				
AB22	GND				



	FG484		FG484	FG484	
Pin Number	A3P600 Function	Pin Number	A3P600 Function	Pin Number	A3P600 Function
A1	GND	B15	NC	D7	GAB0/IO02RSB0
A2	GND	B16	IO47RSB0	D8	IO11RSB0
A3	VCCIB0	B17	IO49RSB0	D9	IO16RSB0
A4	NC	B18	NC	D10	IO18RSB0
A5	NC	B19	NC	D11	IO28RSB0
A6	IO09RSB0	B20	NC	D12	IO34RSB0
A7	IO15RSB0	B21	VCCIB1	D13	IO37RSB0
A8	NC	B22	GND	D14	IO41RSB0
A9	NC	C1	VCCIB3	D15	IO43RSB0
A10	IO22RSB0	C2	NC	D16	GBB1/IO57RSB0
A11	IO23RSB0	C3	NC	D17	GBA0/IO58RSB0
A12	IO29RSB0	C4	NC	D18	GBA1/IO59RSB0
A13	IO35RSB0	C5	GND	D19	GND
A14	NC	C6	NC	D20	NC
A15	NC	C7	NC	D21	NC
A16	IO46RSB0	C8	VCC	D22	NC
A17	IO48RSB0	C9	VCC	E1	NC
A18	NC	C10	NC	E2	NC
A19	NC	C11	NC	E3	GND
A20	VCCIB0	C12	NC	E4	GAB2/IO173PDB3
A21	GND	C13	NC	E5	GAA2/IO174PDB3
A22	GND	C14	VCC	E6	GNDQ
B1	GND	C15	VCC	E7	GAB1/IO03RSB0
B2	VCCIB3	C16	NC	E8	IO13RSB0
B3	NC	C17	NC	E9	IO14RSB0
B4	NC	C18	GND	E10	IO21RSB0
B5	NC	C19	NC	E11	IO27RSB0
B6	IO08RSB0	C20	NC	E12	IO32RSB0
B7	IO12RSB0	C21	NC	E13	IO38RSB0
B8	NC	C22	VCCIB1	E14	IO42RSB0
B9	NC	D1	NC	E15	GBC1/IO55RSB0
B10	IO17RSB0	D2	NC	E16	GBB0/IO56RSB0
B11	NC	D3	NC	E17	IO52RSB0
B12	NC	D4	GND	E18	GBA2/IO60PDB1
B13	IO36RSB0	D5	GAA0/IO00RSB0	E19	IO60NDB1
B14	NC	D6	GAA1/IO01RSB0	E20	GND

Revision	Changes	Page
Advance v0.2, (continued)	Table 2-43 was updated.	2-64
	Table 2-18 was updated.	
	Pin descriptions in the "JTAG Pins" section were updated.	
	The "User I/O Naming Convention" section was updated.	
	Table 3-7 was updated.	3-6
	The "Methodology" section was updated.	3-10
	Table 3-40 and Table 3-39 were updated.	3-33,3-32
	The A3P250 "100-Pin VQFP*" pin table was updated.	4-14
	The A3P250 "208-Pin PQFP*" pin table was updated.	4-23
	The A3P1000 "208-Pin PQFP*" pin table was updated.	4-29
	The A3P250 "144-Pin FBGA*" pin table was updated.	4-36
	The A3P1000 "144-Pin FBGA*" pin table was updated.	4-32
	The A3P250 "256-Pin FBGA*" pin table was updated.	4-45
	The A3P1000 "256-Pin FBGA*" pin table was updated.	4-54
	The A3P1000 "484-Pin FBGA*" pin table was updated.	4-68