



Welcome to E-XFL.COM

#### What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

#### Details

Product Status	Active
Core Processor	ARM® Cortex®-M7
Core Size	32-Bit Single-Core
Speed	216MHz
Connectivity	CANbus, EBI/EMI, Ethernet, I <sup>2</sup> C, IrDA, LINbus, SAI, SD, SPDIF-Rx, SPI, UART/USART, USB OTG
Peripherals	Brown-out Detect/Reset, DMA, I <sup>2</sup> S, LCD, POR, PWM, WDT
Number of I/O	168
Program Memory Size	1MB (1M x 8)
Program Memory Type	FLASH
EEPROM Size	-
RAM Size	320K x 8
Voltage - Supply (Vcc/Vdd)	1.7V ~ 3.6V
Data Converters	A/D 24x12b; D/A 2x12b
Oscillator Type	Internal
Operating Temperature	-40°C ~ 105°C (TA)
Mounting Type	Surface Mount
Package / Case	208-LQFP
Supplier Device Package	208-LQFP (28x28)
Purchase URL	https://www.e-xfl.com/product-detail/stmicroelectronics/stm32f746bgt7

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

# **1.1** Full compatibility throughout the family

The STM32F745xx and STM32F746xx devices are fully pin-to-pin, compatible with the STM32F4xxxx devices, allowing the user to try different peripherals, and reaching higher performances (higher frequency) for a greater degree of freedom during the development cycle.

*Figure 1* give compatible board designs between the STM32F4xx families.



The STM32F745xx and STM32F746xx LQFP144, LQFP176, LQFP208, TFBGA216, UFBGA176, WLCSP143 packages are fully pin to pin compatible with STM32F4xxxx devices.



Each stream is connected to dedicated hardware DMA requests, with support for software trigger on each stream. Configuration is made by software and transfer sizes between source and destination are independent.

The DMA can be used with the main peripherals:

- SPI and I<sup>2</sup>S
- I<sup>2</sup>C
- USART
- General-purpose, basic and advanced-control timers TIMx
- DAC
- SDMMC
- Camera interface (DCMI)
- ADC
- SAI
- SPDIFRX
- Quad-SPI
- HDMI-CEC

# 2.8 Flexible memory controller (FMC)

The Flexible memory controller (FMC) includes three memory controllers:

- The NOR/PSRAM memory controller
- The NAND/memory controller
- The Synchronous DRAM (SDRAM/Mobile LPSDR SDRAM) controller

The main features of the FMC controller are the following:

- Interface with static-memory mapped devices including:
  - Static random access memory (SRAM)
  - NOR Flash memory/OneNAND Flash memory
  - PSRAM (4 memory banks)
  - NAND Flash memory with ECC hardware to check up to 8 Kbytes of data
- Interface with synchronous DRAM (SDRAM/Mobile LPSDR SDRAM) memories
- 8-,16-,32-bit data bus width
- Independent Chip Select control for each memory bank
- Independent configuration for each memory bank
- Write FIFO
- Read FIFO for SDRAM controller
- The Maximum FMC\_CLK/FMC\_SDCLK frequency for synchronous accesses is HCLK/2.

#### LCD parallel interface

The FMC can be configured to interface seamlessly with most graphic LCD controllers. It supports the Intel 8080 and Motorola 6800 modes, and is flexible enough to adapt to specific LCD interfaces. This LCD parallel interface capability makes it easy to build cost-



## 2.15 Boot modes

At startup, the boot memory space is selected by the BOOT pin and BOOT\_ADDx option bytes, allowing to program any boot memory address from 0x0000 0000 to 0x3FFF FFFF which includes:

- All Flash address space mapped on ITCM or AXIM interface
- All RAM address space: ITCM, DTCM RAMs and SRAMs mapped on AXIM interface
- The System memory bootloader

The boot loader is located in system memory. It is used to reprogram the Flash memory through a serial interface.

# 2.16 Power supply schemes

- V<sub>BAT</sub> = 1.65 to 3.6 V: power supply for RTC, external clock 32 kHz oscillator and backup registers (through power switch) when V<sub>DD</sub> is not present.
- V<sub>DD</sub> = 1.7 to 3.6 Vexternal power supply for I/Os and the internal regulator (when enabled), provided externally through V<sub>DD</sub> pins.
- V<sub>SSA</sub>, V<sub>DDA</sub> = 1.7 to 3.6 V: external analog power supplies for ADC, DAC, reset blocks, RCs and PLL. V<sub>DDA</sub> and V<sub>SSA</sub> must be connected to V<sub>DD</sub> and V<sub>SS</sub>, respectively.

Note: V<sub>DD</sub>/V<sub>DDA</sub> minimum value of 1.7 V is obtained when the internal reset is OFF (refer to Section 2.17.2: Internal reset OFF). Refer to Table 3: Voltage regulator configuration mode versus device operating mode to identify the packages supporting this option.

- $V_{DDUSB}$  can be connected either to  $V_{DD}$  or an external independent power supply (3.0 to 3.6V) for USB transceivers (refer to *Figure 4* and *Figure 5*). For example, when device is powered at 1.8V, an independent power supply 3.3V can be connected to  $V_{DDUSB}$ . When the  $V_{DDUSB}$  is connected to a separated power supply, it is independent from  $V_{DD}$  or  $V_{DDA}$  but it must be the last supply to be provided and the first to disappear. The following conditions  $V_{DDUSB}$  must be respected:
  - During power-on phase (V\_DD < V\_DD\_MIN), V\_DDUSB should be always lower than V\_DD
  - During power-down phase (V<sub>DD</sub> < V<sub>DD\_MIN</sub>), V<sub>DDUSB</sub> should be always lower than  $V_{DD}$
  - V<sub>DDSUB</sub> rising and falling time rate specifications must be respected (see *Table 20* and *Table 21*)
  - In operating mode phase, V<sub>DDUSB</sub> could be lower or higher than V<sub>DD</sub>.
    - If USB (USB OTG\_HS/OTG\_FS) is used, the associated GPIOs powered by  $V_{DDUSB}$  are operating between  $V_{DDUSB\ MIN}$  and  $V_{DDUSB\ MAX}.$

- The V<sub>DDUSB</sub> supply both USB transceiver (USB OTG\_HS and USB OTG\_FS). If only one USB transceiver is used in the application, the GPIOs associated to the other USB transceiver are still supplied by V<sub>DDUSB</sub>.

- If USB (USB OTG\_HS/OTG\_FS) is not used, the associated GPIOs powered by  $V_{DDUSB}$  are operating between  $V_{DD\_MIN}$  and  $V_{DD\_MAX}.$ 



## 2.22.1 Advanced-control timers (TIM1, TIM8)

The advanced-control timers (TIM1, TIM8) can be seen as three-phase PWM generators multiplexed on 6 channels. They have complementary PWM outputs with programmable inserted dead times. They can also be considered as complete general-purpose timers. Their 4 independent channels can be used for:

- Input capture
- Output compare
- PWM generation (edge- or center-aligned modes)
- One-pulse mode output

If configured as standard 16-bit timers, they have the same features as the general-purpose TIMx timers. If configured as 16-bit PWM generators, they have full modulation capability (0-100%).

The advanced-control timer can work together with the TIMx timers via the Timer Link feature for synchronization or event chaining.

TIM1 and TIM8 support independent DMA request generation.

### 2.22.2 General-purpose timers (TIMx)

There are ten synchronizable general-purpose timers embedded in the STM32F74xxx devices (see *Table 6* for differences).

#### • TIM2, TIM3, TIM4, TIM5

The STM32F74xxx include 4 full-featured general-purpose timers: TIM2, TIM5, TIM3, and TIM4.The TIM2 and TIM5 timers are based on a 32-bit auto-reload up/downcounter and a 16-bit prescaler. The TIM3 and TIM4 timers are based on a 16-bit auto-reload up/downcounter and a 16-bit prescaler. They all feature 4 independent channels for input capture/output compare, PWM or one-pulse mode output. This gives up to 16 input capture/output compare/PWMs on the largest packages.

The TIM2, TIM3, TIM4, TIM5 general-purpose timers can work together, or with the other general-purpose timers and the advanced-control timers TIM1 and TIM8 via the Timer Link feature for synchronization or event chaining.

Any of these general-purpose timers can be used to generate PWM outputs.

TIM2, TIM3, TIM4, TIM5 all have independent DMA request generation. They are capable of handling quadrature (incremental) encoder signals and the digital outputs from 1 to 4 hall-effect sensors.

#### • TIM9, TIM10, TIM11, TIM12, TIM13, and TIM14

These timers are based on a 16-bit auto-reload upcounter and a 16-bit prescaler. TIM10, TIM11, TIM13, and TIM14 feature one independent channel, whereas TIM9 and TIM12 have two independent channels for input capture/output compare, PWM or one-pulse mode output. They can be synchronized with the TIM2, TIM3, TIM4, TIM5 full-featured general-purpose timers. They can also be used as simple time bases.



#### 2.22.3 Basic timers TIM6 and TIM7

These timers are mainly used for DAC trigger and waveform generation. They can also be used as a generic 16-bit time base.

TIM6 and TIM7 support independent DMA request generation.

#### 2.22.4 Low-power timer (LPTIM1)

The low-power timer has an independent clock and is running also in Stop mode if it is clocked by LSE, LSI or an external clock. It is able to wakeup the devices from Stop mode.

This low-power timer supports the following features:

- 16-bit up counter with 16-bit autoreload register
- 16-bit compare register
- Configurable output: pulse, PWM
- Continuous / one-shot mode
- Selectable software / hardware input trigger
- Selectable clock source:
- Internal clock source: LSE, LSI, HSI or APB clock
- External clock source over LPTIM input (working even with no internal clock source running, used by the Pulse Counter Application)
- Programmable digital glitch filter
- Encoder mode

#### 2.22.5 Independent watchdog

The independent watchdog is based on a 12-bit downcounter and 8-bit prescaler. It is clocked from an independent 32 kHz internal RC and as it operates independently from the main clock, it can operate in Stop and Standby modes. It can be used either as a watchdog to reset the device when a problem occurs, or as a free-running timer for application timeout management. It is hardware- or software-configurable through the option bytes.

#### 2.22.6 Window watchdog

The window watchdog is based on a 7-bit downcounter that can be set as free-running. It can be used as a watchdog to reset the device when a problem occurs. It is clocked from the main clock. It has an early warning interrupt capability and the counter can be frozen in debug mode.

#### 2.22.7 SysTick timer

This timer is dedicated to real-time operating systems, but could also be used as a standard downcounter. It features:

- A 24-bit downcounter
- Autoreload capability
- Maskable system interrupt generation when the counter reaches 0
- Programmable clock source.



#### Pinouts and pin description



#### Figure 18. STM32F74xNx TFBGA216 ballout

1. The above figure shows the package top view.



82/227

DocID027590 Rev 4

				Table 12	2. STM32	F745xx	and STI	M32F74	6xx alte	rnate fu	nction m	napping	(continu	ed)			
		AF0	AF1	AF2	AF3	AF4	AF5	AF6	AF7	AF8	AF9	AF10	AF11	AF12	AF13	AF14	AF15
P	ort	SYS	TIM1/2	TIM3/4/5	TIM8/9/10/ 11/LPTIM 1/CEC	I2C1/2/3/ 4/CEC	SPI1/2/3/ 4/5/6	SPI3/ SAI1	SPI2/3/U SART1/2/ 3/UART5/ SPDIFRX	SAI2/US ART6/UA RT4/5/7/8 /SPDIFR X	CAN1/2/T IM12/13/ 14/QUAD SPI/LCD	SAI2/QU ADSPI/O TG2_HS/ OTG1_FS	ETH/ OTG1_FS	FMC/SD MMC1/O TG2_FS	DCMI	LCD	SYS
D. I.F.	PE14	-	TIM1_C H4	-	-	-	SPI4_M OSI	-	-	-	-	SAI2_MC K_B	-	FMC_D1 1	-	LCD_CL K	EVEN TOUT
Port E	PE15	-	TIM1_B KIN	-	-	-	-	-	-	-	-	-	-	FMC_D1 2	-	LCD_R7	EVEN TOUT
	PF0	-	-	-	-	I2C2_SD A	-	-	-	-	-	-	-	FMC_A0	-	-	EVEN TOUT
	PF1	-	-	-	-	I2C2_SC L	-	-	-	-	-	-	-	FMC_A1	-	-	EVEN TOUT
	PF2	-	-	-	-	I2C2_SM BA	-	-	-	-	-	-	-	FMC_A2	-	-	EVEN TOUT
	PF3	-	-	-	-	-	-	-	-	-	-	-	-	FMC_A3	-	-	EVEN TOUT
	PF4	-	-	-	-	-	-	-	-	-	-	-	-	FMC_A4	-	-	EVEN TOUT
	PF5	-	-	-	-	-	-	-	-	-	-	-	-	FMC_A5	-	-	EVEN TOUT
Port F	PF6	-	-	-	TIM10_C H1	-	SPI5_NS S	SAI1_SD _B	-	UART7_ Rx	QUADSP I_BK1_IO 3	-	-	-	-	-	EVEN TOUT
	PF7	-	-	-	TIM11_CH 1	-	SPI5_SC K	SAI1_M CLK_B	-	UART7_T x	QUADSP I_BK1_IO 2	-	-	-	-	-	EVEN TOUT
	PF8	-	-	-	-	-	SPI5_MI SO	SAI1_SC K_B	-	UART7_ RTS	TIM13_C H1	QUADSPI _BK1_IO0	-	-	-	-	EVEN TOUT
	PF9	-	-	-	-	-	SPI5_M OSI	SAI1_FS _B	-	UART7_ CTS	TIM14_C H1	QUADSPI _BK1_IO1	-	-	-	-	EVEN TOUT
	PF10	-	-	-	-	-	-	-	-	-	-	-	-	-	DCMI_D 11	LCD_DE	EVEN TOUT
	PF11	-	-	-	-	-	SPI5_M OSI	-	-	-	-	SAI2_SD_ B	-	FMC_SD NRAS	DCMI_D 12	-	EVEN TOUT
	PF12	-	-	-	-	-	-	-	-	-	-	-	-	FMC_A6	-	-	EVEN TOUT

# Pinouts and pin description

STM32F745xx STM32F746xx

84/227

DocID027590 Rev 4

				Table 12	2. STM32	F745xx	and STI	M32F74	6xx alte	rnate fu	nction m	napping	(continu	ed)			
		AF0	AF1	AF2	AF3	AF4	AF5	AF6	AF7	AF8	AF9	AF10	AF11	AF12	AF13	AF14	AF15
P	ort	SYS	TIM1/2	TIM3/4/5	TIM8/9/10/ 11/LPTIM 1/CEC	I2C1/2/3/ 4/CEC	SPI1/2/3/ 4/5/6	SPI3/ SAI1	SPI2/3/U SART1/2/ 3/UART5/ SPDIFRX	SAI2/US ART6/UA RT4/5/7/8 /SPDIFR X	CAN1/2/T IM12/13/ 14/QUAD SPI/LCD	SAI2/QU ADSPI/O TG2_HS/ OTG1_FS	ETH/ OTG1_FS	FMC/SD MMC1/O TG2_FS	DCMI	LCD	SYS
	PG11	-	-	-	-	-	-	-	SPDIFRX _IN0	-	-	-	ETH_MII_ TX_EN/E TH_RMII_ TX_EN	-	DCMI_D 3	LCD_B3	EVEN TOUT
	PG12	-	-	-	LPTIM1_I N1	-	SPI6_MI SO	-	SPDIFRX _IN1	USART6 _RTS	LCD_B4	-	-	FMC_NE 4	-	LCD_B1	EVEN TOUT
Port G	PG13	TRACE D0	-	-	LPTIM1_ OUT	-	SPI6_SC K	-	-	USART6 _CTS	-	-	ETH_MII_ TXD0/ET H_RMII_T XD0	FMC_A2	-	LCD_R0	EVEN TOUT
	PG14	TRACE D1	-	-	LPTIM1_E TR	-	SPI6_M OSI	-	-	USART6 _TX	QUADSP I_BK2_IO 3	-	ETH_MII_ TXD1/ET H_RMII_T XD1	FMC_A2 5	-	LCD_B0	EVEN TOUT
	PG15	-	-	-	-	-	-	-	-	USART6 _CTS	-	-	-	FMC_SD NCAS	DCMI_D 13	-	EVEN TOUT
	PH0	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	EVEN TOUT
	PH1	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	EVEN TOUT
	PH2	-	-	-	LPTIM1_I N2	-	-	-	-	-	QUADSP I_BK2_IO 0	SAI2_SC K_B	ETH_MII_ CRS	FMC_SD CKE0	-	LCD_R0	EVEN TOUT
Port H	PH3	-	-	-	-	-	-	-	-	-	QUADSP I_BK2_IO 1	SAI2_MC K_B	ETH_MII_ COL	FMC_SD NE0	-	LCD_R1	EVEN TOUT
	PH4	-	-	-	-	I2C2_SC L	-	-	-	-	-	OTG_HS_ ULPI_NX T	-	-	-	-	EVEN TOUT
	PH5	-	-	-	-	I2C2_SD A	SPI5_NS S	-	-	-	-	-	-	FMC_SD NWE	-	-	EVEN TOUT
	PH6	-	-	-	-	I2C2_SM BA	SPI5_SC K	-	-	-	TIM12_C H1	-	ETH_MII_ RXD2	FMC_SD NE1	DCMI_D 8	-	EVEN TOUT
	PH7	-	-	-	-	I2C3_SC L	SPI5_MI SO	-	-	-	-	-	ETH_MII_ RXD3	FMC_SD CKE1	DCMI_D 9	-	EVEN TOUT

# Pinouts and pin description

STM32F745xx STM32F746xx

Bus	Boundary address	Peripheral
	0x4000 8000- 0x4000 FFFF	Reserved
	0x4000 7C00 - 0x4000 7FFF	UART8
	0x4000 7800 - 0x4000 7BFF	UART7
	0x4000 7400 - 0x4000 77FF	DAC
	0x4000 7000 - 0x4000 73FF	PWR
	0x4000 6C00 - 0x4000 6FFF	HDMI-CEC
	0x4000 6800 - 0x4000 6BFF	CAN2
	0x4000 6400 - 0x4000 67FF	CAN1
	0x4000 6000 - 0x4000 63FF	I2C4
	0x4000 5C00 - 0x4000 5FFF	I2C3
	0x4000 5800 - 0x4000 5BFF	I2C2
	0x4000 5400 - 0x4000 57FF	I2C1
	0x4000 5000 - 0x4000 53FF	UART5
	0x4000 4C00 - 0x4000 4FFF	UART4
	0x4000 4800 - 0x4000 4BFF	USART3
	0x4000 4400 - 0x4000 47FF	USART2
	0x4000 4000 - 0x4000 43FF	SPDIFRX
AFDI	0x4000 3C00 - 0x4000 3FFF	SPI3 / I2S3
	0x4000 3800 - 0x4000 3BFF	SPI2 / I2S2
	0x4000 3400 - 0x4000 37FF	Reserved
	0x4000 3000 - 0x4000 33FF	IWDG
	0x4000 2C00 - 0x4000 2FFF	WWDG
	0x4000 2800 - 0x4000 2BFF	RTC & BKP Registers
	0x4000 2400 - 0x4000 27FF	LPTIM1
	0x4000 2000 - 0x4000 23FF	TIM14
	0x4000 1C00 - 0x4000 1FFF	TIM13
	0x4000 1800 - 0x4000 1BFF	TIM12
	0x4000 1400 - 0x4000 17FF	TIM7
	0x4000 1000 - 0x4000 13FF	TIM6
	0x4000 0C00 - 0x4000 0FFF	TIM5
	0x4000 0800 - 0x4000 0BFF	TIM4
	0x4000 0400 - 0x4000 07FF	TIM3
	0x4000 0000 - 0x4000 03FF	TIM2

# Table 13. STM32F745xx and STM32F746xx register boundary addresses (continued)





Figure 25. Typical V<sub>BAT</sub> current consumption (RTC ON/BKP SRAM OFF and LSE in low drive mode)

Figure 26. Typical V<sub>BAT</sub> current consumption (RTC ON/BKP SRAM OFF and LSE in medium low drive mode)





				-)		
Symbol	Parameter	Conditions	Min <sup>(1)</sup>	Тур	Max <sup>(1)</sup>	Unit
t <sub>ERASE256KB</sub>	Sector (256 KB) erase time	Program/erase parallelism (PSIZE) = x 8	-	2.1	4	
		Program/erase parallelism (PSIZE) = x 16	-	1.5	2.6	s
		Program/erase parallelism (PSIZE) = x 32	-	1	2	
		Program/erase parallelism (PSIZE) = x 8	-	8	16	
t <sub>ME</sub>	Mass erase time	Program/erase parallelism (PSIZE) = x 16	-	5.6	11.2	s
		Program/erase para (PSIZE) = x 32		-	4	8
		32-bit program operation	2.7	-	3	V
V <sub>prog</sub>	Programming voltage	16-bit program operation	2.1	-	3.6	V
		8-bit program operation	1.7	-	3.6	V

Table 48. Flash memory programming (continued)

1. Guaranteed by characterization results.

2. The maximum programming time is measured after 100K erase operations.

Symbol	Parameter	Conditions	Min <sup>(1)</sup>	Тур	Max <sup>(1)</sup>	Unit
t <sub>prog</sub>	Double word programming		-	16	100 <sup>(2)</sup>	μs
t <sub>ERASE32KB</sub>	Sector (32 KB) erase time	T <sub>A</sub> = 0 to +40 °C	-	180	-	
t <sub>ERASE128KB</sub>	Sector (128 KB) erase time	V <sub>DD</sub> = 3.3 V	-	450	-	ms
t <sub>ERASE256KB</sub>	Sector (256 KB) erase time	V <sub>PP</sub> = 8.5 V	-	900	-	
t <sub>ME</sub>	Mass erase time		-	6.9	-	S
V <sub>prog</sub>	Programming voltage	-	2.7	-	3.6	V
V <sub>PP</sub>	V <sub>PP</sub> voltage range	-	7	-	9	V
I <sub>PP</sub>	Minimum current sunk on the $V_{\rm PP}$ pin	-	10	-	-	mA
t <sub>VPP</sub> <sup>(3)</sup>	Cumulative time during which $V_{PP}$ is applied	-	-	-	1	hour

#### Table 49. Flash memory programming with V<sub>PP</sub>

1. Guaranteed by design.

2. The maximum programming time is measured after 100K erase operations.

3.  $V_{PP}$  should only be connected during programming/erasing.



OSPEEDRy [1:0] bit value <sup>(1)</sup>	Symbol	Parameter	Conditions	Min	Тур	Мах	Unit	
	f <sub>max(IO)out</sub>	Maximum frequency <sup>(3)</sup>	$C_L = 30 \text{ pF}, V_{DD} \ge 2.7 \text{ V}$	-	-	100 <sup>(4)</sup>		
			C <sub>L</sub> = 30 pF, V <sub>DD</sub> ≥ 1.8 V	-	-	50		
			C <sub>L</sub> = 30 pF, V <sub>DD</sub> ≥ 1.7 V	-	-	42.5	МН≁	
			C <sub>L</sub> = 10 pF, V <sub>DD</sub> ≥ 2.7 V	-	-	180 <sup>(4)</sup>		
			C <sub>L</sub> = 10 pF, V <sub>DD</sub> ≥ 1.8 V	-	-	100		
11			C <sub>L</sub> = 10 pF, V <sub>DD</sub> ≥ 1.7 V	-	-	72.5		
11			C <sub>L</sub> = 30 pF, V <sub>DD</sub> ≥ 2.7 V	-	-	4		
			C <sub>L</sub> = 30 pF, V <sub>DD</sub> ≥1.8 V	-	-	6		
	t <sub>f(IO)out</sub> /	Output high to low level fall	C <sub>L</sub> = 30 pF, V <sub>DD</sub> ≥1.7 V	-	-	7		
	t <sub>r(IO)out</sub>	level rise time	C <sub>L</sub> = 10 pF, V <sub>DD</sub> ≥ 2.7 V	-	-	2.5	115	
			C <sub>L</sub> = 10 pF, V <sub>DD</sub> ≥1.8 V	-	-	3.5		
			C <sub>L</sub> = 10 pF, V <sub>DD</sub> ≥1.7 V	-	-	4		
-	tEXTIpw	Pulse width of external signals detected by the EXTI controller	-	10	-	-	ns	

Table 58. I/O AC characteristics <sup>(1)(2)</sup> (	(continued)
--	-------------

1. Guaranteed by design.

2. The I/O speed is configured using the OSPEEDRy[1:0] bits. Refer to the STM32F75xxx and STM32F74xxx reference manual for a description of the GPIOx\_SPEEDR GPIO port output speed register.

3. The maximum frequency is defined in *Figure 39*.

4. For maximum frequencies above 50 MHz and  $V_{DD}$  > 2.4 V, the compensation cell should be used.



#### Figure 39. I/O AC characteristics definition



Symbol	Parameter	Conditions	Min	Тур	Max	Unit
I <sub>VREF+</sub> <sup>(2)</sup>	ADC V <sub>REF</sub> DC current consumption in conversion mode	-	-	300	500	μA
I <sub>VDDA</sub> <sup>(2)</sup>	ADC V <sub>DDA</sub> DC current consumption in conversion mode	-	-	1.6	1.8	mA

Table 62. ADC characteristics (continued)

1. V<sub>DDA</sub> minimum value of 1.7 V is obtained with the use of an external power supply supervisor (refer to Section 2.17.2: Internal reset OFF).

2. Guaranteed by characterization results.

3.  $V_{\mathsf{REF}^+}$  is internally connected to  $V_{\mathsf{DDA}}$  and  $V_{\mathsf{REF}^-}$  is internally connected to  $V_{\mathsf{SSA}}.$ 

4.  $R_{ADC}$  maximum value is given for V<sub>DD</sub>=1.7 V, and minimum value for V<sub>DD</sub>=3.3 V.

5. For external triggers, a delay of 1/f<sub>PCLK2</sub> must be added to the latency specified in Table 62.

#### Equation 1: R<sub>AIN</sub> max formula

$$\mathsf{R}_{\mathsf{AIN}} = \frac{(k-0.5)}{\mathsf{f}_{\mathsf{ADC}} \times \mathsf{C}_{\mathsf{ADC}} \times \mathsf{ln}(2^{\mathsf{N}+2})} - \mathsf{R}_{\mathsf{ADC}}$$

The formula above (*Equation 1*) is used to determine the maximum external impedance allowed for an error below 1/4 of LSB. N = 12 (from 12-bit resolution) and k is the number of sampling periods defined in the ADC\_SMPR1 register.

Symbol	Parameter	Test conditions	Тур	Max <sup>(1)</sup>	Unit
ET	Total unadjusted error	(	±3	±4	
EO	Offset error	$f_{ADC} = 18 \text{ MHz}$ V_D_A = 1.7 to 3.6 V	±2	±3	
EG	Gain error	V <sub>REF</sub> = 1.7 to 3.6 V	±1	±3	LSB
ED	Differential linearity error	V <sub>DDA</sub> –V <sub>REF</sub> < 1.2 V	±1	±2	
EL	Integral linearity error		±2	±3	

Table 63. ADC static accuracy at f<sub>ADC</sub> = 18 MHz

1. Guaranteed by characterization results.

Table 64. ADC static accuracy	/ at f <sub>ADC</sub> = 30 MHz
-------------------------------	--------------------------------

Symbol	Parameter	Test conditions	Тур	Max <sup>(1)</sup>	Unit
ET	Total unadjusted error		±2	±5	
EO	Offset error	f <sub>ADC</sub> = 30 MHz, R <sub>AIN</sub> < 10 kΩ	±1.5	±2.5	
EG	Gain error	$V_{DDA} = 2.4 \text{ to } 3.6 \text{ V},$	±1.5	±4	LSB
ED	Differential linearity error	$V_{REF} = 1.7$ to 3.6 V, $V_{DDA} - V_{REF} < 1.2$ V	±1	±2	
EL	Integral linearity error		±1.5	±3	

1. Guaranteed by characterization results.



## 5.3.22 Temperature sensor characteristics

Table 68. 7	Temperature se	ensor characteristics	,
-------------	----------------	-----------------------	---

Symbol	Parameter	Min	Тур	Max	Unit
T <sub>L</sub> <sup>(1)</sup>	V <sub>SENSE</sub> linearity with temperature	-	±1	±2	°C
Avg_Slope <sup>(1)</sup>	Average slope	-	2.5	-	mV/°C
V <sub>25</sub> <sup>(1)</sup>	Voltage at 25 °C	-	0.76	-	V
t <sub>START</sub> <sup>(2)</sup>	Startup time	-	6	10	μs
T <sub>S_temp</sub> <sup>(2)</sup>	ADC sampling time when reading the temperature (1 $^\circ\text{C}$ accuracy)	10	-	-	μs

1. Guaranteed by characterization results.

2. Guaranteed by design.

	Table 69. Temperature sensor calibration value	es
Symbol	Parameter	Memory address
TS_CAL1	TS ADC raw data acquired at temperature of 30 °C, $V_{DDA}$ = 3.3 V	0x1FF0 F44C - 0x1FF0 F44D
TS_CAL2	TS ADC raw data acquired at temperature of 110 °C, $V_{DDA}$ = 3.3 V	0x1FF0 F44E - 0x1FF0 F44F

# 5.3.23 V<sub>BAT</sub> monitoring characteristics

#### Table 70. V<sub>BAT</sub> monitoring characteristics

Symbol	Parameter	Min	Тур	Мах	Unit
R	Resistor bridge for V <sub>BAT</sub>	-	50	-	KΩ
Q	Ratio on V <sub>BAT</sub> measurement	-	4	-	-
Er <sup>(1)</sup>	Error on Q	-1	-	+1	%
T <sub>S_vbat</sub> <sup>(2)(2)</sup>	ADC sampling time when reading the V <sub>BAT</sub> 1 mV accuracy	5	-	-	μs

1. Guaranteed by design.

2. Shortest sampling time can be determined in the application by multiple iterations.

### 5.3.24 Reference voltage

The parameters given in *Table 71* are derived from tests performed under ambient temperature and  $V_{DD}$  supply voltage conditions summarized in *Table 17*.

Table 71. internal reference voltag	qe
-------------------------------------	----

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
V <sub>REFINT</sub>	Internal reference voltage	–40 °C < T <sub>A</sub> < +105 °C	1.18	1.21	1.24	V
T <sub>S_vrefint</sub> <sup>(1)</sup>	ADC sampling time when reading the internal reference voltage	-	10	-	-	μs
V <sub>RERINT_s</sub> <sup>(2)</sup>	Internal reference voltage spread over the temperature range	$V_{DD}$ = 3V $\pm$ 10mV	-	3	5	mV



DocID027590 Rev 4

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
tsu(MI)	Data input actus time	Master mode	5.5	-	-	
tsu(SI)		Slave mode	4	-	-	
th(MI)	Data input hold time	Master mode	4	-	-	
th(SI)		Slave mode	2	-	-	
ta(SO)	Data output access time	Slave mode	7	-	21	
tdis(SO)	Data output disable time	Slave mode	5	-	12	ns
tu(SO)		Slave mode 2.7≤VDD≤3.6V	-	6.5	10	110
10(30)	Data output valid time	Slave mode 1.71≤VDD≤3.6V	-	6.5	13	
tv(MO)		Master mode	-	2	4	
th(SO)	Data output hold time	Slave mode 1.71≤VDD≤3.6V	5.5	-	-	
th(MO)		Master mode	0	-	-	

Table 76. SPI dynamic characteristics<sup>(1)</sup> (continued)

1. Guaranteed by characterization results.

2. Excepting SPI1 with SCK IO pin mapped on PA5. In this configuration, Maximum achievable frequency is 40MHz.

 Maximum Frequency of Slave Transmitter is determined by sum of Tv(SO) and Tsu(MI) intervals which has to fit into SCK level phase preceding the SCK sampling edge. This value can be achieved when it communicates with a Master having Tsu(MI)=0 while signal Duty(SCK)=50%.



Figure 46. SPI timing diagram - slave mode and CPHA = 0



Symbol	Parameter	Min	Мах	Unit
t <sub>w(NE)</sub>	FMC_NE low time	2T <sub>HCLK</sub> - 0.5	2 T <sub>HCLK</sub> +1.5	
t <sub>v(NOE_NE)</sub>	FMC_NEx low to FMC_NOE low	0	1	
t <sub>w(NOE)</sub>	FMC_NOE low time	2T <sub>HCLK</sub> – 1	2T <sub>HCLK</sub> + 1	
t <sub>h(NE_NOE)</sub>	FMC_NOE high to FMC_NE high hold time	0	-	
t <sub>v(A_NE)</sub>	FMC_NEx low to FMC_A valid	-	0.5	
t <sub>h(A_NOE)</sub>	Address hold time after FMC_NOE high	0	-	
$t_{v(BL_NE)}$	FMC_NEx low to FMC_BL valid	-	0.5	ne
t <sub>h(BL_NOE)</sub>	FMC_BL hold time after FMC_NOE high	0	-	115
t <sub>su(Data_NE)</sub>	Data to FMC_NEx high setup time	T <sub>HCLK</sub> - 2	-	
t <sub>su(Data_NOE)</sub>	Data to FMC_NOEx high setup time	T <sub>HCLK</sub> -2	-	
t <sub>h(Data_NOE)</sub>	Data hold time after FMC_NOE high	0	-	
t <sub>h(Data_NE)</sub>	Data hold time after FMC_NEx high	0	-	
t <sub>v(NADV_NE)</sub>	FMC_NEx low to FMC_NADV low	-	0	
t <sub>w(NADV)</sub>	FMC_NADV low time	-	T <sub>HCLK</sub> +1	

 Table 88. Asynchronous non-multiplexed SRAM/PSRAM/NOR read timings<sup>(1)</sup>

1. C<sub>L</sub> = 30 pF.

lable 89. Asynchronous non-multiplexed SRAM/PSRAM/NOR read - NWALL timings'	Table 89. As	ynchronous	non-multiplexe	d SRAM/PSRAM/N	IOR read -	NWAIT	timings <sup>(</sup>
---	--------------	------------	----------------	----------------	------------	-------	----------------------

Symbol	Parameter	Min	Max	Unit
t <sub>w(NE)</sub>	FMC_NE low time	7T <sub>HCLK</sub> –1	7T <sub>HCLK</sub>	
t <sub>w(NOE)</sub>	FMC_NWE low time	5T <sub>HCLK</sub> −1	5T <sub>HCLK</sub> +1	ns
t <sub>w(NWAIT)</sub>	FMC_NWAIT low time	T <sub>HCLK</sub> -0.5		110
t <sub>su(NWAIT_NE)</sub>	FMC_NWAIT valid before FMC_NEx high	5T <sub>HCLK</sub> +1.5	-	
t <sub>h(NE_NWAIT)</sub>	FMC_NEx hold time after FMC_NWAIT invalid	4T <sub>HCLK</sub> +1	-	

1. Guaranteed by characterization results.





#### Figure 69. NAND controller waveforms for common memory write access

Table 100. Switching characteristics for NAND Flash read cycles<sup>(1)</sup>

Symbol	Parameter	Min	Max	Unit
t <sub>w(N0E)</sub>	FMC_NOE low width	4T <sub>HCLK</sub> -0.5	4T <sub>HCLK</sub>	
t <sub>su(D-NOE)</sub>	FMC_D[15-0] valid data before FMC_NOE high	13	-	
t <sub>h(NOE-D)</sub>	FMC_D[15-0] valid data after FMC_NOE high	3	-	ns
t <sub>d(ALE-NOE)</sub>	FMC_ALE valid before FMC_NOE low	-	3T <sub>HCLK</sub> -0.5	
t <sub>h(NOE-ALE)</sub>	FMC_NWE high to FMC_ALE invalid	3T <sub>HCLK</sub> -2	-	

1. Guaranteed by characterization results.

Table 101. Switching characteristics for NAND Flash write cycl	es <sup>(1)</sup>
--	-------------------

Symbol	Parameter	Min	Max	Unit
t <sub>w(NWE)</sub>	FMC_NWE low width	4T <sub>HCLK</sub> -0.5	4T <sub>HCLK</sub>	
t <sub>v(NWE-D)</sub>	FMC_NWE low to FMC_D[15-0] valid	0	-	
t <sub>h(NWE-D)</sub>	FMC_NWE high to FMC_D[15-0] invalid	3T <sub>HCLK</sub> −1	-	ne
t <sub>d(D-NWE)</sub>	FMC_D[15-0] valid before FMC_NWE high	5T <sub>HCLK</sub> -3	-	115
t <sub>d(ALE-NWE)</sub>	FMC_ALE valid before FMC_NWE low	-	3T <sub>HCLK</sub> -0.5	
t <sub>h(NWE-ALE)</sub>	FMC_NWE high to FMC_ALE invalid	3T <sub>HCLK</sub> -2	-	

1. Guaranteed by characterization results.



uata						
Symbol	millimeters			inches <sup>(1)</sup>		
	Min	Тур	Мах	Min	Тур	Мах
А	-	-	1.600	-	-	0.0630
A1	0.050	-	0.150	0.0020	-	0.0059
A2	1.350	1.400	1.450	0.0531	0.0551	0.0571
b	0.170	0.220	0.270	0.0067	0.0087	0.0106
С	0.090	-	0.200	0.0035	-	0.0079
D	15.800	16.000	16.200	0.6220	0.6299	0.6378
D1	13.800	14.000	14.200	0.5433	0.5512	0.5591
D3	-	12.000	-	-	0.4724	-
Е	15.800	16.000	16.200	0.6220	0.6299	0.6378
E1	13.800	14.000	14.200	0.5433	0.5512	0.5591
E3	-	12.000	-	-	0.4724	-
е	-	0.500	-	-	0.0197	-
L	0.450	0.600	0.750	0.0177	0.0236	0.0295
L1	-	1.000	-	-	0.0394	-
k	0°	3.5°	7°	0°	3.5°	7°
CCC	-	-	0.080	-	-	0.0031
	I	l		l		

Table 112. LQPF100,	14 x 14 mm	100-pin low-profile	quad flat package	mechanical
		data		

1. Values in inches are converted from mm and rounded to 4 decimal digits.



				` 	,		
Symbol	millimeters			inches <sup>(1)</sup>			
	Min	Тур	Мах	Min	Тур	Мах	
D	7.850	8.000	8.150	0.3091	0.3150	0.3209	
D1	-	7.200		-	0.2835	-	
E	7.850	8.000	8.150	0.3091	0.3150	0.3209	
E1	-	7.200	-	-	0.2835	-	
е	-	0.800	-	-	0.0315	-	
F	-	0.400	-	-	0.0157	-	
G	-	0.400	-	-	0.0157	-	
ddd	-	-	0.100	-	-	0.0039	
eee	-	-	0.150	-	-	0.0059	
fff	-	-	0.080	-	-	0.0031	

# Table 113. TFBGA100, 8 x 8 × 0.8 mm thin fine-pitch ball grid arraypackage mechanical data (continued)

1. Values in inches are converted from mm and rounded to 4 decimal digits.





1. Dimensions are expressed in millimeters.



Symbol	millimeters			inches <sup>(1)</sup>			
	Min	Тур	Max	Min	Тур	Max	
A2	-	0.380	-	-	0.0150	-	
A3 <sup>(2)</sup>	-	0.025	-	-	0.0010	-	
b <sup>(3)</sup>	0.220	0.250	0.280	0.0087	0.0098	0.0110	
D	4.504	4.539	4.574	0.1773	0.1787	0.1801	
E	5.814	5.849	5.884	0.2289	0.2303	0.2317	
е	-	0.400	-	-	0.0157	-	
e1	-	4.000	-	-	0.1575	-	
e2	-	4.800	-	-	0.1890	-	
F	-	0.2695	-	-	0.0106	-	
G	-	0.5245	-	-	0.0206	-	
ааа	-	-	0.100	-	-	0.0039	
bbb	-	-	0.100	-	-	0.0039	
CCC	-	-	0.100	-	-	0.0039	
ddd	-	-	0.050	-	-	0.0020	
eee	-	-	0.050	-	-	0.0020	

# Table 115. WLCSP143, 4.539x 5.849 mm, 0.4 mm pitch wafer level chip scalepackage mechanical data (continued)

1. Values in inches are converted from mm and rounded to 4 decimal digits.

2. Back side coating.

3. Dimension is measured at the maximum bump diameter parallel to primary datum Z.

# Figure 86. WLCSP143, 4.539x 5.849 mm, 0.4 mm pitch wafer level chip scale package recommended footprint



