



Welcome to [E-XFL.COM](https://www.e-xfl.com)

### Understanding [Embedded - FPGAs \(Field Programmable Gate Array\)](#)

Embedded - FPGAs, or Field Programmable Gate Arrays, are advanced integrated circuits that offer unparalleled flexibility and performance for digital systems. Unlike traditional fixed-function logic devices, FPGAs can be programmed and reprogrammed to execute a wide array of logical operations, enabling customized functionality tailored to specific applications. This reprogrammability allows developers to iterate designs quickly and implement complex functions without the need for custom hardware.

### Applications of Embedded - FPGAs

The versatility of Embedded - FPGAs makes them indispensable in numerous fields. In telecommunications.

#### Details



|                                |   |
|--------------------------------|---|
| Product Status                 | Obsolete  |
| Number of LABs/CLBs            | 359200  |
| Number of Logic Elements/Cells | 952000  |
| Total RAM Bits                 | 53248000  |
| Number of I/O                  | 840   |
| Number of Gates                | -   |
| Voltage - Supply               | 0.87V ~ 0.93V   |
| Mounting Type                  | Surface Mount   |
| Operating Temperature          | -40°C ~ 100°C (TJ)  |
| Package / Case                 | 1932-BBGA, FCBGA  |
| Supplier Device Package        | 1932-FBGA, FC (45x45)   |
| Purchase URL                   | <a href="https://www.e-xfl.com/product-detail/intel/5sgxmabn1f45i2n">https://www.e-xfl.com/product-detail/intel/5sgxmabn1f45i2n</a> |

## Recommended Operating Conditions

This section lists the functional operating limits for the AC and DC parameters for Stratix V devices. Table 6 lists the steady-state voltage and current values expected from Stratix V devices. Power supply ramps must all be strictly monotonic, without plateaus.

**Table 6. Recommended Operating Conditions for Stratix V Devices (Part 1 of 2)**

| Symbol                            | Description   | Condition  | Min <sup>(4)</sup> | Typ  | Max <sup>(4)</sup> | Unit |
|-----------------------------------|---|------------|--------------------|------|--------------------|------|
| V <sub>CC</sub>                   | Core voltage and periphery circuitry power supply (C1, C2, I2, and I3YY speed grades)                             | —          | 0.87               | 0.9  | 0.93               | V    |
|                                   | Core voltage and periphery circuitry power supply (C2L, C3, C4, I2L, I3, I3L, and I4 speed grades) <sup>(3)</sup> | —          | 0.82               | 0.85 | 0.88               | V    |
| V <sub>CCPT</sub>                 | Power supply for programmable power technology  | —          | 1.45               | 1.50 | 1.55               | V    |
| V <sub>CC_AUX</sub>               | Auxiliary supply for the programmable power technology  | —          | 2.375              | 2.5  | 2.625              | V    |
| V <sub>CCPD</sub> <sup>(1)</sup>  | I/O pre-driver (3.0 V) power supply   | —          | 2.85               | 3.0  | 3.15               | V    |
|                                   | I/O pre-driver (2.5 V) power supply   | —          | 2.375              | 2.5  | 2.625              | V    |
| V <sub>CCIO</sub>                 | I/O buffers (3.0 V) power supply  | —          | 2.85               | 3.0  | 3.15               | V    |
|                                   | I/O buffers (2.5 V) power supply  | —          | 2.375              | 2.5  | 2.625              | V    |
|                                   | I/O buffers (1.8 V) power supply  | —          | 1.71               | 1.8  | 1.89               | V    |
|                                   | I/O buffers (1.5 V) power supply  | —          | 1.425              | 1.5  | 1.575              | V    |
|                                   | I/O buffers (1.35 V) power supply   | —          | 1.283              | 1.35 | 1.45               | V    |
|                                   | I/O buffers (1.25 V) power supply   | —          | 1.19               | 1.25 | 1.31               | V    |
|                                   | I/O buffers (1.2 V) power supply  | —          | 1.14               | 1.2  | 1.26               | V    |
| V <sub>CCPGM</sub>                | Configuration pins (3.0 V) power supply   | —          | 2.85               | 3.0  | 3.15               | V    |
|                                   | Configuration pins (2.5 V) power supply   | —          | 2.375              | 2.5  | 2.625              | V    |
|                                   | Configuration pins (1.8 V) power supply   | —          | 1.71               | 1.8  | 1.89               | V    |
| V <sub>CCA_FPLL</sub>             | PLL analog voltage regulator power supply   | —          | 2.375              | 2.5  | 2.625              | V    |
| V <sub>CCD_FPLL</sub>             | PLL digital voltage regulator power supply  | —          | 1.45               | 1.5  | 1.55               | V    |
| V <sub>CCBAT</sub> <sup>(2)</sup> | Battery back-up power supply (For design security volatile key register)  | —          | 1.2                | —    | 3.0                | V    |
| V <sub>I</sub>                    | DC input voltage  | —          | −0.5               | —    | 3.6                | V    |
| V <sub>O</sub>                    | Output voltage  | —          | 0                  | —    | V <sub>CCIO</sub>  | V    |
| T <sub>J</sub>                    | Operating junction temperature  | Commercial | 0                  | —    | 85                 | °C   |
|                                   |   | Industrial | −40                | —    | 100                | °C   |

-  You typically use the interactive Excel-based Early Power Estimator before designing the FPGA to get a magnitude estimate of the device power. The Quartus II PowerPlay Power Analyzer provides better quality estimates based on the specifics of the design after you complete place-and-route. The PowerPlay Power Analyzer can apply a combination of user-entered, simulation-derived, and estimated signal activities that, when combined with detailed circuit models, yields very accurate power estimates.
-  For more information about power estimation tools, refer to the *PowerPlay Early Power Estimator User Guide* and the *PowerPlay Power Analysis* chapter in the *Quartus II Handbook*.

**Table 23. Transceiver Specifications for Stratix V GX and GS Devices <sup>(1)</sup> (Part 5 of 7)**

| Symbol/<br>Description  | Conditions   | Transceiver Speed<br>Grade 1 |                     |       | Transceiver Speed<br>Grade 2 |                     |       | Transceiver Speed<br>Grade 3 |                     |                                     | Unit     |
|---|--|------------------------------|---------------------|-------|------------------------------|---------------------|-------|------------------------------|---------------------|-------------------------------------|----------|
|   |  | Min                          | Typ                 | Max   | Min                          | Typ                 | Max   | Min                          | Typ                 | Max                                 |          |
| Programmable<br>DC gain   | DC Gain<br>Setting = 0                                     | —                            | 0                   | —     | —                            | 0                   | —     | —                            | 0                   | —                                   | dB       |
|   | DC Gain<br>Setting = 1                                     | —                            | 2                   | —     | —                            | 2                   | —     | —                            | 2                   | —                                   | dB       |
|   | DC Gain<br>Setting = 2                                     | —                            | 4                   | —     | —                            | 4                   | —     | —                            | 4                   | —                                   | dB       |
|   | DC Gain<br>Setting = 3                                     | —                            | 6                   | —     | —                            | 6                   | —     | —                            | 6                   | —                                   | dB       |
|   | DC Gain<br>Setting = 4                                     | —                            | 8                   | —     | —                            | 8                   | —     | —                            | 8                   | —                                   | dB       |
| <b>Transmitter</b>  |  |                              |                     |       |                              |                     |       |                              |                     |                                     |          |
| Supported I/O<br>Standards  | —  | 1.4-V and 1.5-V PCML         |                     |       |                              |                     |       |                              |                     |                                     |          |
| Data rate<br>(Standard PCS)   | —  | 600                          | —                   | 12200 | 600                          | —                   | 12200 | 600                          | —                   | 8500/<br>10312.5<br><sup>(24)</sup> | Mbps     |
| Data rate<br>(10G PCS)  | —  | 600                          | —                   | 14100 | 600                          | —                   | 12500 | 600                          | —                   | 8500/<br>10312.5<br><sup>(24)</sup> | Mbps     |
| Differential on-<br>chip termination<br>resistors                     | 85- $\Omega$<br>setting                                    | —                            | 85 $\pm$<br>20%     | —     | —                            | 85 $\pm$<br>20%     | —     | —                            | 85 $\pm$<br>20%     | —                                   | $\Omega$ |
|   | 100- $\Omega$<br>setting                                   | —                            | 100<br>$\pm$<br>20% | —     | —                            | 100<br>$\pm$<br>20% | —     | —                            | 100<br>$\pm$<br>20% | —                                   | $\Omega$ |
|   | 120- $\Omega$<br>setting                                   | —                            | 120<br>$\pm$<br>20% | —     | —                            | 120<br>$\pm$<br>20% | —     | —                            | 120<br>$\pm$<br>20% | —                                   | $\Omega$ |
|   | 150- $\Omega$<br>setting                                   | —                            | 150<br>$\pm$<br>20% | —     | —                            | 150<br>$\pm$<br>20% | —     | —                            | 150<br>$\pm$<br>20% | —                                   | $\Omega$ |
| V <sub>OCM</sub> (AC<br>coupled)                                      | 0.65-V<br>setting  | —                            | 650                 | —     | —                            | 650                 | —     | —                            | 650                 | —                                   | mV       |
| V <sub>OCM</sub> (DC<br>coupled)                                      | —  | —                            | 650                 | —     | —                            | 650                 | —     | —                            | 650                 | —                                   | mV       |
| Rise time <sup>(7)</sup>  | 20% to 80%   | 30                           | —                   | 160   | 30                           | —                   | 160   | 30                           | —                   | 160                                 | ps       |
| Fall time <sup>(7)</sup>  | 80% to 20%   | 30                           | —                   | 160   | 30                           | —                   | 160   | 30                           | —                   | 160                                 | ps       |
| Intra-differential<br>pair skew                                       | Tx V <sub>CM</sub> =<br>0.5 V and<br>slew rate of<br>15 ps | —                            | —                   | 15    | —                            | —                   | 15    | —                            | —                   | 15                                  | ps       |
| Intra-transceiver<br>block transmitter<br>channel-to-<br>channel skew | x6 PMA<br>bonded mode                                      | —                            | —                   | 120   | —                            | —                   | 120   | —                            | —                   | 120                                 | ps       |

**Table 23. Transceiver Specifications for Stratix V GX and GS Devices <sup>(1)</sup> (Part 6 of 7)**

| Symbol/<br>Description  | Conditions                                   | Transceiver Speed<br>Grade 1 |     |                               | Transceiver Speed<br>Grade 2 |     |                               | Transceiver Speed<br>Grade 3 |     |                                     | Unit |
|---|--|------------------------------|-----|-------------------------------|------------------------------|-----|-------------------------------|------------------------------|-----|-------------------------------------|------|
|   |  | Min                          | Typ | Max                           | Min                          | Typ | Max                           | Min                          | Typ | Max                                 |      |
| Inter-transceiver<br>block transmitter<br>channel-to-<br>channel skew | xN PMA<br>bonded mode                        | —                            | —   | 500                           | —                            | —   | 500                           | —                            | —   | 500                                 | ps   |
| <b>CMU PLL</b>  |  |                              |     |                               |                              |     |                               |                              |     |                                     |      |
| Supported Data<br>Range   | —  | 600                          | —   | 12500                         | 600                          | —   | 12500                         | 600                          | —   | 8500/<br>10312.5<br><sup>(24)</sup> | Mbps |
| t <sub>pll_powerdown</sub> <sup>(15)</sup>                            | —  | 1                            | —   | —                             | 1                            | —   | —                             | 1                            | —   | —                                   | μs   |
| t <sub>pll_lock</sub> <sup>(16)</sup>                                 | —  | —                            | —   | 10                            | —                            | —   | 10                            | —                            | —   | 10                                  | μs   |
| <b>ATX PLL</b>  |  |                              |     |                               |                              |     |                               |                              |     |                                     |      |
| Supported Data<br>Rate Range  | VCO<br>post-divider<br>L=2                   | 8000                         | —   | 14100                         | 8000                         | —   | 12500                         | 8000                         | —   | 8500/<br>10312.5<br><sup>(24)</sup> | Mbps |
|   | L=4  | 4000                         | —   | 7050                          | 4000                         | —   | 6600                          | 4000                         | —   | 6600                                | Mbps |
|   | L=8  | 2000                         | —   | 3525                          | 2000                         | —   | 3300                          | 2000                         | —   | 3300                                | Mbps |
|   | L=8,<br>Local/Central<br>Clock Divider<br>=2 | 1000                         | —   | 1762.5                        | 1000                         | —   | 1762.5                        | 1000                         | —   | 1762.5                              | Mbps |
| t <sub>pll_powerdown</sub> <sup>(15)</sup>                            | —  | 1                            | —   | —                             | 1                            | —   | —                             | 1                            | —   | —                                   | μs   |
| t <sub>pll_lock</sub> <sup>(16)</sup>                                 | —  | —                            | —   | 10                            | —                            | —   | 10                            | —                            | —   | 10                                  | μs   |
| <b>fPLL</b>   |  |                              |     |                               |                              |     |                               |                              |     |                                     |      |
| Supported Data<br>Range   | —  | 600                          | —   | 3250/<br>3125 <sup>(25)</sup> | 600                          | —   | 3250/<br>3125 <sup>(25)</sup> | 600                          | —   | 3250/<br>3125 <sup>(25)</sup>       | Mbps |
| t <sub>pll_powerdown</sub> <sup>(15)</sup>                            | —  | 1                            | —   | —                             | 1                            | —   | —                             | 1                            | —   | —                                   | μs   |

**Table 23. Transceiver Specifications for Stratix V GX and GS Devices <sup>(1)</sup> (Part 7 of 7)**

| Symbol/<br>Description | Conditions | Transceiver Speed<br>Grade 1 |     |     | Transceiver Speed<br>Grade 2 |     |     | Transceiver Speed<br>Grade 3 |     |     | Unit |
|------------------------|------------|------------------------------|-----|-----|------------------------------|-----|-----|------------------------------|-----|-----|------|
|                        |            | Min                          | Typ | Max | Min                          | Typ | Max | Min                          | Typ | Max |      |
| $t_{pll\_lock}^{(16)}$ | —          | —                            | —   | 10  | —                            | —   | 10  | —                            | —   | 10  | μs   |

**Notes to Table 23:**

- (1) Speed grades shown in Table 23 refer to the PMA Speed Grade in the device ordering code. The maximum data rate could be restricted by the Core/PCS speed grade. Contact your Altera Sales Representative for the maximum data rate specifications in each speed grade combination offered. For more information about device ordering codes, refer to the *Stratix V Device Overview*.
- (2) The reference clock common mode voltage is equal to the  $V_{CCR\_GXB}$  power supply level.
- (3) This supply must be connected to 1.0 V if the transceiver is configured at a data rate > 6.5 Gbps, and to 1.05 V if configured at a data rate > 10.3 Gbps when DFE is used. For data rates up to 6.5 Gbps, you can connect this supply to 0.85 V.
- (4) This supply follows  $V_{CCR\_GXB}$ .
- (5) The device cannot tolerate prolonged operation at this absolute maximum.
- (6) The differential eye opening specification at the receiver input pins assumes that **Receiver Equalization** is disabled. If you enable **Receiver Equalization**, the receiver circuitry can tolerate a lower minimum eye opening, depending on the equalization level.
- (7) The Quartus II software automatically selects the appropriate slew rate depending on the configured data rate or functional mode.
- (8) The input reference clock frequency options depend on the data rate and the device speed grade.
- (9) The line data rate may be limited by PCS-FPGA interface speed grade.
- (10) Refer to Figure 1 for the GX channel AC gain curves. The total effective AC gain is the AC gain minus the DC gain.
- (11)  $t_{LTR}$  is the time required for the receive CDR to lock to the input reference clock frequency after coming out of reset.
- (12)  $t_{LTD}$  is time required for the receiver CDR to start recovering valid data after the rx\_is\_lockedtodata signal goes high.
- (13)  $t_{LTD\_manual}$  is the time required for the receiver CDR to start recovering valid data after the rx\_is\_lockedtodata signal goes high when the CDR is functioning in the manual mode.
- (14)  $t_{LTR\_LTD\_manual}$  is the time the receiver CDR must be kept in lock to reference (LTR) mode after the rx\_is\_lockedtoref signal goes high when the CDR is functioning in the manual mode.
- (15)  $t_{pll\_powerdown}$  is the PLL powerdown minimum pulse width.
- (16)  $t_{pll\_lock}$  is the time required for the transmitter CMU/ATX PLL to lock to the input reference clock frequency after coming out of reset.
- (17) To calculate the REFCLK rms phase jitter requirement for PCIe at reference clock frequencies other than 100 MHz, use the following formula: REFCLK rms phase jitter at f(MHz) = REFCLK rms phase jitter at 100 MHz  $\times$  100/f.
- (18) The maximum peak to peak differential input voltage  $V_{ID}$  after device configuration is equal to  $4 \times (\text{absolute } V_{MAX} \text{ for receiver pin} - V_{ICM})$ .
- (19) For ES devices,  $R_{REF}$  is  $2000 \Omega \pm 1\%$ .
- (20) To calculate the REFCLK phase noise requirement at frequencies other than 622 MHz, use the following formula: REFCLK phase noise at f(MHz) = REFCLK phase noise at 622 MHz +  $20 \times \log(f/622)$ .
- (21) SFP/+ optical modules require the host interface to have RD+/- differentially terminated with  $100 \Omega$ . The internal OCT feature is available after the Stratix V FPGA configuration is completed. Altera recommends that FPGA configuration is completed before inserting the optical module. Otherwise, minimize unnecessary removal and insertion with unconfigured devices.
- (22) Refer to Figure 2.
- (23) For oversampling designs to support data rates less than the minimum specification, the CDR needs to be in LTR mode only.
- (24) I3YY devices can achieve data rates up to 10.3125 Gbps.
- (25) When you use fPLL as a TXPLL of the transceiver.
- (26) REFCLK performance requires to meet transmitter REFCLK phase noise specification.
- (27) Minimum eye opening of 85 mV is only for the unstressed input eye condition.

**Table 28. Transceiver Specifications for Stratix V GT Devices (Part 1 of 5) <sup>(1)</sup>**

| Symbol/<br>Description   | Conditions   | Transceiver<br>Speed Grade 2   |           |      | Transceiver<br>Speed Grade 3 |           |      | Unit |
|--|--|--|-----------|------|------------------------------|-----------|------|------|
|  |  | Min  | Typ       | Max  | Min                          | Typ       | Max  |      |
| Reference Clock  |  |  |           |      |                              |           |      |      |
| Supported I/O<br>Standards                                     | Dedicated<br>reference<br>clock pin                    | 1.2-V PCML, 1.4-V PCML, 1.5-V PCML, 2.5-V PCML, Differential LVPECL, LVDS,<br>and HCSL |           |      |                              |           |      |      |
|  | RX reference<br>clock pin                              | 1.4-V PCML, 1.5-V PCML, 2.5-V PCML, LVPECL, and LVDS                                   |           |      |                              |           |      |      |
| Input Reference Clock<br>Frequency (CMU<br>PLL) <sup>(6)</sup> | —  | 40   | —         | 710  | 40                           | —         | 710  | MHz  |
| Input Reference Clock<br>Frequency (ATX PLL) <sup>(6)</sup>    | —  | 100  | —         | 710  | 100                          | —         | 710  | MHz  |
| Rise time  | 20% to 80%   | —  | —         | 400  | —                            | —         | 400  | ps   |
| Fall time  | 80% to 20%   | —  | —         | 400  | —                            | —         | 400  |      |
| Duty cycle   | —  | 45   | —         | 55   | 45                           | —         | 55   | %    |
| Spread-spectrum<br>modulating clock<br>frequency               | PCI Express<br>(PCIe)                                  | 30   | —         | 33   | 30                           | —         | 33   | kHz  |
| Spread-spectrum<br>downspread                                  | PCIe   | —  | 0 to −0.5 | —    | —                            | 0 to −0.5 | —    | %    |
| On-chip termination<br>resistors <sup>(19)</sup>               | —  | —  | 100       | —    | —                            | 100       | —    | Ω    |
| Absolute V <sub>MAX</sub> <sup>(3)</sup>                       | Dedicated<br>reference<br>clock pin                    | —  | —         | 1.6  | —                            | —         | 1.6  | V    |
|  | RX reference<br>clock pin                              | —  | —         | 1.2  | —                            | —         | 1.2  |      |
| Absolute V <sub>MIN</sub>                                      | —  | -0.4   | —         | —    | -0.4                         | —         | —    | V    |
| Peak-to-peak<br>differential input<br>voltage                  | —  | 200  | —         | 1600 | 200                          | —         | 1600 | mV   |
| V <sub>ICM</sub> (AC coupled)                                  | Dedicated<br>reference<br>clock pin                    | 1050/1000 <sup>(2)</sup>   |           |      | 1050/1000 <sup>(2)</sup>     |           |      | mV   |
|  | RX reference<br>clock pin                              | 1.0/0.9/0.85 <sup>(22)</sup>   |           |      | 1.0/0.9/0.85 <sup>(22)</sup> |           |      | V    |
| V <sub>ICM</sub> (DC coupled)                                  | HCSL I/O<br>standard for<br>PCIe<br>reference<br>clock | 250  | —         | 550  | 250                          | —         | 550  | mV   |

**Table 28. Transceiver Specifications for Stratix V GT Devices (Part 2 of 5) <sup>(1)</sup>**

| Symbol/<br>Description  | Conditions  | Transceiver<br>Speed Grade 2                         |               |        | Transceiver<br>Speed Grade 3 |               |        | Unit     |
|---|---|--|---------------|--------|------------------------------|---------------|--------|----------|
|   |   | Min  | Typ           | Max    | Min                          | Typ           | Max    |          |
| Transmitter REFCLK<br>Phase Noise (622<br>MHz) <sup>(18)</sup>  | 100 Hz  | —  | —             | -70    | —                            | —             | -70    | dBc/Hz   |
|   | 1 kHz   | —  | —             | -90    | —                            | —             | -90    |          |
|   | 10 kHz  | —  | —             | -100   | —                            | —             | -100   |          |
|   | 100 kHz   | —  | —             | -110   | —                            | —             | -110   |          |
|   | ≥ 1 MHz   | —  | —             | -120   | —                            | —             | -120   |          |
| Transmitter REFCLK<br>Phase Jitter (100<br>MHz) <sup>(15)</sup>   | 10 kHz to<br>1.5 MHz<br>(PCIe)  | —  | —             | 3      | —                            | —             | 3      | ps (rms) |
| RREF <sup>(17)</sup>  | —   | —  | 1800<br>± 1%  | —      | —                            | 1800<br>± 1%  | —      | Ω        |
| <b>Transceiver Clocks</b>   |   |  |               |        |                              |               |        |          |
| fixedclk clock<br>frequency   | PCIe<br>Receiver<br>Detect  | —  | 100 or<br>125 | —      | —                            | 100 or<br>125 | —      | MHz      |
| Reconfiguration clock<br>(mgmt_clk_clk)<br>frequency  | —   | 100  | —             | 125    | 100                          | —             | 125    | MHz      |
| <b>Receiver</b>   |   |  |               |        |                              |               |        |          |
| Supported I/O<br>Standards  | —   | 1.4-V PCML, 1.5-V PCML, 2.5-V PCML, LVPECL, and LVDS |               |        |                              |               |        |          |
| Data rate<br>(Standard PCS) <sup>(21)</sup>   | GX channels   | 600  | —             | 8500   | 600                          | —             | 8500   | Mbps     |
| Data rate<br>(10G PCS) <sup>(21)</sup>  | GX channels   | 600  | —             | 12,500 | 600                          | —             | 12,500 | Mbps     |
| Data rate   | GT channels   | 19,600   | —             | 28,050 | 19,600                       | —             | 25,780 | Mbps     |
| Absolute V <sub>MAX</sub> for a<br>receiver pin <sup>(3)</sup>  | GT channels   | —  | —             | 1.2    | —                            | —             | 1.2    | V        |
| Absolute V <sub>MIN</sub> for a<br>receiver pin   | GT channels   | -0.4   | —             | —      | -0.4                         | —             | —      | V        |
| Maximum peak-to-peak<br>differential input<br>voltage V <sub>ID</sub> (diff p-p)<br>before device<br>configuration <sup>(20)</sup>                  | GT channels   | —  | —             | 1.6    | —                            | —             | 1.6    | V        |
|   | GX channels   | <sup>(8)</sup>                                       |               |        |                              |               |        |          |
| Maximum peak-to-peak<br>differential input<br>voltage V <sub>ID</sub> (diff p-p)<br>after device<br>configuration <sup>(16)</sup> , <sup>(20)</sup> | GT channels<br>V <sub>CCR_GTB</sub> =<br>1.05 V<br>(V <sub>ICM</sub> =<br>0.65 V) | —  | —             | 2.2    | —                            | —             | 2.2    | V        |
|   | GX channels   | <sup>(8)</sup>                                       |               |        |                              |               |        |          |
| Minimum differential<br>eye opening at receiver<br>serial input pins <sup>(4)</sup> , <sup>(20)</sup>   | GT channels   | 200  | —             | —      | 200                          | —             | —      | mV       |
|   | GX channels   | <sup>(8)</sup>                                       |               |        |                              |               |        |          |



**Table 28. Transceiver Specifications for Stratix V GT Devices (Part 4 of 5) <sup>(1)</sup>**

| Symbol/<br>Description   | Conditions                                   | Transceiver<br>Speed Grade 2 |     |                                | Transceiver<br>Speed Grade 3 |     |                                | Unit |
|--|--|------------------------------|-----|--------------------------------|------------------------------|-----|--------------------------------|------|
|  |  | Min                          | Typ | Max                            | Min                          | Typ | Max                            |      |
| Data rate  | GT channels                                  | 19,600                       | —   | 28,050                         | 19,600                       | —   | 25,780                         | Mbps |
| Differential on-chip<br>termination resistors                      | GT channels                                  | —                            | 100 | —                              | —                            | 100 | —                              | Ω    |
|  | GX channels                                  | (8)                          |     |                                |                              |     |                                |      |
| V <sub>OCM</sub> (AC coupled)                                      | GT channels                                  | —                            | 500 | —                              | —                            | 500 | —                              | mV   |
|  | GX channels                                  | (8)                          |     |                                |                              |     |                                |      |
| Rise/Fall time   | GT channels                                  | —                            | 15  | —                              | —                            | 15  | —                              | ps   |
|  | GX channels                                  | (8)                          |     |                                |                              |     |                                |      |
| Intra-differential pair<br>skew                                    | GX channels                                  | (8)                          |     |                                |                              |     |                                |      |
| Intra-transceiver block<br>transmitter channel-to-<br>channel skew | GX channels                                  | (8)                          |     |                                |                              |     |                                |      |
| Inter-transceiver block<br>transmitter channel-to-<br>channel skew | GX channels                                  | (8)                          |     |                                |                              |     |                                |      |
| CMU PLL  |  |                              |     |                                |                              |     |                                |      |
| Supported Data Range   | —  | 600                          | —   | 12500                          | 600                          | —   | 8500                           | Mbps |
| t <sub>pll_powerdown</sub> <sup>(13)</sup>                         | —  | 1                            | —   | —                              | 1                            | —   | —                              | μs   |
| t <sub>pll_lock</sub> <sup>(14)</sup>                              | —  | —                            | —   | 10                             | —                            | —   | 10                             | μs   |
| ATX PLL  |  |                              |     |                                |                              |     |                                |      |
| Supported Data Rate<br>Range for GX Channels                       | VCO post-<br>divider L=2                     | 8000                         | —   | 12500                          | 8000                         | —   | 8500                           | Mbps |
|  | L=4  | 4000                         | —   | 6600                           | 4000                         | —   | 6600                           | Mbps |
|  | L=8  | 2000                         | —   | 3300                           | 2000                         | —   | 3300                           | Mbps |
|  | L=8,<br>Local/Central<br>Clock Divider<br>=2 | 1000                         | —   | 1762.5                         | 1000                         | —   | 1762.5                         | Mbps |
| Supported Data Rate<br>Range for GT Channels                       | VCO post-<br>divider L=2                     | 9800                         | —   | 14025                          | 9800                         | —   | 12890                          | Mbps |
| t <sub>pll_powerdown</sub> <sup>(13)</sup>                         | —  | 1                            | —   | —                              | 1                            | —   | —                              | μs   |
| t <sub>pll_lock</sub> <sup>(14)</sup>                              | —  | —                            | —   | 10                             | —                            | —   | 10                             | μs   |
| fPLL   |  |                              |     |                                |                              |     |                                |      |
| Supported Data Range   | —  | 600                          | —   | 3250/<br>3.125 <sup>(23)</sup> | 600                          | —   | 3250/<br>3.125 <sup>(23)</sup> | Mbps |
| t <sub>pll_powerdown</sub> <sup>(13)</sup>                         | —  | 1                            | —   | —                              | 1                            | —   | —                              | μs   |

**Table 31. PLL Specifications for Stratix V Devices (Part 2 of 3)**

| Symbol   | Parameter  | Min  | Typ     | Max  | Unit      |
|--|--|------|---------|--|-----------|
| $t_{\text{INCCJ}}$ <sup>(3), (4)</sup>             | Input clock cycle-to-cycle jitter ( $f_{\text{REF}} \geq 100$ MHz)   | —    | —       | 0.15   | UI (p-p)  |
|  | Input clock cycle-to-cycle jitter ( $f_{\text{REF}} < 100$ MHz)  | −750 | —       | +750   | ps (p-p)  |
| $t_{\text{OUTPJ\_DC}}$ <sup>(5)</sup>              | Period Jitter for dedicated clock output ( $f_{\text{OUT}} \geq 100$ MHz)                                    | —    | —       | 175 <sup>(1)</sup>                           | ps (p-p)  |
|  | Period Jitter for dedicated clock output ( $f_{\text{OUT}} < 100$ MHz)                                       | —    | —       | 17.5 <sup>(1)</sup>                          | mUI (p-p) |
| $t_{\text{FOUTPJ\_DC}}$ <sup>(5)</sup>             | Period Jitter for dedicated clock output in fractional PLL ( $f_{\text{OUT}} \geq 100$ MHz)                  | —    | —       | 250 <sup>(11)</sup> ,<br>175 <sup>(12)</sup> | ps (p-p)  |
|  | Period Jitter for dedicated clock output in fractional PLL ( $f_{\text{OUT}} < 100$ MHz)                     | —    | —       | 25 <sup>(11)</sup> ,<br>17.5 <sup>(12)</sup> | mUI (p-p) |
| $t_{\text{OUTCCJ\_DC}}$ <sup>(5)</sup>             | Cycle-to-Cycle Jitter for a dedicated clock output ( $f_{\text{OUT}} \geq 100$ MHz)                          | —    | —       | 175  | ps (p-p)  |
|  | Cycle-to-Cycle Jitter for a dedicated clock output ( $f_{\text{OUT}} < 100$ MHz)                             | —    | —       | 17.5   | mUI (p-p) |
| $t_{\text{FOUTCCJ\_DC}}$ <sup>(5)</sup>            | Cycle-to-cycle Jitter for a dedicated clock output in fractional PLL ( $f_{\text{OUT}} \geq 100$ MHz)        | —    | —       | 250 <sup>(11)</sup> ,<br>175 <sup>(12)</sup> | ps (p-p)  |
|  | Cycle-to-cycle Jitter for a dedicated clock output in fractional PLL ( $f_{\text{OUT}} < 100$ MHz)+          | —    | —       | 25 <sup>(11)</sup> ,<br>17.5 <sup>(12)</sup> | mUI (p-p) |
| $t_{\text{OUTPJ\_IO}}$ <sup>(5), (8)</sup>         | Period Jitter for a clock output on a regular I/O in integer PLL ( $f_{\text{OUT}} \geq 100$ MHz)            | —    | —       | 600  | ps (p-p)  |
|  | Period Jitter for a clock output on a regular I/O ( $f_{\text{OUT}} < 100$ MHz)                              | —    | —       | 60   | mUI (p-p) |
| $t_{\text{FOUTPJ\_IO}}$ <sup>(5), (8), (11)</sup>  | Period Jitter for a clock output on a regular I/O in fractional PLL ( $f_{\text{OUT}} \geq 100$ MHz)         | —    | —       | 600 <sup>(10)</sup>                          | ps (p-p)  |
|  | Period Jitter for a clock output on a regular I/O in fractional PLL ( $f_{\text{OUT}} < 100$ MHz)            | —    | —       | 60 <sup>(10)</sup>                           | mUI (p-p) |
| $t_{\text{OUTCCJ\_IO}}$ <sup>(5), (8)</sup>        | Cycle-to-cycle Jitter for a clock output on a regular I/O in integer PLL ( $f_{\text{OUT}} \geq 100$ MHz)    | —    | —       | 600  | ps (p-p)  |
|  | Cycle-to-cycle Jitter for a clock output on a regular I/O in integer PLL ( $f_{\text{OUT}} < 100$ MHz)       | —    | —       | 60 <sup>(10)</sup>                           | mUI (p-p) |
| $t_{\text{FOUTCCJ\_IO}}$ <sup>(5), (8), (11)</sup> | Cycle-to-cycle Jitter for a clock output on a regular I/O in fractional PLL ( $f_{\text{OUT}} \geq 100$ MHz) | —    | —       | 600 <sup>(10)</sup>                          | ps (p-p)  |
|  | Cycle-to-cycle Jitter for a clock output on a regular I/O in fractional PLL ( $f_{\text{OUT}} < 100$ MHz)    | —    | —       | 60   | mUI (p-p) |
| $t_{\text{CASC\_OUTPJ\_DC}}$ <sup>(5), (6)</sup>   | Period Jitter for a dedicated clock output in cascaded PLLs ( $f_{\text{OUT}} \geq 100$ MHz)                 | —    | —       | 175  | ps (p-p)  |
|  | Period Jitter for a dedicated clock output in cascaded PLLs ( $f_{\text{OUT}} < 100$ MHz)                    | —    | —       | 17.5   | mUI (p-p) |
| $f_{\text{DRIFT}}$                                 | Frequency drift after PFDENA is disabled for a duration of 100 $\mu$ s                                       | —    | —       | $\pm 10$                                     | %         |
| $dK_{\text{BIT}}$                                  | Bit number of Delta Sigma Modulator (DSM)  | 8    | 24      | 32   | Bits      |
| $k_{\text{VALUE}}$                                 | Numerator of Fraction  | 128  | 8388608 | 2147483648                                   | —         |

**Table 31. PLL Specifications for Stratix V Devices (Part 3 of 3)**

| Symbol    | Parameter  | Min    | Typ  | Max   | Unit |
|-----------|--|--------|------|-------|------|
| $f_{RES}$ | Resolution of VCO frequency ( $f_{INPFD} = 100$ MHz) | 390625 | 5.96 | 0.023 | Hz   |

**Notes to Table 31:**

- (1) This specification is limited in the Quartus II software by the I/O maximum frequency. The maximum I/O frequency is different for each I/O standard.
- (2) This specification is limited by the lower of the two: I/O  $f_{MAX}$  or  $f_{OUT}$  of the PLL.
- (3) A high input jitter directly affects the PLL output jitter. To have low PLL output clock jitter, you must provide a clean clock source < 120 ps.
- (4)  $f_{REF}$  is  $f_{IN}/N$  when  $N = 1$ .
- (5) Peak-to-peak jitter with a probability level of  $10^{-12}$  (14 sigma, 99.9999999974404% confidence level). The output jitter specification applies to the intrinsic jitter of the PLL, when an input jitter of 30 ps is applied. The external memory interface clock output jitter specifications use a different measurement method and are available in Table 44 on page 52.
- (6) The cascaded PLL specification is only applicable with the following condition:
  - a. Upstream PLL:  $0.59\text{MHz} \leq \text{Upstream PLL BW} < 1$  MHz
  - b. Downstream PLL: Downstream PLL BW > 2 MHz
- (7) High bandwidth PLL settings are not supported in external feedback mode.
- (8) The external memory interface clock output jitter specifications use a different measurement method, which is available in Table 42 on page 50.
- (9) The VCO frequency reported by the Quartus II software in the PLL Usage Summary section of the compilation report takes into consideration the VCO post-scale counter K value. Therefore, if the counter K has a value of 2, the frequency reported can be lower than the  $f_{VCO}$  specification.
- (10) This specification only covers fractional PLL for low bandwidth. The  $f_{VCO}$  for fractional value range 0.05 - 0.95 must be  $\geq 1000$  MHz, while  $f_{VCO}$  for fractional value range 0.20 - 0.80 must be  $\geq 1200$  MHz.
- (11) This specification only covered fractional PLL for low bandwidth. The  $f_{VCO}$  for fractional value range 0.05-0.95 must be  $\geq 1000$  MHz.
- (12) This specification only covered fractional PLL for low bandwidth. The  $f_{VCO}$  for fractional value range 0.20-0.80 must be  $\geq 1200$  MHz.

## DSP Block Specifications

Table 32 lists the Stratix V DSP block performance specifications.

**Table 32. Block Performance Specifications for Stratix V DSP Devices (Part 1 of 2)**

| Mode   | Peformance |         |         |     |               |     |     | Unit |
|--|------------|---------|---------|-----|---------------|-----|-----|------|
|  | C1         | C2, C2L | I2, I2L | C3  | I3, I3L, I3YY | C4  | I4  |      |
| Modes using one DSP                          |            |         |         |     |               |     |     |      |
| Three 9 x 9                                  | 600        | 600     | 600     | 480 | 480           | 420 | 420 | MHz  |
| One 18 x 18                                  | 600        | 600     | 600     | 480 | 480           | 420 | 400 | MHz  |
| Two partial 18 x 18 (or 16 x 16)             | 600        | 600     | 600     | 480 | 480           | 420 | 400 | MHz  |
| One 27 x 27                                  | 500        | 500     | 500     | 400 | 400           | 350 | 350 | MHz  |
| One 36 x 18                                  | 500        | 500     | 500     | 400 | 400           | 350 | 350 | MHz  |
| One sum of two 18 x 18(One sum of 2 16 x 16) | 500        | 500     | 500     | 400 | 400           | 350 | 350 | MHz  |
| One sum of square                            | 500        | 500     | 500     | 400 | 400           | 350 | 350 | MHz  |
| One 18 x 18 plus 36 (a x b) + c              | 500        | 500     | 500     | 400 | 400           | 350 | 350 | MHz  |
| Modes using two DSPs                         |            |         |         |     |               |     |     |      |
| Three 18 x 18                                | 500        | 500     | 500     | 400 | 400           | 350 | 350 | MHz  |
| One sum of four 18 x 18                      | 475        | 475     | 475     | 380 | 380           | 300 | 300 | MHz  |
| One sum of two 27 x 27                       | 465        | 465     | 450     | 380 | 380           | 300 | 290 | MHz  |
| One sum of two 36 x 18                       | 475        | 475     | 475     | 380 | 380           | 300 | 300 | MHz  |
| One complex 18 x 18                          | 500        | 500     | 500     | 400 | 400           | 350 | 350 | MHz  |
| One 36 x 36                                  | 475        | 475     | 475     | 380 | 380           | 300 | 300 | MHz  |

**Table 32. Block Performance Specifications for Stratix V DSP Devices (Part 2 of 2)**

| Mode                   | Peformance |         |         |     |               |     |     | Unit |
|------------------------|------------|---------|---------|-----|---------------|-----|-----|------|
|                        | C1         | C2, C2L | I2, I2L | C3  | I3, I3L, I3YY | C4  | I4  |      |
| Modes using Three DSPs |            |         |         |     |               |     |     |      |
| One complex 18 x 25    | 425        | 425     | 415     | 340 | 340           | 275 | 265 | MHz  |
| Modes using Four DSPs  |            |         |         |     |               |     |     |      |
| One complex 27 x 27    | 465        | 465     | 465     | 380 | 380           | 300 | 290 | MHz  |

### Memory Block Specifications

Table 33 lists the Stratix V memory block specifications.

**Table 33. Memory Block Performance Specifications for Stratix V Devices <sup>(1)</sup>, <sup>(2)</sup> (Part 1 of 2)**

| Memory | Mode                                       | Resources Used |        | Performance |         |     |     |         |               |     | Unit |
|--------|--|----------------|--------|-------------|---------|-----|-----|---------|---------------|-----|------|
|        |  | ALUTs          | Memory | C1          | C2, C2L | C3  | C4  | I2, I2L | I3, I3L, I3YY | I4  |      |
| MLAB   | Single port, all supported widths          | 0              | 1      | 450         | 450     | 400 | 315 | 450     | 400           | 315 | MHz  |
|        | Simple dual-port, x32/x64 depth            | 0              | 1      | 450         | 450     | 400 | 315 | 450     | 400           | 315 | MHz  |
|        | Simple dual-port, x16 depth <sup>(3)</sup> | 0              | 1      | 675         | 675     | 533 | 400 | 675     | 533           | 400 | MHz  |
|        | ROM, all supported widths                  | 0              | 1      | 600         | 600     | 500 | 450 | 600     | 500           | 450 | MHz  |

**Table 36. High-Speed I/O Specifications for Stratix V Devices <sup>(1)</sup>, <sup>(2)</sup> (Part 3 of 4)**

| Symbol   | Conditions  | C1             |     |                | C2, C2L, I2, I2L |     |                | C3, I3, I3L, I3YY |     |                | C4, I4         |     |                | Unit |
|--|---|----------------|-----|----------------|------------------|-----|----------------|-------------------|-----|----------------|----------------|-----|----------------|------|
|  |   | Min            | Typ | Max            | Min              | Typ | Max            | Min               | Typ | Max            | Min            | Typ | Max            |      |
| $t_{DUTY}$   | Transmitter output clock duty cycle for both True and Emulated Differential I/O Standards   | 45             | 50  | 55             | 45               | 50  | 55             | 45                | 50  | 55             | 45             | 50  | 55             | %    |
| $t_{RISE}$ & $t_{FALL}$                                    | True Differential I/O Standards   | —              | —   | 160            | —                | —   | 160            | —                 | —   | 200            | —              | —   | 200            | ps   |
|  | Emulated Differential I/O Standards with three external output resistor networks  | —              | —   | 250            | —                | —   | 250            | —                 | —   | 250            | —              | —   | 300            | ps   |
| TCCS   | True Differential I/O Standards   | —              | —   | 150            | —                | —   | 150            | —                 | —   | 150            | —              | —   | 150            | ps   |
|  | Emulated Differential I/O Standards   | —              | —   | 300            | —                | —   | 300            | —                 | —   | 300            | —              | —   | 300            | ps   |
| <b>Receiver</b>  |   |                |     |                |                  |     |                |                   |     |                |                |     |                |      |
| True Differential I/O Standards - $f_{HSDRDP}$ (data rate) | SERDES factor J = 3 to 10 <sup>(11)</sup> , <sup>(12)</sup> , <sup>(13)</sup> , <sup>(14)</sup> , <sup>(15)</sup> , <sup>(16)</sup> | 150            | —   | 1434           | 150              | —   | 1434           | 150               | —   | 1250           | 150            | —   | 1050           | Mbps |
|  | SERDES factor J $\geq 4$  | 150            | —   | 1600           | 150              | —   | 1600           | 150               | —   | 1600           | 150            | —   | 1250           | Mbps |
|  | LVDS RX with DPA <sup>(12)</sup> , <sup>(14)</sup> , <sup>(15)</sup> , <sup>(16)</sup>  | 150            | —   | 1600           | 150              | —   | 1600           | 150               | —   | 1600           | 150            | —   | 1250           | Mbps |
|  | SERDES factor J = 2, uses DDR Registers   | <sup>(6)</sup> | —   | <sup>(7)</sup> | <sup>(6)</sup>   | —   | <sup>(7)</sup> | <sup>(6)</sup>    | —   | <sup>(7)</sup> | <sup>(6)</sup> | —   | <sup>(7)</sup> | Mbps |
|  | SERDES factor J = 1, uses SDR Register  | <sup>(6)</sup> | —   | <sup>(7)</sup> | <sup>(6)</sup>   | —   | <sup>(7)</sup> | <sup>(6)</sup>    | —   | <sup>(7)</sup> | <sup>(6)</sup> | —   | <sup>(7)</sup> | Mbps |

**Table 36. High-Speed I/O Specifications for Stratix V Devices <sup>(1), (2)</sup> (Part 4 of 4)**

| Symbol                        | Conditions                              | C1  |     |           | C2, C2L, I2, I2L |     |           | C3, I3, I3L, I3YY |     |           | C4, I4 |     |           | Unit  |
|-------------------------------|---|-----|-----|-----------|------------------|-----|-----------|-------------------|-----|-----------|--------|-----|-----------|-------|
|                               |   | Min | Typ | Max       | Min              | Typ | Max       | Min               | Typ | Max       | Min    | Typ | Max       |       |
| f <sub>HSDR</sub> (data rate) | SERDES factor J = 3 to 10               | (6) | —   | (8)       | (6)              | —   | (8)       | (6)               | —   | (8)       | (6)    | —   | (8)       | Mbps  |
|                               | SERDES factor J = 2, uses DDR Registers | (6) | —   | (7)       | (6)              | —   | (7)       | (6)               | —   | (7)       | (6)    | —   | (7)       | Mbps  |
|                               | SERDES factor J = 1, uses SDR Register  | (6) | —   | (7)       | (6)              | —   | (7)       | (6)               | —   | (7)       | (6)    | —   | (7)       | Mbps  |
| <b>DPA Mode</b>               |   |     |     |           |                  |     |           |                   |     |           |        |     |           |       |
| DPA run length                | —                                       | —   | —   | 1000<br>0 | —                | —   | 1000<br>0 | —                 | —   | 1000<br>0 | —      | —   | 1000<br>0 | UI    |
| <b>Soft CDR mode</b>          |   |     |     |           |                  |     |           |                   |     |           |        |     |           |       |
| Soft-CDR PPM tolerance        | —                                       | —   | —   | 300       | —                | —   | 300       | —                 | —   | 300       | —      | —   | 300       | ± PPM |
| <b>Non DPA Mode</b>           |   |     |     |           |                  |     |           |                   |     |           |        |     |           |       |
| Sampling Window               | —                                       | —   | —   | 300       | —                | —   | 300       | —                 | —   | 300       | —      | —   | 300       | ps    |

**Notes to Table 36:**

- (1) When J = 3 to 10, use the serializer/deserializer (SERDES) block.
- (2) When J = 1 or 2, bypass the SERDES block.
- (3) This only applies to DPA and soft-CDR modes.
- (4) Clock Boost Factor (W) is the ratio between the input data rate to the input clock rate.
- (5) This is achieved by using the **LVDS** clock network.
- (6) The minimum specification depends on the clock source (for example, the PLL and clock pin) and the clock routing resource (global, regional, or local) that you use. The I/O differential buffer and input register do not have a minimum toggle rate.
- (7) The maximum ideal frequency is the SERDES factor (J) x the PLL maximum output frequency (f<sub>OUT</sub>) provided you can close the design timing and the signal integrity simulation is clean.
- (8) You can estimate the achievable maximum data rate for non-DPA mode by performing link timing closure analysis. You must consider the board skew margin, transmitter delay margin, and receiver sampling margin to determine the maximum data rate supported.
- (9) If the receiver with DPA enabled and transmitter are using shared PLLs, the minimum data rate is 150 Mbps.
- (10) You must calculate the leftover timing margin in the receiver by performing link timing closure analysis. You must consider the board skew margin, transmitter channel-to-channel skew, and receiver sampling margin to determine leftover timing margin.
- (11) The F<sub>MAX</sub> specification is based on the fast clock used for serial data. The interface F<sub>MAX</sub> is also dependent on the parallel clock domain which is design-dependent and requires timing analysis.
- (12) Stratix V RX LVDS will need DPA. For Stratix V TX LVDS, the receiver side component must have DPA.
- (13) Stratix V LVDS serialization and de-serialization factor needs to be x4 and above.
- (14) Requires package skew compensation with PCB trace length.
- (15) Do not mix single-ended I/O buffer within LVDS I/O bank.
- (16) Chip-to-chip communication only with a maximum load of 5 pF.
- (17) When using True LVDS RX channels for emulated LVDS TX channel, only serialization factors 1 and 2 are supported.

Figure 7 shows the dynamic phase alignment (DPA) lock time specifications with the DPA PLL calibration option enabled.

**Figure 7. DPA Lock Time Specification with DPA PLL Calibration Enabled**



Table 37 lists the DPA lock time specifications for Stratix V devices.

**Table 37. DPA Lock Time Specifications for Stratix V GX Devices Only <sup>(1), (2), (3)</sup>**

| Standard           | Training Pattern     | Number of Data Transitions in One Repetition of the Training Pattern | Number of Repetitions per 256 Data Transitions <sup>(4)</sup> | Maximum              |
|--------------------|----------------------|--|---|----------------------|
| SPI-4              | 00000000001111111111 | 2  | 128   | 640 data transitions |
| Parallel Rapid I/O | 00001111             | 2  | 128   | 640 data transitions |
|                    | 10010000             | 4  | 64  | 640 data transitions |
| Miscellaneous      | 10101010             | 8  | 32  | 640 data transitions |
|                    | 01010101             | 8  | 32  | 640 data transitions |

**Notes to Table 37:**

- (1) The DPA lock time is for one channel.
- (2) One data transition is defined as a 0-to-1 or 1-to-0 transition.
- (3) The DPA lock time stated in this table applies to both commercial and industrial grade.
- (4) This is the number of repetitions for the stated training pattern to achieve the 256 data transitions.

Figure 8 shows the LVDS soft-clock data recovery (CDR)/DPA sinusoidal jitter tolerance specification for a data rate  $\geq 1.25$  Gbps. Table 38 lists the LVDS soft-CDR/DPA sinusoidal jitter tolerance specification for a data rate  $\geq 1.25$  Gbps.

**Figure 8. LVDS Soft-CDR/DPA Sinusoidal Jitter Tolerance Specification for a Data Rate  $\geq 1.25$  Gbps**



**Table 40. DQS Phase Offset Delay Per Setting for Stratix V Devices <sup>(1), (2)</sup> (Part 2 of 2)**

| Speed Grade | Min | Max | Unit |
|-------------|-----|-----|------|
| C4,I4       | 8   | 16  | ps   |

**Notes to Table 40:**

- (1) The typical value equals the average of the minimum and maximum values.
- (2) The delay settings are linear with a cumulative delay variation of 40 ps for all speed grades. For example, when using a –2 speed grade and applying a 10-phase offset setting to a 90° phase shift at 400 MHz, the expected average cumulative delay is  $[625 \text{ ps} + (10 \times 10 \text{ ps}) \pm 20 \text{ ps}] = 725 \text{ ps} \pm 20 \text{ ps}$ .

Table 41 lists the DQS phase shift error for Stratix V devices.

**Table 41. DQS Phase Shift Error Specification for DLL-Delayed Clock ( $t_{\text{DQS\_PSERR}}$ ) for Stratix V Devices <sup>(1)</sup>**

| Number of DQS Delay Buffers | C1  | C2, C2L, I2, I2L | C3, I3, I3L, I3YY | C4,I4 | Unit |
|-----------------------------|-----|------------------|-------------------|-------|------|
| 1                           | 28  | 28               | 30                | 32    | ps   |
| 2                           | 56  | 56               | 60                | 64    | ps   |
| 3                           | 84  | 84               | 90                | 96    | ps   |
| 4                           | 112 | 112              | 120               | 128   | ps   |

**Notes to Table 41:**

- (1) This error specification is the absolute maximum and minimum error. For example, skew on three DQS delay buffers in a –2 speed grade is  $\pm 78 \text{ ps}$  or  $\pm 39 \text{ ps}$ .

Table 42 lists the memory output clock jitter specifications for Stratix V devices.

**Table 42. Memory Output Clock Jitter Specification for Stratix V Devices <sup>(1), (Part 1 of 2)</sup> <sup>(2), (3)</sup>**

| Clock Network | Parameter                    | Symbol                 | C1   |     | C2, C2L, I2, I2L |     | C3, I3, I3L, I3YY |      | C4,I4 |      | Unit |
|---------------|------------------------------|------------------------|------|-----|------------------|-----|-------------------|------|-------|------|------|
|               |                              |                        | Min  | Max | Min              | Max | Min               | Max  | Min   | Max  |      |
| Regional      | Clock period jitter          | $t_{\text{JIT(per)}}$  | –50  | 50  | –50              | 50  | –55               | 55   | –55   | 55   | ps   |
|               | Cycle-to-cycle period jitter | $t_{\text{JIT(cc)}}$   | –100 | 100 | –100             | 100 | –110              | 110  | –110  | 110  | ps   |
|               | Duty cycle jitter            | $t_{\text{JIT(duty)}}$ | –50  | 50  | –50              | 50  | –82.5             | 82.5 | –82.5 | 82.5 | ps   |
| Global        | Clock period jitter          | $t_{\text{JIT(per)}}$  | –75  | 75  | –75              | 75  | –82.5             | 82.5 | –82.5 | 82.5 | ps   |
|               | Cycle-to-cycle period jitter | $t_{\text{JIT(cc)}}$   | –150 | 150 | –150             | 150 | –165              | 165  | –165  | 165  | ps   |
|               | Duty cycle jitter            | $t_{\text{JIT(duty)}}$ | –75  | 75  | –75              | 75  | –90               | 90   | –90   | 90   | ps   |



## FPP Configuration Timing when DCLK-to-DATA [] = 1

Figure 12 shows the timing waveform for FPP configuration when using a MAX II or MAX V device as an external host. This waveform shows timing when the DCLK-to-DATA [] ratio is 1.

**Figure 12. FPP Configuration Timing Waveform When the DCLK-to-DATA[] Ratio is 1 <sup>(1), (2)</sup>**



### Notes to Figure 12:

- (1) Use this timing waveform when the DCLK-to-DATA [] ratio is 1.
- (2) The beginning of this waveform shows the device in user mode. In user mode, nCONFIG, nSTATUS, and CONF\_DONE are at logic-high levels. When nCONFIG is pulled low, a reconfiguration cycle begins.
- (3) After power-up, the Stratix V device holds nSTATUS low for the time of the POR delay.
- (4) After power-up, before and during configuration, CONF\_DONE is low.
- (5) Do not leave DCLK floating after configuration. DCLK is ignored after configuration is complete. It can toggle high or low if required.
- (6) For FPP x16, use DATA [15..0]. For FPP x8, use DATA [7..0]. DATA [31..0] are available as a user I/O pin after configuration. The state of this pin depends on the dual-purpose pin settings.
- (7) To ensure a successful configuration, send the entire configuration data to the Stratix V device. CONF\_DONE is released high when the Stratix V device receives all the configuration data successfully. After CONF\_DONE goes high, send two additional falling edges on DCLK to begin initialization and enter user mode.
- (8) After the option bit to enable the INIT\_DONE pin is configured into the device, the INIT\_DONE goes low.

Table 50 lists the timing parameters for Stratix V devices for FPP configuration when the DCLK-to-DATA [] ratio is 1.

**Table 50. FPP Timing Parameters for Stratix V Devices <sup>(1)</sup>**

| Symbol                            | Parameter   | Minimum  | Maximum              | Units |
|-----------------------------------|---|--|----------------------|-------|
| t <sub>CF2CD</sub>                | nCONFIG low to CONF_DONE low                      | —  | 600                  | ns    |
| t <sub>CF2ST0</sub>               | nCONFIG low to nSTATUS low                        | —  | 600                  | ns    |
| t <sub>CFG</sub>                  | nCONFIG low pulse width                           | 2  | —                    | μs    |
| t <sub>STATUS</sub>               | nSTATUS low pulse width                           | 268  | 1,506 <sup>(2)</sup> | μs    |
| t <sub>CF2ST1</sub>               | nCONFIG high to nSTATUS high                      | —  | 1,506 <sup>(3)</sup> | μs    |
| t <sub>CF2CK</sub> <sup>(6)</sup> | nCONFIG high to first rising edge on DCLK         | 1,506  | —                    | μs    |
| t <sub>ST2CK</sub> <sup>(6)</sup> | nSTATUS high to first rising edge of DCLK         | 2  | —                    | μs    |
| t <sub>DSU</sub>                  | DATA [] setup time before rising edge on DCLK     | 5.5  | —                    | ns    |
| t <sub>DH</sub>                   | DATA [] hold time after rising edge on DCLK       | 0  | —                    | ns    |
| t <sub>CH</sub>                   | DCLK high time                                    | $0.45 \times 1/f_{\text{MAX}}$                             | —                    | s     |
| t <sub>CL</sub>                   | DCLK low time                                     | $0.45 \times 1/f_{\text{MAX}}$                             | —                    | s     |
| t <sub>CLK</sub>                  | DCLK period                                       | $1/f_{\text{MAX}}$   | —                    | s     |
| f <sub>MAX</sub>                  | DCLK frequency (FPP $\times 8/\times 16$ )        | —  | 125                  | MHz   |
|                                   | DCLK frequency (FPP $\times 32$ )                 | —  | 100                  | MHz   |
| t <sub>CD2UM</sub>                | CONF_DONE high to user mode <sup>(4)</sup>        | 175  | 437                  | μs    |
| t <sub>CD2CU</sub>                | CONF_DONE high to CLKUSR enabled                  | 4 × maximum DCLK period                                    | —                    | —     |
| t <sub>CD2UMC</sub>               | CONF_DONE high to user mode with CLKUSR option on | t <sub>CD2CU</sub> + (8576 × CLKUSR period) <sup>(5)</sup> | —                    | —     |

**Notes to Table 50:**

- (1) Use these timing parameters when the decompression and design security features are disabled.
- (2) This value is applicable if you do not delay configuration by extending the nCONFIG or nSTATUS low pulse width.
- (3) This value is applicable if you do not delay configuration by externally holding the nSTATUS low.
- (4) The minimum and maximum numbers apply only if you chose the internal oscillator as the clock source for initializing the device.
- (5) To enable the CLKUSR pin as the initialization clock source and to obtain the maximum frequency specification on these pins, refer to the Initialization section of the “Configuration, Design Security, and Remote System Upgrades in Stratix V Devices” chapter.
- (6) If nSTATUS is monitored, follow the t<sub>ST2CK</sub> specification. If nSTATUS is not monitored, follow the t<sub>CF2CK</sub> specification.

### FPP Configuration Timing when DCLK-to-DATA [] > 1

Figure 13 shows the timing waveform for FPP configuration when using a MAX II device, MAX V device, or microprocessor as an external host. This waveform shows timing when the DCLK-to-DATA [] ratio is more than 1.

**Figure 13. FPP Configuration Timing Waveform When the DCLK-to-DATA[] Ratio is >1 (1), (2)****Notes to Figure 13:**

- (1) Use this timing waveform and parameters when the DCLK-to-DATA [] ratio is >1. To find out the DCLK-to-DATA [] ratio for your system, refer to Table 49 on page 55.
- (2) The beginning of this waveform shows the device in user mode. In user mode, nCONFIG, nSTATUS, and CONF\_DONE are at logic high levels. When nCONFIG is pulled low, a reconfiguration cycle begins.
- (3) After power-up, the Stratix V device holds nSTATUS low for the time as specified by the POR delay.
- (4) After power-up, before and during configuration, CONF\_DONE is low.
- (5) Do not leave DCLK floating after configuration. You can drive it high or low, whichever is more convenient.
- (6) "r" denotes the DCLK-to-DATA [] ratio. For the DCLK-to-DATA [] ratio based on the decompression and the design security feature enable settings, refer to Table 49 on page 55.
- (7) If needed, pause DCLK by holding it low. When DCLK restarts, the external host must provide data on the DATA [31 . . 0] pins prior to sending the first DCLK rising edge.
- (8) To ensure a successful configuration, send the entire configuration data to the Stratix V device. CONF\_DONE is released high after the Stratix V device receives all the configuration data successfully. After CONF\_DONE goes high, send two additional falling edges on DCLK to begin initialization and enter user mode.
- (9) After the option bit to enable the INIT\_DONE pin is configured into the device, the INIT\_DONE goes low.

## Active Serial Configuration Timing

Table 52 lists the DCLK frequency specification in the AS configuration scheme.

**Table 52. DCLK Frequency Specification in the AS Configuration Scheme <sup>(1), (2)</sup>**

| Minimum | Typical | Maximum | Unit |
|---------|---------|---------|------|
| 5.3     | 7.9     | 12.5    | MHz  |
| 10.6    | 15.7    | 25.0    | MHz  |
| 21.3    | 31.4    | 50.0    | MHz  |
| 42.6    | 62.9    | 100.0   | MHz  |

**Notes to Table 52:**

- (1) This applies to the DCLK frequency specification when using the internal oscillator as the configuration clock source.
- (2) The AS multi-device configuration scheme does not support DCLK frequency of 100 MHz.

Figure 14 shows the single-device configuration setup for an AS ×1 mode.

**Figure 14. AS Configuration Timing**



**Notes to Figure 14:**

- (1) If you are using AS ×4 mode, this signal represents the AS\_DATA [3 : 0] and EPCQ sends in 4-bits of data for each DCLK cycle.
- (2) The initialization clock can be from internal oscillator or CLKUSR pin.
- (3) After the option bit to enable the INIT\_DONE pin is configured into the device, the INIT\_DONE goes low.

Table 53 lists the timing parameters for AS ×1 and AS ×4 configurations in Stratix V devices.

**Table 53. AS Timing Parameters for AS ×1 and AS ×4 Configurations in Stratix V Devices <sup>(1), (2)</sup> (Part 1 of 2)**

| Symbol   | Parameter                                   | Minimum | Maximum | Units |
|----------|---|---------|---------|-------|
| $t_{CO}$ | DCLK falling edge to AS_DATA0/ASDO output   | —       | 2       | ns    |
| $t_{SU}$ | Data setup time before falling edge on DCLK | 1.5     | —       | ns    |
| $t_H$    | Data hold time after falling edge on DCLK   | 0       | —       | ns    |

**Table 60. Glossary (Part 4 of 4)**

| Letter   | Subject       | Definitions  |
|----------|---------------|--|
| <b>V</b> | $V_{CM(DC)}$  | DC common mode input voltage.  |
|          | $V_{ICM}$     | Input common mode voltage—The common mode of the differential signal at the receiver.  |
|          | $V_{ID}$      | Input differential voltage swing—The difference in voltage between the positive and complementary conductors of a differential transmission at the receiver.     |
|          | $V_{DIF(AC)}$ | AC differential input voltage—Minimum AC input differential voltage required for switching.  |
|          | $V_{DIF(DC)}$ | DC differential input voltage— Minimum DC input differential voltage required for switching.   |
|          | $V_{IH}$      | Voltage input high—The minimum positive voltage applied to the input which is accepted by the device as a logic high.  |
|          | $V_{IH(AC)}$  | High-level AC input voltage  |
|          | $V_{IH(DC)}$  | High-level DC input voltage  |
|          | $V_{IL}$      | Voltage input low—The maximum positive voltage applied to the input which is accepted by the device as a logic low.  |
|          | $V_{IL(AC)}$  | Low-level AC input voltage   |
|          | $V_{IL(DC)}$  | Low-level DC input voltage   |
|          | $V_{OCM}$     | Output common mode voltage—The common mode of the differential signal at the transmitter.  |
|          | $V_{OD}$      | Output differential voltage swing—The difference in voltage between the positive and complementary conductors of a differential transmission at the transmitter. |
|          | $V_{SWING}$   | Differential input voltage   |
|          | $V_X$         | Input differential cross point voltage   |
|          | $V_{OX}$      | Output differential cross point voltage  |
| <b>W</b> | W             | High-speed I/O block—clock boost factor  |
| <b>X</b> | —             | —  |
| <b>Y</b> |               |  |
| <b>Z</b> |               |  |