

Welcome to E-XFL.COM

What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

Details

Product Status	Active
Core Processor	PIC
Core Size	8-Bit
Speed	4MHz
Connectivity	-
Peripherals	Brown-out Detect/Reset, POR, WDT
Number of I/O	13
Program Memory Size	3.5KB (2K x 14)
Program Memory Type	OTP
EEPROM Size	-
RAM Size	128 x 8
Voltage - Supply (Vcc/Vdd)	2.5V ~ 6V
Data Converters	·
Oscillator Type	External
Operating Temperature	0°C ~ 70°C (TA)
Mounting Type	Surface Mount
Package / Case	18-SOIC (0.295", 7.50mm Width)
Supplier Device Package	18-SOIC
Purchase URL	https://www.e-xfl.com/product-detail/microchip-technology/pic16lc622-04-so

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

NOTES:

FIGURE 4-6: DATA MEMORY MAP FOR THE PIC16C620A/CR620A/621A

File Address	5		File Address
00h	INDF ⁽¹⁾	INDF ⁽¹⁾	80h
01h	TMR0	OPTION	81h
02h	PCL	PCL	82h
03h	STATUS	STATUS	83h
04h	FSR	FSR	84h
05h	PORTA	TRISA	85h
06h	PORTB	TRISB	86h
07h			87h
08h			88h
09h			89h
0Ah	PCLATH	PCLATH	8Ah
0Bh	INTCON	INTCON	8Bh
0Ch	PIR1	PIE1	8Ch
0Dh			8Dh
0Eh		PCON	8Eh
0Fh			8Fh
10h			90h
11h			91h
12h			92h
13h			93h
14h			94h
15h			95h
16h			96h
17h			97h
18h			98h
19h			99h
1Ah			9Ah
1Bh			9Bh
1Ch			9Ch
1Dh			9Dh
1Eh			9Eh
1Fh	CMCON	VRCON	9Fh
20h	General Purpose Register		A0h
6Fh			
70h	General		F0h
7011	Purpose	Accesses	
7Fh	Register	1011-1711	FFh
	Bank 0	Bank 1	
Unimp	lemented data mer	nory locations, re	ad as '0'.
Note 1:	Not a physical re	gister.	

FIGURE 4-7: DATA MEMORY MAP FOR THE PIC16C622A

File Address	;		File Address
00h	INDF ⁽¹⁾	INDF ⁽¹⁾	80h
01h	TMR0	OPTION	81h
02h	PCL	PCL	82h
03h	STATUS	STATUS	83h
04h	FSR	FSR	84h
05h	PORTA	TRISA	85h
06h	PORTB	TRISB	86h
07h			87h
08h			88h
09h			89h
0Ah	PCLATH	PCLATH	8Ah
0Bh	INTCON	INTCON	8Bh
0Ch	PIR1	PIE1	8Ch
0Dh			8Dh
0Eh		PCON	8Eh
0Fh			8Fh
10h			90h
11h			91h
12h			92h
13h			93h
14h			94h
15h			95h
16h			96h
17h			97h
18h			98h
19h			99h
1Ah			9Ah
1Bh			9Bh
1Ch			9Ch
1Dn			
1En	014001		9En
1Fn	CMCON	VRCON	9Fn
20h	General	General	A0h
	Purpose	Purpose	
	Register	Register	BFh
			C0h
			0011
6Fh			– F0h
70h	General	Accesses	
	Register	70h-7Fh	EEh
/Fhl	Bank 0	Bank 1	
Unimp	elemented data me	mory locations, re	ead as '0'.
Note 1:	Not a physical re	egister.	

4.2.2.1 STATUS Register

The STATUS register, shown in Register 4-1, contains the arithmetic status of the ALU, the RESET status and the bank select bits for data memory.

The STATUS register can be the destination for any instruction, like any other register. If the STATUS register is the destination for an instruction that affects the Z, DC or C bits, then the write to these three bits is disabled. These bits are set or cleared according to the device logic. Furthermore, the TO and PD bits are not writable. Therefore, the result of an instruction with the STATUS register as destination may be different than intended.

For example, CLRF STATUS will clear the upper-three bits and set the Z bit. This leaves the STATUS register as 000uuluu (where u = unchanged).

It is recommended, therefore, that only BCF, BSF, SWAPF and MOVWF instructions are used to alter the STATUS register, because these instructions do not affect any STATUS bit. For other instructions not affecting any STATUS bits, see the "Instruction Set Summary".

- Note 1: The IRP and RP1 bits (STATUS<7:6>) are not used by the PIC16C62X and should be programmed as '0'. Use of these bits as general purpose R/W bits is NOT recommended, since this may affect upward compatibility with future products.
 - 2: The <u>C and DC bits</u> operate as a Borrow and Digit Borrow out bit, respectively, in subtraction. See the SUBLW and SUBWF instructions for examples.

REGISTER 4-1: STATUS REGISTER (ADDRESS 03H OR 83H)

Reserved	Reserved	R/W-0	R-1	R-1	R/W-x	R/W-x	R/W-x
IRP	RP1	RP0	TO	PD	Z	DC	С
bit 7	•						bit 0
IRP: Regis	ster Bank Sele	ect bit (used	d for indirect	addressing)		
1 = Bank 2	2, 3 (100h - 1F	FFh)					
0 = Bank (The IRP hi), 1 (UUN - FFI it is reserved	n) on the PIC:	16C62X alw	/avs maintai	in this hit cle	ar	
RP<1·0>	Register Banl	C Select hits	s (used for c	lirect addres	sina)		
01 = Bank	1 (80h - FFh)			Joinig)		
00 = Bank	0 (00h - 7Fh))					
Each bank	is 128 bytes.	The RP1 b	oit is reserve	ed on the Pl	C16C62X; a	lways maint	ain this bit
clear.							
IU: Time-o			tion of at t	I Dinatruati	~~		
1 = Alter p 0 = A WD1	ower-up, сък Г time-out осо	curred		EP Instructi	on		
PD: Power	r-down bit						
1 = After p	ower-up or by	/ the CLRWI	DT instructio	n			
0 = By exe	ecution of the	SLEEP inst	ruction				
Z: Zero bit							
1 = The re	sult of an ariti	hmetic or lo	gic operatio	n is zero	`		
	suit of an and) instructions)(for borrow)	the polarity
is reversed	any/bonow b 1)	IL (ADDWF ,	ADDLW, SU	вым, зовиг	Instructions		the polarity
1 = A carry	/-out from the	4th low or	der bit of the	result occu	rred		
0 = No car	ry-out from th	e 4th low o	rder bit of th	ie result			
C: Carry/b	orrow bit (ADI	DWF, ADDI	W,SUBLW,S	SUBWF instr	uctions)		
1 = A carry	/-out from the	Most Signi	ficant bit of	the result of	ccurred		
0 = No car	ry-out from th	ie Most Sig	nificant dit o		occurrea	مرامي مراما	
Note:	complement	of the seco	s reversed. nd operand	For rotate	ON IS EXECUT) instruction	s this bit is
	loaded with e	ither the high	gh or low or	der bit of the	e source reg	ister.	o, and bit lo
Legend:							
R = Reada	able bit	VV = VV	ritable bit	U = Unin	nplemented	bit, read as	'0'
- n = Value	e at POR	'1' = Bi	t is set	'0' = Bit i	s cleared	x = Bit is u	nknown
	Reserved IRP bit 7 IRP: Regis 1 = Bank 2 0 = Bank 0 The IRP bit RP<1:0>: 01 = Bank 0 0 = Bank 0 I = After p 0 = A WD1 PD: Power 1 = After p 0 = By exee Z: Zero bit 1 = The re 0 = The re DC: Digit c is reversed 1 = A carry 0 = No car C: Carry/b 1 = A carry 0 = No car Note: Legend: R = Reada - n = Value	ReservedReservedIRPRP1bit 7IRP: Register Bank Sele1 = Bank 2, 3 (100h - 1f0 = Bank 0, 1 (00h - FFIThe IRP bit is reservedRP<1:0>: Register Bank01 = Bank 1 (80h - FFh)00 = Bank 0 (00h - 7Fh)Each bank is 128 bytes.clear.TO: Time-out bit1 = After power-up, CLR0 = A WDT time-out occPD: Power-down bit1 = After power-up or by0 = By execution of theZ: Zero bit1 = The result of an arith0 = The result of an arith0 = The result of an arith0 = No carry-out from the0 = No carry-out from	ReservedRevolR/W-0IRPRP1RP0bit 7IRP: Register Bank Select bit (used1 = Bank 2, 3 (100h - 1FFh)0 = Bank 0, 1 (00h - FFh)The IRP bit is reserved on the PIC? RP<1:0> : Register Bank Select bits01 = Bank 1 (80h - FFh)00 = Bank 0 (00h - 7Fh)Each bank is 128 bytes. The RP1 bitclear. TO : Time-out bit1 = After power-up, CLRWDT instruct0 = A WDT time-out occurred PD : Power-down bit1 = After power-up or by the CLRWD0 = By execution of the SLEEP inst Z : Zero bit1 = The result of an arithmetic or lo0 = The result of an arithmetic or lo0 = The result of an arithmetic or lo0 = C: Digit carry/borrow bit (ADDWF, is reversed)1 = A carry-out from the 4th low or0 = No carry-out from the Most Signi0 = No carry-out from the Most Signi <td>Reserved R/W-0 R-1 IRP RP1 RP0 TO bit 7 IRP: Register Bank Select bit (used for indirect 1 = Bank 2, 3 (100h - 1FFh) 0 = Bank 0, 1 (00h - FFh) The IRP bit is reserved on the PIC16C62X; alw RP<1:0>: Register Bank Select bits (used for d 01 = Bank 1 (80h - FFh) 00 = Bank 0 (00h - 7Fh) Each bank is 128 bytes. The RP1 bit is reserved clear. TO: Time-out bit 1 = After power-up, CLRWDT instruction, or SLE 0 = A WDT time-out occurred PD: Power-down bit 1 = After power-up or by the CLRWDT instruction 2: Zero bit 1 = The result of an arithmetic or logic operation DC: Digit carry/borrow bit (ADDWF, ADDLW, SUD is reversed) 1 = A carry-out from the 4th low order bit of the 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Mo</td> <td>Reserved Revol R-1 R-1 R-1 IRP RP1 RP0 TO PD bit 7 IRP: Register Bank Select bit (used for indirect addressing 1 = Bank 2, 3 (100h - 1FFh) 0 = Bank 0, 1 (00h - FFh) The IRP bit is reserved on the PIC16C62X; always maintait RP<1:0>: Register Bank Select bits (used for direct address 01 = Bank 1 (80h - FFh) 00 = Bank 0 (00h - 7Fh) Each bank is 128 bytes. The RP1 bit is reserved on the PIC clear. TO: Time-out bit 1 = After power-up, CLRWDT instruction, or SLEEP instruction 0 = A WDT time-out occurred PD: Power-down bit 1 = After power-up or by the CLRWDT instruction 0 = By execution of the SLEEP instruction 2: Zero bit 1 = The result of an arithmetic or logic operation is zero 0 = The result of an arithmetic or logic operation is not zero DC: Digit carry/borrow bit (ADDWF, ADDLW, SUBLW, SUBWF is reversed) 1 = A carry-out from the 4th low order bit of the result occur 0 = No carry-out from the Most Significant bit of the result of 0 = No carry-out from the Most Significant bit of the result of 0 = No carry-out from the Most Significant bit of the result of 0 = No carry-out from the Most Significant bit of the result of 0 = No carry-out from the Most Significant bit of the result of 0 = No carry-out from the Most Significant bit of the result of 0 = No carry-out from the Most Significant bit of the result of 0 = No carry-out from the Most Significant bit of the result of 0 =</td> <td>Reserved Reserved R/W-0 R-1 R-1 R/W-x IRP RP1 RP0 TO PD Z bit 7 IRP: Register Bank Select bit (used for indirect addressing) 1 = Bank 2, 3 (100h - 1FFh) 0 = Bank 0, 1 (00h - FFh) The IRP bit is reserved on the PIC16C62X; always maintain this bit cle RP<1:0>: Register Bank Select bits (used for direct addressing) 01 = Bank 1 (80h - FFh) 0 = Bank 0 (00h - 7Fh) Each bank is 128 bytes. The RP1 bit is reserved on the PIC16C62X; a clear. TO: Time-out bit 1 = After power-up, CLRWDT instruction, or SLEEP instruction 0 = A WDT time-out occurred PD: Power-down bit 1 = After power-up or by the CLRWDT instruction 0 = By execution of the SLEEP instruction 2: Zero bit 1 = The result of an arithmetic or logic operation is zero 0 = The result of an arithmetic or logic operation is not zero DC: Digit carry/borrow bit (ADDWF, ADDLW, SUBLW, SUBWF instructions) 1 = A carry-out from the 4th low order bit of the result C: Carry/borrow bit (ADDWF, ADDLW, SUBLW, SUBWF instructions) 1 = A carry-out from the Most Significant bit of the result occurred 0 = No carry-out from the</td> <td>Reserved Reserved R/W-0 R-1 R-1 R/W-x R/W-x IRP RP1 RP0 TO PD Z DC bit 7 IRP: Register Bank Select bit (used for indirect addressing) 1 Bank 2, 3 (100h - 1FFh) 0 Bank 0, 1 (00h - FFh) The IRP bit is reserved on the PIC16C62X; always maintain this bit clear. RP<1:0>: Register Bank Select bits (used for direct addressing) 01 = Bank 1 (80h - FFh) 00 Bank 0 (00h - 7Fh) Each bank is 128 bytes. The RP1 bit is reserved on the PIC16C62X; always maintain thicear. TO: Time-out bit 1 After power-up, CLRWDT instruction, or SLEEP instruction 0 0 = A WDT time-out occurred PD: Power-down bit 1 1 = After power-up or by the CLRWDT instruction 0 = By execution of the SLEEP instruction 2: Zero bit 1 The result of an arithmetic or logic operation is zero 0 1 = The result of an arithmetic or logic operation is not zero DC DC D: Digit carry/borrow bit (ADDWF, ADDLW, SUBLW, SUBWF instructions)(for borrow is reversed) 1 A carry-out from the 4th low order bit of the result occurred 0 No carry-out from the Most Significant bit of the result occurred <</td>	Reserved R/W-0 R-1 IRP RP1 RP0 TO bit 7 IRP: Register Bank Select bit (used for indirect 1 = Bank 2, 3 (100h - 1FFh) 0 = Bank 0, 1 (00h - FFh) The IRP bit is reserved on the PIC16C62X; alw RP<1:0>: Register Bank Select bits (used for d 01 = Bank 1 (80h - FFh) 00 = Bank 0 (00h - 7Fh) Each bank is 128 bytes. The RP1 bit is reserved clear. TO: Time-out bit 1 = After power-up, CLRWDT instruction, or SLE 0 = A WDT time-out occurred PD: Power-down bit 1 = After power-up or by the CLRWDT instruction 2: Zero bit 1 = The result of an arithmetic or logic operation DC: Digit carry/borrow bit (ADDWF, ADDLW, SUD is reversed) 1 = A carry-out from the 4th low order bit of the 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Most Significant bit of 0 = No carry-out from the Mo	Reserved Revol R-1 R-1 R-1 IRP RP1 RP0 TO PD bit 7 IRP: Register Bank Select bit (used for indirect addressing 1 = Bank 2, 3 (100h - 1FFh) 0 = Bank 0, 1 (00h - FFh) The IRP bit is reserved on the PIC16C62X; always maintait RP<1:0>: Register Bank Select bits (used for direct address 01 = Bank 1 (80h - FFh) 00 = Bank 0 (00h - 7Fh) Each bank is 128 bytes. The RP1 bit is reserved on the PIC clear. TO: Time-out bit 1 = After power-up, CLRWDT instruction, or SLEEP instruction 0 = A WDT time-out occurred PD: Power-down bit 1 = After power-up or by the CLRWDT instruction 0 = By execution of the SLEEP instruction 2: Zero bit 1 = The result of an arithmetic or logic operation is zero 0 = The result of an arithmetic or logic operation is not zero DC: Digit carry/borrow bit (ADDWF, ADDLW, SUBLW, SUBWF is reversed) 1 = A carry-out from the 4th low order bit of the result occur 0 = No carry-out from the Most Significant bit of the result of 0 = No carry-out from the Most Significant bit of the result of 0 = No carry-out from the Most Significant bit of the result of 0 = No carry-out from the Most Significant bit of the result of 0 = No carry-out from the Most Significant bit of the result of 0 = No carry-out from the Most Significant bit of the result of 0 = No carry-out from the Most Significant bit of the result of 0 = No carry-out from the Most Significant bit of the result of 0 =	Reserved Reserved R/W-0 R-1 R-1 R/W-x IRP RP1 RP0 TO PD Z bit 7 IRP: Register Bank Select bit (used for indirect addressing) 1 = Bank 2, 3 (100h - 1FFh) 0 = Bank 0, 1 (00h - FFh) The IRP bit is reserved on the PIC16C62X; always maintain this bit cle RP<1:0>: Register Bank Select bits (used for direct addressing) 01 = Bank 1 (80h - FFh) 0 = Bank 0 (00h - 7Fh) Each bank is 128 bytes. The RP1 bit is reserved on the PIC16C62X; a clear. TO: Time-out bit 1 = After power-up, CLRWDT instruction, or SLEEP instruction 0 = A WDT time-out occurred PD: Power-down bit 1 = After power-up or by the CLRWDT instruction 0 = By execution of the SLEEP instruction 2: Zero bit 1 = The result of an arithmetic or logic operation is zero 0 = The result of an arithmetic or logic operation is not zero DC: Digit carry/borrow bit (ADDWF, ADDLW, SUBLW, SUBWF instructions) 1 = A carry-out from the 4th low order bit of the result C: Carry/borrow bit (ADDWF, ADDLW, SUBLW, SUBWF instructions) 1 = A carry-out from the Most Significant bit of the result occurred 0 = No carry-out from the	Reserved Reserved R/W-0 R-1 R-1 R/W-x R/W-x IRP RP1 RP0 TO PD Z DC bit 7 IRP: Register Bank Select bit (used for indirect addressing) 1 Bank 2, 3 (100h - 1FFh) 0 Bank 0, 1 (00h - FFh) The IRP bit is reserved on the PIC16C62X; always maintain this bit clear. RP<1:0>: Register Bank Select bits (used for direct addressing) 01 = Bank 1 (80h - FFh) 00 Bank 0 (00h - 7Fh) Each bank is 128 bytes. The RP1 bit is reserved on the PIC16C62X; always maintain thicear. TO: Time-out bit 1 After power-up, CLRWDT instruction, or SLEEP instruction 0 0 = A WDT time-out occurred PD: Power-down bit 1 1 = After power-up or by the CLRWDT instruction 0 = By execution of the SLEEP instruction 2: Zero bit 1 The result of an arithmetic or logic operation is zero 0 1 = The result of an arithmetic or logic operation is not zero DC DC D: Digit carry/borrow bit (ADDWF, ADDLW, SUBLW, SUBWF instructions)(for borrow is reversed) 1 A carry-out from the 4th low order bit of the result occurred 0 No carry-out from the Most Significant bit of the result occurred <

4.2.2.3 INTCON Register

The INTCON register is a readable and writable register, which contains the various enable and flag bits for all interrupt sources except the comparator module. See Section 4.2.2.4 and Section 4.2.2.5 for a description of the comparator enable and flag bits.

Note: Interrupt flag bits get set when an interrupt condition occurs, regardless of the state of its corresponding enable bit or the global enable bit, GIE (INTCON<7>).

	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-x		
	GIE	PEIE	T0IE	INTE	RBIE	T0IF	INTF	RBIF		
	bit 7			<u>.</u>		<u>.</u>		bit 0		
bit 7	GIE: Globa	I Interrupt E	nable bit							
	1 = Enables	s all un-mas	sked interrup	ots						
1.11.0		s all interru	pts							
0 110	PEIE: Perip		upt Enable i	DIT 	-					
	1 = Enables 0 = Disable	s all un-mas	sked periphe eral interrun	eral interrupt	S					
bit 5		0 Overflow	Interrunt En	able bit						
bit o	1 = Enables	s the TMR0	interrupt							
	0 = Disable	s the TMR) interrupt							
bit 4	INTE: RB0/	INT Externa	al Interrupt E	Enable bit						
	1 = Enables	1 = Enables the RB0/INT external interrupt								
	0 = Disable	s the RB0/I	NT external	interrupt						
bit 3	RBIE: RB F	ort Change	Interrupt E	nable bit						
	1 = Enables	s the RB po	rt change in	iterrupt						
L:4 0			oft change in	iterrupi						
DIL ∠		J OVernow i		g Dit	- ared in coff	+				
	1 = TMR0 r 0 = TMR0 r	register did	not overflow	(ที่มีประ มีฮ มีฮ /	aleu ili son	ware				
bit 1	INTF: RB0/	INT Externa	al Interrupt F	-lag bit						
	1 = The RB	30/INT exter	nal interrup	t occurred (n	nust be clea	ared in softwa	are)			
	0 = The RB	30/INT exter	nal interrupt	t did not occ	ur					
bit 0	RBIF : RB F	ort Change	Interrupt Fl	lag bit						
	1 = When a	at least one	of the RB<7	':4> pins cha	anged state	(must be cle	ared in soft	ware)		
	0 = None o	f the RB<1	4> pins nave	e changea s	tate					
	Larandi									
	Legend:									

REGISTER 4-3:	INTCON REGISTER (ADDRESS 0BH OR 8BH)	

Legend:			
R = Readable bit	W = Writable bit	U = Unimplemented	bit, read as '0'
- n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown

6.0 TIMER0 MODULE

The Timer0 module timer/counter has the following features:

- 8-bit timer/counter
- · Readable and writable
- 8-bit software programmable prescaler
- · Internal or external clock select
- · Interrupt on overflow from FFh to 00h
- · Edge select for external clock

Figure 6-1 is a simplified block diagram of the Timer0 module.

Timer mode is selected by clearing the T0CS bit (OPTION<5>). In Timer mode, the TMR0 will increment every instruction cycle (without prescaler). If Timer0 is written, the increment is inhibited for the following two cycles (Figure 6-2 and Figure 6-3). The user can work around this by writing an adjusted value to TMR0.

Counter mode is selected by setting the T0CS bit. In this mode, Timer0 will increment either on every rising or falling edge of pin RA4/T0CKI. The incrementing edge is determined by the source edge (T0SE) control bit (OPTION<4>). Clearing the T0SE bit selects the rising edge. Restrictions on the external clock input are discussed in detail in Section 6.2.

The prescaler is shared between the Timer0 module and the Watchdog Timer. The prescaler assignment is controlled in software by the control bit PSA (OPTION<3>). Clearing the PSA bit will assign the prescaler to Timer0. The prescaler is not readable or writable. When the prescaler is assigned to the Timer0 module, prescale value of 1:2, 1:4, ..., 1:256 are selectable. Section 6.3 details the operation of the prescaler.

6.1 TIMER0 Interrupt

Timer0 interrupt is generated when the TMR0 register timer/counter overflows from FFh to 00h. This overflow sets the T0IF bit. The interrupt can be masked by clearing the T0IE bit (INTCON<5>). The T0IF bit (INTCON<2>) must be cleared in software by the Timer0 module interrupt service routine before reenabling this interrupt. The Timer0 interrupt cannot wake the processor from SLEEP, since the timer is shut off during SLEEP. See Figure 6-4 for Timer0 interrupt timing.



FIGURE 6-2: TIMER0 (TMR0) TIMING: INTERNAL CLOCK/NO PRESCALER

Counter)	(PC-1	X PC	(PC+1)	PC+2	PC+3	PC+4	<u>PC+5</u> χ	PC+6
Instruction Fetch	1 1 1	MOVWF TMR	0MOVF TMR0,V	MOVF TMR0,V	MOVF TMR0,W	MOVF TMR0,V	MOVF TMR0,W	I
TMR0	T0 X	T0+1)	T0+2	I	NT0		NT0+1 \	NT0+2 \
Instruction	1 1 1	1 1 1	≜	≜	1	≜	↑	≜
Executed	1	1	Write TMR0	Read TMR0	Read TMR0	Read TMR0	Read TMR0	Read TMR0

PIC16C62X









9.1 Configuration Bits

The configuration bits can be programmed (read as '0') or left unprogrammed (read as '1') to select various device configurations. These bits are mapped in program memory location 2007h.

The user will note that address 2007h is beyond the user program memory space. In fact, it belongs to the special test/configuration memory space (2000h - 3FFFh), which can be accessed only during programming.

REGISTER 9-1: CONFIGURATION WORD (ADDRESS 2007h)

CP1	CP0 (2)	CP1	CP0 (2)	CP1	CP0 (2)		BODEN	CP1	CP0 ⁽²⁾	PWRTE	WDTE	F0SC1	F0SC0
bit 13							Į		ļ		<u> </u>	ļ	bit 0
bit 13-8 5-4:	B, CP Cod 10 = 01 = 00 = Cod 11 = 10 = 01 = 00 =	CP<1:0>: Code protection bit pairs ⁽²⁾ Code protection for 2K program memory 11 = Program memory code protection off 10 = 0400h-07FFh code protected 01 = 0200h-07FFh code protected 00 = 0000h-07FFh code protected Code protection for 1K program memory 11 = Program memory code protection off 10 = Program memory code protection off 01 = 0200h-03FFh code protected 00 = 0000h-03FFh code protected											
	Cod 11 = 10 = 01 = 00 =	Code protection for 0.5K program memory 11 = Program memory code protection off 10 = Program memory code protection off 01 = Program memory code protection off 00 = 0000h-01FFh code protected											
bit 7	Uniı	npleme	e nted : Re	ead as 'C)'								
bit 6	BOI	DEN: Br	own-out	Reset E	nable bit	(1)							
	1 = 0 =	BOR en BOR dis	abled sabled										
bit 3	PWI 1 = 0 =	PWRTE : Power-up Timer Enable bit ^(1, 3) 1 = PWRT disabled 0 = PWRT enabled											
bit 2	WD 1 = ' 0 = '	WDTE: Watchdog Timer Enable bit 1 = WDT enabled 0 = WDT disabled											
bit 1-0	FOS	C1:FO	SCO: Oso	cillator S	election	bits							
	11 - 10 = 01 = 00 =	11 = RC oscillator 10 = HS oscillator 01 = XT oscillator 00 = LP oscillator											
	Note	e 1: Er va er 2: או	nabling B alue of bit nabled.	PWRTE	it Reset E. Ensur	automa e the Po we to be	itically ena ower-up Ti	bles Pov mer is e	wer-up T nabled a	imer (PWF nytime Bro	RT) rega own-out l	rdless of Detect R	the eset is
		lis 3: Ui	ited. nprogram	nmed pa	rts defai	ult the F	Power-up T	imer dis	abled.				
Logond	1.												
R = Re	ı. adable b	it		W = 1	Writable	bit	U =	Unimple	emented	bit, read a	s '0'		

TABLE 9-4: INITIALIZATION CONDITION FOR SPECIAL REGISTERS

Condition	Program Counter	STATUS Register	PCON Register
Power-on Reset	000h	0001 1xxx	0x
MCLR Reset during normal operation	000h	000u uuuu	uu
MCLR Reset during SLEEP	000h	0001 0uuu	uu
WDT Reset	000h	0000 uuuu	uu
WDT Wake-up	PC + 1	uuu0 0uuu	uu
Brown-out Reset	000h	000x xuuu	u0
Interrupt Wake-up from SLEEP	PC + 1 ⁽¹⁾	uuul 0uuu	uu

Legend: u = unchanged, x = unknown, - = unimplemented bit, reads as '0'.

Note 1: When the wake-up is due to an interrupt and global enable bit, GIE is set, the PC is loaded with the interrupt vector (0004h) after execution of PC+1.

Register	Address	Power-on Reset	MCLR Reset during normal operation MCLR Reset during SLEEP WDT Reset Brown-out Reset ⁽¹⁾	 Wake-up from SLEEP through interrupt Wake-up from SLEEP through WDT time-out
W		****		1111111 1111111
INDF	00h		_	_
TMR0	01h	xxxx xxxx	<u>uuuu</u> uuuu	<u>uuuu</u> uuuu
PCL	02h	0000 0000	0000 0000	PC + 1 ⁽³⁾
STATUS	03h	0001 1xxx	000q quuu ⁽⁴⁾	uuuq quuu ⁽⁴⁾
FSR	04h	xxxx xxxx	uuuu uuuu	uuuu uuuu
PORTA	05h	x xxxx	u uuuu	u uuuu
PORTB	06h	xxxx xxxx	uuuu uuuu	uuuu uuuu
CMCON	1Fh	00 0000	00 0000	uu uuuu
PCLATH	0Ah	0 0000	0 0000	u uuuu
INTCON	0Bh	0000 000x	0000 000u	uuuu uqqq ⁽²⁾
PIR1	0Ch	-0	-0	-q (2,5)
OPTION	81h	1111 1111	1111 1111	սսսս սսսս
TRISA	85h	1 1111	1 1111	u uuuu
TRISB	86h	1111 1111	1111 1111	սսսս սսսս
PIE1	8Ch	-0	-0	-u
PCON	8Eh	0x	uq ^(1,6)	uu
VRCON	9Fh	000- 0000	000- 0000	uuu- uuuu

TABLE 9-5: INITIALIZATION CONDITION FOR REGISTERS

 $\label{eq:legend: u = unchanged, x = unknown, - = unimplemented bit, reads as `0', q = value depends on condition.$

Note 1: If VDD goes too low, Power-on Reset will be activated and registers will be affected differently.

2: One or more bits in INTCON, PIR1 and/or PIR2 will be affected (to cause wake-up).

3: When the wake-up is due to an interrupt and the GIE bit is set, the PC is loaded with the interrupt vector (0004h).

4: See Table 9-4 for RESET value for specific condition.

5: If wake-up was due to comparator input changing, then bit 6 = 1. All other interrupts generating a wake-up will cause bit 6 = u.

6: If RESET was due to brown-out, then bit 0 = 0. All other RESETS will cause bit 0 = u.

10.0 INSTRUCTION SET SUMMARY

Each PIC16C62X instruction is a 14-bit word divided into an OPCODE which specifies the instruction type and one or more operands which further specify the operation of the instruction. The PIC16C62X instruction set summary in Table 10-2 lists **byte-oriented**, **bitoriented**, and **literal and control** operations. Table 10-1 shows the opcode field descriptions.

For **byte-oriented** instructions, 'f' represents a file register designator and 'd' represents a destination designator. The file register designator specifies which file register is to be used by the instruction.

The destination designator specifies where the result of the operation is to be placed. If 'd' is zero, the result is placed in the W register. If 'd' is one, the result is placed in the file register specified in the instruction.

For **bit-oriented** instructions, 'b' represents a bit field designator which selects the number of the bit affected by the operation, while 'f' represents the number of the file in which the bit is located.

For **literal and control** operations, 'k' represents an eight or eleven bit constant or literal value.

TABLE 10-1: OPCODE FIELD DESCRIPTIONS

Field	Description
f	Register file address (0x00 to 0x7F)
W	Working register (accumulator)
b	Bit address within an 8-bit file register
k	Literal field, constant data or label
х	Don't care location (= 0 or 1) The assembler will generate code with $x = 0$. It is the recommended form of use for compatibility with all Microchip software tools.
d	Destination select; d = 0: store result in W, d = 1: store result in file register f. Default is d = 1
label	Label name
TOS	Top of Stack
PC	Program Counter
PCLAT H	Program Counter High Latch
GIE	Global Interrupt Enable bit
WDT	Watchdog Timer/Counter
то	Time-out bit
PD	Power-down bit
dest	Destination either the W register or the specified register file location
[]	Options
()	Contents
\rightarrow	Assigned to
<>	Register bit field
∈	In the set of
italics	User defined term (font is courier)

The instruction set is highly orthogonal and is grouped into three basic categories:

- · Byte-oriented operations
- **Bit-oriented** operations
- Literal and control operations

All instructions are executed within one single instruction cycle, unless a conditional test is true or the program counter is changed as a result of an instruction. In this case, the execution takes two instruction cycles with the second cycle executed as a NOP. One instruction cycle consists of four oscillator periods. Thus, for an oscillator frequency of 4 MHz, the normal instruction execution time is 1 μ s. If a conditional test is true or the program counter is changed as a result of an instruction, the instruction execution time is 2 μ s.

Table 10-1 lists the instructions recognized by the MPASM $^{\rm TM}$ assembler.

Figure 10-1 shows the three general formats that the instructions can have.

Note:	To maintain upward compatibility with
	future PICmicro [®] products, <u>do not use</u> the
	OPTION and TRIS instructions.

All examples use the following format to represent a hexadecimal number:

0xhh

where h signifies a hexadecimal digit.

FIGURE 10-1: GENERAL FORMAT FOR INSTRUCTIONS



10.1 Instruction Descriptions

ADDLW	Add Literal and W							
Syntax:	[<i>label</i>] ADDLW k							
Operands:	$0 \leq k \leq 255$							
Operation:	$(W) + k \to (W)$							
Status Affected:	C, DC, Z							
Encoding:	11 111x kkkk kkkk							
Description:	added to the eight bit literal 'k' and the result is placed in the W register.							
Cycles:	1							
Example	ADDLW 0x15							
	Before Instruction W = 0x10 After Instruction W = 0x25							

ANDLW	AND Literal with W						
Syntax:	[<i>label</i>] ANDLW k						
Operands:	$0 \le k \le 255$						
Operation:	(W) .AND. (k) \rightarrow (W)						
Status Affected:	Z						
Encoding:	11 1001 kkkk kkkk						
Description:	The contents of W register are AND'ed with the eight bit literal 'k'. The result is placed in the W register.						
Words:	1						
Cycles:	1						
Example	ANDLW 0x5F						
	Before Instruction W = 0xA3 After Instruction W = 0x03						
ANDWF	AND W with f						

ADDWF	Add W and f							
Syntax:	[<i>label</i>] ADDWF f,d							
Operands:	$\begin{array}{l} 0 \leq f \leq 127 \\ d \in [0,1] \end{array}$							
Operation:	$(W) + (f) \rightarrow (dest)$							
Status Affected:	C, DC, Z							
Encoding:	00 0111 dfff ffff							
Description:	Add the contents of the W register with register 'f'. If 'd' is 0, the result is stored in the W register. If 'd' is 1, the result is stored back in register 'f'.							
Words:	1							
Cycles:	1							
Example	ADDWF FSR, O							
	Before Instruction W = 0x17 FSR = 0xC2 After Instruction W = 0xD9 FSR = 0xC2							

ANDWF	AND W with f						
Syntax:	[<i>label</i>] ANDWF f,d						
Operands:	$\begin{array}{l} 0 \leq f \leq 127 \\ d \in [0,1] \end{array}$						
Operation:	(W) .AND. (f) \rightarrow (dest)						
Status Affected:	Z						
Encoding:	00 0101 dfff ffff						
Description:	AND the W register with register 'f'. If 'd' is 0, the result is stored in the W register. If 'd' is 1, the result is stored back in register 'f'.						
Words:	1						
Cycles:	1						
Example	ANDWF FSR, 1						
	Before Instruction W = 0x17 FSR = 0xC2 After Instruction W = 0x17 FSR = 0x02						

BTFSS	Bit Test f, Skip if Set	CALL	Call Subroutine
Syntax:	[<i>label</i>]BTFSS f,b	Syntax:	[<i>label</i>] CALL k
Operands:	$0 \leq f \leq 127$	Operands:	$0 \le k \le 2047$
Operation:	0 ≤ b < 7 skip if (f) = 1	Operation:	(PC)+ 1→ TOS, k → PC<10:0>, (PCLATH<4:3>) → PC<12:11>
Encoding:		Status Affected:	None
Encouring.	If hit 'h' in register 'f is '1', then the	Encoding:	10 Okkk kkkk kkkk
Description.	next instruction is skipped. If bit 'b' is '1', then the next instruc- tion fetched during the current instruction execution, is discarded and a NOP is executed instead, making this a two-cycle instruction.	Description:	Call Subroutine. First, return address (PC+1) is pushed onto the stack. The eleven bit immedi- ate address is loaded into PC bits <10:0>. The upper bits of the PC are loaded from PCLATH. CALL is
Words:	1		a two-cycle instruction.
Cycles:	1(2)	vvords:	1
Example	HERE BTFSS FLAG,1	Cycles:	2
	TRUE • DE	Example	HERE CALL THER E
	Before Instruction PC = address HERE After Instruction if FLAG<1> = 0, PC = address FALSE if FLAG<1> = 1, PC = address TRUE		PC = Address HERE After Instruction PC = Address THERE TOS = Address HERE+1
		CLRF	Clear f
		Syntax:	[<i>label</i>] CLRF f
		Operands:	$0 \le f \le 127$
		Operation:	$\begin{array}{l} 00h \rightarrow (f) \\ 1 \rightarrow Z \end{array}$
		Status Affected:	<u>Z</u>
		Encoding:	00 0001 1fff ffff
		Description:	The contents of register 'f' are cleared and the Z bit is set.
		Words:	1
		Cycles:	1
		Example	CLRF FLAG_REG
			Before Instruction FLAG_REG = 0x5A After Instruction FLAG_REG = 0x00 Z = 1

11.9 MPLAB ICE 2000 High Performance Universal In-Circuit Emulator

The MPLAB ICE 2000 universal in-circuit emulator is intended to provide the product development engineer with a complete microcontroller design tool set for PICmicro microcontrollers. Software control of the MPLAB ICE 2000 in-circuit emulator is advanced by the MPLAB Integrated Development Environment, which allows editing, building, downloading and source debugging from a single environment.

The MPLAB ICE 2000 is a full-featured emulator system with enhanced trace, trigger and data monitoring features. Interchangeable processor modules allow the system to be easily reconfigured for emulation of different processors. The universal architecture of the MPLAB ICE in-circuit emulator allows expansion to support new PICmicro microcontrollers.

The MPLAB ICE 2000 in-circuit emulator system has been designed as a real-time emulation system with advanced features that are typically found on more expensive development tools. The PC platform and Microsoft[®] Windows 32-bit operating system were chosen to best make these features available in a simple, unified application.

11.10 MPLAB ICE 4000 High Performance Universal In-Circuit Emulator

The MPLAB ICE 4000 universal in-circuit emulator is intended to provide the product development engineer with a complete microcontroller design tool set for highend PICmicro microcontrollers. Software control of the MPLAB ICE in-circuit emulator is provided by the MPLAB Integrated Development Environment, which allows editing, building, downloading and source debugging from a single environment.

The MPLAB ICD 4000 is a premium emulator system, providing the features of MPLAB ICE 2000, but with increased emulation memory and high speed performance for dsPIC30F and PIC18XXXX devices. Its advanced emulator features include complex triggering and timing, up to 2 Mb of emulation memory, and the ability to view variables in real-time.

The MPLAB ICE 4000 in-circuit emulator system has been designed as a real-time emulation system with advanced features that are typically found on more expensive development tools. The PC platform and Microsoft Windows 32-bit operating system were chosen to best make these features available in a simple, unified application.

11.11 MPLAB ICD 2 In-Circuit Debugger

Microchip's In-Circuit Debugger, MPLAB ICD 2, is a powerful, low cost, run-time development tool, connecting to the host PC via an RS-232 or high speed USB interface. This tool is based on the FLASH PICmicro MCUs and can be used to develop for these and other PICmicro microcontrollers. The MPLAB ICD 2 utilizes the in-circuit debugging capability built into the FLASH devices. This feature, along with Microchip's In-Circuit Serial Programming[™] (ICSP[™]) protocol, offers cost effective in-circuit FLASH debugging from the graphical user interface of the MPLAB Integrated Development Environment. This enables a designer to develop and debug source code by setting breakpoints, single-stepping and watching variables, CPU status and peripheral registers. Running at full speed enables testing hardware and applications in real-time. MPLAB ICD 2 also serves as a development programmer for selected PICmicro devices.

11.12 PRO MATE II Universal Device Programmer

The PRO MATE II is a universal, CE compliant device programmer with programmable voltage verification at VDDMIN and VDDMAX for maximum reliability. It features an LCD display for instructions and error messages and a modular detachable socket assembly to support various package types. In Stand-Alone mode, the PRO MATE II device programmer can read, verify, and program PICmicro devices without a PC connection. It can also set code protection in this mode.

11.13 PICSTART Plus Development Programmer

The PICSTART Plus development programmer is an easy-to-use, low cost, prototype programmer. It connects to the PC via a COM (RS-232) port. MPLAB Integrated Development Environment software makes using the programmer simple and efficient. The PICSTART Plus development programmer supports most PICmicro devices up to 40 pins. Larger pin count devices, such as the PIC16C92X and PIC17C76X, may be supported with an adapter socket. The PICSTART Plus development programmer is CE compliant.



FIGURE 12-4: PIC16C62XA VOLTAGE-FREQUENCY GRAPH, $-40^{\circ}C \le Ta \le 0^{\circ}C$, $+70^{\circ}C \le Ta \le +125^{\circ}C$



PIC16C62X







12.2 DC Characteristics: PIC16C62XA-04 (Commercial, Industrial, Extended) PIC16C62XA-20 (Commercial, Industrial, Extended) PIC16LC62XA-04 (Commercial, Industrial, Extended) (CONT.)

PIC16C62XA			$\begin{array}{l lllllllllllllllllllllllllllllllllll$						
PIC16LC62XA				dard O ating te	perati empera	ng Con ature -4 -4	$\begin{array}{ll} \mbox{ditions (unless otherwise stated)} \\ 10^{\circ}C &\leq TA \leq +85^{\circ}C \mbox{ for industrial and} \\ 0^{\circ}C &\leq TA \leq +70^{\circ}C \mbox{ for commercial and} \\ 0^{\circ}C &\leq TA \leq +125^{\circ}C \mbox{ for extended} \end{array}$		
Param. No.	Sym	Characteristic	Min	Тур†	Max	Units	Conditions		
D010	IDD	Supply Current ^(2, 4)	_	1.2 0.4	2.0 1.2	mA mA	Fosc = 4 MHz, VDD = 5.5V, WDT disabled, XT mode, (Note 4)* Fosc = 4 MHz, VDD = 3.0V, WDT disabled, XT mode (Note 4)*		
				1.0 4.0	2.0 6.0	mA mA	Fosc = 10 MHz, VDD = 3.0V, WDT dis- abled, HS mode, (Note 6) Fosc = 20 MHz, VDD = 4.5V, WDT dis-		
			-	4.0 35	7.0 70	mA μA	abled, HS mode Fosc = 20 MHz, VDD = 5.5V, WDT dis- abled*, HS mode Fosc = 32 kHz, VDD = 3.0V, WDT dis- abled. LP mode		
D010	IDD	Supply Current ⁽²⁾	_	1.2	2.0 1.1	mA mA	Fosc = 4 MHz, VDD = 5.5V, WDT disabled, XT mode, (Note 4)* Fosc = 4 MHz, VDD = 2.5V, WDT disabled, XT mode, (Note 4)		
			_	35	70	μA	Fosc = 32 kHz, VDD = 2.5V, WDT dis- abled, LP mode		
D020	IPD	Power-down Current ⁽³⁾	 		2.2 5.0 9.0 15	μΑ μΑ μΑ μΑ	VDD = 3.0V VDD = 4.5V* VDD = 5.5V VDD = 5.5V VDD = 5.5V Extended Temp.		
D020	IPD	Power-down Current ⁽³⁾	 	 	2.0 2.2 9.0 15	μΑ μΑ μΑ μΑ	VDD = 2.5V VDD = 3.0V* VDD = 5.5V VDD = 5.5V Extended Temp.		

These parameters are characterized but not tested.

† Data in "Typ" column is at 5V, 25°C unless otherwise stated. These parameters are for design guidance only and are not tested.

Note 1: This is the limit to which VDD can be lowered without losing RAM data.

2: The supply current is mainly a function of the operating voltage and frequency. Other factors such as I/O pin loading and switching rate, oscillator type, internal code execution pattern, and temperature also have an impact on the current consumption.

The test conditions for all IDD measurements in Active Operation mode are:

OSC1 = external square wave, from rail to rail; all I/O pins tri-stated, pulled to VDD,

MCLR = VDD; WDT enabled/disabled as specified.

3: The power-down current in SLEEP mode does not depend on the oscillator type. Power-down current is measured with the part in SLEEP mode, with all I/O pins in hi-impedance state and tied to VDD or Vss.

4: For RC osc configuration, current through REXT is not included. The current through the resistor can be estimated by the formula: Ir = VDD/2REXT (mA) with REXT in kΩ.

5: The ∆ current is the additional current consumed when this peripheral is enabled. This current should be added to the base IDD or IPD measurement.

6: Commercial temperature range only.

12.4 DC Characteristics: PIC16C62X/C62XA/CR62XA (Commercial, Industrial, Extended) PIC16LC62X/LC62XA/LCR62XA (Commercial, Industrial, Extended) (CONT.)

PIC16C62X/C62XA/CR62XA		$ \begin{array}{ c c c c c } \hline \textbf{Standard Operating Conditions (unless otherwise stated)} \\ \hline \textbf{Operating temperature} & -40^\circ \text{C} & \leq \text{TA} \leq +85^\circ \text{C} \text{ for industrial and} \\ & 0^\circ \text{C} & \leq \text{TA} \leq +70^\circ \text{C} \text{ for commercial and} \\ & -40^\circ \text{C} & \leq \text{TA} \leq +125^\circ \text{C} \text{ for extended} \\ \hline \end{array} $								
PIC16LC62X/LC62XA/LCR62XA			Standa Operat	$\begin{array}{llllllllllllllllllllllllllllllllllll$						
Param. No.	Sym	Characteristic	Min	Min Typ† Max Units Conditions						
	Vol	Output Low Voltage								
D080		I/O ports	_	_	0.6	V	IoL = 8.5 mA, VDD = 4.5V, -40° to +85°C			
			_	_	0.6	V	IOL = 7.0 mA, VDD = 4.5V, +125°C			
D083		OSC2/CLKOUT (RC only)	_	_	0.6	V	IOL = 1.6 mA, VDD = 4.5V, -40° to +85°C			
			_	_	0.6	V	IOL = 1.2 mA, VDD = 4.5V, +125°C			
	Vон	Output High Voltage ⁽³⁾								
D090		I/O ports (Except RA4)	VDD-0.7		_	v	IOH = -3.0 mA, VDD = 4.5V, -40° to +85°С			
			VDD-0.7		_	V	Іон = -2.5 mA, Vdd = 4.5V, +125°С			
D092		OSC2/CLKOUT (RC only)	VDD-0.7	_	_	V	IOH = -1.3 mA, VDD = 4.5V, -40° to +85°С			
			VDD-0.7	_	_	V	IOH = -1.0 mA, VDD = 4.5V, +125°С			
	Vон	Output High Voltage ⁽³⁾								
D090		I/O ports (Except RA4)	VDD-0.7	_	_	V	IOH = -3.0 mA, VDD = 4.5V, -40° to +85°C			
			VDD-0.7	_	_	V	IOH = -2.5 mA, VDD = 4.5V, +125°С			
D092		OSC2/CLKOUT (RC only)	VDD-0.7	—	-	V	IOH = -1.3 mA, VDD = 4.5V, -40° to +85°C			
			VDD-0.7		—	V	IOH = -1.0 mA, VDD = 4.5V, +125°C			
D150	Vod	Open-Drain High Voltage			10 8.5*	V	RA4 pin PIC16C62X, PIC16LC62X RA4 pin PIC16C62XA, PIC16LC62XA, PIC16CR62XA, PIC16LCR62XA			
D150	Vod	Open-Drain High Voltage			10 8.5*	V	RA4 pin PIC16C62X, PIC16LC62X RA4 pin PIC16C62XA, PIC16LC62XA, PIC16CR62XA, PIC16LCR62XA			
		Capacitive Loading Specs on Output Pins								
D100	COSC 2	OSC2 pin			15	pF	In XT, HS and LP modes when external clock used to drive OSC1.			
D101	Сю	All I/O pins/OSC2 (in RC mode)			50	pF				
		Capacitive Loading Specs on Output Pins								
D100	COSC 2	OSC2 pin			15	pF	In XT, HS and LP modes when external clock used to drive OSC1.			
D101	Сю	All I/O pins/OSC2 (in RC mode)			50	pF				

These parameters are characterized but not tested.

† Data in "Typ" column is at 5V, 25°C unless otherwise stated. These parameters are for design guidance only and are not tested.

Note 1: In RC oscillator configuration, the OSC1 pin is a Schmitt Trigger input. It is not recommended that the PIC16C62X(A) be driven with external clock in RC mode.

2: The leakage current on the MCLR pin is strongly dependent on applied voltage level. The specified levels represent normal operating conditions. Higher leakage current may be measured at different input voltages.

3: Negative current is defined as coming out of the pin.

*

13.0 DEVICE CHARACTERIZATION INFORMATION

The graphs and tables provided in this section are for design guidance and are not tested. In some graphs or tables, the data presented is outside specified operating range (e.g., outside specified VDD range). This is for information only and devices will operate properly only within the specified range.

The data presented in this section is a statistical summary of data collected on units from different lots over a period of time. "Typical" represents the mean of the distribution, while "max" or "min" represents (mean + 3σ) and (mean - 3σ) respectively, where σ is standard deviation.



FIGURE 13-1: IDD VS. FREQUENCY (XT MODE, VDD = 5.5V)

FIGURE 13-2: PIC16C622A IPD VS. VDD (WDT DISABLE)



© 2003 Microchip Technology Inc.

PIC16C62X

NOTES:

PRODUCT IDENTIFICATION SYSTEM

To order or obtain information, e.g., on pricing or delivery, refer to the factory or the listed sales office.

PART NO.	<u>-xx</u>	¥	<u>/xx</u>	xxx	E	xamples:
Device	Frequency Range	Temperature Range	Package	Pattern	a)	 PIC16C621A - 04/P 301 = Commercial temp PDIP package, 4 MHz, normal VDD limits, QT pattern #301.
Device Frequency Range	PIC16C6 PIC16C6 PIC16C6 PIC16LC PIC16LC PIC16LC PIC16LC PIC16LC PIC16CF PIC16CF PIC16CC PIC16LC 04 200 04 4 M 20 20 M	52X: VDD range 3.0 52X: VDD range 3.0 52XA: VDD range 3.0 52XA: VDD range 2.5 562XA: VDD range 2.5 572XA: VD range	/ to 6.0V DV to 6.0V (Tape DV to 5.5V OV to 5.5V (Taj SV to 6.0V .5V to 6.0V (Taj .5V to 5.5V 2.5V to 5.5V 2.5V to 5.5V 2.5V to 5.5V 2.5V to 5.5V 2.5V to 5.5V 2.0V to 5.5V a 2.0V to 5.5V (Taj .5V to 5.5V (Taj .5V to 5.5V .5V to 5.5V .2V to 5.5V .5V to 5.5V .2V to 5.5V to 5.5V .2V to 5.5V to 5.5V .2V to 5.5V to 5.5V .2V to 5.5V t	e and Reel) be and Reel) be and Reel) ape and Reel) ape and Reel) Tape and Reel))	 PIC16LC622- 04I/SO = Industrial temp., SOI package, 200 kHz, extended VDD limits.
emperature Range	e - = I = E =	0°C to +70°C -40°C to +85°C -40°C to +125°C				
Package	P = SO = SS = JW* =	PDIP SOIC (Gull Wing, SSOP (209 mil) Windowed CERD	, 300 mil body) NP			
Pattern	3-Digit Pa	attern Code for QTF	Optimize (blank otherwise)	se)		

* JW Devices are UV erasable and can be programmed to any device configuration. JW Devices meet the electrical requirement of each oscillator type.

Sales and Support

Data Sheets

Products supported by a preliminary Data Sheet may have an errata sheet describing minor operational differences and recommended workarounds. To determine if an errata sheet exists for a particular device, please contact one of the following:

- 1. Your local Microchip sales office
- 2. The Microchip Corporate Literature Center U.S. FAX: (480) 792-7277
- 3. The Microchip Worldwide Site (www.microchip.com)

Please specify which device, revision of silicon and Data Sheet (include Literature #) you are using.

New Customer Notification System

Register on our web site (www.microchip.com/cn) to receive the most current information on our products.