

#### Welcome to E-XFL.COM

#### What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

### Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

#### Details

÷ХГ

Product Status	Active
Core Processor	PIC
Core Size	16-Bit
Speed	32MHz
Connectivity	I <sup>2</sup> C, IrDA, LINbus, SPI, UART/USART
Peripherals	Brown-out Detect/Reset, HLVD, POR, PWM, WDT
Number of I/O	24
Program Memory Size	32KB (11K x 24)
Program Memory Type	FLASH
EEPROM Size	512 x 8
RAM Size	2K x 8
Voltage - Supply (Vcc/Vdd)	1.8V ~ 3.6V
Data Converters	A/D 13x12b
Oscillator Type	Internal
Operating Temperature	-40°C ~ 125°C (TA)
Mounting Type	Surface Mount
Package / Case	28-VQFN Exposed Pad
Supplier Device Package	28-QFN (6x6)
Purchase URL	https://www.e-xfl.com/product-detail/microchip-technology/pic24f32ka302-e-ml

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

# TABLE 1-3: PIC24FV32KA304 FAMILY PINOUT DESCRIPTIONS (CONTINUED)

			F					FV						
		Pin Number					Pin Number							
Function	20-Pin PDIP/ SSOP/ SOIC	28-Pin SPDIP/ SSOP/ SOIC	28-Pin QFN	44-Pin QFN/ TQFP	48-Pin UQFN	20-Pin PDIP/ SSOP/ SOIC	28-Pin SPDIP/ SSOP/ SOIC	28-Pin QFN	44-Pin QFN/ TQFP	48-Pin UQFN	I/O	Buffer	Description	
CTPLS	16	24	21	11	12	16	24	21	11	12	0	_	CTMU Pulse Output	
HLVDIN	15	23	20	10	11	15	23	20	10	11	I	ST	High/Low-Voltage Detect Input	
IC1	14	19	16	6	6	11	19	16	6	6	I	ST	Input Capture 1 Input	
IC2	13	18	15	5	5	13	18	15	5	5	I	ST	Input Capture 2 Input	
IC3	15	23	20	13	14	15	23	20	13	14	I	ST	Input Capture 3 Input	
INT0	11	16	13	43	47	11	16	13	43	47	I	ST	Interrupt 0 Input	
INT1	17	25	22	14	15	17	25	22	14	15	1	ST	Interrupt 1 Input	
INT2	14	20	17	7	7	15	23	20	10	11	1	ST	Interrupt 2 Input	
MCLR	1	1	26	18	19	1	1	26	18	19	1	ST	Master Clear (Device Reset) Input (active-low)	
OC1	14	20	17	7	7	11	16	13	43	47	0	_	Output Compare/PWM1 Output	
OC2	4	22	19	4	4	4	22	19	4	4	0	—	Output Compare/PWM2 Output	
OC3	5	21	18	12	13	5	21	18	12	13	0	_	Output Compare/PWM3 Output	
OCFA	17	25	22	14	15	17	25	22	14	15	0	_	Output Compare Fault A	
OFCB	16	24	21	32	35	16	24	21	32	35	0	_	Output Compare Fault B	
OSCI	7	9	6	30	33	7	9	6	30	33	I	ANA	Main Oscillator Input	
OSCO	8	10	7	31	34	8	10	7	31	34	0	ANA	Main Oscillator Output	
PGEC1	5	5	2	22	24	5	5	2	22	24	I/O	ST	ICSP™ Clock 1	
PCED1	4	4	1	21	23	4	4	1	21	23	I/O	ST	ICSP Data 1	
PGEC2	2	22	19	19	10	2	22	19	19	10	I/O	ST	ICSP Clock 2	
PGED2	3	21	18	8	9	3	21	18	8	9	I/O	ST	ICSP Data 2	
PGEC3	10	15	12	42	46	10	15	12	42	46	I/O	ST	ICSP Clock 3	
PGED3	9	14	11	41	45	9	14	11	41	45	I/O	ST	ICSP Data 3	

### REGISTER 3-2: CORCON: CPU CONTROL REGISTER

U-0	U-0	U-0	U-0	U-0	U-0	U-0	U-0
—	—	—	—	—	—	—	—
bit 15							bit 8

U-0	U-0	U-0	U-0	R/C-0, HSC	R/W-0	U-0	U-0
—	—		—	IPL3 <sup>(1)</sup>	PSV	—	—
bit 7							bit 0

Legend:	HSC = Hardware Settable/Clearable bit						
R = Readable bit	W = Writable bit	U = Unimplemented bit, read	d as '0'				
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown				

bit 15-4	Unimplemented: Read as '0'
bit 3	IPL3: CPU Interrupt Priority Level Status bit <sup>(1)</sup>
	<ul> <li>1 = CPU Interrupt Priority Level is greater than 7</li> <li>0 = CPU Interrupt Priority Level is 7 or less</li> </ul>
bit 2	PSV: Program Space Visibility in Data Space Enable bit
	1 = Program space is visible in data space
	0 = Program space is not visible in data space
bit 1-0	Unimplemented: Read as '0'

**Note 1:** User interrupts are disabled when IPL3 = 1.

# 3.3 Arithmetic Logic Unit (ALU)

The PIC24F ALU is 16 bits wide and is capable of addition, subtraction, bit shifts and logic operations. Unless otherwise mentioned, arithmetic operations are 2's complement in nature. Depending on the operation, the ALU may affect the values of the Carry (C), Zero (Z), Negative (N), Overflow (OV) and Digit Carry (DC) Status bits in the SR register. The C and DC Status bits operate as Borrow and Digit Borrow bits, respectively, for subtraction operations.

The ALU can perform 8-bit or 16-bit operations, depending on the mode of the instruction that is used. Data for the ALU operation can come from the W register array, or data memory, depending on the addressing mode of the instruction. Likewise, output data from the ALU can be written to the W register array or a data memory location.

The PIC24F CPU incorporates hardware support for both multiplication and division. This includes a dedicated hardware multiplier and support hardware division for 16-bit divisor.

### 3.3.1 MULTIPLIER

The ALU contains a high-speed, 17-bit x 17-bit multiplier. It supports unsigned, signed or mixed sign operation in several multiplication modes:

- 16-bit x 16-bit signed
- 16-bit x 16-bit unsigned
- 16-bit signed x 5-bit (literal) unsigned
- 16-bit unsigned x 16-bit unsigned
- 16-bit unsigned x 5-bit (literal) unsigned
- 16-bit unsigned x 16-bit signed
- 8-bit unsigned x 8-bit unsigned

# 3.3.2 DIVIDER

The divide block supports 32-bit/16-bit and 16-bit/16-bit signed and unsigned integer divide operations with the following data sizes:

- 1. 32-bit signed/16-bit signed divide
- 2. 32-bit unsigned/16-bit unsigned divide
- 3. 16-bit signed/16-bit signed divide
- 4. 16-bit unsigned/16-bit unsigned divide

The quotient for all divide instructions ends up in W0 and the remainder in W1. Sixteen-bit signed and unsigned DIV instructions can specify any W register for both the 16-bit divisor (Wn), and any W register (aligned) pair (W(m + 1):Wm) for the 32-bit dividend. The divide algorithm takes one cycle per bit of divisor, so both 32-bit/16-bit and 16-bit/16-bit instructions take the same number of cycles to execute.

# 3.3.3 MULTI-BIT SHIFT SUPPORT

The PIC24F ALU supports both single bit and single-cycle, multi-bit arithmetic and logic shifts. Multi-bit shifts are implemented using a shifter block, capable of performing up to a 15-bit arithmetic right shift, or up to a 15-bit left shift, in a single cycle. All multi-bit shift instructions only support Register Direct Addressing for both the operand source and result destination.

A full summary of instructions that use the shift operation is provided in Table 3-2.

# TABLE 3-2: INSTRUCTIONS THAT USE THE SINGLE AND MULTI-BIT SHIFT OPERATION

Instruction	Description
ASR	Arithmetic shift right source register by one or more bits.
SL	Shift left source register by one or more bits.
LSR	Logical shift right source register by one or more bits.

### 4.2.2 DATA MEMORY ORGANIZATION AND ALIGNMENT

To maintain backward compatibility with PIC<sup>®</sup> MCU devices and improve data space memory usage efficiency, the PIC24F instruction set supports both word and byte operations. As a consequence of byte accessibility, all Effective Address (EA) calculations are internally scaled to step through word-aligned memory. For example, the core recognizes that Post-Modified Register Indirect Addressing mode [Ws++] will result in a value of Ws + 1 for byte operations and Ws + 2 for word operations.

Data byte reads will read the complete word, which contains the byte, using the LSB of any EA to determine which byte to select. The selected byte is placed onto the LSB of the data path. That is, data memory and the registers are organized as two parallel, byte-wide entities with shared (word) address decode, but separate write lines. Data byte writes only write to the corresponding side of the array or register, which matches the byte address.

All word accesses must be aligned to an even address. Misaligned word data fetches are not supported, so care must be taken when mixing byte and word operations, or translating from 8-bit MCU code. If a misaligned read or write is attempted, an address error trap will be generated. If the error occurred on a read, the instruction underway is completed; if it occurred on a write, the instruction will be executed, but the write will not occur. In either case, a trap is then executed, allowing the system and/or user to examine the machine state prior to execution of the address Fault.

All byte loads into any W register are loaded into the LSB; the MSB is not modified.

A Sign-Extend (SE) instruction is provided to allow the users to translate 8-bit signed data to 16-bit signed values. Alternatively, for 16-bit unsigned data, users

can clear the MSB of any W register by executing a Zero-Extend (ZE) instruction on the appropriate address.

Although most instructions are capable of operating on word or byte data sizes, it should be noted that some instructions operate only on words.

# 4.2.3 NEAR DATA SPACE

The 8-Kbyte area between 0000h and 1FFFh is referred to as the Near Data Space (NDS). Locations in this space are directly addressable via a 13-bit absolute address field within all memory direct instructions. The remainder of the data space is addressable indirectly. Additionally, the whole data space is addressable using MOV instructions, which support Memory Direct Addressing (MDA) with a 16-bit address field. For PIC24FV32KA304 family devices, the entire implemented data memory lies in Near Data Space.

# 4.2.4 SFR SPACE

The first 2 Kbytes of the Near Data Space, from 0000h to 07FFh, are primarily occupied with Special Function Registers (SFRs). These are used by the PIC24F core and peripheral modules for controlling the operation of the device.

SFRs are distributed among the modules that they control and are generally grouped together by the module. Much of the SFR space contains unused addresses; these are read as '0'. The SFR space, where the SFRs are actually implemented, is provided in Table 4-2. Each implemented area indicates a 32-byte region, where at least one address is implemented as an SFR. A complete listing of implemented SFRs, including their addresses, is provided in Table 4-3 through Table 4-25.

			SFR Space Ad	dress					
	xx00	xx20	xx40	xx60	xx80	xxA0	xxC0	xxE0	
000h		Cor	e	ICN	In	_			
100h	Tin	ners	Capture	—	Compare	_	—		
200h	l <sup>2</sup> C™	UART	SPI			_	I/O		
300h			A/D/CMTU		_	_	—	_	
400h	_	_	—	—	_	_	—	_	
500h	_	—	—	—		—	—	_	
600h	_	RTC/Comp	CRC						
700h		—	System/DS/HLVD	NVM/PMD	_	_	—	_	

# TABLE 4-2: IMPLEMENTED REGIONS OF SFR DATA SPACE

**Legend:** — = No implemented SFRs in this block.

# TABLE 4-3: CPU CORE REGISTERS MAP

File Name	Start Addr	Bit 15	Bit 14	Bit 13	Bit 12	Bit 11	Bit 10	Bit 9	Bit 8	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0	All Resets
WREG0	0000								WF	REG0								0000
WREG1	0002				WREG1										0000			
WREG2	0004				WREG2 0										0000			
WREG3	0006								WF	REG3								0000
WREG4	8000				WREG4 00										0000			
WREG5	000A								WF	REG5								0000
WREG6	000C								WF	REG6								0000
WREG7	000E								WF	REG7								0000
WREG8	0010								WF	REG8								0000
WREG9	0012								WF	REG9								0000
WREG10	0014								WR	EG10								0000
WREG11	0016								WR	EG11								0000
WREG12	0018								WR	EG12								0000
WREG13	001A								WR	EG13								0000
WREG14	001C								WR	EG14								0000
WREG15	001E								WR	EG15								0000
SPLIM	0020								SI	PLIM								XXXX
PCL	002E								F	PCL								0000
PCH	0030	_	—	—	—	—	—	_	_	_				PCH				0000
TBLPAG	0032	_	—	—	—	_	—	_	_				TBI	LPAG				0000
PSVPAG	0034	_	—	—	—	_	—	_	_				PS	VPAG				0000
RCOUNT	0036								RC	OUNT								XXXXX
SR	0042	_	—	_	—		—	—	DC	IPL2	IPL1	IPL0	RA	Ν	OV	Z	С	0000
CORCON	0044	—	—	—	_	—	—	—	—	—	—	—	—	IPL3	PSV	—	—	0000
DISICNT	0052	_	—							DISIC	NT							XXXX

DS39995D-page 39

Legend: — = unimplemented, read as '0'. Reset values are shown in hexadecimal.

# EXAMPLE 5-4: LOADING THE WRITE BUFFERS – 'C' LANGUAGE CODE

```
// C example using MPLAB C30
   #define NUM INSTRUCTION PER ROW 64
  int __attribute__ ((space(auto_psv))) progAddr = 0x1234; // Global variable located in Pgm Memory
  unsigned int offset;
  unsigned int i;
  unsigned int progData[2*NUM INSTRUCTION PER ROW]; // Buffer of data to write
  //Set up NVMCON for row programming
  NVMCON = 0 \times 4001;
                                                               // Initialize NVMCON
  //Set up pointer to the first memory location to be written
  TBLPAG = __builtin_tblpage(&progAddr); // Initialize PM Page Boundary SFR
offset = __builtin_tbloffset(&progAddr); // Initialize lower word of address
  offset = __builtin_tbloffset(&progAddr);
                                                             // Initialize lower word of address
  //Perform TBLWT instructions to write necessary number of latches
  for(i=0; i < 2*NUM INSTRUCTION PER ROW; i++)</pre>
   {
      __builtin_tblwtl(offset, progData[i++]);
                                                              // Write to address low word
       __builtin_tblwth(offset, progData[i]);
                                                               // Write to upper byte
       offset = offset + 2;
                                                               // Increment address
   }
```

# EXAMPLE 5-5: INITIATING A PROGRAMMING SEQUENCE – ASSEMBLY LANGUAGE CODE

DISI	#5	; Block all interrupts
		for next 5 instructions
MOV	#0x55, W0	
MOV	W0, NVMKEY	; Write the 55 key
MOV	#0xAA, W1	;
MOV	W1, NVMKEY	; Write the AA key
BSET	NVMCON, #WR	; Start the erase sequence
NOP		; 2 NOPs required after setting WR
NOP		;
BTSC	NVMCON, #15	; Wait for the sequence to be completed
BRA	\$-2	;

### EXAMPLE 5-6: INITIATING A PROGRAMMING SEQUENCE – 'C' LANGUAGE CODE

// C example using MPLAB C30	
asm("DISI #5");	<pre>// Block all interrupts for next 5 instructions</pre>
builtin_write_NVM();	// Perform unlock sequence and set WR

REGISTER	14-1: ICxC	ON1: INPUT	CAPTURE x	CONTROL R	EGISTER 1						
U-0	U-0	R/W-0	R/W-0	R/W-0	R/W-0	U-0	U-0				
_	—	ICSIDL	ICTSEL2	ICTSEL1	ICTSEL0		—				
bit 15							bit 8				
U-0	R/W-0	R/W-0	R-0 HSC	R-0 HSC	R/W-0	R/W-0	R/W-0				
	ICI1	ICIO	ICOV	ICBNE	ICM2	ICM1	ICM0				
bit 7							bit 0				
Legend:		HSC = Hardv	vare Settable/C	learable bit							
R = Readab	le bit	W = Writable	bit	U = Unimplem	nented bit, read	as '0'					
-n = Value a	t POR	'1' = Bit is set		'0' = Bit is clea	ared	x = Bit is unkn	iown				
bit 15-14	Unimplemer	nted: Read as '	0'								
bit 13	ICSIDL: Inpu	t Capture x Mo	dule Stop in Idl	e Control bit							
	1 = Input capture module halts in CPU Idle mode										
	0 = Input capture module continues to operate in CPU Idle mode										
bit 12-10	ICISEL<2:0>: Input Capture x Timer Select bits										
	111 = System clock (FOSC/2) $110 = Reserved$										
	101 = Reserved										
	100 = Timer1										
	011 = Timer5										
	010 = IImer4 001 = Timer2										
	000 = Timer	3									
bit 9-7	Unimplemer	ted: Read as '	0'								
bit 6-5	ICI<1:0>: Se	CI<1:0>: Select Number of Captures per Interrupt bits									
	11 = Interrupt on every fourth capture event										
	10 = Interrupt on every third capture event										
	01 = Interrupt on every second capture event										
hit 4		Canture x Over	flow Status Flag	n hit (read-only)	)						
	1 = Input cap	ture overflow o	ccurred		/						
	0 = No input	capture overflo	w occurred								
bit 3	ICBNE: Input	t Capture x Buf	fer Empty Statu	is bit (read-only	/)						
	1 = Input cap	ture buffer is no	ot empty, at lea	st one more ca	pture value can	be read					
	0 = Input cap	ture buffer is e	mpty								
bit 2-0	ICM<2:0>: In	put Capture M	ode Select bits				ia ia Olasa an				
	III = Interru Idle m	111 = Interrupt mode: Input capture functions as an interrupt pin only when the device is in Sleep or Idle mode (rising edge detect only all other control bits are not applicable)									
	110 = Unuse	ed (module disa	abled)								
	101 = Presc	aler Capture m	ode: Capture o	n every 16th ris	sing edge						
	100 = Presc	aler Capture m	ode: Capture o	n every 4th risi	ng edge						
	orr – Simbl		e. Capture on e	every namy edg							

- 010 = Simple Capture mode: Capture on every falling edge
- 001 = Edge Detect Capture mode: Capture on every edge (rising and falling); ICI<1:0 bits do not control interrupt generation for this mode
- 000 = Input capture module is turned off



### FIGURE 15-1: OUTPUT COMPARE x BLOCK DIAGRAM (16-BIT MODE)

### **REGISTER 15-1:** OCxCON1: OUTPUT COMPARE x CONTROL REGISTER 1 (CONTINUED)

### bit 2-0 OCM<2:0>: Output Compare x Mode Select bits<sup>(1)</sup>

- 111 = Center-Aligned PWM mode on OCx
  - 110 = Edge-Aligned PWM mode on OCx
  - 101 = Double Compare Continuous Pulse mode: Initialize OCx pin low; toggle OCx state continuously on alternate matches of OCxR and OCxRS
  - 100 = Double Compare Single-Shot mode: Initialize OCx pin low; toggle OCx state on matches of OCxR and OCxRS for one cycle
  - 011 = Single Compare Continuous Pulse mode: Compare events continuously toggle the OCx pin
  - 010 = Single Compare Single-Shot mode: Initialize OCx pin high; compare event forces the OCx pin low
  - 001 = Single Compare Single-Shot mode: Initialize OCx pin low, compare event forces the OCx pin high
  - 000 = Output compare channel is disabled
- **Note 1:** The comparator module used for Fault input varies with the OCx module. OC1 and OC2 use Comparator 1; OC3 and OC4 use Comparator 2; OC5 uses Comparator 3.

# 19.0 REAL-TIME CLOCK AND CALENDAR (RTCC)

Note: This data sheet summarizes the features of this group of PIC24F devices. It is not intended to be a comprehensive reference source. For more information on the Real-Time Clock and Calendar, refer to the "PIC24F Family Reference Manual", Section 29. "Real-Time Clock and Calendar (RTCC)" (DS39696).

The RTCC provides the user with a Real-Time Clock and Calendar (RTCC) function that can be calibrated.

Key features of the RTCC module are:

- Operates in Deep Sleep mode
- Selectable clock source
- Provides hours, minutes and seconds using 24-hour format
- · Visibility of one half second period
- Provides calendar weekday, date, month and year
- Alarm-configurable for half a second, one second, 10 seconds, one minute, 10 minutes, one hour, one day, one week, one month or one year
- · Alarm repeat with decrementing counter
- · Alarm with indefinite repeat chime
- · Year 2000 to 2099 leap year correction

- · BCD format for smaller software overhead
- Optimized for long-term battery operation
- User calibration of the 32.768 kHz clock crystal/32K INTRC frequency with periodic auto-adjust
- · Optimized for long-term battery operation
- · Fractional second synchronization
- Calibration to within ±2.64 seconds error per month
- · Calibrates up to 260 ppm of crystal error
- Ability to periodically wake-up external devices without CPU intervention (external power control)
- · Power control output for external circuit control
- · Calibration takes effect every 15 seconds
- · Runs from any one of the following:
  - External Real-Time Clock of 32.768 kHz
  - Internal 31.25 kHz LPRC Clock
  - 50 Hz or 60 Hz External Input

# 19.1 RTCC Source Clock

The user can select between the SOSC crystal oscillator, LPRC internal oscillator or an external 50 Hz/60 Hz power line input as the clock reference for the RTCC module. This gives the user an option to trade off system cost, accuracy and power consumption, based on the overall system needs.



# © 2011-2013 Microchip Technology Inc.

P/M/ 0	11-0	P/M/ 0	11-0	11-0	11-0	11-0	11-0
	0-0		0-0	0-0	0-0	0-0	0-0
hit 15		TIEGIDE					 bit 8
bit 15							5110
R/W-0	R/W-0	R/W-0	U-0	R/W-0	R/W-0	R/W-0	R/W-0
VDIR	BGVST	IRVST	_				
bit 7	20101						bit 0
Legend:							
R = Readable	e bit	W = Writable I	oit	U = Unimplem	nented bit, read	as '0'	
-n = Value at	POR	'1' = Bit is set		'0' = Bit is clea	ared	x = Bit is unkn	own
bit 15	HLVDEN: Hig	h/Low-Voltage	Detect Power	Enable bit			
	1 = HLVD is e	enabled					
	0 = HLVD is (	disabled					
bit 14	Unimplemen	ted: Read as '0	)' • • • • •				
bit 13	HLSIDL: HLV	D Stop in Idle N	Ade bit		1		
	1 = Discontin0 = Continue	iues module op s module opera	eration when d	levice enters id de	le mode		
bit 12-8	Unimplement	ted: Read as '(	)'				
bit 7	VDIR: Voltage	- Change Direc	tion Select bit				
	1 = Event occ	urs when voltage	ge equals or ex	ceeds trip poir	nt (HLVDL<3:0>	>)	
	0 = Event occ	urs when volta	ge equals or fa	lls below trip pe	pint (HLVDL<3:	0>)	
bit 6	BGVST: Band	d Gap Voltage S	Stable Flag bit				
	1 = Indicates	that the band g	ap voltage is s	table			
h:1 <b>F</b>		that the band g	ap voltage is u	nstable			
DIL 5	1 = Indicates	that the interna	al reference vo	ilag bit Itage is stable	and the high-ve	oltage detect lo	ogic generates
	the interr	upt flag at the s	pecified voltag	e range			gio generateo
	0 = Indicates	that the interna	al reference vo	ltage is unstab	le and the high	n-voltage detec	t logic will not
	generate	the interrupt fla	ag at the spec	ified voltage ra	nge, and the F	ILVD interrupt	should not be
hit 4	Unimplemen	ted: Read as '(	)'				
bit 3-0	HI VDI <3:0>:	High/Low-Volt	age Detection	l imit bits			
2.1.0.0	1111 = Exteri	nal analog inpu	t is used (input	comes from th	e HLVDIN pin)		
	1110 <b>= Trip P</b>	Point 1 <sup>(1)</sup>			. ,		
	1101 = Trip P	Point $2^{(1)}$					
	•	$raint 4 \pi(1)$					
		UNIT 15.7					

### REGISTER 21-1: HLVDCON: HIGH/LOW-VOLTAGE DETECT CONTROL REGISTER



# REGISTER 22-10: AD1CTMUENH: A/D CTMU ENABLE REGISTER (HIGH WORD)<sup>(1)</sup>

U-0	U-0	U-0	U-0	U-0	U-0	U-0	U-0
—	—	—	—	—	—	—	—
bit 15							bit 8
U-0	U-0	U-0	U-0	U-0	U-0	R/W-0	R/W-0
	—	—	—	—	—	CTMEN17	CTMEN16
bit 7							bit 0
Logondy							

Legena:			
R = Readable bit	W = Writable bit	U = Unimplemented bit, read	d as '0'
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown

bit 15-2 Unimplemented: Read as '0'.

bit 1-0 CTMEN<17:16>: CTMU Enabled During Conversion bits

1 = CTMU is enabled and connected to the selected channel during conversion0 = CTMU is not connected to this channel

Note 1: Unimplemented channels are read as '0'.

# REGISTER 22-11: AD1CTMUENL: A/D CTMU ENABLE REGISTER (LOW WORD)<sup>(1)</sup>

R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0
CTMEN15	CTMEN14	CTMEN13	CTMEN12	CTMUEN11	CTMEN10	CTMEN9	CTMEN8
bit 15							bit 8

| R/W-0  |
|--------|--------|--------|--------|--------|--------|--------|--------|
| CTMEN7 | CTMEN6 | CTMEN5 | CTMEN4 | CTMEN3 | CTMEN2 | CTMEN1 | CTMEN0 |
| bit 7  |        |        |        |        |        |        | bit 0  |

Legend:				
R = Readable bit	R = Readable bit W = Writable bit U = Unimplemented bit, read as '0'			
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown	

bit 15-0 CTMEN<15:0>: CTMU Enabled During Conversion bits

1 = CTMU is enabled and connected to the selected channel during conversion

0 = CTMU is not connected to this channel

Note 1: Unimplemented channels are read as '0'.

# FIGURE 25-1: TYPICAL CONNECTIONS AND INTERNAL CONFIGURATION FOR CAPACITANCE MEASUREMENT



# 25.2 Measuring Time

Time measurements on the pulse width can be similarly performed using the A/D module's Internal Capacitor (CAD) and a precision resistor for current calibration. Figure 25-2 displays the external connections used for time measurements, and how the CTMU and A/D modules are related in this application. This example also shows both edge events coming from the external CTEDx pins, but other configurations using internal edge sources are possible.

# FIGURE 25-2: TYPICAL CONNECTIONS AND INTERNAL CONFIGURATION FOR TIME MEASUREMENT



# 26.4 Deep Sleep Watchdog Timer (DSWDT)

In PIC24FV32KA304 family devices, in addition to the WDT module, a DSWDT module is present which runs while the device is in Deep Sleep, if enabled. It is driven by either the SOSC or LPRC oscillator. The clock source is selected by the Configuration bit, DSWDTOSC (FDS<4>).

The DSWDT can be configured to generate a time-out, at 2.1 ms to 25.7 days, by selecting the respective postscaler. The postscaler can be selected by the Configuration bits, DSWDTPS<3:0> (FDS<3:0>). When the DSWDT is enabled, the clock source is also enabled.

DSWDT is one of the sources that can wake-up the device from Deep Sleep mode.

# 26.5 Program Verification and Code Protection

For all devices in the PIC24FV32KA304 family, code protection for the boot segment is controlled by the Configuration bit, BSS0, and the general segment by the Configuration bit, GSS0. These bits inhibit external reads and writes to the program memory space This has no direct effect in normal execution mode.

Write protection is controlled by bit, BWRP, for the boot segment and bit, GWRP, for the general segment in the Configuration Word. When these bits are programmed to '0', internal write and erase operations to program memory are blocked.

# 26.6 In-Circuit Serial Programming

PIC24FV32KA304 family microcontrollers can be serially programmed while in the end application circuit. This is simply done with two lines for clock (PGECx) and data (PGEDx), and three other lines for power, ground and the programming voltage. This allows customers to manufacture boards with unprogrammed devices and then program the microcontroller just before shipping the product. This also allows the most recent firmware or a custom firmware to be programmed.

# 26.7 In-Circuit Debugger

When MPLAB<sup>®</sup> ICD 3, MPLAB REAL ICE<sup>™</sup> or PICkit<sup>™</sup> 3 is selected as a debugger, the in-circuit debugging functionality is enabled. This function allows simple debugging functions when used with MPLAB IDE. Debugging functionality is controlled through the PGECx and PGEDx pins.

To use the in-circuit debugger function of the device, the design must implement ICSP connections to  $\overline{MCLR}$ , VDD, VSS, PGECx, PGEDx and the pin pair. In addition, when the feature is enabled, some of the resources are not available for general use. These resources include the first 80 bytes of data RAM and two I/O pins.

# 28.0 INSTRUCTION SET SUMMARY

Note:	This chapter is a brief summary of the								
	PIC24F instruction set architecture and is								
	not intended to be a comprehensive								
	reference source.								

The PIC24F instruction set adds many enhancements to the previous PIC<sup>®</sup> MCU instruction sets, while maintaining an easy migration from previous PIC MCU instruction sets. Most instructions are a single program memory word. Only three instructions require two program memory locations.

Each single-word instruction is a 24-bit word divided into an 8-bit opcode, which specifies the instruction type and one or more operands, which further specify the operation of the instruction. The instruction set is highly orthogonal and is grouped into four basic categories:

- Word or byte-oriented operations
- Bit-oriented operations
- · Literal operations
- Control operations

Table 28-1 lists the general symbols used in describing the instructions. The PIC24F instruction set summary in Table 28-2 lists all the instructions, along with the status flags affected by each instruction.

Most word or byte-oriented W register instructions (including barrel shift instructions) have three operands:

- The first source operand, which is typically a register 'Wb' without any address modifier
- The second source operand, which is typically a register 'Ws' with or without an address modifier
- The destination of the result, which is typically a register 'Wd' with or without an address modifier

However, word or byte-oriented file register instructions have two operands:

- The file register specified by the value, 'f'
- The destination, which could either be the file register, 'f', or the W0 register, which is denoted as 'WREG'

Most bit-oriented instructions (including simple rotate/shift instructions) have two operands:

- The W register (with or without an address modifier) or file register (specified by the value of 'Ws' or 'f')
- The bit in the W register or file register (specified by a literal value or indirectly by the contents of register 'Wb')

The literal instructions that involve data movement may use some of the following operands:

- A literal value to be loaded into a W register or file register (specified by the value of 'k')
- The W register or file register where the literal value is to be loaded (specified by 'Wb' or 'f')

However, literal instructions that involve arithmetic or logical operations use some of the following operands:

- The first source operand, which is a register 'Wb' without any address modifier
- The second source operand, which is a literal value
- The destination of the result (only if not the same as the first source operand), which is typically a register 'Wd' with or without an address modifier

The control instructions may use some of the following operands:

- · A program memory address
- The mode of the table read and table write instructions

All instructions are a single word, except for certain double-word instructions, which were made double-word instructions so that all of the required information is available in these 48 bits. In the second word, the 8 MSbs are '0's. If this second word is executed as an instruction (by itself), it will execute as a NOP.

Most single-word instructions are executed in a single instruction cycle, unless a conditional test is true or the Program Counter (PC) is changed as a result of the instruction. In these cases, the execution takes two instruction cycles, with the additional instruction cycle(s) executed as a NOP. Notable exceptions are the BRA (unconditional/computed branch), indirect CALL/GOTO, all table reads and writes, and RETURN/RETFIE instructions, which are single-word instructions but take two or three cycles.

Certain instructions that involve skipping over the subsequent instruction require either two or three cycles if the skip is performed, depending on whether the instruction being skipped is a single-word or two-word instruction. Moreover, double-word moves require two cycles. The double-word instructions execute in two instruction cycles.

			Standard Operating Conditions: 1.8V to 3.6V PIC24F32KA3XX					
DC CH/	ARACT	ERISTICS	$\begin{array}{llllllllllllllllllllllllllllllllllll$					
Param No.	Sym	Characteristic	Min	Typ <sup>(1)</sup>	Мах	Units	Conditions	
	VIL	Input Low Voltage <sup>(4)</sup>						
DI10		I/O Pins	Vss	—	0.2 Vdd	V		
DI15		MCLR	Vss		0.2 Vdd	V		
DI16		OSCI (XT mode)	Vss	—	0.2 Vdd	V		
DI17		OSCI (HS mode)	Vss	—	0.2 Vdd	V		
DI18		I/O Pins with I <sup>2</sup> C™ Buffer	Vss	—	0.3 Vdd	V	SMBus is disabled	
DI19		I/O Pins with SMBus Buffer	Vss	—	0.8	V	SMBus is enabled	
	Vih	Input High Voltage <sup>(4)</sup>						
DI20		I/O Pins: with Analog Functions Digital Only	0.8 Vdd 0.8 Vdd		Vdd Vdd	V V		
DI25		MCLR	0.8 Vdd		Vdd	V		
DI26		OSCI (XT mode)	0.7 Vdd	—	Vdd	V		
DI27		OSCI (HS mode)	0.7 Vdd		Vdd	V		
DI28		I/O Pins with I <sup>2</sup> C Buffer: with Analog Functions Digital Only	0.7 Vdd 0.7 Vdd		Vdd Vdd	V V		
DI29		I/O Pins with SMBus	2.1		Vdd	V	$2.5V \le V\text{PIN} \le V\text{DD}$	
DI30	ICNPU	CNx Pull-up Current	50	250	500	μA	VDD = 3.3V, VPIN = VSS	
	lı∟	Input Leakage Current <sup>(2,3)</sup>						
D150		I/O Ports	_	0.05	0.1	μA	$Vss \le VPIN \le VDD$ , Pin at high-impedance	
DI55		MCLR	—	—	0.1	μA	$Vss \leq V \text{PIN} \leq V \text{DD}$	
DI56		OSCI	—		5	μΑ	$\label{eq:VSS} \begin{split} &V{\sf SS} \leq V{\sf PIN} \leq V{\sf DD}, \\ &X{\sf T} \text{ and }H{\sf S} \text{ modes} \end{split}$	

# TABLE 29-9: DC CHARACTERISTICS: I/O PIN INPUT SPECIFICATIONS

**Note 1:** Data in "Typ" column is at 3.3V, +25°C unless otherwise stated. Parameters are for design guidance only and are not tested.

2: The leakage current on the MCLR pin is strongly dependent on the applied voltage level. The specified levels represent normal operating conditions. Higher leakage current may be measured at different input voltages.

**3:** Negative current is defined as current sourced by the pin.

4: Refer to Table 1-3 for I/O pin buffer types.



#### FIGURE 29-22: A/D CONVERSION TIMING

2: This is a minimal RC delay (typically 100 ns) which also disconnects the holding capacitor from the analog input.

			Standard Operating Conditions:1.8V to 3.6V PIC24F32KA3XX2.0V to 5.5V PIC24FV32KA3XXOperating temperature $-40^{\circ}C \le TA \le +85^{\circ}C$ for Industrial $-40^{\circ}C \le TA \le +125^{\circ}C$ for Extended					
Param No.	Symbol	Characteristic	Min.	Тур	Max.	Units	Conditions	
		(	Clock Pa	rameter	s			
AD50	Tad	A/D Clock Period	600	—	—	ns	Tcy = 75 ns, AD1CON3 in default state	
AD51	TRC	A/D Internal RC Oscillator Period	-	1.67	—	μs		
			Convers	ion Rate	)			
AD55	TCONV	Conversion Time	_	12 14	_	Tad Tad	10-bit results 12-bit results	
AD56	FCNV	Throughput Rate			100	ksps		
AD57	TSAMP	Sample Time	_	1	_	Tad		
AD58	TACQ	Acquisition Time	750	—	—	ns	(Note 2)	
AD59	Tswc	Switching Time from Convert to Sample	-	-	(Note 3)			
AD60	TDIS	Discharge Time	12	_	—	TAD		
		(	Clock Pa	rameter	s			
AD61	TPSS	Sample Start Delay from Setting Sample bit (SAMP)	2	—	3	Tad		

# TABLE 29-41: A/D CONVERSION TIMING REQUIREMENTS<sup>(1)</sup>

**Note 1:** Because the sample caps will eventually lose charge, clock rates below 10 kHz can affect linearity performance, especially at elevated temperatures.

2: The time for the holding capacitor to acquire the "New" input voltage when the voltage changes full scale after the conversion (VDD to Vss or Vss to VDD).

**3:** On the following cycle of the device clock.



28-Lead Plastic Shrink Small Outline (SS) - 5.30 mm Body [SSOP]

**Note:** For the most current package drawings, please see the Microchip Packaging Specification located at http://www.microchip.com/packaging



	MILLIMETERS			
Dimension	MIN	NOM	MAX	
Contact Pitch	Е	0.65 BSC		
Contact Pad Spacing	С		7.20	
Contact Pad Width (X28)	X1			0.45
Contact Pad Length (X28)	Y1			1.75
Distance Between Pads	G	0.20		

Notes:

1. Dimensioning and tolerancing per ASME Y14.5M

BSC: Basic Dimension. Theoretically exact value shown without tolerances.

Microchip Technology Drawing No. C04-2073A

# 48-Lead Plastic Ultra Thin Quad Flat, No Lead Package (MV) – 6x6x0.5 mm Body [UQFN]

**Note:** For the most current package drawings, please see the Microchip Packaging Specification located at http://www.microchip.com/packaging



	Units	MILLIMETERS			
Dimensi	on Limits	MIN	NOM	MAX	
Number of Pins	Ν		48		
Pitch	е		0.40 BSC		
Overall Height	Α	0.45	0.50	0.55	
Standoff	A1	0.00	0.02	0.05	
Contact Thickness	A3	0.127 REF			
Overall Width	Е		6.00 BSC		
Exposed Pad Width	E2	4.45	4.60	4.75	
Overall Length	D	6.00 BSC			
Exposed Pad Length	D2	4.45	4.60	4.75	
Contact Width	b	0.15	0.20	0.25	
Contact Length	L	0.30	0.40	0.50	
Contact-to-Exposed Pad	K	0.20	-	-	

Notes:

1. Pin 1 visual index feature may vary, but must be located within the hatched area.

2. Package is saw singulated.

3. Dimensioning and tolerancing per ASME Y14.5M.

BSC: Basic Dimension. Theoretically exact value shown without tolerances. REF: Reference Dimension, usually without tolerance, for information purposes only.

Microchip Technology Drawing C04-153A Sheet 2 of 2