Welcome to E-XFL.COM

Understanding Embedded - FPGAs (Field Programmable Gate Array)

Embedded - FPGAs, or Field Programmable Gate Arrays, are advanced integrated circuits that offer unparalleled flexibility and performance for digital systems. Unlike traditional fixed-function logic devices, FPGAs can be programmed and reprogrammed to execute a wide array of logical operations, enabling customized functionality tailored to specific applications. This reprogrammability allows developers to iterate designs quickly and implement complex functions without the need for custom hardware.

Applications of Embedded - FPGAs

The versatility of Embedded - FPGAs makes them indispensable in numerous fields. In telecommunications.

Details	
Product Status	Active
Number of LABs/CLBs	98520
Number of Logic Elements/Cells	1724100
Total RAM Bits	260812800
Number of I/O	702
Number of Gates	-
Voltage - Supply	0.873V ~ 0.927V
Mounting Type	Surface Mount
Operating Temperature	0°C ~ 100°C (TJ)
Package / Case	2104-BBGA, FCBGA
Supplier Device Package	2104-FCBGA (47.5x47.5)
Purchase URL	https://www.e-xfl.com/product-detail/xilinx/xcvu7p-3flvb2104e

Recommended Operating Conditions

Table 2: **Recommended Operating Conditions(1)(2)**

Symbol	Description	Min	Typ	Max	Units
FPGA Logic					
V_{CCINT}	Internal supply voltage.	0.825	0.850	0.876	V
	For -2LE (V_{CCINT} = 0.72V) devices: internal supply voltage.	0.698	0.720	0.742	V
	For -3E devices: internal supply voltage.	0.873	0.900	0.927	V
V_{CCINT_IO}(3)	Internal supply voltage for the I/O banks.	0.825	0.850	0.876	V
	For -2LE devices (V_{CCINT} = 0.85V): internal supply voltage for the I/O banks.	0.825	0.850	0.876	V
	For -3E devices: internal supply voltage for the I/O banks.	0.873	0.900	0.927	V
V_{CCBRAM}	Block RAM supply voltage.	0.825	0.850	0.876	V
	For -3E devices: block RAM supply voltage.	0.873	0.900	0.927	V
V_{CCAUX}	Auxiliary supply voltage.	1.746	1.800	1.854	V
V_{CCO}(4)(5)	Supply voltage for I/O banks.	0.950	–	1.900	V
V_{CCAUX_IO}(6)	Auxiliary I/O supply voltage.	1.746	1.800	1.854	V
V_{IN}(7)	I/O input voltage.	–0.200	–	V_{CCO} + 0.200	V
I_{IN}(8)	Maximum current through any pin in a powered or unpowered bank when forward biasing the clamp diode.	–	–	10	mA
V_{BATT}(9)	Battery voltage.	1.000	–	1.890	V
GTY Transceiver					
$V_{MGTAVCC}$(10)	Analog supply voltage for the GTY transceiver.	0.873	0.900	0.927	V
$V_{MGTAVTT}$(10)	Analog supply voltage for the GTY transmitter and receiver termination circuits.	1.164	1.20	1.236	V
$V_{MGTVCCAUX}$(10)	Auxiliary analog QPLL voltage supply for the transceivers.	1.746	1.80	1.854	V
$V_{MGTAVTTRCAL}$(10)	Analog supply voltage for the resistor calibration circuit of the GTY transceiver column.	1.164	1.20	1.236	V