



Welcome to [E·XFL.COM](https://www.e-xfl.com)

## Understanding [Embedded - CPLDs \(Complex Programmable Logic Devices\)](#)

Embedded - CPLDs, or Complex Programmable Logic Devices, are highly versatile digital logic devices used in electronic systems. These programmable components are designed to perform complex logical operations and can be customized for specific applications. Unlike fixed-function ICs, CPLDs offer the flexibility to reprogram their configuration, making them an ideal choice for various embedded systems. They consist of a set of logic gates and programmable interconnects, allowing designers to implement complex logic circuits without needing custom hardware.

## Applications of Embedded - CPLDs

### Details

|                                 |                                                                                                                                                                       |
|---------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Product Status                  | Obsolete                                                                                                                                                              |
| Programmable Type               | In System Programmable                                                                                                                                                |
| Delay Time tpd(1) Max           | 10 ns                                                                                                                                                                 |
| Voltage Supply - Internal       | 3V ~ 3.6V                                                                                                                                                             |
| Number of Logic Elements/Blocks | -                                                                                                                                                                     |
| Number of Macrocells            | 256                                                                                                                                                                   |
| Number of Gates                 | -                                                                                                                                                                     |
| Number of I/O                   | 68                                                                                                                                                                    |
| Operating Temperature           | 0°C ~ 70°C (TA)                                                                                                                                                       |
| Mounting Type                   | Surface Mount                                                                                                                                                         |
| Package / Case                  | 100-BQFP                                                                                                                                                              |
| Supplier Device Package         | 100-PQFP (14x20)                                                                                                                                                      |
| Purchase URL                    | <a href="https://www.e-xfl.com/product-detail/lattice-semiconductor/m5lv-256-68-10yc">https://www.e-xfl.com/product-detail/lattice-semiconductor/m5lv-256-68-10yc</a> |

Table 2. MACH 5 Speed Grades

| Device              | Speed Grade <sup>1</sup> |    |      |      |      |      |     |
|---------------------|--------------------------|----|------|------|------|------|-----|
|                     | -5                       | -6 | -7   | -10  | -12  | -15  | -20 |
| M5-128 <sup>2</sup> |                          |    | C    | C, I | C, I | C, I | I   |
| M5-128/1            | C                        |    | C, I | C, I | C, I | C, I | I   |
| M5LV-128            | C                        |    | C, I | C, I | C, I | I    |     |
| M5-192/1            | C                        |    | C, I | C, I | C, I | C, I | I   |
| M5-256 <sup>2</sup> |                          |    | C    | C, I | C, I | C, I | I   |
| M5-256/1            | C                        |    | C, I | C, I | C, I | C, I | I   |
| M5LV-256            | C                        |    | C, I | C, I | C, I | I    |     |
| M5-320              |                          | C  | C, I | C, I | C, I | C, I | I   |
| M5LV-320            |                          | C  | C, I | C, I | C, I | C, I | I   |
| M5-384              |                          | C  | C, I | C, I | C, I | C, I | I   |
| M5LV-384            |                          | C  | C, I | C, I | C, I | C, I | I   |
| M5-512              |                          | C  | C, I | C, I | C, I | C, I | I   |
| M5LV-512            |                          | C  | C, I | C, I | C, I | C, I | I   |

**Note:**

1. C = Commercial grade, I = Industrial grade
2. /1 version recommended for new designs

With Lattice's unique hierarchical architecture, the MACH 5 family provides densities up to 512 macrocells to support full system logic integration. Extensive routing resources ensure pinout retention as well as high utilization. It is ideal for PAL<sup>®</sup> block device integration and a wide range of other applications including high-speed computing, low-power applications, communications, and embedded control. At each macrocell density point, Lattice offers several I/O and package options to meet a wide range of design needs (Table 3).

Table 3. MACH 5 Package and I/O Options <sup>1</sup>


| Supply Voltage | M5-128/1<br>M5LV-128 |        | M5-192/1 | M5-256/1<br>M5LV-256 |         | M5-320<br>M5LV-320 |      | M5-384<br>M5LV-384 |      | M5-512<br>M5LV-512 |      |
|----------------|----------------------|--------|----------|----------------------|---------|--------------------|------|--------------------|------|--------------------|------|
|                | 5                    | 3.3    |          | 5                    | 3.3     | 5                  | 3.3  | 5                  | 3.3  | 5                  | 3.3  |
| 100-pin TQFP   | 68                   | 68, 74 | 68       | 68                   | 68*, 74 |                    |      |                    |      |                    |      |
| 100-pin PQFP   | 68                   | 68*    | 68*      | 68*                  | 68      |                    |      |                    |      |                    |      |
| 144-pin TQFP   |                      | 104    |          |                      | 104     |                    |      |                    |      |                    |      |
| 144-pin PQFP   | 104                  | 104*   | 104*     | 104*                 | 104*    |                    |      |                    |      |                    |      |
| 160-pin PQFP   | 120                  | 120    | 120      | 120                  | 120     | 120*               | 120  | 120*               | 120  | 120*               | 120  |
| 208-pin PQFP   |                      |        |          | 160                  | 160     | 160                | 160  | 160                | 160  | 160                | 160  |
| 240-pin PQFP   |                      |        |          |                      |         | 184*               | 184* | 184*               | 184* | 184*               | 184* |
| 256-ball BGA   |                      |        |          |                      |         | 192                | 192* | 192*               | 192* | 192*               | 192* |
| 352-ball BGA   |                      |        |          |                      |         |                    |      |                    |      | 256                | 256  |

**Note:**

1. The I/O options indicated with a "\*" are obsolete, please contact factory for more information.

Advanced power management options allow designers to incrementally reduce power while maintaining the level of performance needed for today's complex designs. I/O safety features allow for mixed-voltage design,

Select devices have been discontinued.  
See Ordering Information section for product status.



20446G-002

**Figure 2. PAL Block Structure**

## Product-Term Array and Logic Allocator

The product-term array uses the same sum-of-products architecture as PAL devices and consists of 32 inputs (plus their complements) and 64 product terms arranged in 16 **clusters**. A cluster is a sum-of-products function with either 3 or 4 product terms.

**Logic allocators** assign the clusters to macrocells. Each macrocell can accept up to eight clusters of three or four product terms, but a given cluster can only be steered to one macrocell (Table 4). If only three product terms in a cluster are steered, the fourth can be used as an input to an XOR gate for separate logic generation and/or polarity control.

The **wide logic allocator** is comprised of all 16 of the individual logic allocators and acts as an output switch matrix by reassigning logic to macrocells to retain pinout as designs change. The logic allocation scheme in the MACH 5 device allows for the implementation of large equations (up to 32 product terms) with only one pass through the logic array.

**Table 4. Product Term Steering Options for PT Clusters and Macrocells**

| Macrocell      | Available Clusters                                                                                                                     | Macrocell       | Available Clusters                                                                                                                          |
|----------------|----------------------------------------------------------------------------------------------------------------------------------------|-----------------|---------------------------------------------------------------------------------------------------------------------------------------------|
| M <sub>0</sub> | C <sub>0</sub> , C <sub>1</sub> , C <sub>2</sub> , C <sub>3</sub> , C <sub>4</sub>                                                     | M <sub>8</sub>  | C <sub>5</sub> , C <sub>6</sub> , C <sub>7</sub> , C <sub>8</sub> , C <sub>9</sub> , C <sub>10</sub> , C <sub>11</sub> , C <sub>12</sub>    |
| M <sub>1</sub> | C <sub>0</sub> , C <sub>1</sub> , C <sub>2</sub> , C <sub>3</sub> , C <sub>4</sub> , C <sub>5</sub>                                    | M <sub>9</sub>  | C <sub>6</sub> , C <sub>7</sub> , C <sub>8</sub> , C <sub>9</sub> , C <sub>10</sub> , C <sub>11</sub> , C <sub>12</sub> , C <sub>13</sub>   |
| M <sub>2</sub> | C <sub>0</sub> , C <sub>1</sub> , C <sub>2</sub> , C <sub>3</sub> , C <sub>4</sub> , C <sub>5</sub> , C <sub>6</sub>                   | M <sub>10</sub> | C <sub>7</sub> , C <sub>8</sub> , C <sub>9</sub> , C <sub>10</sub> , C <sub>11</sub> , C <sub>12</sub> , C <sub>13</sub> , C <sub>14</sub>  |
| M <sub>3</sub> | C <sub>0</sub> , C <sub>1</sub> , C <sub>2</sub> , C <sub>3</sub> , C <sub>4</sub> , C <sub>5</sub> , C <sub>6</sub> , C <sub>7</sub>  | M <sub>11</sub> | C <sub>8</sub> , C <sub>9</sub> , C <sub>10</sub> , C <sub>11</sub> , C <sub>12</sub> , C <sub>13</sub> , C <sub>14</sub> , C <sub>15</sub> |
| M <sub>4</sub> | C <sub>0</sub> , C <sub>1</sub> , C <sub>2</sub> , C <sub>3</sub> , C <sub>4</sub> , C <sub>5</sub> , C <sub>6</sub> , C <sub>7</sub>  | M <sub>12</sub> | C <sub>8</sub> , C <sub>9</sub> , C <sub>10</sub> , C <sub>11</sub> , C <sub>12</sub> , C <sub>13</sub> , C <sub>14</sub> , C <sub>15</sub> |
| M <sub>5</sub> | C <sub>1</sub> , C <sub>2</sub> , C <sub>3</sub> , C <sub>4</sub> , C <sub>5</sub> , C <sub>6</sub> , C <sub>7</sub> , C <sub>8</sub>  | M <sub>13</sub> | C <sub>9</sub> , C <sub>10</sub> , C <sub>11</sub> , C <sub>12</sub> , C <sub>13</sub> , C <sub>14</sub> , C <sub>15</sub>                  |
| M <sub>6</sub> | C <sub>2</sub> , C <sub>3</sub> , C <sub>4</sub> , C <sub>5</sub> , C <sub>6</sub> , C <sub>7</sub> , C <sub>8</sub> , C <sub>9</sub>  | M <sub>14</sub> | C <sub>10</sub> , C <sub>11</sub> , C <sub>12</sub> , C <sub>13</sub> , C <sub>14</sub> , C <sub>15</sub>                                   |
| M <sub>7</sub> | C <sub>3</sub> , C <sub>4</sub> , C <sub>5</sub> , C <sub>6</sub> , C <sub>7</sub> , C <sub>8</sub> , C <sub>9</sub> , C <sub>10</sub> | M <sub>15</sub> | C <sub>11</sub> , C <sub>12</sub> , C <sub>13</sub> , C <sub>14</sub> , C <sub>15</sub>                                                     |

Select devices have been discontinued.  
See Ordering Information section for product status.


- ◆ Global clock (0, 1, 2, or 3) with positive and negative edge clock enable (biphase)

#### Clock Line 2 Options

- ◆ Global clock (0, 1, 2, or 3) with clock enable


#### Clock Line 3 Options

- ◆ Complement of clock line 2 (same clock enable)
- ◆ Product-term clock (if clock line 2 does not use clock enable)



20446G-004

**Figure 4. Clock Generator**



20446G-005

**Figure 5. Set/Reset Generator**

The set/reset generation portion of the control generator (Figure 5) creates three set/reset lines for the PAL block. Each macrocell can choose one of these three lines or choose no set/reset at all. All three lines can be configured for product term set/reset and two of the three lines can be configured as sum term set/reset and one of the lines can be configured as product-term or sum-term latch enable. While the set/reset signals are generated in the control generator, whether that signal sets or resets a flip-flop is determined within the individual macrocell. The same signal can set one flip-flop and reset another. PT2 or /PT2 can also be used as a latch enable for macrocells configured as latches.

**Select devices have been discontinued.  
See Ordering Information section for product status.**

## MACH 5 TIMING MODEL

The primary focus of the MACH 5 timing model is to accurately represent the timing in a MACH 5 device, and at the same time, be easy to understand. This model accurately describes all combinatorial and registered paths through the device, making a distinction between **internal feedback** and **external feedback**. A signal uses internal feedback when it is fed back into the switch matrix or block without having to go through the output buffer. The input register specifications are also reported as internal feedback. When a signal is fed back into the switch matrix after having gone through the output buffer, it is using external feedback.

The parameter,  $t_{BUF}$  is defined as the time it takes to go through the output buffer to the I/O pad. If a signal goes to the internal feedback rather than to the I/O pad, the parameter designator is followed by an "i". By adding  $t_{BUF}$  to this internal parameter, the external parameter is derived. For example,  $t_{PD} = t_{PDi} + t_{BUF}$ . A diagram representing the modularized MACH 5 timing model is shown in Figure 7. Refer to the Technical Note entitled *MACH 5 Timing and High Speed Design* for a more detailed discussion about the timing parameters.





Figure 7. MACH 5 Timing Model

20446G-014

Select devices have been discontinued.  
See Ordering Information section for product status.



---

## MULTIPLE I/O AND DENSITY OPTIONS

The MACH 5 family offers six macrocell densities in a number of I/O options. This allows designers to choose a device close to their logic density and I/O requirements, thus minimizing costs. For the same package type, every density has the same pin-out. With proper design considerations, a design can be moved to a higher or lower density part as required.

## IEEE 1149.1 - COMPLIANT BOUNDARY SCAN TESTABILITY

Most MACH 5 devices have boundary scan registers and are compliant to the IEEE 1149.1 standard. This allows functional testing of the circuit board on which the device is mounted through a serial scan path that can access all critical logic nodes. Internal registers are linked internally, allowing test data to be shifted in and loaded directly onto test nodes, or test node data to be captured and shifted out for verification. In addition, these devices can be linked into a board-level serial scan path for more complete board-level testing.

## IEEE 1149.1 - COMPLIANT IN-SYSTEM PROGRAMMING

Programming devices in-system provides a number of significant benefits including: rapid prototyping, lower inventory levels, higher quality, and the ability to make in-field modifications. All MACH 5 devices provide in-system programming (ISP) capability through their IEEE 1149.1-compliant Boundary Scan Test Access Port. By using the IEEE 1149.1-compliant Boundary Scan Test Access Port as the communication interface through which ISP is achieved, customers get the benefit of a standard, well-defined interface.


MACH 5 devices can be programmed across the commercial temperature and voltage range. The PC-based LatticePRO software facilitates in-system programming of MACH 5 devices. LatticePRO software takes the JEDEC file output produced by design implementation software, along with information about the Boundary Scan chain, and creates a set of vectors that are used to drive the Boundary Scan chain. LatticePRO software can use these vectors to drive a Boundary Scan chain via the parallel port of a PC. Alternatively, LatticePRO software can output files in formats understood by common automated test equipment. This equipment can then be used to program MACH 5 devices during the testing of a circuit board.

## PCI COMPLIANT

MACH 5 devices in the -5/-6/-7/-10/-12 speed grades are compliant with the *PCI Local Bus Specification* version 2.1, published by the PCI Special Interest Group (SIG). The 5-V devices are fully PCI-compliant. The 3.3-V devices are mostly compliant but do not meet the PCI condition to clamp the inputs as they rise above  $V_{CC}$  because of their 5-V input tolerant feature. MACH 5 devices provide the speed, drive, density, output enables and I/Os for the most complex PCI designs.

Select devices have been discontinued.  
See Ordering Information section for product status.


## MACH 5 PAL BLOCK



Select devices have been discontinued.  
See Ordering Information section for product status.

20446G-015

# BLOCK DIAGRAM — M5(LV)-256/XXX




Select devices have been discontinued.  
See Ordering Information section for product status.

20446G-009



# BLOCK DIAGRAM — M5(LV)-320/XXX



Select devices have been discontinued.  
See Ordering Information section for product status.

20446G-010

11



20446G-013

## ABSOLUTE MAXIMUM RATINGS

### M5LV

Storage Temperature. . . . . -65°C to +150°C  
Device Junction Temperature. . . . . +130°C  
Supply Voltage  
with Respect to Ground. . . . . -0.5 V to +4.5 V  
DC Input Voltage. . . . . -0.5 V to 5.5 V  
Static Discharge Voltage. . . . . 2000 V  
Latchup Current (-40°C to +85°C). . . . . 200 mA

*Stresses above those listed under Absolute Maximum Ratings may cause permanent device failure. Functionality at or above these limits is not implied. Exposure to Absolute Maximum Ratings for extended periods may affect device reliability.*

## OPERATING RANGES

### Commercial (C) Devices

Ambient Temperature ( $T_A$ )  
Operating in Free Air. . . . . 0°C to +70°C  
Supply Voltage ( $V_{CC}$ )  
with Respect to Ground. . . . . +3.0 V to +3.6 V

### Industrial (I) Devices

Ambient Temperature ( $T_A$ )  
Operating in Free Air. . . . . -40°C to +85°C  
Supply Voltage ( $V_{CC}$ )  
with Respect to Ground. . . . . +3.0 V to +3.6 V  
*Operating ranges define those limits between which the functionality of the device is guaranteed.*

## 3.3-V DC CHARACTERISTICS OVER OPERATING RANGES

| Parameter Symbol | Parameter Description                 | Test Description                                                                          |                                   | Min            | Max  | Unit    |
|------------------|---------------------------------------|-------------------------------------------------------------------------------------------|-----------------------------------|----------------|------|---------|
| $V_{OH}$         | Output HIGH Voltage                   | $V_{CC} = \text{Min}$                                                                     | $I_{OH} = -100 \mu A$             | $V_{CC} - 0.2$ |      | V       |
|                  |                                       | $V_{IN} = V_{IH} \text{ or } V_{IL}$                                                      | $I_{OH} = 3.2 \text{ mA}$         | 2.4            |      | V       |
| $V_{OL}$         | Output LOW Voltage                    | $V_{CC} = \text{Min}$                                                                     | $I_{OL} = 100 \mu A$              |                | 0.2  | V       |
|                  |                                       | $V_{IN} = V_{IH} \text{ or } V_{IL}$                                                      | $I_{OL} = 16 \text{ mA (Note 1)}$ |                | 0.5  | V       |
| $V_{IH}$         | Input HIGH Voltage                    | $V_{OUT} \geq V_{OH} \text{ Min or } V_{OUT} \leq V_{OL} \text{ Max (Note 2)}$            |                                   | 2.0            | 5.5  | V       |
| $V_{IL}$         | Input LOW Voltage                     | $V_{OUT} \geq V_{OH} \text{ Min or } V_{OUT} \leq V_{OL} \text{ Max (Note 2)}$            |                                   | -0.3           | 0.8  | V       |
| $I_{IH}$         | Input HIGH Leakage Current            | $V_{IN} = 3.6, V_{CC} = \text{Max (Note 3)}$                                              |                                   |                | 10   | $\mu A$ |
| $I_{IL}$         | Input LOW Leakage Current             | $V_{IN} = 0, V_{CC} = \text{Max (Note 3)}$                                                |                                   |                | -10  | $\mu A$ |
| $I_{OZH}$        | Off-State Output Leakage Current HIGH | $V_{OUT} = 3.6, V_{CC} = \text{Max}, V_{IN} = V_{IH} \text{ or } V_{IL} \text{ (Note 3)}$ |                                   |                | 10   | $\mu A$ |
| $I_{OZL}$        | Off-State Output Leakage Current LOW  | $V_{OUT} = 0, V_{CC} = \text{Max}, V_{IN} = V_{IH} \text{ or } V_{IL} \text{ (Note 3)}$   |                                   |                | -10  | $\mu A$ |
| $I_{SC}$         | Output Short-Circuit Current          | $V_{OUT} = 0.5 V_{CC} = \text{Max}, V_{IN} = V_{IH} \text{ or } V_{IL} \text{ (Note 4)}$  |                                   | -15            | -160 | mA      |

#### Notes:

1. Total  $I_{OL}$  between ground pins should not exceed 64 mA.
2. These are absolute values with respect to device ground, and all overshoots due to system and/or tester noise are included.
3. I/O pin leakage is the worst case of  $I_{IL}$  and  $I_{OZL}$  or  $I_{IH}$  and  $I_{OZH}$ .
4. Not more than one output should be shorted at one time. Duration of the short-circuit should not exceed one second.

Select devices have been discontinued.  
See Ordering Information section for product status.

## CAPACITANCE<sup>1</sup>

| Parameter Symbol | Parameter Description | Test conditions          |                            | Typ | Unit |
|------------------|-----------------------|--------------------------|----------------------------|-----|------|
| $C_{IN}$         | I/CLK pin             | $V_{IN} = 2.0\text{ V}$  | 3.3 V or 5 V, 25° C, 1 MHz | 12  | pF   |
| $C_{I/O}$        | I/O pin               | $V_{OUT} = 2.0\text{ V}$ | 3.3 V or 5 V, 25° C, 1 MHz | 10  | pF   |

1. These parameters are not 100% tested, but are calculated at initial characterization and at any time the design is modified where these parameters may be affected.

## $I_{CC}$ vs. FREQUENCY

These curves represent the typical power consumption for a particular device at system frequency. The selected “typical” pattern is a 16-bit up-down counter. This pattern fills the device and exercises every macrocell. Maximum frequency shown uses internal feedback and a D-type register. Power/Speed are optimized to obtain the highest counter frequency and the lowest power. The highest frequency (LSBs) is placed in common PAL blocks, which are set to high power. The lowest frequency signals (MSBs) are placed in a common PAL block and set to lowest power. For a more detailed discussion about MACH 5 power consumption, refer to the application note entitled *MACH 5 Power* in the Application Notes section on the Lattice Data Book CD-ROM or Lattice web site.

## $I_{CC}$ CURVES AT HIGH /LOW POWER MODES





Figure 8.  $I_{CC}$  Curves at High/Low Power Modes

Select devices have been discontinued. See Ordering Information section for product status.

# 100-PIN PQFP CONNECTION DIAGRAM

## Top View

100-Pin PQFP (68 I/O)



\*Package obsolete, contact factory.


20446G-016

Select devices have been discontinued.  
See Ordering Information section for product status.

## Pin Designations

CLK = Clock  
GND = Ground  
I = Input  
I/O = Input/Output  
NC = No Connect


V<sub>CC</sub> = Supply Voltage  
TDI = Test Data In  
TCK = Test Clock  
TMS = Test Mode Select  
TDO = Test Data Out



# 144-PIN PQFP CONNECTION DIAGRAM

## Top View

144-Pin PQFP



Select devices have been discontinued.  
See Ordering Information section for product status.


\*Package obsolete, contact factory.

20446G-019

### Pin Designations

CLK = Clock  
GND = Ground  
I = Input  
I/O = Input/Output  
NC = No Connect


V<sub>CC</sub> = Supply Voltage  
TDI = Test Data In  
TCK = Test Clock  
TMS = Test Mode Select  
TDO = Test Data Out



# 160-PIN PQFP (WITH INTERNAL HEAT SPREADER) CONNECTION DIAGRAM

## Top View

160-Pin PQFP (320, 384, 512 Macrocells)



\*Package obsolete, contact factory.


Select devices have been discontinued.  
See Ordering Information section for product status.

20446G-022

### Pin Designations

CLK = Clock  
GND = Ground  
I = Input  
I/O = Input/Output  
NC = No Connect

V<sub>CC</sub> = Supply Voltage  
TDI = Test Data In  
TCK = Test Clock  
TMS = Test Mode Select  
TDO = Test Data Out




██████████

**Select devices have been discontinued.  
See Ordering Information section for product status.**

## Pin Designations

CLK = Clock  
 GND = Ground  
 I = Input  
 I/O = Input/Output  
 NC = No Connect

|                 |   |                  |
|-----------------|---|------------------|
| V <sub>CC</sub> | = | Supply Voltage   |
| TDI             | = | Test Data In     |
| TCK             | = | Test Clock       |
| TMS             | = | Test Mode Select |
| TDO             | = | Test Data Out    |





## 256-BALL BGA CONNECTION DIAGRAM — M5-320

### Bottom View (I/O Pin-outs)

256-Ball BGA

|   | 20    | 19    | 18              | 17              | 16              | 15    | 14              | 13    | 12    | 11    | 10    | 9      | 8      | 7               | 6      | 5               | 4               | 3               | 2      | 1      |   |
|---|-------|-------|-----------------|-----------------|-----------------|-------|-----------------|-------|-------|-------|-------|--------|--------|-----------------|--------|-----------------|-----------------|-----------------|--------|--------|---|
| A | GND   | I/O11 | GND             | I/O44           | I/O58           | GND   | I/O70           | I/O76 | GND   | GND   | GND   | GND    | I/O108 | I/O116          | GND    | I/O128          | I/O134          | GND             | GND    | GND    | A |
| B | GND   | I/O12 | I/O28           | I/O45           | I/O59           | I/O64 | I/O71           | I/O77 | I/O84 | I/O90 | I/O96 | I/O102 | I/O109 | I/O117          | I/O122 | I/O129          | I/O135          | I/O148          | I/O164 | GND    | B |
| C | I/O0  | I/O13 | V <sub>CC</sub> | I/O46           | I/O60           | I/O65 | I/O72           | I/O78 | I/O85 | I/O91 | I/O97 | I/O103 | I/O110 | I/O118          | I/O123 | I/O130          | I/O136          | V <sub>CC</sub> | I/O165 | I/O181 | C |
| D | I/O1  | I/O14 | I/O29           | V <sub>CC</sub> | V <sub>CC</sub> | I/O66 | V <sub>CC</sub> | I/O79 | I/O86 | I/O92 | I/O98 | I/O104 | I/O111 | V <sub>CC</sub> | I/O124 | V <sub>CC</sub> | V <sub>CC</sub> | I/O149          | I/O166 | I/O182 | D |
| E | I/O2  | I/O15 | I/O30           | TDI             |                 |       |                 |       |       |       |       |        |        |                 |        |                 | TDO             | I/O150          | I/O167 | I/O183 | E |
| F | GND   | I/O16 | I/O31           | I/O47           |                 |       |                 |       |       |       |       |        |        |                 |        |                 | I/O137          | I/O151          | I/O168 | GND    | F |
| G | I/O3  | I/O17 | I/O32           | V <sub>CC</sub> |                 |       |                 |       |       |       |       |        |        |                 |        |                 | V <sub>CC</sub> | I/O152          | I/O169 | I/O184 | G |
| H | GND   | I/O18 | I/O33           | I/O48           |                 |       |                 |       |       |       |       |        |        |                 |        |                 | I/O138          | I/O153          | I/O170 | GND    | H |
| J | I/O4  | I/O19 | I/O34           | I/O49           |                 |       |                 |       |       |       |       |        |        |                 |        |                 | I/O139          | I/O154          | I/O171 | I/O185 | J |
| K | GND   | I/O20 | I/O35           | I/O50           |                 |       |                 |       |       |       |       |        |        |                 |        |                 | I/O140          | I/O155          | I/O172 | I/O186 | K |
| L | I/O5  | I/O21 | I/O36           | I/O51           |                 |       |                 |       |       |       |       |        |        |                 |        |                 | I/O141          | I/O156          | I/O173 | GND    | L |
| M | I/O6  | I/O22 | I/O37           | I/O52           |                 |       |                 |       |       |       |       |        |        |                 |        |                 | I/O142          | I/O157          | I/O174 | I/O187 | M |
| N | GND   | I/O23 | I/O38           | I/O53           |                 |       |                 |       |       |       |       |        |        |                 |        |                 | I/O143          | I/O158          | I/O175 | GND    | N |
| P | I/O7  | I/O24 | I/O39           | V <sub>CC</sub> |                 |       |                 |       |       |       |       |        |        |                 |        |                 | V <sub>CC</sub> | I/O159          | I/O176 | I/O188 | P |
| R | GND   | I/O25 | I/O40           | I/O54           |                 |       |                 |       |       |       |       |        |        |                 |        |                 | I/O144          | I/O160          | I/O177 | GND    | R |
| T | I/O8  | I/O26 | I/O41           | TCK             |                 |       |                 |       |       |       |       |        |        |                 |        |                 | TMS             | I/O161          | I/O178 | I/O189 | T |
| U | I/O9  | I/O27 | I/O42           | V <sub>CC</sub> |                 |       |                 |       |       |       |       |        |        |                 |        |                 | V <sub>CC</sub> | I/O162          | I/O179 | I/O190 | U |
| V | I/O10 | I/O28 | V <sub>CC</sub> | I/O55           |                 |       |                 |       |       |       |       |        |        |                 |        |                 | I/O145          | V <sub>CC</sub> | I/O180 | I/O191 | V |
| W | GND   | I/O29 | I/O43           | I/O56           |                 |       |                 |       |       |       |       |        |        |                 |        |                 | I/O146          | I/O163          | I/O181 | GND    | W |
| Y | GND   | I/O30 | GND             | I/O57           |                 |       |                 |       |       |       |       |        |        |                 |        |                 | I/O147          | GND             | I/O182 | I/O192 | Y |

#### Pin Designations

|                 |   |                  |
|-----------------|---|------------------|
| CLK             | = | Clock            |
| GND             | = | Ground           |
| I               | = | Input            |
| I/O             | = | Input/Output     |
| NC              | = | No Connect       |
| V <sub>CC</sub> | = | Supply Voltage   |
| TDI             | = | Test Data In     |
| TCK             | = | Test Clock       |
| TMS             | = | Test Mode Select |
| TDO             | = | Test Data Out    |

Select devices have been discontinued.  
See Ordering Information section for product status.

20446G-026

# 256-BALL BGA CONNECTION DIAGRAM — M5-320

## Bottom View (Macrocell Association)

256-Ball BGA

|    | A    | B    | C               | D               | E                                                                                                                                                                                                                                                                                                                                                                                                                                                                       | F               | G               | H               | J               | K       | L       | M   | N    | P               | R               | T    | U               | V               | W   | Y   |     |
|----|------|------|-----------------|-----------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------|-----------------|-----------------|-----------------|---------|---------|-----|------|-----------------|-----------------|------|-----------------|-----------------|-----|-----|-----|
| 1  | GND  | GND  | 3A11            | 3D15            | 3D12                                                                                                                                                                                                                                                                                                                                                                                                                                                                    | GND             | 3D7             | GND             | 3D3             | 3D2     | GND     | 2D2 | GND  | 2D7             | GND             | 2D10 | 2D13            | 2D15            | GND | GND | 1   |
| 2  | GND  | 3B2  | 3A3             | 3A8             | 3A13                                                                                                                                                                                                                                                                                                                                                                                                                                                                    | 3D13            | 3D9             | 3D8             | 3D4             | 13/CLK3 | 12/CLK2 | 2D3 | 2D4  | 2D8             | 2D12            | 2A15 | 2A13            | 2A12            | 2A9 | 2A7 | 2   |
| 3  | GND  | 3B8  | V <sub>CC</sub> | 3A2             | 3A4                                                                                                                                                                                                                                                                                                                                                                                                                                                                     | 3A12            | 3D14            | 3D10            | 3D5             | 3D0     | 2D0     | 2D5 | 2D9  | 2D14            | 2A14            | 2A10 | 2A8             | V <sub>CC</sub> | 2A3 | GND | 3   |
| 4  | 3B13 | 3B11 | 3B3             | V <sub>CC</sub> | TDO                                                                                                                                                                                                                                                                                                                                                                                                                                                                     | 3A7             | V <sub>CC</sub> | 3D11            | 3D6             | 3D1     | 2D1     | 2D6 | 2D11 | V <sub>CC</sub> | 2A11            | TMS  | V <sub>CC</sub> | 2A6             | 2A2 | 2A0 | 4   |
| 5  | 4B14 | 4B15 | 3B4             | V <sub>CC</sub> | <div>Pin Designations</div> <div>CLK = Clock</div> <div>GND = Ground</div> <div>I = Input</div> <div>I/O = Input/Output</div> <div>NC = No Connect</div> <div>V<sub>CC</sub> = Supply Voltage</div> <div>TDI = Test Data In</div> <div>TCK = Test Clock</div> <div>TMS = Test Mode Select</div> <div>TDO = Test Data Out</div> <div><div><div>4</div><div>D</div><div>15</div></div><div>Macrocell (0-15)</div><div>PAL Block (A-D)</div><div>Segment (0-4)</div></div> | 4B8             | 4B10            | 4B13            | V <sub>CC</sub> | 2A4     | 2A1     | 2B0 | 2B1  | 5               |                 |      |                 |                 |     |     |     |
| 6  | GND  | 4B11 | 3B12            | 3B7             |                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | V <sub>CC</sub> | 2B3             | 2B6             | 2B9             | 2B11    | 6       |     |      |                 |                 |      |                 |                 |     |     |     |
| 7  | 4B8  | 4B10 | 4B13            | V <sub>CC</sub> |                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | V <sub>CC</sub> | 2B2             | 2B5             | 2B7             | 7       |         |     |      |                 |                 |      |                 |                 |     |     |     |
| 8  | 4B4  | 4B6  | 4B9             | 4B12            |                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | 2B8             | 2B10            | 2B12            | GND             | 8       |         |     |      |                 |                 |      |                 |                 |     |     |     |
| 9  | GND  | 4B3  | 4B5             | 4B7             |                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | 2B13            | 2B14            | 2B15            | GND             | 9       |         |     |      |                 |                 |      |                 |                 |     |     |     |
| 10 | GND  | 4B0  | 4B1             | 4B2             |                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | 1B13            | 1B14            | 1B15            | GND             | 10      |         |     |      |                 |                 |      |                 |                 |     |     |     |
| 11 | GND  | 4A0  | 4A1             | 4A2             |                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | 1B8             | 1B10            | 1B12            | GND             | 11      |         |     |      |                 |                 |      |                 |                 |     |     |     |
| 12 | GND  | 4A3  | 4A5             | 4A7             |                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | 1B3             | 1B6             | 1B9             | 1B11            | 12      |         |     |      |                 |                 |      |                 |                 |     |     |     |
| 13 | 4A4  | 4A6  | 4A9             | 4A12            |                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | V <sub>CC</sub> | 1B2             | 1B5             | 1B7             | 13      |         |     |      |                 |                 |      |                 |                 |     |     |     |
| 14 | 4A8  | 4A10 | 4A13            | V <sub>CC</sub> |                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | 1A4             | 1A1             | 1B4             | GND             | 14      |         |     |      |                 |                 |      |                 |                 |     |     |     |
| 15 | GND  | 4A11 | 0B12            | 0B7             |                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | V <sub>CC</sub> | 1A5             | 1B0             | 1B1             | 15      |         |     |      |                 |                 |      |                 |                 |     |     |     |
| 16 | 4A14 | 4A15 | 0B4             | V <sub>CC</sub> |                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | TDI             | 0A7             | V <sub>CC</sub> | 0D11            | 0D6     | 0D1     | 1D1 | 1D6  | 1D11            | V <sub>CC</sub> | 1A11 | TCK             | V <sub>CC</sub> | 1A6 | 1A2 | 1A0 |
| 17 | 0B13 | 0B11 | 0B3             | V <sub>CC</sub> | 0A4                                                                                                                                                                                                                                                                                                                                                                                                                                                                     | 0A12            | 0D14            | 0D9             | 0D5             | 0D0     | 1D0     | 1D5 | 1D10 | 1D14            | 1A14            | 1A10 | 1A8             | V <sub>CC</sub> | 1A3 | GND | 17  |
| 18 | GND  | 0B8  | V <sub>CC</sub> | 0A2             | 0A13                                                                                                                                                                                                                                                                                                                                                                                                                                                                    | 0D12            | 0D8             | 0D4             | 0D3             | 10/CLK0 | 11/CLK1 | 1D4 | 1D8  | 1D9             | 1D13            | 1A15 | 1A12            | 1A9             | 1A7 | GND | 18  |
| 19 | 0B2  | 0A3  | 0A8             | 0A11            | 0A13                                                                                                                                                                                                                                                                                                                                                                                                                                                                    | 0D12            | 0D8             | 0D4             | 0D3             | 10/CLK0 | 11/CLK1 | 1D4 | 1D8  | 1D9             | 1D13            | 1A15 | 1A12            | 1A9             | 1A7 | GND | 19  |
| 20 | GND  | GND  | 0D15            | 0D13            | 0D10                                                                                                                                                                                                                                                                                                                                                                                                                                                                    | GND             | 0D7             | GND             | 0D2             | GND     | 1D2     | 1D3 | GND  | 1D7             | GND             | 1D12 | 1D15            | 1A13            | GND | GND | 20  |

Select devices have been discontinued.  
See Ordering Information section for product status.



# 352-BALL BGA CONNECTION DIAGRAM — M5-512, M5LV-512

## Bottom View (Macrocell Association)

352-Ball BGA

|    | A    | B    | C    | D               | E   | F   | G    | H               | J    | K               | L    | M   | N                                | P                                | R   | T   | U    | V               | W    | Y               | AA   | AB  | AC              | AD   | AE   | AF   |      |
|----|------|------|------|-----------------|-----|-----|------|-----------------|------|-----------------|------|-----|----------------------------------|----------------------------------|-----|-----|------|-----------------|------|-----------------|------|-----|-----------------|------|------|------|------|
| 1  | NC   | NC   | NC   | GND             | 5A0 | 5A3 | 5A6  | V <sub>CC</sub> | 5A11 | V <sub>CC</sub> | 5D12 | 5D7 | 5D2                              | V <sub>CC</sub>                  | 4D3 | 4D8 | 4D12 | V <sub>CC</sub> | 4A11 | V <sub>CC</sub> | 4A4  | 4A0 | V <sub>CC</sub> | 3A14 | 3A15 | 3A13 | 3A12 |
| 2  | NC   | NC   | NC   | 5A2             | 5A5 | 5A9 | 5A14 | 5A15            | 5D13 | 5D10            | 5D8  | 5D4 | 5D1                              | 4D0                              | 4D2 | 4D6 | 4D10 | 4D13            | 4A15 | 4A12            | 4A9  | 4A8 | 4A3             | 4A1  | GND  | NC   | NC   |
| 3  | GND  | GND  | NC   | 5A1             | 5A4 | 5A7 | 5A8  | 5A10            | 5A13 | 5D14            | 5D9  | 5D5 | 5D1                              | I <sub>2</sub> /CLK <sub>2</sub> | 4D4 | 4D7 | 4D11 | 4D14            | 4A14 | 4A10            | 4A7  | 4A5 | 4A2             | TMS  | NC   | NC   |      |
| 4  | NC   | 6A14 | NC   | TDO             | 5A0 | 5A3 | 5A6  | V <sub>CC</sub> | 5A11 | V <sub>CC</sub> | 5D12 | 5D7 | 5D2                              | V <sub>CC</sub>                  | 4D3 | 4D8 | 4D12 | V <sub>CC</sub> | 4A11 | V <sub>CC</sub> | 4A4  | 4A0 | V <sub>CC</sub> | 3A14 | 3A15 | 3A13 | 3A12 |
| 5  | GND  | 6A12 | 6A13 | V <sub>CC</sub> |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | 3A14            | 3A11 | 3A9  | GND  | 3A12 |
| 6  | NC   | 6A9  | 6A10 | 6A15            |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | 3A10            | 3A8  | 3A7  | 3A5  |      |
| 7  | GND  | 6A6  | 6A8  | 6A11            |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | 3A6             | 3A4  | 3A3  | 3A0  |      |
| 8  | 6A1  | 6A4  | 6A5  | 6A7             |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | 3A2             | 3A1  | 3B0  | NC   |      |
| 9  | 6B1  | 6A0  | 6A2  | 6A3             |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | V <sub>CC</sub> | 3B1  | 3B2  | GND  |      |
| 10 | GND  | 6B2  | 6B0  | V <sub>CC</sub> |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | 3B3             | 3B4  | 3B5  | 3B6  |      |
| 11 | 6B6  | 6B5  | 6B4  | 6B3             |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | 3B7             | 3B8  | 3B9  | 3B10 |      |
| 12 | 6B10 | 6B9  | 6B8  | 6B7             |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | 3B11            | 3B12 | 3B13 | 3B14 |      |
| 13 | 6B14 | 6B13 | 6B12 | 6B11            |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | V <sub>CC</sub> | 2B15 | 3B15 | GND  | 3B14 |
| 14 | GND  | 7B15 | 6B15 | V <sub>CC</sub> |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | 2B11            | 2B12 | 2B13 | 2B14 |      |
| 15 | 7B14 | 7B13 | 7B12 | 7B11            |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | 2B7             | 2B8  | 2B9  | 2B10 |      |
| 16 | NC   | 7B10 | 7B9  | 7B8             |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | 2B3             | 2B4  | 2B5  | 2B6  |      |
| 17 | 7B7  | 7B6  | 7B5  | 7B4             |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | V <sub>CC</sub> | 2B0  | 2B2  | GND  |      |
| 18 | GND  | 7B3  | 7B2  | V <sub>CC</sub> |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | 2A3             | 2A2  | 2A0  | 2B1  |      |
| 19 | 7B1  | 7B0  | 7A1  | 7A4             |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | 2A7             | 2A5  | 2A4  | 2A1  |      |
| 20 | 7A0  | 7A2  | 7A3  | 7A8             |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | 2A11            | 2A8  | 2A6  | GND  |      |
| 21 | 7A5  | 7A6  | 7A7  | 7A12            |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | 2A15            | 2A10 | 2A9  | NC   |      |
| 22 | GND  | 7A9  | 7A11 | 7A15            |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | V <sub>CC</sub> | 2A13 | 2A12 | GND  |      |
| 23 | 7A10 | 7A13 | 7A14 | V <sub>CC</sub> |     |     |      |                 |      |                 |      |     |                                  |                                  |     |     |      |                 |      |                 |      |     | TCK             | NC   | 2A14 | NC   |      |
| 24 | NC   | NC   | TDI  | 0A2             | 0A5 | 0A7 | 0A10 | 0A11            | 0D14 | 0D11            | 0D8  | 0D4 | I <sub>0</sub> /CLK <sub>0</sub> | 1D1                              | 1D5 | 1D9 | 1D14 | 1A13            | 1A10 | 1A8             | 1A7  | 1A4 | 1A1             | NC   | GND  | GND  |      |
| 25 | GND  | GND  | 0A1  | 0A3             | 0A8 | 0A9 | 0A12 | 0A15            | 0D13 | 0D10            | 0D6  | 0D2 | 0D0                              | 1D0                              | 1D4 | 1D8 | 1D10 | 1D13            | 1A15 | 1A14            | 1A9  | 1A5 | 1A2             | NC   | NC   | NC   |      |
| 26 | NC   | NC   | GND  | 0A6             | NC  | GND | 0A13 | 0D15            | GND  | 0D9             | 0D5  | 0D1 | GND                              | I <sub>1</sub> /CLK <sub>1</sub> | 1D3 | 1D6 | GND  | 1D11            | 1D15 | GND             | 1A12 | NC  | GND             | NC   | NC   | NC   |      |

Pin Designations

CLK = Clock

GND = Ground

I = Input

I/O = Input/Output

NC = No Connect

V<sub>CC</sub> = Supply Voltage

TDI = Test Data In

TCK = Test Clock

TMS = Test Mode Select

TDO = Test Data Out

7

D

15

Macrocell (0-15)


PAL Block (A-D)

Segment (0-7)

20446G-031

### Pin Designations

- CLK = Clock
- GND = Ground
- I = Input
- I/O = Input/Output
- NC = No Connect
- V<sub>CC</sub> = Supply Voltage
- TDI = Test Data In
- TCK = Test Clock
- TMS = Test Mode Select
- TDO = Test Data Out




20446G-031

Select devices have been discontinued.  
See Ordering Information section for product status.

## 3.3V M5LV ORDERING INFORMATION<sup>1</sup>

Lattice standard products are available in several packages and operating ranges. The order number (Valid Combination) is formed by a combination of the elements below.



### Note:

1. See below for valid device/package combinations.

| Valid Combinations |                                  |        |
|--------------------|----------------------------------|--------|
| M5LV-128/68        | Commercial:<br>-5, -7, -10, -12  | VC, VI |
| M5LV-128/74        |                                  | VC, VI |
| M5LV-128/104       |                                  | VC, VI |
| M5LV-128/120       |                                  | YC, YI |
| M5LV-256/68        | Industrial:<br>-7, -10, -12, -15 | YC, YI |
| M5LV-256/74        |                                  | VC, VI |
| M5LV-256/104       |                                  | VC, VI |
| M5LV-256/120       |                                  | YC, YI |
| M5LV-256/160       |                                  | YC, YI |

### Device Marking

Actual device marking differs from the ordering part number (OPN). All MACH devices are dual-marked with both Commercial and Industrial grades. The Industrial grade is slower, i.e., M5LV-512/256-7AC-10AI.

| Valid Combinations |                                      |          |
|--------------------|--------------------------------------|----------|
| M5LV-320/120       | Commercial:<br>-6, -7, -10, -12, -15 | YC, YI   |
| M5LV-320/160       |                                      | YC, YI   |
| M5LV-384/120       |                                      | YC, YI   |
| M5LV-384/160       |                                      | YC, YI   |
| M5LV-512/120       | Industrial:<br>-10, -12, -15, -20    | YC, YI   |
| M5LV-512/160       |                                      | YC, YI   |
| M5LV-512/256       |                                      | SAC, SAI |

### Valid Combinations

Valid Combinations list configurations planned to be supported in volume for this device. Consult the local Lattice sales office to confirm availability of specific valid combinations and to check on newly released combinations.

Select devices have been discontinued.  
See Ordering Information section for product status.