



Welcome to E-XFL.COM

What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

Details

Product Status	Obsolete
Core Processor	Z8
Core Size	8-Bit
Speed	8MHz
Connectivity	-
Peripherals	HLVD, POR, WDT
Number of I/O	32
Program Memory Size	4KB (4K x 8)
Program Memory Type	OTP
EEPROM Size	-
RAM Size	237 x 8
Voltage - Supply (Vcc/Vdd)	2V ~ 3.6V
Data Converters	-
Oscillator Type	Internal
Operating Temperature	-40°C ~ 125°C (TA)
Mounting Type	Through Hole
Package / Case	40-DIP (0.620", 15.75mm)
Supplier Device Package	-
Purchase URL	https://www.e-xfl.com/product-detail/zilog/zgp323lap4004c

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

Z8 GPTM OTP MCU Family Product Specification



List of Tables

Table 1.	Features
Table 2.	Power Connections
Table 3.	20-Pin PDIP/SOIC/SSOP/CDIP* Pin Identification
Table 4.	28-Pin PDIP/SOIC/SSOP/CDIP* Pin Identification
Table 5.	40- and 48-Pin Configuration 8
Table 6.	Absolute Maximum Ratings 10
Table 7.	Capacitance
Table 8.	DC Characteristics 11
Table 9.	EPROM/OTP Characteristics
Table 10.	AC Characteristics 15
Table 11.	Port 3 Pin Function Summary 21
Table 12.	CTR0(D)00H Counter/Timer8 Control Register 31
Table 13.	CTR1(0D)01H T8 and T16 Common Functions
Table 14.	CTR2(D)02H: Counter/Timer16 Control Register
Table 15.	CTR3 (D)03H: T8/T16 Control Register 37
Table 16.	Interrupt Types, Sources, and Vectors
Table 17.	IRQ Register 50
Table 18.	SMR2(F)0DH:Stop Mode Recovery Register 2* 56
Table 19.	Stop Mode Recovery Source 58
Table 20.	Watch-Dog Timer Time Select 61
Table 21.	EPROM Selectable Options 62

Z8 GPTM OTP MCU Family Product Specification



Table 2. Power Connections

Connection	Circuit	Device	
Power	V _{CC}	V _{DD}	
Ground	GND	V _{SS}	



Note: Refer to the specific package for available pins.

Figure 1. Functional Block Diagram





Figure 3. 20-Pin PDIP/SOIC/SSOP/CDIP* Pin Configuration

Table 3.	20-Pin PDIP/SOIC/SSOP/CDIP*	Pin	Identification
			achtinoution

Pin #	Symbol	Function	Direction
1–3	P25–P27	Port 2, Bits 5,6,7	Input/Output
4	P07	Port 0, Bit 7	Input/Output
5	V _{DD}	Power Supply	
6	XTAL2	Crystal Oscillator Clock	Output
7	XTAL1	Crystal Oscillator Clock	Input
8–10	P31–P33	Port 3, Bits 1,2,3	Input
11,12	P34. P36	Port 3, Bits 4,6	Output
13	P00/Pref1/P30	Port 0, Bit 0/Analog reference input Port 3 Bit 0	Input/Output for P00 Input for Pref1/P30
14	P01	Port 0, Bit 1	Input/Output
15	V _{SS}	Ground	
16–20	P20-P24	Port 2, Bits 0,1,2,3,4	Input/Output

Note: *Windowed Cerdip. These units are intended to be used for engineering code development only. ZiLOG does not recommend/guarantee this package for production use.

>

Z8 GPTM OTP MCU Family Product Specification



	1		1 7			
NC		1	\bigcirc	18	_	NC
DOF		2		40		NC
P20		2		47		NC DO4
P26		3		40		P24
P27		4		45		P23
P04	E	5		44		P22
N/C		6		43		P21
P05		7		42		P20
P06		8		41		P03
P14		9		40		P13
P15		10		39		P12
P07	E	11	40 D'	38		VSS
VDD	E	12	48-PIN	37		VSS
VDD		13	330P	36		N/C
N/C	C	14		35		P02
P16		15		34		P11
P17		16		33		P10
XTAL2		17		32		P01
XTAL1		18		31		P00
P31		19		30		N/C
P32		20		29		PREF1/P30
P33		21		28		P36
P34		22		27		P37
NC		23		26	_	P35
VSS	H	20		20	_	RESET
.00	_	24		20		

Figure 6. 48-Pin SSOP Pin Configuration

Table 5. 40- and 48-Pin Configuration

40-Pin PDIP/CDIP* #	48-Pin SSOP #	Symbol
26	31	P00
27	32	P01
30	35	P02
34	41	P03
5	5	P04
6	7	P05
7	8	P06
10	11	P07
28	33	P10
29	34	P11
32	39	P12



AC Characteristics

Figure 8 and Table 10 describe the Alternating Current (AC) characteristics.









Figure 12. Port 3 Configuration

Two on-board comparators process analog signals on P31 and P32, with reference to the voltage on Pref1 and P33. The analog function is enabled by programming the Port 3 Mode Register (bit 1). P31 and P32 are programmable as rising, falling, or both edge triggered interrupts (IRQ register bits 6 and 7). Pref1 and P33 are the comparator reference voltage inputs. Access to the Counter Timer edgedetection circuit is through P31 or P20 (see "T8 and T16 Common Functions—



Timers

T8_Capture_HI—HI8(D)0BH

This register holds the captured data from the output of the 8-bit Counter/Timer0. Typically, this register holds the number of counts when the input signal is 1.

Field	Bit Position		Description	
T8_Capture_HI	[7:0]	R/W	Captured Data - No Effect	

T8_Capture_LO—L08(D)0AH

This register holds the captured data from the output of the 8-bit Counter/Timer0. Typically, this register holds the number of counts when the input signal is 0.

Field	Bit Position		Description	
T8_Capture_L0	[7:0]	R/W	Captured Data - No Effect	

T16_Capture_HI—HI16(D)09H

This register holds the captured data from the output of the 16-bit Counter/ Timer16. This register holds the MS-Byte of the data.

Field	Bit Position		Description	
T16_Capture_HI	[7:0]	R/W	Captured Data - No Effect	

T16_Capture_LO—L016(D)08H

This register holds the captured data from the output of the 16-bit Counter/ Timer16. This register holds the LS-Byte of the data.

Field	Bit Position	Description
T16_Capture_LO	[7:0]	R/W Captured Data - No Effect

Counter/Timer2 MS-Byte Hold Register—TC16H(D)07H

Field	Bit Position		Description
T16_Data_HI	[7:0]	R/W	Data

32

Table 12. CTR0(D)00H Counter/Timer8 Control Register (Continued)

Field	Bit Position		Value	Description
Counter_INT_Mask	1-	R/W	0 1	Disable Time-Out Interrupt Enable Time-Out Interrupt
P34_Out	0	R/W	0* 1	P34 as Port Output T8 Output on P34

Note:

*Indicates the value upon Power-On Reset.

T8 Enable

This field enables T8 when set (written) to 1.

Single/Modulo-N

When set to 0 (Modulo-N), the counter reloads the initial value when the terminal count is reached. When set to 1 (single-pass), the counter stops when the terminal count is reached.

Timeout

This bit is set when T8 times out (terminal count reached). To reset this bit, write a 1 to its location.



Caution: Writing a 1 is the only way to reset the Terminal Count status condition. Reset this bit before using/enabling the counter/timers.

The first clock of T8 might not have complete clock width and can occur any time when enabled.

Note: Take care when using the OR or AND commands to manipulate CTR0, bit 5 and CTR1, bits 0 and 1 (Demodulation Mode). These instructions use a Read-Modify-Write sequence in which the current status from the CTR0 and CTR1 registers is ORed or ANDed with the designated value and then written back into the registers.

T8 Clock

This bit defines the frequency of the input signal to T8.

37

In Demodulation Mode, when set to 0, T16 captures and reloads on detection of all the edges. When set to 1, T16 captures and detects on the first edge but ignores the subsequent edges. For details, see the description of T16 Demodulation Mode on page 45.

Time_Out

This bit is set when T16 times out (terminal count reached). To reset the bit, write a 1 to this location.

T16_Clock

This bit defines the frequency of the input signal to Counter/Timer16.

Capture_INT_Mask

This bit is set to allow an interrupt when data is captured into LO16 and HI16.

Counter_INT_Mask

Set this bit to allow an interrupt when T16 times out.

P35_Out

This bit defines whether P35 is used as a normal output pin or T16 output.

CTR3 T8/T16 Control Register—CTR3(D)03H

Table 15 lists and briefly describes the fields for this register. This register allows the T_8 and T_{16} counters to be synchronized.

Table 15. CTR3 (D)03H: 18/116 Control Regist
--

Field	Bit Position		Value	Description	
T ₁₆ Enable	7	R	0*	Counter Disabled	
		R	1	Counter Enabled	
		W	0	Stop Counter	
		W	1	Enable Counter	
T ₈ Enable	-6	R	0*	Counter Disabled	
-		R	1	Counter Enabled	
		W	0	Stop Counter	
		W	1	Enable Counter	
Sync Mode	5	R/W	0**	Disable Sync Mode	
			1	Enable Sync Mode	



Name	Source	Vector Location	Comments
IRQ0	P32	0,1	External (P32), Rising, Falling Edge Triggered
IRQ1	P33	2,3	External (P33), Falling Edge Triggered
IRQ2	P31, T _{IN}	4,5	External (P31), Rising, Falling Edge Triggered
IRQ3	T16	6,7	Internal
IRQ4	T8	8,9	Internal
IRQ5	LVD	10,11	Internal

Table 16. Interrupt Types, Sources, and Vectors

When more than one interrupt is pending, priorities are resolved by a programmable priority encoder controlled by the Interrupt Priority Register. An interrupt machine cycle activates when an interrupt request is granted. As a result, all subsequent interrupts are disabled, and the Program Counter and Status Flags are saved. The cycle then branches to the program memory vector location reserved for that interrupt. All Z8 GPTM OTP MCU Family interrupts are vectored through locations in the program memory. This memory location and the next byte contain the 16-bit address of the interrupt service routine for that particular interrupt request. To accommodate polled interrupt systems, interrupt inputs are masked, and the Interrupt Request register is polled to determine which of the interrupt requests require service.

An interrupt resulting from AN1 is mapped into IRQ2, and an interrupt from AN2 is mapped into IRQ0. Interrupts IRQ2 and IRQ0 can be rising, falling, or both edge triggered. These interrupts are programmable by the user. The software can poll to identify the state of the pin.

Programming bits for the Interrupt Edge Select are located in the IRQ Register (R250), bits D7 and D6. The configuration is indicated in Table 17.

IRQ		Interrupt Edge			
D7	D6	IRQ2 (P31)	IRQ0 (P32)		
0	0	F	F		
0	1	F	R		
1	0	R	F		
1	1	R/F	R/F		
Note: F = Falling Edge; R = Rising Edge					

Table 17. IRQ Register

Power-On Reset

A timer circuit clocked by a dedicated on-board RC-oscillator is used for the Power-On Reset (POR) timer function. The POR time allows V_{DD} and the oscillator circuit to stabilize before instruction execution begins.

The POR timer circuit is a one-shot timer triggered by one of three conditions:

- Power Fail to Power OK status, including Waking up from V_{BO} Standby
- Stop-Mode Recovery (if D5 of SMR = 1)
- WDT Timeout

The POR timer is 2.5 ms minimum. Bit 5 of the Stop-Mode Register determines whether the POR timer is bypassed after Stop-Mode Recovery (typical for external clock).

HALT Mode

This instruction turns off the internal CPU clock, but not the XTAL oscillation. The counter/timers and external interrupts IRQ0, IRQ1, IRQ2, IRQ3, IRQ4, and IRQ5 remain active. The devices are recovered by interrupts, either externally or internally generated. An interrupt request must be executed (enabled) to exit HALT Mode. After the interrupt service routine, the program continues from the instruction after HALT Mode.

STOP Mode

This instruction turns off the internal clock and external crystal oscillation, reducing the standby current to 10 μ A or less. STOP Mode is terminated only by a reset, such as WDT timeout, POR, SMR or external reset. This condition causes the processor to restart the application program at address 000CH. To enter STOP (or HALT) mode, first flush the instruction pipeline to avoid suspending execution in mid-instruction. Execute a NOP (Opcode = FFH) immediately before the appropriate sleep instruction, as follows:





SMR(0F)0BH



* Default after Power On Reset or Watch-Dog Reset

- * * Set after STOP Mode Recovery
- * * * At the XOR gate input

* * * * Default setting after reset. Must be 1 if using a crystal or resonator clock source.

Figure 33. STOP Mode Recovery Register

SCLK/TCLK Divide-by-16 Select (D0)

D0 of the SMR controls a divide-by-16 prescaler of SCLK/TCLK (Figure 34). This control selectively reduces device power consumption during normal processor execution (SCLK control) and/or Halt Mode (where TCLK sources interrupt logic). After Stop Mode Recovery, this bit is set to a 0.

61

Table 20. Watch-Dog Timer Time Select

D1	D0	Timeout of Internal RC-Oscillator
0	0	5ms min.
0	1	10ms min.
1	0	20ms min.
1	1	80ms min.

WDTMR During Halt (D2)

This bit determines whether or not the WDT is active during HALT Mode. A 1 indicates active during HALT. The default is 1. See Figure 38.



* CLR1 and CLR2 enable the WDT/POR and 18 Clock Reset timers respectively upon a Low-to-High input translation.

Figure 38. Resets and WDT





CTR3(0D)03H

D7	D6	D5	D4	D3	D2	D1	D0	
								Reserved No effect when written Always reads 11111
								Sync Mode 0* Disable Sync Mode** 1 Enable Sync Mode
								T ₈ Enable R 0* T ₈ Disabled R 1 T ₈ Enabled W0 Stop T ₈ W1 Enable T ₈
								T ₁₆ Enable R 0* T ₁₆ Disabled R 1 T ₁₆ Enabled W 0 Stop T ₁₆ W 1 Enable T ₁₆

* Default setting after reset. ** Default setting after reset. Not reset with Stop Mode recovery.

Figure 42. T8/T16 Control Register (0D)03H: Read/Write (Except Where Noted)

Note: If Sync Mode is enabled, the first pulse of T8 carrier is always synchronized with T16 (demodulated signal). It can always provide a full carrier pulse.





Note: If used in conjunction with SMR, either of the two specified events causes a Stop-Mode Recovery.

* Default setting after reset

* * At the XOR gate input





R252 Flags(FCH)



Figure 54. Flag Register (FCH: Read/Write)

R253 RP(FDH)



Default setting after reset = 0000 0000

Figure 55. Register Pointer (FDH: Read/Write)

Z8 GP[™] OTP MCU Family Product Specification





0.0.00		MILLIMETER		INCH		
SIMBOL	MIN	NOM	MAX	MIN	NOM	MAX
A	1.73	1.85	1.98	0.068	0.073	0.078
A1	0.05	0.13	0.21	0.002	0.005	0.008
A2	1.68	1.73	1.83	0.066	0.068	0.072
В	0.25	0.30	0.38	0.010	0.012	0.015
С	0.13	0.15	0.22	0.005	0.006	0.009
D	7.07	7.20	7.33	0.278	0.283	0.289
E	5.20	5.30	5.38	0.205	0.209	0.212
e	0.65 BSC				0.0256 BSC	;
Н	7.65	7.80	7.90	0.301	0.307	0.311
L	0.56	0.75	0.94	0.022	0.030	0.037
Q1	0.74	0.78	0.82	0.029	0.031	0.032



CONTROLLING DIMENSIONS : MM LEADS ARE COPLANAR WITHIN .004 INCH.

Figure 61. 20-Pin SSOP Package Diagram

Н

0-"8

DETAIL A

Z8 GP[™] OTP MCU Family Product Specification

INCH

NOM

0.073

0.005

0.068

0.006

0.402

0.209

0.307

0.030

0.0256 TYP



MAX

0.078

0.008

0.070

0.015

0.008

0.407

0.212

0.311

0.037





(
	0-8

DETAIL 'A'

SYMBOL

А

A1

A2

В

С

D

Е

е

Н

L

MIN

1.73

0.05

1.68

0.25

0.09

10.07

5.20

7.65

0.63

CONTROLLING DIMENSIONS: MM LEADS ARE COPLANAR WITHIN .004 INCHES.

MILLIMETER

NOM

1.86

0.13

1.73

_

10.20

5.30

0.65 TYP

7.80

0.75

MAX

1.99

0.21

1.78

0.38

0.20

10.33

5.38

7.90

0.95

MIN

0.068

0.002

0.066

0.010

0.004

0.397

0.205

0.301

0.025

Figure 65. 28-Pin SSOP Package Diagram







Figure 66. 40-Pin CDIP Package



MILLIMETER INCH SYMBOL MIN MAX MIN MAX .040 A1 0.51 .020 A2 3.94 .125 .155 3.18 В 0.38 0.53 .015 .021 B1 .040 .060 1.02 1.52 С 0.38 .009 .015 0.23 D 2.050 2.070 52.07 52.58 Ε 15.24 15.75 .600 .620 .100 TYP E1 13.59 .59 14.22 2.54 TYP .535 e .660 eA 15.49 16.76 .610 3.81 .120 .150 L 3.05 Q1 1.91 .075 1.40 .055 S .060 1.52 2.29 .090

Figure 67. 40-Pin PDIP Package Diagram

CONTROLLING DIMENSIONS : INCH

Z8 GP[™] OTP MCU Family Product Specification



T8 and T16 common control functions 65 T8/T16 control 68 TC16H(D)07h 30 TC16L(D)06h 31 TC8 control 64 TC8H(D)05h 31 TC8L(D)04h 31 voltage detection 69 watch-dog timer 73 register description Counter/Timer2 LS-Byte Hold 31 Counter/Timer2 MS-Byte Hold 30 Counter/Timer8 Control 31 Counter/Timer8 High Hold 31 Counter/Timer8 Low Hold 31 CTR2 Counter/Timer 16 Control 35 CTR3 T8/T16 Control 37 Stop Mode Recovery2 38 T16 Capture LO 30 T8 and T16 Common functions 33 T8_Capture_HI 30 T8 Capture LO 30 register file 28 expanded 24 register pointer 27 detail 29 reset pin function 23 resets and WDT 61

S

SCLK circuit 56 single-pass mode T16_OUT 45 T8_OUT 41 stack 29 standard test conditions 10 standby modes 1 stop instruction, counter/timer 52 stop mode recovery 2 register 59 source 57 stop mode recovery 2 59 stop mode recovery register 55

Т

T16 transmit mode 44 T16_Capture_HI 30 T8 transmit mode 38 T8_Capture_HI 30 test conditions, standard 10 test load diagram 10 timing diagram, AC 14 transmit mode flowchart 39

V

VCC 5 voltage brown-out/standby 62 detection and flags 63 voltage detection register 69

W

watch-dog timer mode registerwatch-dog timer mode register 60 time select 61

Χ

XTAL1 5 XTAL1 pin function 16 XTAL2 5 XTAL2 pin function 16