



Welcome to E-XFL.COM

What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

Details

| Product Status | Obsolete |
|----------------------------|---|
| Core Processor | Z8 |
| Core Size | 8-Bit |
| Speed | 8MHz |
| Connectivity | - |
| Peripherals | HLVD, POR, WDT |
| Number of I/O | 32 |
| Program Memory Size | 32KB (32K x 8) |
| Program Memory Type | ОТР |
| EEPROM Size | - |
| RAM Size | 237 x 8 |
| Voltage - Supply (Vcc/Vdd) | 2V ~ 3.6V |
| Data Converters | - |
| Oscillator Type | Internal |
| Operating Temperature | 0°C ~ 70°C (TA) |
| Mounting Type | Through Hole |
| Package / Case | 40-DIP (0.620", 15.75mm) |
| Supplier Device Package | - |
| Purchase URL | https://www.e-xfl.com/product-detail/zilog/zgp323lsp4032g |

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

Development Features

Table 1 lists the features of $ZiLOG^{(R)}$'s Z8 GP^{TM} OTP MCU Family family members.

Table 1. Features

| Device | OTP (KB) | RAM (Bytes) | I/O Lines | Voltage Range |
|---------------------------|--------------|-------------|--------------|---------------|
| ZGP323L OTP MCU Family | 4, 8, 16, 32 | 237 | 32, 24 or 16 | 2.0V-3.6V |

- Low power consumption–6mW (typical)
- T = Temperature
 - S = Standard 0° to +70°C
 - $E = Extended 40^{\circ} to + 105^{\circ}C$
 - A = Automotive -40° to $+125^{\circ}$ C
- Three standby modes:
 - STOP-2µA (typical)
 - HALT-0.8mA (typical)
 - Low voltage reset
- Special architecture to automate both generation and reception of complex pulses or signals:
 - One programmable 8-bit counter/timer with two capture registers and two load registers
 - One programmable 16-bit counter/timer with one 16-bit capture register pair and one 16-bit load register pair
 - Programmable input glitch filter for pulse reception
- Six priority interrupts
 - Three external
 - Two assigned to counter/timers
 - One low-voltage detection interrupt
- Low voltage detection and high voltage detection flags
- Programmable Watch-Dog Timer/Power-On Reset (WDT/POR) circuits
- Two independent comparators with programmable interrupt polarity
- Programmable EPROM options
 - Port 0: 0–3 pull-up transistors
 - Port 0: 4–7 pull-up transistors





Figure 3. 20-Pin PDIP/SOIC/SSOP/CDIP* Pin Configuration

| Table 3. | 20-Pin PDIP/SOIC/SSOP/CDIP* | Pin | Identification |
|----------|-----------------------------|-----|----------------|
| | | | achtinoution |

| Pin # | Symbol | Function | Direction |
|-------|-----------------|--|---|
| 1–3 | P25–P27 | Port 2, Bits 5,6,7 | Input/Output |
| 4 | P07 | Port 0, Bit 7 | Input/Output |
| 5 | V _{DD} | Power Supply | |
| 6 | XTAL2 | Crystal Oscillator Clock | Output |
| 7 | XTAL1 | Crystal Oscillator Clock | Input |
| 8–10 | P31–P33 | Port 3, Bits 1,2,3 | Input |
| 11,12 | P34. P36 | Port 3, Bits 4,6 | Output |
| 13 | P00/Pref1/P30 | Port 0, Bit 0/Analog reference input Port 3 Bit 0 | Input/Output for P00 Input for Pref1/P30 |
| 14 | P01 | Port 0, Bit 1 | Input/Output |
| 15 | V _{SS} | Ground | |
| 16–20 | P20-P24 | Port 2, Bits 0,1,2,3,4 | Input/Output |

Note: *Windowed Cerdip. These units are intended to be used for engineering code development only. ZiLOG does not recommend/guarantee this package for production use.

>



| P05 5 24 P20 P06 6 28-Pin 23 P03 P07 7 PDIP 22 V _{SS} V _{DD} 8 SOIC 21 P02 XTAL2 9 SSOP 20 P01 XTAL1 10 19 P00 P31 11 P32 12 17 P36 P37 P34 P34 14 15 P35 P35 |
|---|
|---|

Figure 4. 28-Pin PDIP/SOIC/SSOP/CDIP* Pin Configuration

| Table 4. | 28-Pin | PDIP/SOIC/SS | SOP/CDIP* | Pin | Identification |
|----------|--------|--------------|-----------|-----|----------------|
|----------|--------|--------------|-----------|-----|----------------|

| Pin | Symbol | Direction | Description |
|-------|-----------------|--------------|--|
| 1-3 | P25-P27 | Input/Output | Port 2, Bits 5,6,7 |
| 4-7 | P04-P07 | Input/Output | Port 0, Bits 4,5,6,7 |
| 8 | V _{DD} | | Power supply |
| 9 | XTAL2 | Output | Crystal, oscillator clock |
| 10 | XTAL1 | Input | Crystal, oscillator clock |
| 11-13 | P31-P33 | Input | Port 3, Bits 1,2,3 |
| 14 | P34 | Output | Port 3, Bit 4 |
| 15 | P35 | Output | Port 3, Bit 5 |
| 16 | P37 | Output | Port 3, Bit 7 |
| 17 | P36 | Output | Port 3, Bit 6 |
| 18 | Pref1/P30 | Input | Analog ref input; connect to V _{CC} if not used |
| | Port 3 Bit 0 | | Input for Pref1/P30 |
| 19-21 | P00-P02 | Input/Output | Port 0, Bits 0,1,2 |
| 22 | V _{SS} | | Ground |
| 23 | P03 | Input/Output | Port 0, Bit 3 |
| 24-28 | P20-P24 | Input/Output | Port 2, Bits 0-4 |



Note: *Windowed Cerdip. These units are intended to be used for engineering code development only. ZiLOG does not recommend/guarantee this package for production use.





| | Г | | | | |
|-------|----------|----|---------------|------|--------------|
| NC | | 1 | $\overline{}$ | 40 | ⊐ NC |
| P25 | | 2 | | 39 | ⊐ P24 |
| P26 | | 3 | | 38 | ⊐ P23 |
| P27 | | 4 | | 37 | ⊐ P22 |
| P04 | | 5 | | 36 | 🗆 P21 |
| P05 | d | 6 | 40-Pir | 35 | ⊐ P20 |
| P06 | | 7 | PDIP | 34 | ⊐ P03 |
| P14 | | 8 | CDIP' | . 33 | 🗖 P13 |
| P15 | | 9 | • | 32 | ⊐ P12 |
| P07 | d | 10 | | 31 | ⊐ VSS |
| VDD | | 11 | | 30 | ⊐ P02 |
| P16 | d | 12 | | 39 | 🗆 P11 |
| P17 | d | 13 | | 28 | ⊐ P10 |
| XTAL2 | d | 14 | | 27 | ⊐ P01 |
| XTAL1 | d | 15 | | 26 | ⊐ P00 |
| P31 | d | 16 | | 25 | □ Pref1/P30 |
| P32 | d | 17 | | 24 | ⊐ P36 |
| P33 | þ | 18 | | 23 | ⊐ P37 |
| P34 | d | 19 | | 22 | □ <u>P35</u> |
| NC | | 20 | | 21 | RESET |

Figure 5. 40-Pin PDIP/CDIP* Pin Configuration

Note: *Windowed Cerdip. These units are intended to be used for engineering code development only. ZiLOG does not recommend/guarantee this package for production use.

27

The upper nibble of the register pointer (see Figure 16) selects which working register group, of 16 bytes in the register file, is accessed out of the possible 256. The lower nibble selects the expanded register file bank and, in the case of the Z8 GP family, banks 0, F, and D are implemented. A $_{0\rm H}$ in the lower nibble allows the normal register file (bank 0) to be addressed. Any other value from 1H to FH exchanges the lower 16 registers to an expanded register bank.





Figure 16. Register Pointer

Example: Z8 GP: (See Figure 15 on page 26)

R253 RP = 00h R0 = Port 0 R1 = Port 1 R2 = Port 2 R3 = Port 3

But if:

R253 RP = 0Dh R0 = CTRL0 R1 = CTRL1 R2 = CTRL2R3 = Reserved



T16 Transmit Mode

In NORMAL or PING-PONG mode, the output of T16 when not enabled, is dependent on CTR1, D0. If it is a 0, T16_OUT is a 1; if it is a 1, T16_OUT is 0. You can force the output of T16 to either a 0 or 1 whether it is enabled or not by programming CTR1 D3; D2 to a 10 or 11.

When T16 is enabled, TC16H * 256 + TC16L is loaded, and T16_OUT is switched to its initial value (CTR1, D0). When T16 counts down to 0, T16_OUT is toggled (in NORMAL or PING-PONG mode), an interrupt (CTR2, D1) is generated (if enabled), and a status bit (CTR2, D5) is set. See Figure 25.



Figure 25. 16-Bit Counter/Timer Circuits

Note: Global interrupts override this function as described in "Interrupts" on page 48.

If T16 is in SINGLE-PASS mode, it is stopped at this point (see Figure 26). If it is in Modulo-N Mode, it is loaded with TC16H * 256 + TC16L, and the counting continues (see Figure 27).

You can modify the values in TC16H and TC16L at any time. The new values take effect when they are loaded.

Z8 GP[™] OTP MCU Family Product Specification



Caution: Do not load these registers at the time the values are to be loaded into the counter/timer to ensure known operation. An initial count of 1 is not allowed. An initial count of 0 causes T16 to count from 0 to FFFFH to FFFFH. Transition from 0 to FFFFH is not a timeout condition.







Figure 27. T16_OUT in Modulo-N Mode

T16 DEMODULATION Mode

The user must program TC16L and TC16H to FFH. After T16 is enabled, and the first edge (rising, falling, or both depending on CTR1 D5; D4) is detected, T16 captures HI16 and LO16, reloads, and begins counting.

If D6 of CTR2 Is 0

When a subsequent edge (rising, falling, or both depending on CTR1, D5; D4) is detected during counting, the current count in T16 is complemented and put into HI16 and LO16. When data is captured, one of the edge detect status bits (CTR1, D1; D0) is set, and an interrupt is generated if enabled (CTR2, D2). T16 is loaded with FFFFH and starts again.

This T16 mode is generally used to measure space time, the length of time between bursts of carrier signal (marks).



During PING-PONG Mode

The enable bits of T8 and T16 (CTR0, D7; CTR2, D7) are set and cleared alternately by hardware. The timeout bits (CTR0, D5; CTR2, D5) are set every time the counter/timers reach the terminal count.

Timer Output

The output logic for the timers is illustrated in Figure 29. P34 is used to output T8-OUT when D0 of CTR0 is set. P35 is used to output the value of TI6-OUT when D0 of CTR2 is set. When D6 of CTR1 is set, P36 outputs the logic combination of T8-OUT and T16-OUT determined by D5 and D4 of CTR1.

Interrupts

The Z8 GPTM OTP MCU Family features six different interrupts (Table 16). The interrupts are maskable and prioritized (Figure 30). The six sources are divided as follows: three sources are claimed by Port 3 lines P33–P31, two by the counter/ timers (Table 16) and one for low voltage detection. The Interrupt Mask Register (globally or individually) enables or disables the six interrupt requests.

The source for IRQ is determined by bit 1 of the Port 3 mode register (P3M). When in digital mode, Pin P33 is the source. When in analog mode the output of the Stop mode recovery source logic is used as the source for the interrupt. See Figure 35, Stop Mode Recovery Source, on page 57.



Stop Mode Recovery Register 2 (SMR2)

This register determines the mode of Stop Mode Recovery for SMR2 (Figure 36).

SMR2(0F)DH

| D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 |] |
|----|----|----|----|----|----|----|----|--|
| | | | | | | | | Reserved (Must be 0) Reserved (Must be 0) Stop-Mode Recovery Source 2 000 POR Only * 001 NAND P20, P21, P22, P23 010 NAND P20, P21, P22, P23, P24, P25, P26, P27 011 NOR P31, P32, P33 100 NAND P31, P32, P33 101 NOR P31, P32, P33, P00, P07 110 NAND P31, P32, P33, P00, P07 |
| | | | | | | | | Reserved (Must be 0) Recovery Level * * 0 Low * 1 High |
| | | | | | | | | Reserved (Must be 0) |

Note: If used in conjunction with SMR, either of the two specified events causes a Stop-Mode Recovery.

* Default setting after reset

* * At the XOR gate input

Figure 36. Stop Mode Recovery Register 2 ((0F)DH:D2–D4, D6 Write Only)

If SMR2 is used in conjunction with SMR, either of the specified events causes a Stop Mode Recovery.



Note: Port pins configured as outputs are ignored as an SMR or SMR2 recovery source. For example, if the NAND or P23–P20 is selected as the recovery source and P20 is configured as an output, the remaining SMR pins (P23–P21) form the NAND equation.



Watch-Dog Timer Mode Register (WDTMR)

The Watch-Dog Timer (WDT) is a retriggerable one-shot timer that resets the Z8[®] CPU if it reaches its terminal count. The WDT must initially be enabled by executing the WDT instruction. On subsequent executions of the WDT instruction, the WDT is refreshed. The WDT circuit is driven by an on-board RC-oscillator. The WDT instruction affects the Zero (Z), Sign (S), and Overflow (V) flags.

The POR clock source the internal RC-oscillator. Bits 0 and 1 of the WDT register control a tap circuit that determines the minimum timeout period. Bit 2 determines whether the WDT is active during HALT, and Bit 3 determines WDT activity during Stop. Bits 4 through 7 are reserved (Figure 37). This register is accessible only during the first 60 processor cycles (120 XTAL clocks) from the execution of the first instruction after Power-On-Reset, Watch-Dog Reset, or a Stop-Mode Recovery (Figure 36). After this point, the register cannot be modified by any means (intentional or otherwise). The WDTMR cannot be read. The register is located in Bank F of the Expanded Register Group at address location 0Fh. It is organized as shown in Figure 37.

WDTMR(0F)0Fh



* Default setting after reset

Figure 37. Watch-Dog Timer Mode Register (Write Only)

WDT Time Select (D0, D1)

This bit selects the WDT time period. It is configured as indicated in Table 20.



WDTMR During STOP (D3)

This bit determines whether or not the WDT is active during STOP Mode. Because the XTAL clock is stopped during STOP Mode, the on-board RC has to be selected as the clock source to the WDT/POR counter. A 1 indicates active during Stop. The default is 1.

EPROM Selectable Options

There are seven EPROM Selectable Options to choose from based on ROM code requirements. These options are listed in Table 21.

Table 21. EPROM Selectable Options

| Port 00–03 Pull-Ups | On/Off |
|-----------------------------------|--------|
| Port 04–07 Pull-Ups | On/Off |
| Port 10–13 Pull-Ups | On/Off |
| Port 14–17 Pull-Ups | On/Off |
| Port 20–27 Pull-Ups | On/Off |
| EPROM Protection | On/Off |
| Watch-Dog Timer at Power-On Reset | On/Off |

Voltage Brown-Out/Standby

An on-chip Voltage Comparator checks that the V_{DD} is at the required level for correct operation of the device. Reset is globally driven when V_{DD} falls below V_{BO}. A small drop in V_{DD} causes the XTAL1 and XTAL2 circuitry to stop the crystal or resonator clock. If the V_{DD} is allowed to stay above V_{RAM}, the RAM content is preserved. When the power level is returned to above V_{BO}, the device performs a POR and functions normally.



Expanded Register File Control Registers (0D)

The expanded register file control registers (0D) are depicted in Figure 39 through Figure 43.

CTR0(0D)00H



* Default setting after reset

**Default setting after reset. Not reset with Stop Mode recovery.

Figure 39. TC8 Control Register ((0D)O0H: Read/Write Except Where Noted)





Notes: Take care in differentiating the Transmit Mode from Demodulation Mode. Depending on which of these two modes is operating, the CTR1 bit has different functions.

Changing from one mode to another cannot be performed without disabling the counter/timers.



WDTMR(0F)0FH



* Default setting after reset

Figure 47. Watch-Dog Timer Register ((0F) 0FH: Write Only)

Standard Control Registers

R246 P2M(F6H)



* Default setting after reset

Figure 48. Port 2 Mode Register (F6H: Write Only)



ZILOG

R249 IPR(F9H)



Figure 51. Interrupt Priority Register (F9H: Write Only)











Figure 59. 20-Pin PDIP Package Diagram



CONTROLLING DIMENSIONS : INCH



Figure 60. 20-Pin SOIC Package Diagram

| CYLIDOL | MILLI | METER | INCH | | |
|---------|-------|-------|------|------|--|
| STMBOL | MIN | MAX | MIN | MAX | |
| A | 2.40 | 2.65 | .094 | .104 | |
| A1 | 0.10 | 0.30 | .004 | .012 | |
| A2 | 2.24 | 2.44 | .088 | .096 | |
| в | 0.36 | 0.46 | .014 | .018 | |
| С | 0.23 | 0.30 | .009 | .012 | |
| D | 12.60 | 12.95 | .496 | .510 | |
| E | 7.40 | 7.60 | .291 | .299 | |
| e | 1.27 | BSC | .050 | BSC | |
| н | 10.00 | 10.65 | .394 | .419 | |
| h | 0.30 | 0.40 | .012 | .016 | |
| L | 0.60 | 1.00 | .024 | .039 | |
| Q1 | 0.97 | 1.07 | .038 | .042 | |

CONTROLLING DIMENSIONS : MM LEADS ARE COPLANAR WITHIN .004 INCH.

Z8 GP[™] OTP MCU Family Product Specification

INCH

NOM

0.073

0.005

0.068

0.006

0.402

0.209

0.307

0.030

0.0256 TYP



MAX

0.078

0.008

0.070

0.015

0.008

0.407

0.212

0.311

0.037





| (| |
|---|-----|
| | 0-8 |

DETAIL 'A'

SYMBOL

А

A1

A2

В

С

D

Е

е

Н

L

MIN

1.73

0.05

1.68

0.25

0.09

10.07

5.20

7.65

0.63

CONTROLLING DIMENSIONS: MM LEADS ARE COPLANAR WITHIN .004 INCHES.

MILLIMETER

NOM

1.86

0.13

1.73

_

10.20

5.30

0.65 TYP

7.80

0.75

MAX

1.99

0.21

1.78

0.38

0.20

10.33

5.38

7.90

0.95

MIN

0.068

0.002

0.066

0.010

0.004

0.397

0.205

0.301

0.025

Figure 65. 28-Pin SSOP Package Diagram







Figure 66. 40-Pin CDIP Package



MILLIMETER INCH SYMBOL MIN MAX MIN MAX .040 A1 0.51 .020 A2 3.94 .125 .155 3.18 В 0.38 0.53 .015 .021 B1 .040 .060 1.02 1.52 С 0.38 .009 .015 0.23 D 2.050 2.070 52.07 52.58 Ε 15.24 15.75 .600 .620 .100 TYP E1 13.59 .59 14.22 2.54 TYP .535 e .660 eA 15.49 16.76 .610 3.81 .120 .150 L 3.05 Q1 1.91 .075 1.40 .055 S .060 1.52 2.29 .090

Figure 67. 40-Pin PDIP Package Diagram

CONTROLLING DIMENSIONS : INCH



Precharacterization Product

The product represented by this document is newly introduced and ZiLOG has not completed the full characterization of the product. The document states what ZiLOG knows about this product at this time, but additional features or nonconformance with some aspects of the document might be found, either by ZiLOG or its customers in the course of further application and characterization work. In addition, ZiLOG cautions that delivery might be uncertain at times, due to start-up yield issues.

ZiLOG, Inc.

532 Race Street San Jose, CA 95126-3432 Telephone: (408) 558-8500 FAX: 408 558-8300 Internet: <u>http://www.ZiLOG.com</u>

Z8 GP[™] OTP MCU Family Product Specification



Index

Numerics

16-bit counter/timer circuits 44 20-pin DIP package diagram 81 20-pin SSOP package diagram 82 28-pin DIP package diagram 85 28-pin SOICpackage diagram 84 28-pin SSOP package diagram 86 40-pin DIP package diagram 87 48-pin SSOP package diagram 88 8-bit counter/timer circuits 40

Α

absolute maximum ratings 10 AC characteristics 14 timing diagram 14 address spaces, basic 2 architecture 2 expanded register file 26

В

basic address spaces 2 block diagram, ZLP32300 functional 3

С

capacitance 11 characteristics AC 14 DC 11 clock 51 comparator inputs/outputs 23 configuration port 0 17 port 1 18 port 2 19 port 3 20 port 3 counter/timer 22 counter/timer 16-bit circuits 44 8-bit circuits 40 brown-out voltage/standby 62 clock 51 demodulation mode count capture flowchart 42 demodulation mode flowchart 43 EPROM selectable options 62 glitch filter circuitry 38 halt instruction 52 input circuit 38 interrupt block diagram 49 interrupt types, sources and vectors 50 oscillator configuration 51 output circuit 47 ping-pong mode 46 port configuration register 53 resets and WDT 61 SCLK circuit 56 stop instruction 52 stop mode recovery register 55 stop mode recovery register 2 59 stop mode recovery source 57 T16 demodulation mode 45 T16 transmit mode 44 T16_OUT in modulo-N mode 45 T16 OUT in single-pass mode 45 T8 demodulation mode 41 T8 transmit mode 38 T8 OUT in modulo-N mode 41 T8 OUT in single-pass mode 41 transmit mode flowchart 39 voltage detection and flags 63 watch-dog timer mode register 60 watch-dog timer time select 61 CTR(D)01h T8 and T16 Common Functions 33