

Welcome to E-XFL.COM

What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

Details

E·XFI

Product Status	Active
Core Processor	dsPIC
Core Size	16-Bit
Speed	70 MIPs
Connectivity	CANbus, I ² C, IrDA, LINbus, SPI, UART/USART
Peripherals	Brown-out Detect/Reset, DMA, POR, PWM, WDT
Number of I/O	25
Program Memory Size	64KB (22K x 24)
Program Memory Type	FLASH
EEPROM Size	-
RAM Size	4K x 16
Voltage - Supply (Vcc/Vdd)	3V ~ 3.6V
Data Converters	A/D 8x10b/12b
Oscillator Type	Internal
Operating Temperature	-40°C ~ 85°C (TA)
Mounting Type	Surface Mount
Package / Case	36-VFTLA Exposed Pad
Supplier Device Package	36-VTLA (5x5)
Purchase URL	https://www.e-xfl.com/product-detail/microchip-technology/dspic33ep64gp503t-i-tl

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

Pin Diagrams (Continued)



Pin Diagrams (Continued)



TO OUR VALUED CUSTOMERS

It is our intention to provide our valued customers with the best documentation possible to ensure successful use of your Microchip products. To this end, we will continue to improve our publications to better suit your needs. Our publications will be refined and enhanced as new volumes and updates are introduced.

If you have any questions or comments regarding this publication, please contact the Marketing Communications Department via E-mail at **docerrors@microchip.com**. We welcome your feedback.

Most Current Data Sheet

To obtain the most up-to-date version of this data sheet, please register at our Worldwide Web site at:

http://www.microchip.com

You can determine the version of a data sheet by examining its literature number found on the bottom outside corner of any page. The last character of the literature number is the version number, (e.g., DS30000000A is version A of document DS30000000).

Errata

An errata sheet, describing minor operational differences from the data sheet and recommended workarounds, may exist for current devices. As device/documentation issues become known to us, we will publish an errata sheet. The errata will specify the revision of silicon and revision of document to which it applies.

To determine if an errata sheet exists for a particular device, please check with one of the following:

- Microchip's Worldwide Web site; http://www.microchip.com
- Your local Microchip sales office (see last page)

When contacting a sales office, please specify which device, revision of silicon and data sheet (include literature number) you are using.

Customer Notification System

Register on our web site at www.microchip.com to receive the most current information on all of our products.

TABLE 4-37: PMD REGISTER MAP FOR PIC24EPXXXGP20X DEVICES ONLY

File Name	Addr.	Bit 15	Bit 14	Bit 13	Bit 12	Bit 11	Bit 10	Bit 9	Bit 8	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0	All Resets
PMD1	0760	T5MD	T4MD	T3MD	T2MD	T1MD	-	-	-	I2C1MD	U2MD	U1MD	SPI2MD	SPI1MD	—	—	AD1MD	0000
PMD2	0762	_	_	—	_	IC4MD	IC3MD	IC2MD	IC1MD	_	_	_	-	OC4MD	OC3MD	OC2MD	OC1MD	0000
PMD3	0764	_	_	_	_	_	CMPMD	_	_	CRCMD	_	_	_	_	_	I2C2MD	_	0000
PMD4	0766	_	_	_	_	_	_	_	_	_	_	_	_	REFOMD	CTMUMD	_	_	0000
PMD6	076A	_	_	_	_	_	_	_	_	_	_	_	_	_	_	_	_	0000
													DMA0MD					
	0760												DMA1MD	DTCMD				0000
PIVID7	0760	_	_	_	_	_	_	_	_	_	_	_	DMA2MD	PIGMD	_	_	_	0000
													DMA3MD					

Legend: — = unimplemented, read as '0'. Reset values are shown in hexadecimal.

TABLE 4-38: PMD REGISTER MAP FOR PIC24EPXXXMC20X DEVICES ONLY

File Name	Addr.	Bit 15	Bit 14	Bit 13	Bit 12	Bit 11	Bit 10	Bit 9	Bit 8	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0	All Resets
PMD1	0760	T5MD	T4MD	T3MD	T2MD	T1MD	QEI1MD	PWMMD	_	I2C1MD	U2MD	U1MD	SPI2MD	SPI1MD	_	_	AD1MD	0000
PMD2	0762	_	—	—	_	IC4MD	IC3MD	IC2MD	IC1MD	—	_	—		OC4MD	OC3MD	OC2MD	OC1MD	0000
PMD3	0764	_	_	_	_	_	CMPMD	_	_	CRCMD	_	_	_	_	_	I2C2MD	_	0000
PMD4	0766	_	_	_	_	_	_	_	_	_	_	_	_	REFOMD	CTMUMD	_	_	0000
PMD6	076A	_	_	_	_	_	PWM3MD	PWM2MD	PWM1MD	_	_	_	_	_	_	_	_	0000
													DMA0MD					
	0760												DMA1MD	DTCMD				0000
FIND	0/00	_	_	_	_	_	_	_	_	_	_	_	DMA2MD	FIGND	_	_		0000
													DMA3MD					1

Legend: — = unimplemented, read as '0'. Reset values are shown in hexadecimal.

Internut Course	Vector	IRQ		Inte	errupt Bit L	ocation
Interrupt Source	#	#	IVI Address	Flag	Enable	Priority
	Highe	est Natura	al Order Priority			
INT0 – External Interrupt 0	8	0	0x000014	IFS0<0>	IEC0<0>	IPC0<2:0>
IC1 – Input Capture 1	9	1	0x000016	IFS0<1>	IEC0<1>	IPC0<6:4>
OC1 – Output Compare 1	10	2	0x000018	IFS0<2>	IEC0<2>	IPC0<10:8>
T1 – Timer1	11	3	0x00001A	IFS0<3>	IEC0<3>	IPC0<14:12>
DMA0 – DMA Channel 0	12	4	0x00001C	IFS0<4>	IEC0<4>	IPC1<2:0>
IC2 – Input Capture 2	13	5	0x00001E	IFS0<5>	IEC0<5>	IPC1<6:4>
OC2 – Output Compare 2	14	6	0x000020	IFS0<6>	IEC0<6>	IPC1<10:8>
T2 – Timer2	15	7	0x000022	IFS0<7>	IEC0<7>	IPC1<14:12>
T3 – Timer3	16	8	0x000024	IFS0<8>	IEC0<8>	IPC2<2:0>
SPI1E – SPI1 Error	17	9	0x000026	IFS0<9>	IEC0<9>	IPC2<6:4>
SPI1 – SPI1 Transfer Done	18	10	0x000028	IFS0<10>	IEC0<10>	IPC2<10:8>
U1RX – UART1 Receiver	19	11	0x00002A	IFS0<11>	IEC0<11>	IPC2<14:12>
U1TX – UART1 Transmitter	20	12	0x00002C	IFS0<12>	IEC0<12>	IPC3<2:0>
AD1 – ADC1 Convert Done	21	13	0x00002E	IFS0<13>	IEC0<13>	IPC3<6:4>
DMA1 – DMA Channel 1	22	14	0x000030	IFS0<14>	IEC0<14>	IPC3<10:8>
Reserved	23	15	0x000032	_	_	_
SI2C1 – I2C1 Slave Event	24	16	0x000034	IFS1<0>	IEC1<0>	IPC4<2:0>
MI2C1 – I2C1 Master Event	25	17	0x000036	IFS1<1>	IEC1<1>	IPC4<6:4>
CM – Comparator Combined Event	26	18	0x000038	IFS1<2>	IEC1<2>	IPC4<10:8>
CN – Input Change Interrupt	27	19	0x00003A	IFS1<3>	IEC1<3>	IPC4<14:12>
INT1 – External Interrupt 1	28	20	0x00003C	IFS1<4>	IEC1<4>	IPC5<2:0>
Reserved	29-31	21-23	0x00003E-0x000042	_	_	_
DMA2 – DMA Channel 2	32	24	0x000044	IFS1<8>	IEC1<8>	IPC6<2:0>
OC3 – Output Compare 3	33	25	0x000046	IFS1<9>	IEC1<9>	IPC6<6:4>
OC4 – Output Compare 4	34	26	0x000048	IFS1<10>	IEC1<10>	IPC6<10:8>
T4 – Timer4	35	27	0x00004A	IFS1<11>	IEC1<11>	IPC6<14:12>
T5 – Timer5	36	28	0x00004C	IFS1<12>	IEC1<12>	IPC7<2:0>
INT2 – External Interrupt 2	37	29	0x00004E	IFS1<13>	IEC1<13>	IPC7<6:4>
U2RX – UART2 Receiver	38	30	0x000050	IFS1<14>	IEC1<14>	IPC7<10:8>
U2TX – UART2 Transmitter	39	31	0x000052	IFS1<15>	IEC1<15>	IPC7<14:12>
SPI2E – SPI2 Error	40	32	0x000054	IFS2<0>	IEC2<0>	IPC8<2:0>
SPI2 – SPI2 Transfer Done	41	33	0x000056	IFS2<1>	IEC2<1>	IPC8<6:4>
C1RX – CAN1 RX Data Ready ⁽¹⁾	42	34	0x000058	IFS2<2>	IEC2<2>	IPC8<10:8>
C1 – CAN1 Event ⁽¹⁾	43	35	0x00005A	IFS2<3>	IEC2<3>	IPC8<14:12>
DMA3 – DMA Channel 3	44	36	0x00005C	IFS2<4>	IEC2<4>	IPC9<2:0>
IC3 – Input Capture 3	45	37	0x00005E	IFS2<5>	IEC2<5>	IPC9<6:4>
IC4 – Input Capture 4	46	38	0x000060	IFS2<6>	IEC2<6>	IPC9<10:8>
Reserved	47-56	39-48	0x000062-0x000074	—	—	_
SI2C2 – I2C2 Slave Event	57	49	0x000076	IFS3<1>	IEC3<1>	IPC12<6:4>
MI2C2 – I2C2 Master Event	58	50	0x000078	IFS3<2>	IEC3<2>	IPC12<10:8>
Reserved	59-64	51-56	0x00007A-0x000084			
PSEM – PWM Special Event Match ⁽²⁾	65	57	0x000086	IFS3<9>	IEC3<9>	IPC14<6:4>

TABLE 7-1: INTERRUPT VECTOR DETAILS

Note 1: This interrupt source is available on dsPIC33EPXXXGP50X and dsPIC33EPXXXMC50X devices only.

2: This interrupt source is available on dsPIC33EPXXXMC20X/50X and PIC24EPXXXMC20X devices only.

REGISTER 7-3: INTCON1: INTERRUPT CONTROL REGISTER 1 (CONTINUED)

bit 4	MATHERR: Math Error Status bit
	1 = Math error trap has occurred
	0 = Math error trap has not occurred
bit 3	ADDRERR: Address Error Trap Status bit
	1 = Address error trap has occurred0 = Address error trap has not occurred
bit 2	STKERR: Stack Error Trap Status bit
	1 = Stack error trap has occurred
	0 = Stack error trap has not occurred
bit 1	OSCFAIL: Oscillator Failure Trap Status bit
	1 = Oscillator failure trap has occurred
	0 = Oscillator failure trap has not occurred
bit 0	Unimplemented: Read as '0'

Note 1: These bits are available on dsPIC33EPXXXMC20X/50X and dsPIC33EPXXXGP50X devices only.

U-0	U-0	U-0	U-0	U-0	U-0	U-0	U-0
—	—	—		—	—	—	
bit 15							bit 8
U-0	U-0	U-0	U-0	R-0	R-0	R-0	R-0
		<u> </u>		RQCOL3	RQCOL2	RQCOL1	RQCOL0
bit 7							bit 0
Legend:							
R = Readable	bit	W = Writable	bit	U = Unimpler	mented bit, read	as '0'	
-n = Value at I	POR	'1' = Bit is set		'0' = Bit is cle	ared	x = Bit is unkr	iown
bit 15-4	Unimplemen	ted: Read as '	י)				
bit 3	RQCOL3: DM	IA Channel 3 T	ransfer Requ	est Collision Fl	lag bit		
	1 = User forc	e and interrupt	-based reques	st collision is d	etected		
	0 = No reque	est collision is d	etected				
bit 2	RQCOL2: DM	IA Channel 2 T	ransfer Requ	est Collision Fl	lag bit		
	1 = User forc	e and interrupt	-based reques	st collision is d	etected		
	0 = No reque	est collision is d	etected				
bit 1	RQCOL1: DM	1A Channel 1 T	ransfer Reque	est Collision Fl	lag bit		
	1 = User forc 0 = No reque	e and interrupt st collision is d	-based reques etected	st collision is d	etected		
bit 0	RQCOL0: DM	1A Channel 0 T	ransfer Requ	est Collision Fl	lag bit		
	1 = User forc	e and interrupt	-based reques	st collision is d	etected		

REGISTER 8-12: DMARQC: DMA REQUEST COLLISION STATUS REGISTER

0 = No request collision is detected

10.3 Doze Mode

The preferred strategies for reducing power consumption are changing clock speed and invoking one of the powersaving modes. In some circumstances, this cannot be practical. For example, it may be necessary for an application to maintain uninterrupted synchronous communication, even while it is doing nothing else. Reducing system clock speed can introduce communication errors, while using a power-saving mode can stop communications completely.

Doze mode is a simple and effective alternative method to reduce power consumption while the device is still executing code. In this mode, the system clock continues to operate from the same source and at the same speed. Peripheral modules continue to be clocked at the same speed, while the CPU clock speed is reduced. Synchronization between the two clock domains is maintained, allowing the peripherals to access the SFRs while the CPU executes code at a slower rate.

Doze mode is enabled by setting the DOZEN bit (CLKDIV<11>). The ratio between peripheral and core clock speed is determined by the DOZE<2:0> bits (CLKDIV<14:12>). There are eight possible configurations, from 1:1 to 1:128, with 1:1 being the default setting.

Programs can use Doze mode to selectively reduce power consumption in event-driven applications. This allows clock-sensitive functions, such as synchronous communications, to continue without interruption while the CPU Idles, waiting for something to invoke an interrupt routine. An automatic return to full-speed CPU operation on interrupts can be enabled by setting the ROI bit (CLKDIV<15>). By default, interrupt events have no effect on Doze mode operation.

For example, suppose the device is operating at 20 MIPS and the ECAN[™] module has been configured for 500 kbps, based on this device operating speed. If the device is placed in Doze mode with a clock frequency ratio of 1:4, the ECAN module continues to communicate at the required bit rate of 500 kbps, but the CPU now starts executing instructions at a frequency of 5 MIPS.

10.4 Peripheral Module Disable

The Peripheral Module Disable (PMD) registers provide a method to disable a peripheral module by stopping all clock sources supplied to that module. When a peripheral is disabled using the appropriate PMD control bit, the peripheral is in a minimum power consumption state. The control and status registers associated with the peripheral are also disabled, so writes to those registers do not have effect and read values are invalid.

A peripheral module is enabled only if both the associated bit in the PMD register is cleared and the peripheral is supported by the specific dsPIC[®] DSC variant. If the peripheral is present in the device, it is enabled in the PMD register by default.

Note:	If a PMD bit is set, the corresponding
	module is disabled after a delay of one
	instruction cycle. Similarly, if a PMD bit is
	cleared, the corresponding module is
	enabled after a delay of one instruction
	cycle (assuming the module control regis-
	ters are already configured to enable
	module operation).

10.5 Power-Saving Resources

Many useful resources are provided on the main product page of the Microchip web site for the devices listed in this data sheet. This product page, which can be accessed using this link, contains the latest updates and additional information.



10.5.1 KEY RESOURCES

- "Watchdog Timer and Power-Saving Modes" (DS70615) in the "dsPIC33/PIC24 Family Reference Manual"
- Code Samples
- Application Notes
- Software Libraries
- Webinars
- All Related "dsPIC33/PIC24 Family Reference Manual" Sections
- Development Tools

REGISTER	(10-2: PMD	2: PERIPHER		DISABLE C	UNIKOL RE	GISTER 2	
U-0	U-0	U-0	U-0	R/W-0	R/W-0	R/W-0	R/W-0
_	—	—	_	IC4MD	IC3MD	IC2MD	IC1MD
bit 15							bit 8
U-0	U-0	U-0	U-0	R/W-0	R/W-0	R/W-0	R/W-0
			_	OC4MD	OC3MD	OC2MD	OC1MD
bit 7							bit 0
Legend:							
R = Readab	ole bit	W = Writable b	bit	U = Unimplen	nented bit, read	d as '0'	
-n = Value a	at POR	'1' = Bit is set		'0' = Bit is cle	ared	x = Bit is unkr	iown
hit 15-12	Unimpleme	nted: Read as '(,'				
bit 11		It Capture 4 Mod	, Iula Disabla bi	+			
	1 = Input Ca	nture 4 module i	s disabled	L .			
	0 = Input Ca	pture 4 module i	s enabled				
bit 10	IC3MD: Inpu	It Capture 3 Mod	ule Disable bi	t			
	1 = Input Ca	, pture 3 module i	s disabled				
	0 = Input Ca	pture 3 module i	s enabled				
bit 9	IC2MD: Inpu	it Capture 2 Mod	ule Disable bi	t			
	1 = Input Ca	pture 2 module i	s disabled				
hit 0		plure 2 mouule i					
DILO		nturo 1 modulo i	ule Disable bi	L			
	0 = Input Ca	pture 1 module i pture 1 module i	s enabled				
bit 7-4	Unimpleme	nted: Read as '0)'				
bit 3	OC4MD: Ou	tput Compare 4	Module Disab	le bit			
	1 = Output C	 Compare 4 modu	le is disabled				
	0 = Output C	ompare 4 modu	le is enabled				
bit 2	OC3MD: Ou	tput Compare 3	Module Disab	le bit			
	1 = Output C	ompare 3 modu	le is disabled				
	0 = Output C	compare 3 modu	le is enabled				
bit 1	OC2MD: Ou	tput Compare 2	Module Disab	le bit			
	1 = Output C	Compare 2 modu	le is disabled				
h:+ 0		ompare 2 modu	le is enabled Medule Disch				
		ipui Compare 1					
	$\perp = Output C$ 0 = Output C	Compare 1 modu	le is usabled				

~

U-0	U-0	U-0	U-0	U-0	U-0	U-0	U-0
	_	—	—	_	—	_	—
bit 15		L	I	4			bit 8
U-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0
—				INT2R<6:0>			
bit 7							bit 0
Legend:							
R = Readable	bit	W = Writable	bit	U = Unimpler	mented bit, read	l as '0'	
-n = Value at F	POR	'1' = Bit is set		'0' = Bit is cle	ared	x = Bit is unkr	nown
-n = Value at F	POR	'1' = Bit is set		'0' = Bit is cle	ared	x = Bit is unkr	iown
-n = Value at F bit 15-7	POR Unimplemen	<pre>'1' = Bit is set ted: Read as '0</pre>	0'	ʻ0' = Bit is cle	ared	x = Bit is unkr	iown
-n = Value at F bit 15-7 bit 6-0	Unimplement INT2R<6:0>: (see Table 11-	'1' = Bit is set ted: Read as '0 Assign Externa -2 for input pin)' al Interrupt 2 (selection nun	'0' = Bit is cle (INT2) to the C nbers)	orresponding R	x = Bit is unkr Pn Pin bits	iown
-n = Value at F bit 15-7 bit 6-0	POR Unimplement INT2R<6:0>: (see Table 11- 1111001 = In	'1' = Bit is set ted: Read as '0 Assign Externa -2 for input pin uput tied to RPI	o' al Interrupt 2 (selection nun 121	'0' = Bit is cle (INT2) to the C nbers)	ared	x = Bit is unkr Pn Pin bits	iown
-n = Value at F bit 15-7 bit 6-0	OR Unimplemen INT2R<6:0>: (see Table 11- 1111001 = In	'1' = Bit is set ted: Read as '(Assign Externa -2 for input pin put tied to RPI	o' al Interrupt 2 (selection nun 121	'0' = Bit is cle (INT2) to the C nbers)	orresponding R	x = Bit is unkr Pn Pin bits	iown
-n = Value at F bit 15-7 bit 6-0	POR Unimplement INT2R<6:0>: (see Table 11- 1111001 = In	'1' = Bit is set ted: Read as '0 Assign Externa 2 for input pin uput tied to RPI	o' al Interrupt 2 (selection nun 121	'0' = Bit is cle (INT2) to the C nbers)	orresponding R	x = Bit is unkr Pn Pin bits	iown
-n = Value at F bit 15-7 bit 6-0	POR Unimplement INT2R<6:0>: (see Table 11- 1111001 = In	'1' = Bit is set ted: Read as '0 Assign Externa 2 for input pin put tied to RPI	o' al Interrupt 2 (selection nun 121 P1	'0' = Bit is cle (INT2) to the C nbers)	orresponding R	x = Bit is unkr Pn Pin bits	iown
-n = Value at F bit 15-7 bit 6-0	Unimplement INT2R<6:0>: (see Table 11- 1111001 = In 0000001 = In 0000000 = In	'1' = Bit is set ted: Read as '0 Assign Externa 2 for input pin put tied to RPI put tied to CMI put tied to Vss	o' al Interrupt 2 (selection nun 121 P1	'0' = Bit is cle (INT2) to the C nbers)	orresponding R	x = Bit is unkr	iown

REGISTER 11-2: RPINR1: PERIPHERAL PIN SELECT INPUT REGISTER 1

REGISTER 11-3: RPINR3: PERIPHERAL PIN SELECT INPUT REGISTER 3

U-0	U-0	U-0	U-0	U-0	U-0	U-0	U-0
—	_		_				_
bit 15							bit 8
U-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0
—				T2CKR<6:0>			
bit 7							bit 0
Legend:							
R = Readabl	le bit	W = Writable I	bit	U = Unimplem	nented bit, read	as '0'	
-n = Value at	t POR	'1' = Bit is set		'0' = Bit is clea	ared	x = Bit is unkn	own
bit 15-7	Unimplemen	ted: Read as 'o)'				
bit 15-7 bit 6-0	Unimplemen T2CKR<6:0> (see Table 11	ted: Read as '(: Assign Timer2 -2 for input pin)' 2 External Clo selection nur	ock (T2CK) to th nbers)	e Correspondi	ng RPn pin bits	
bit 15-7 bit 6-0	Unimplemen T2CKR<6:0> (see Table 11 1111001 = Ir	ted: Read as '(: Assign Timer2 -2 for input pin nput tied to RPI) [;] 2 External Clo selection nur 121	ock (T2CK) to th nbers)	ie Correspondii	ng RPn pin bits	
bit 15-7 bit 6-0	Unimplemen T2CKR<6:0> (see Table 11 1111001 = Ir	ted: Read as '(: Assign Timer2 -2 for input pin nput tied to RPI) [;] 2 External Clo selection nur 121	ock (T2CK) to th nbers)	e Correspondi	ng RPn pin bits	
bit 15-7 bit 6-0	Unimplemen T2CKR<6:0> (see Table 11 1111001 = Ir	ted: Read as ' : Assign Timer2 -2 for input pin nput tied to RPI)' 2 External Cle selection nur 121	ock (T2CK) to th nbers)	e Correspondi	ng RPn pin bits	
bit 15-7 bit 6-0	Unimplemen T2CKR<6:0> (see Table 11 1111001 = Ir	ted: Read as 'c : Assign Timer2 -2 for input pin nput tied to RPI)' 2 External Clo selection nur 121 P1	ock (T2CK) to th nbers)	le Correspondi	ng RPn pin bits	
bit 15-7 bit 6-0	Unimplemen T2CKR<6:0> (see Table 11 1111001 = Ir 0000001 = Ir 0000000 = Ir	ted: Read as '(: Assign Timer2 -2 for input pin nput tied to RPI nput tied to CMI nput tied to Vss)' 2 External Clo selection nur 121 P1	ock (T2CK) to th nbers)	e Correspondi	ng RPn pin bits	

14.2 Input Capture Registers

REGISTER 14-1: ICxCON1: INPUT CAPTURE x CONTROL REGISTER 1

U-0	U-0	R/W-0	R/W-0	R/W-0	R/W-0	U-0	U-0
—	—	ICSIDL	ICTSEL2	ICTSEL1	ICTSEL0	_	—
bit 15							bit 8

U-0	R/W-0	R/W-0	R/HC/HS-0	R/HC/HS-0	R/W-0	R/W-0	R/W-0
—	ICI1	ICI0	ICOV	ICBNE	ICM2	ICM1	ICM0
bit 7							bit 0

Legend:	HC = Hardware Clearable bit	HS = Hardware Settable bit	
R = Readable bit	W = Writable bit	U = Unimplemented bit, rea	d as '0'
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown

bit 15-14	Unimplemented: Read as '0'
bit 13	ICSIDL: Input Capture Stop in Idle Control bit
	1 = Input capture will Halt in CPU Idle mode
	0 = Input capture will continue to operate in CPU Idle mode
bit 12-10	ICTSEL<2:0>: Input Capture Timer Select bits
	111 = Peripheral clock (FP) is the clock source of the ICx
	110 = Reserved
	101 = Reserved
	100 - 11 CLR is the clock source of the ICx (only the synchronous clock is supported) 011 = T5CLK is the clock source of the ICx
	010 = T4CLK is the clock source of the ICx
	001 = T2CLK is the clock source of the ICx
	000 = T3CLK is the clock source of the ICx
bit 9-7	Unimplemented: Read as '0'
bit 6-5	ICI<1:0>: Number of Captures per Interrupt Select bits (this field is not used if ICM<2:0> = 001 or 111)
	11 = Interrupt on every fourth capture event
	10 = Interrupt on every third capture event
	01 = Interrupt on every second capture event
hit 4	ICOV: Input Capture Overflow Status Flag bit (read-only)
Dit 4	1 = Input capture buffer overflow occurred
	0 = No input capture buffer overflow occurred
bit 3	ICBNE: Input Capture Buffer Not Empty Status bit (read-only)
	1 = Input capture buffer is not empty, at least one more capture value can be read
	0 = Input capture buffer is empty
bit 2-0	ICM<2:0>: Input Capture Mode Select bits
	111 = Input capture functions as interrupt pin only in CPU Sleep and Idle modes (rising edge detect only, all other control bits are not applicable)
	110 = Unused (module is disabled)
	101 = Capture mode, every 16th rising edge (Prescaler Capture mode)
	100 = Capture mode, every 4th rising edge (Prescaler Capture mode)
	011 = Capture mode, every falling edge (Simple Capture mode)
	001 = Capture mode, every edge rising and falling (Edge Detect mode (ICI<1:0>) is not used in this mode)
	000 = Input capture module is turned off

r							
R/W-0	R/W-0	R/W-0	R/W-0	U-0	U-0	U-0	R/W-0
FLTMD	FLTOUT	FLTTRIEN	OCINV	—	—	—	OC32
bit 15							bit 8
R/W-0	R/W-0, HS	R/W-0	R/W-0	R/W-1	R/W-1	R/W-0	R/W-0
OCTRIC	G TRIGSTAT	OCTRIS	SYNCSEL4	SYNCSEL3	SYNCSEL2	SYNCSEL1	SYNCSEL0
bit 7							bit 0
r							
Legend:		HS = Hardwa	ire Settable bit				
R = Reada	able bit	W = Writable	bit	U = Unimplem	nented bit, read	l as '0'	
-n = Value	at POR	'1' = Bit is set	['0' = Bit is clea	ared	x = Bit is unkn	own
bit 15	FLTMD: Fault	Mode Select	bit				
	1 = Fault mo	de is maintain	ed until the Fa	ault source is r	removed; the c	orresponding	OCFLTx bit is
	cleared in	n software and	a new PWM pe	eriod starts	loved and a po	N DWM poriod	etarte
hit 14							Starts
DIL 14	1 = PWM out	nut is driven h	iah on a Fault				
	0 = PWM out	put is driven lo	w on a Fault				
bit 13	FLTTRIEN: Fa	ault Output Sta	ate Select bit				
	1 = OCx pin i	s tri-stated on	a Fault conditio	on			
	0 = OCx pin I	/O state is def	ined by the FLT	OUT bit on a F	ault condition		
bit 12	OCINV: Outpu	ut Compare x I	nvert bit				
	1 = OCx outp	out is inverted	bo				
hit 11_9		ted: Read as '	0'				
bit 8	OC32. Casca	de Two OCx M	° Iodules Enable	hit (32-hit oper	ration)		
bit 0	1 = Cascade	module opera	tion is enabled		allony		
	0 = Cascade	module opera	tion is disabled				
bit 7	OCTRIG: Out	put Compare >	k Trigger/Sync S	Select bit			
	1 = Triggers (0 = Synchron	OCx from the s izes OCx with	source designat the source des	ted by the SYN	CSELx bits SYNCSELx bit	s	
bit 6	TRIGSTAT: Ti	mer Trigger St	atus bit	0 ,			
	1 = Timer sou	urce has been	triggered and is	s running			
	0 = Timer sou	urce has not be	een triggered a	nd is being held	d clear		
bit 5	OCTRIS: Out	put Compare x	Coutput Pin Dir	ection Select b	it		
	1 = OCx is tri	-stated					
		ompare x mod	ule drives the C	DCx pin			
Note 1:	Do not use the O	Cx module as i	its own Synchro	nization or Trig	ger source.		
2:	When the OCy module as a Trigg	odule is turned jer source, the	l OFF, it sends a OCy module m	a trigger out sig nust be unseled	gnal. If the OCx	module uses t source prior	he OCy to disabling it.
3:	Each Output Com	ipare x module	e (OCx) has one	e PTG Trigger/S	Synchronization	n source. See S	Section 24.0
	PTGO0 = OC1	Jei Generator			malion.		
	PTGO1 = OC2						
	PTGO2 = OC3						
	PTGO3 = OC4						

REGISTER 15-2: OCxCON2: OUTPUT COMPARE x CONTROL REGISTER 2

HS/HC-	0 HS/HC-0	HS/HC-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0
FLTSTAT	-(1) CLSTAT ⁽¹⁾	TRGSTAT	FLTIEN	CLIEN	TRGIEN	ITB ⁽²⁾	MDCS ⁽²⁾
bit 15	bit 15						
R/W-0	R/W-0	R/W-0	U-0	R/W-0	R/W-0	R/W-0	R/W-0
DTC1	DTC0	DTCP ⁽³⁾		MTBS	CAM ^(2,4)	XPRES ⁽⁵⁾	IUE ⁽²⁾
bit 7							bit 0
r							
Legend:		HC = Hardware	Clearable bit	HS = Hardwa	are Settable bit		
R = Reada	able bit	W = Writable b	it	U = Unimplei	mented bit, rea	d as '0'	
-n = Value	at POR	'1' = Bit is set		'0' = Bit is cle	eared	x = Bit is unk	nown
			(4)				
bit 15	FLTSTAT: Fai	ult Interrupt State	us bit ⁽¹⁾				
	1 = Fault inter	rrupt is pending	na				
	This bit is clea	ared by setting F	LTIEN = 0.				
bit 14	CLSTAT: Cur	rent-Limit Interru	pt Status bit ⁽¹⁾				
	1 = Current-li	mit interrupt is pe	ending				
	0 = No curren	t-limit interrupt is	s pending				
	I his bit is clea	ared by setting C	SLIEN = 0.				
bit 13	TRGSTAT: Ir	igger Interrupt S	tatus bit				
	1 = 1 rigger in 0 = No trigger	terrupt is pendin interrupt is pend	g dina				
	This bit is clea	ared by setting T	RGIEN = 0.				
bit 12	FLTIEN: Faul	t Interrupt Enabl	e bit				
	1 = Fault inter	rrupt is enabled					
	0 = Fault inter	rrupt is disabled	and the FLTST	AT bit is cleare	ed		
bit 11	CLIEN: Curre	ent-Limit Interrup	t Enable bit				
	1 = Current-li	mit interrupt is er	habled		cloared		
hit 10		nnt interrupt is ui	sableu allu ille able hit	CLOTAT DIL IS	cleared		
DIL TO	1 = A trigger e	event generates	an interrunt rec	nuest			
	0 = Trigger ev	vent interrupts ar	e disabled and	the TRGSTAT	bit is cleared		
bit 9	ITB: Independ	dent Time Base	Mode bit ⁽²⁾				
	1 = PHASEx	register provides	s time base peri	iod for this PW	/M generator		
	0 = PTPER re	egister provides	timing for this F	WM generato	r		
bit 8	MDCS: Maste	er Duty Cycle Re	gister Select bi	it ⁽²⁾			
	1 = MDC regi 0 = PDCx reg	ster provides du ister provides du	ty cycle informa ity cycle inform	ation for this P ation for this F	WM generator WM generator		
Note 1.	Software must clea	ar the interrunt st	tatus here and i	in the correspo	onding IFSx hit	in the interrur	ot controller
2:	These bits should	not be changed	after the PWM	is enabled (P	TEN = 1		
3:	DTC<1:0> = 11 for	DTCP to be eff	ective; otherwis	se, DTCP is ia	nored.		
4:	The Independent T	ime Base (ITB =	= 1) mode must	be enabled to	use Center-Ali	igned mode. If	ITB = 0, the
	CAM bit is ignored						
_	The second secon		1 I	N 16 11 1 1 1 1 1 1 1 1			

REGISTER 16-7: PWMCONx: PWMx CONTROL REGISTER

5: To operate in External Period Reset mode, the ITB bit must be '1' and the CLMOD bit in the FCLCONx register must be '0'.

R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	U-0	U-0
PHR	PHF	PLR	PLF	FLTLEBEN	CLLEBEN	_	_
bit 15	1		1		1		bit 8
U-0	U-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0
—	—	BCH(")	BCL	BPHH	BPHL	BPLH	BPLL
bit 7							bit 0
Legend:							
R = Readable	bit	W = Writable	bit	U = Unimpler	mented bit, read	as '0'	
-n = Value at F	POR	'1' = Bit is set		'0' = Bit is cle	ared	x = Bit is unkr	nown
bit 15	PHR: PWMxH	Rising Edge	Trigger Enabl	e bit			
	\perp = Rising edg 0 = Leading-E	ge of PyvivixH v Edge Blanking i	anores risina	edge of PWM	anking counter kH		
bit 14	PHF: PWMxH	Falling Edge	Trigger Enabl	e bit			
	1 = Falling ed	ge of PWMxH	will trigger Le	ading-Edge Bla	anking counter		
	0 = Leading-E	Edge Blanking i	gnores falling	g edge of PWM	хH		
bit 13	PLR: PWMxL	. Rising Edge T	rigger Enable	e bit oding Edgo Blo	nking countor		
	0 = Leading-E	Edge Blanking i	gnores rising	edge of PWM	kL		
bit 12	PLF: PWMxL	Falling Edge T	rigger Enable	e bit			
	1 = Falling ed	ge of PWMxL	will trigger Le	ading-Edge Bla	anking counter		
	0 = Leading-E	Edge Blanking i	gnores falling	g edge of PWM	xL		
bit 11	1 = Leading-F	-ault Input Lea Edge Blanking i	ding-Edge Bla	anking Enable	bit		
	0 = Leading-E	Edge Blanking i	s not applied	to selected Fa	ult input		
bit 10	CLLEBEN: C	urrent-Limit Le	ading-Edge E	Blanking Enable	e bit		
	1 = Leading-E	Edge Blanking i	s applied to s	selected curren	t-limit input		
hit 0.6	0 = Leading-E	tode Blanking I	s not applied	to selected cul	rrent-limit input		
bit 5	BCH Blankin	a in Selected F	J Blanking Sign	al High Enable	hit(1)		
bit 5	1 = State blan	kina (of curren	t-limit and/or	Fault input sigr	nals) when seled	ted blanking s	ianal is hiah
	0 = No blankii	ng when select	ed blanking s	signal is high	,	5	0 0
bit 4	BCL: Blanking	g in Selected B	lanking Signa	al Low Enable I	bit ⁽¹⁾		
	1 = State blan	iking (of curren	t-limit and/or	Fault input sigr	nals) when seled	cted blanking s	ignal is low
bit 3	BPHH: Blanki	ing in PWMxH	High Enable	hit			
bit o	1 = State blan	iking (of curren	t-limit and/or	Fault input sigr	nals) when PWN	/IxH output is h	igh
	0 = No blanki	ng when PWM	xH output is h	nigh			-
bit 2	BPHL: Blanki	ng in PWMxH	Low Enable b	pit			
	1 = State blan 0 = No blankii	nking (of curren ng when PWM	t-limit and/or xH output is le	Fault input sigr ow	nals) when PWN	IxH output is lo	W
bit 1	BPLH: Blanki	ng in PWMxL I	High Enable b	oit			
	1 = State blan 0 = No blankii	nking (of curren ng when PWM	t-limit and/or xL output is h	Fault input sigr igh	nals) when PWN	/IxL output is hi	igh
bit 0	BPLL: Blanki	ng in PWMxL L	ow Enable b	it			
	1 = State blan	king (of curren	t-limit and/or	Fault input sigr	nals) when PWN	IxL output is lo	W
	v = i N o diankii		x∟ output is io	JVV			

REGISTER 16-16: LEBCONX: PWMx LEADING-EDGE BLANKING CONTROL REGISTER

Note 1: The blanking signal is selected via the BLANKSELx bits in the AUXCONx register.

REGISTER 17-13: QEI1LECH: QEI1 LESS THAN OR EQUAL COMPARE HIGH WORD REGISTER

R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0				
QEILEC<31:24>											
bit 15	bit 15 bit 8										
R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0				
			QEILE	C<23:16>							
bit 7							bit 0				
Legend:											
R = Readable I	R = Readable bit W = Writable bit U = Unimplemented bit, read as '0'										
-n = Value at POR '1' = Bit is set '0' = Bit is cleared x = Bit is unknown							nown				

bit 15-0 QEILEC<31:16>: High Word Used to Form 32-Bit Less Than or Equal Compare Register (QEI1LEC) bits

REGISTER 17-14: QEI1LECL: QEI1 LESS THAN OR EQUAL COMPARE LOW WORD REGISTER

R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0					
	QEILEC<15:8>											
bit 15							bit 8					
R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0					
			QEILI	EC<7:0>								
bit 7							bit 0					
Legend:												
R = Readable bit W = Writable bit U = Unimplemented bit, read as '0'												
-n = Value at P	OR	'1' = Bit is set		'0' = Bit is cleared x = Bit is unknown								
~												

bit 15-0 QEILEC<15:0>: Low Word Used to Form 32-Bit Less Than or Equal Compare Register (QEI1LEC) bits

19.0 INTER-INTEGRATED CIRCUIT[™] (I²C[™])

- Note 1: This data sheet summarizes the features of the dsPIC33EPXXXGP50X, dsPIC33EPXXXGP50X and PIC24EPXXXGP/MC20X families of devices. It is not intended to be a comprehensive reference source. To complement the information in this data sheet, refer to "Inter-Integrated Circuit™ (I²C™)" (DS70330) in the "dsPIC33/ PIC24 Family Reference Manual", which is available from the Microchip web site (www.microchip.com).
 - 2: Some registers and associated bits described in this section may not be available on all devices. Refer to **Section 4.0 "Memory Organization"** in this data sheet for device-specific register and bit information.
 - 3: There are minimum bit rates of approximately FCY/512. As a result, high processor speeds may not support 100 Kbit/second operation. See timing specifications, IM10 and IM11, and the "Baud Rate Generator" in the "dsPIC33/PIC24 Family Reference Manual".

The dsPIC33EPXXXGP50X, dsPIC33EPXXXMC20X/ 50X and PIC24EPXXXGP/MC20X family of devices contains two Inter-Integrated Circuit (I²C) modules: I2C1 and I2C2.

The l^2C module provides complete hardware support for both Slave and Multi-Master modes of the l^2C serial communication standard, with a 16-bit interface.

The I^2C module has a 2-pin interface:

- · The SCLx pin is clock
- The SDAx pin is data

The I²C module offers the following key features:

- I²C interface supporting both Master and Slave modes of operation
- I²C Slave mode supports 7 and 10-bit addressing
- I²C Master mode supports 7 and 10-bit addressing
- I²C port allows bidirectional transfers between master and slaves
- Serial clock synchronization for I²C port can be used as a handshake mechanism to suspend and resume serial transfer (SCLREL control)
- I²C supports multi-master operation, detects bus collision and arbitrates accordingly
- Intelligent Platform Management Interface (IPMI)
 support
- System Management Bus (SMBus) support

REGISTER 25-5:	CMxMSKCON: COMPARATOR x MASK GATING
	CONTROL REGISTER

R/W-0	U-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0
HLMS		OCEN	OCNEN	OBEN	OBNEN	OAEN	OANEN
bit 15							bit 8
R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0
NAGS	PAGS	ACEN	ACNEN	ABEN	ABNEN	AAEN	AANEN
bit 7							bit 0
Legend							
R = Readable	e hit	W = Writable	hit	= Inimple	mented hit read	1 as '0'	
n = Value at	POR	'1' = Rit is set		(0) = 0	eared	x = Ritis unk	nown
	1010	1 - Dit 13 3C			carca		
bit 15	HLMS: Hiah	or Low-Level	/asking Select	bits			
	1 = The mask	king (blanking)	function will pre	event any asse	erted ('0') compa	rator signal fro	m propagating
	0 = The mas	king (blanking)	function will pre	event any asse	erted ('1') compa	rator signal fro	m propagating
bit 14	Unimpleme	nted: Read as	'0'				
bit 13	OCEN: OR (Gate C Input Er	nable bit				
	1 = MCI is co	onnected to OF	t gate				
	0 = MCI is no	ot connected to	OR gate				
bit 12	OCNEN: OR	Gate C Input	nverted Enable	e bit			
	1 = Inverted	MCI is connect	ed to OR gate	ate			
hit 11		Sate B Input Fr	heeled to on g	juic			
bit II	1 = MBI is co	onnected to OR	aate				
	0 = MBI is no	ot connected to	OR gate				
bit 10	OBNEN: OR	Gate B Input I	nverted Enable	e bit			
	1 = Inverted	MBI is connect	ed to OR gate				
	0 = Inverted	MBI is not con	nected to OR g	jate			
bit 9	OAEN: OR (Gate A Input Er	nable bit				
	1 = MAI is co	onnected to OF	l gate				
hit 8			Norted Enable	o hit			
DILO	1 = Inverted	MAL is connect	red to OR date				
	0 = Inverted	MAI is not con	nected to OR g	gate			
bit 7	NAGS: AND	Gate Output In	nverted Enable	e bit			
	1 = Inverted	ANDI is conne	cted to OR gat	e			
	0 = Inverted	ANDI is not co		gate			
bit 6		Gate Output E	nable bit				
	1 = ANDI is 0 0 = ANDI is r	not connected to O	to OR gate				
bit 5	ACEN: AND	Gate C Input E	Enable bit				
	1 = MCI is co	onnected to AN	D gate				
	0 = MCI is no	ot connected to	AND gate				
bit 4	ACNEN: AN	D Gate C Input	Inverted Enab	ole bit			
	1 = Inverted	MCI is connect	ed to AND gat	e,			
	0 = Inverted	MCI is not con	nected to AND	gate			

	30-37.											
АС СН	ARACTE	RISTICS	$\begin{array}{l} \mbox{Standard Operating Conditions: 3.0V to 3.6V} \\ \mbox{(unless otherwise stated)}^{(1)} \\ \mbox{Operating temperature} & -40^{\circ}C \leq TA \leq +85^{\circ}C \mbox{ for Industrial} \\ & -40^{\circ}C \leq TA \leq +125^{\circ}C \mbox{ for Extended} \end{array}$									
Param No.	Symbol	Characteristic	Conditions									
Device Supply												
AD01	AVDD	Module VDD Supply	Greater of: VDD – 0.3 or 3.0	—	Lesser of: VDD + 0.3 or 3.6	V						
AD02	AVss	Module Vss Supply	Vss – 0.3	_	Vss + 0.3	V						
		·	Refer	ence In	puts							
AD05	Vrefh	VREFH Reference Voltage High		—	AVdd	V	VREFH = VREF+ VREFL = VREF- (Note 1)					
AD05a			3.0	—	3.6	V	VREFH = AVDD VREFL = AVSS = 0					
AD06	VREFL	Reference Voltage Low	AVss	_	AVDD – 2.5	V	(Note 1)					
AD06a	-		0	—	0	V	VREFH = AVDD VREFL = AVSS = 0					
AD07	Vref	Absolute Reference Voltage	2.5	—	3.6	V	VREF = VREFH - VREFL					
AD08	IREF	Current Drain	_	_	10 600	μΑ μΑ	ADC off ADC on					
AD09	IAD	Operating Current ⁽²⁾	—	5	—	mA	ADC operating in 10-bit mode (Note 1)					
			—	2	—	mA	ADC operating in 12-bit mode (Note 1)					
			Ana	log Inp	out	•						
AD12	Vinh	Input Voltage Range Vinн	VINL	_	Vrefh	V	This voltage reflects Sample-and- Hold Channels 0, 1, 2 and 3 (CH0-CH3), positive input					
AD13	VINL	Input Voltage Range VINL	VREFL		AVss + 1V	V	This voltage reflects Sample-and- Hold Channels 0, 1, 2 and 3 (CH0-CH3), negative input					
AD17	Rin	Recommended Impedance of Analog Voltage Source	_		200	Ω	Impedance to achieve maximum performance of ADC					

TABLE 30-57: ADC MODULE SPECIFICATIONS

Note 1: Device is functional at VBORMIN < VDD < VDDMIN, but will have degraded performance. Device functionality is tested, but not characterized. Analog modules (ADC, op amp/comparator and comparator voltage reference) may have degraded performance. Refer to Parameter BO10 in Table 30-13 for the minimum and maximum BOR values.

2: Parameter is characterized but not tested in manufacturing.

44-Lead Plastic Quad Flat, No Lead Package (ML) - 8x8 mm Body [QFN]

Note: For the most current package drawings, please see the Microchip Packaging Specification located at http://www.microchip.com/packaging



	MILLIMETERS				
Dimension	Dimension Limits				
Contact Pitch	E	0.65 BSC			
Optional Center Pad Width	W2			6.60	
Optional Center Pad Length			6.60		
Contact Pad Spacing	C1		8.00		
Contact Pad Spacing	C2		8.00		
Contact Pad Width (X44)	X1			0.35	
Contact Pad Length (X44)			0.85		
Distance Between Pads	G	0.25			

Notes:

1. Dimensioning and tolerancing per ASME Y14.5M

BSC: Basic Dimension. Theoretically exact value shown without tolerances.

Microchip Technology Drawing No. C04-2103B

PRODUCT IDENTIFICATION SYSTEM

To order or obtain information, e.g., on pricing or delivery, refer to the factory or the listed sales office.

Microchip Tradema Architecture — Flash Memory Fam Program Memory S Product Group — Pin Count — Tape and Reel Flag Temperature Range Package Pattern	rk ily ize (Kb (if app	dsPI	C 33 EP 64 MC5 04 T 1/PT - XXX	Examples: dsPIC33EP64MC504-I/PT: dsPIC33, Enhanced Performance, 64-Kbyte Program Memory, Motor Control, 44-Pin, Industrial Temperature, TQFP package.
Architecture:	33 24	= =	16-bit Digital Signal Controller 16-bit Microcontroller	
Flash Memory Family:	EP	=	Enhanced Performance	
Product Group:	GP MC	= =	General Purpose family Motor Control family	
Pin Count:	02 03 04 06	= = =	28-pin 36-pin 44-pin 64-pin	
Temperature Range:	l E	= =	-40°C to+85°C (Industrial) -40°C to+125°C (Extended)	
Package:	ML MR MV PT SO SP SS TL TL		Plastic Quad, No Lead Package - (44-pin) 8x8 mm body (QFN) Plastic Quad, No Lead Package - (28-pin) 6x6 mm body (QFN-S) Plastic Quad, No Lead Package - (64-pin) 9x9 mm body (QFN) Thin Quad, No Lead Package - (64-pin) 9x9 mm body (UQFN) Plastic Thin Quad Flatpack - (64-pin) 10x10 mm body (TQFP) Plastic Thin Quad Flatpack - (64-pin) 10x10 mm body (TQFP) Plastic Small Outline, Wide - (28-pin) 7.50 mm body (SOIC) Skinny Plastic Dual In-Line - (28-pin) 300 mil body (SPDIP) Plastic Shrink Small Outline - (28-pin) 5.30 mm body (SOP) Very Thin Leadless Array - (36-pin) 5x5 mm body (VTLA) Very Thin Leadless Array - (44-pin) 6x6 mm body (VTLA)	