# Intel - 5AGXFB1H4F35C5N Datasheet





Welcome to <u>E-XFL.COM</u>

#### Understanding <u>Embedded - FPGAs (Field</u> <u>Programmable Gate Array)</u>

Embedded - FPGAs, or Field Programmable Gate Arrays, are advanced integrated circuits that offer unparalleled flexibility and performance for digital systems. Unlike traditional fixed-function logic devices, FPGAs can be programmed and reprogrammed to execute a wide array of logical operations, enabling customized functionality tailored to specific applications. This reprogrammability allows developers to iterate designs quickly and implement complex functions without the need for custom hardware.

#### **Applications of Embedded - FPGAs**

The versatility of Embedded - FPGAs makes them indispensable in numerous fields. In telecommunications.

### Details

Detuns	
Product Status	Obsolete
Number of LABs/CLBs	14151
Number of Logic Elements/Cells	300000
Total RAM Bits	17358848
Number of I/O	544
Number of Gates	-
Voltage - Supply	1.07V ~ 1.13V
Mounting Type	Surface Mount
Operating Temperature	0°C ~ 85°C (TJ)
Package / Case	1152-BBGA, FCBGA Exposed Pad
Supplier Device Package	1152-FBGA (35x35)
Purchase URL	https://www.e-xfl.com/product-detail/intel/5agxfb1h4f35c5n

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

AV-51002 2017.02.10

Symbol	Description	Condition	Minimum <sup>(7)</sup>	Typical	Maximum <sup>(7)</sup>	Unit
	HPS I/O	3.3 V	3.135	3.3	3.465	V
V <sub>CCPD_HPS</sub> <sup>(8)</sup>	pre-driver	3.0 V	2.85	3.0	3.15	V
	supply	2.5 V	2.375	2.5	2.625	V
		3.3 V	3.135	3.3	3.465	V
		3.0 V	2.85	3.0	3.15	V
	HPS I/O	2.5 V	2.375	2.5	2.625	V
V <sub>CCIO_HPS</sub>	buffers power	1.8 V	1.71	1.8	1.89	V
	supply	1.5 V	1.425	1.5	1.575	V
		1.35 V <sup>(9)</sup>	1.283	1.35	1.418	V
		1.2 V	1.14	1.2	1.26	V
	HPS reset	3.3 V	3.135	3.3	3.465	V
V	and clock	3.0 V	2.85	3.0	3.15	V
V CCRSTCLK_HPS	power	2.5 V	2.375	2.5	2.625	V
	supply	1.8 V	1.71	1.8	1.89	V
V <sub>CCPLL_HPS</sub>	HPS PLL analog voltage regulator power supply	_	2.375	2.5	2.625	V



<sup>&</sup>lt;sup>(7)</sup> The power supply value describes the budget for the DC (static) power supply tolerance and does not include the dynamic tolerance requirements. Refer to the PDN tool for the additional budget for the dynamic tolerance requirements.

<sup>&</sup>lt;sup>(8)</sup> V<sub>CCPD\_HPS</sub> must be 2.5 V when V<sub>CCIO\_HPS</sub> is 2.5, 1.8, 1.5, or 1.2 V. V<sub>CCPD\_HPS</sub> must be 3.0 V when V<sub>CCIO\_HPS</sub> is 3.0 V. V<sub>CCPD\_HPS</sub> must be 3.3 V when V<sub>CCIO\_HPS</sub> is 3.3 V.

 $<sup>^{(9)}\,</sup>$  V<sub>CCIO\_HPS</sub> 1.35 V is supported for HPS row I/O bank only.

# I/O Pin Leakage Current

# Table 1-6: I/O Pin Leakage Current for Arria V Devices

Symbol	Description	Condition	Min	Тур	Max	Unit
II	Input pin	$V_{I} = 0 V$ to $V_{CCIOMAX}$	-30	—	30	μΑ
I <sub>OZ</sub>	Tri-stated I/O pin	$V_{O} = 0 V$ to $V_{CCIOMAX}$	-30		30	μΑ

# **Bus Hold Specifications**

#### Table 1-7: Bus Hold Parameters for Arria V Devices

The bus-hold trip points are based on calculated input voltages from the JEDEC standard.

								V <sub>CCI</sub>	<sub>0</sub> (V)						
Parameter	Symbol	Condition	1.	.2	1	.5	1	.8	2	.5	3.	.0	3	.3	Unit
			Min	Max	Min	Max	Min	Max	Min	Max	Min	Max	Min	Max	
Bus-hold, low, sustaining current	I <sub>SUSL</sub>	V <sub>IN</sub> > V <sub>IL</sub> (max)	8	_	12		30	_	50		70		70		μΑ
Bus-hold, high, sustaining current	I <sub>SUSH</sub>	V <sub>IN</sub> < V <sub>IH</sub> (min)	-8	_	-12		-30	_	-50		-70	_	-70		μΑ
Bus-hold, low, overdrive current	I <sub>ODL</sub>	$\begin{array}{c} 0 \ \mathrm{V} < \mathrm{V_{IN}} \\ < \mathrm{V_{CCIO}} \end{array}$		125	_	175	_	200		300		500	_	500	μΑ
Bus-hold, high, overdrive current	I <sub>ODH</sub>	0 V <v<sub>IN <v<sub>CCIO</v<sub></v<sub>	_	-125	_	-175	_	-200		-300	_	-500	_	-500	μΑ

Arria V GX, GT, SX, and ST Device Datasheet

**Altera Corporation** 



								V <sub>CCI</sub>	<sub>0</sub> (V)						
Parameter	Symbol	Condition	1	.2	1	.5	1	.8	2	.5	3	.0	3	.3	Unit
			Min	Мах	Min	Max	Min	Max	Min	Мах	Min	Max	Min	Max	
Bus-hold trip point	V <sub>TRIP</sub>	_	0.3	0.9	0.375	1.125	0.68	1.07	0.7	1.7	0.8	2	0.8	2	V

# **OCT Calibration Accuracy Specifications**

If you enable on-chip termination (OCT) calibration, calibration is automatically performed at power up for I/Os connected to the calibration block.

# Table 1-8: OCT Calibration Accuracy Specifications for Arria V Devices

Calibration accuracy for the calibrated on-chip series termination ( $R_S$  OCT) and on-chip parallel termination ( $R_T$  OCT) are applicable at the moment of calibration. When process, voltage, and temperature (PVT) conditions change after calibration, the tolerance may change.

Symbol	Description	Condition (\/)	Ca	alibration Accura	су	Unit
Symbol	Description		–I3, –C4	–I5, –C5	-C6	Ont
25-Ω R <sub>S</sub>	Internal series termination with calibration (25- $\Omega$ setting)	V <sub>CCIO</sub> = 3.0, 2.5, 1.8, 1.5, 1.2	±15	±15	±15	%
50-Ω R <sub>S</sub>	Internal series termination with calibration (50- $\Omega$ setting)	V <sub>CCIO</sub> = 3.0, 2.5, 1.8, 1.5, 1.2	±15	±15	±15	%
34- $\Omega$ and 40- $\Omega$ $R_S$	Internal series termination with calibration (34- $\Omega$ and 40- $\Omega$ setting)	V <sub>CCIO</sub> = 1.5, 1.35, 1.25, 1.2	±15	±15	±15	%
48-Ω, 60-Ω, and 80- Ω R <sub>S</sub>	Internal series termination with calibration (48- $\Omega$ , 60- $\Omega$ , and 80- $\Omega$ setting)	$V_{CCIO} = 1.2$	±15	±15	±15	%
50-Ω $R_T$	Internal parallel termination with calibration (50- $\Omega$ setting)	V <sub>CCIO</sub> = 2.5, 1.8, 1.5, 1.2	-10 to +40	-10 to +40	-10 to +40	%
20- $\Omega$ , 30- $\Omega$ , 40- $\Omega$ ,60- $\Omega$ , and 120- $\Omega$ R <sub>T</sub>	Internal parallel termination with calibration (20- $\Omega$ , 30- $\Omega$ , 40- $\Omega$ , 60- $\Omega$ , and 120- $\Omega$ setting)	V <sub>CCIO</sub> = 1.5, 1.35, 1.25	-10 to +40	-10 to +40	-10 to +40	%



Symbol/Description	Condition	Transceiver Speed Grade 4			Transc	Unit		
Symbol/Description	Condition	Min	Тур	Max	Min	Тур	Max	Ont
Inter-transceiver block transmitter channel-to- channel skew <sup>(39)</sup>	×N PMA bonded mode			500		_	500	ps

# Table 1-24: CMU PLL Specifications for Arria V GX and SX Devices

Symbol/Description	Transceiver S	peed Grade 4	Transceiver S	peed Grade 6	Unit
Symbol/Description	Min	Мах	Min	Мах	Ont
Supported data range	611	6553.6	611	3125	Mbps
fPLL supported data range	611	3125	611	3125	Mbps

# Table 1-25: Transceiver-FPGA Fabric Interface Specifications for Arria V GX and SX Devices

Symbol/Description	Transceiver Spee	ed Grade 4 and 6	Unit
Symbol Description	Min	Max	
Interface speed (single-width mode)	25	187.5	MHz
Interface speed (double-width mode)	25	163.84	MHz

#### **Related Information**

- CTLE Response at Data Rates > 3.25 Gbps across Supported AC Gain and DC Gain on page 1-35
- CTLE Response at Data Rates  $\leq$  3.25 Gbps across Supported AC Gain and DC Gain on page 1-36
- Arria V GT, GX, ST, and SX Device Family Pin Connection Guidelines Provides more information about the power supply connection for different data rates.



<sup>&</sup>lt;sup>(39)</sup> This specification is only applicable to channels on one side of the device across two transceiver banks.

Protocol	Sub-protocol	Data Rate (Mbps)
	CPRI E6LV	614.4
	CPRI E6HV	614.4
	CPRI E6LVII	614.4
	CPRI E12LV	1,228.8
	CPRI E12HV	1,228.8
	CPRI E12LVII	1,228.8
Common Public Radio Interface (CPRI)	CPRI E24LV	2,457.6
	CPRI E24LVII	2,457.6
	CPRI E30LV	3,072
	CPRI E30LVII	3,072
	CPRI E48LVII	4,915.2
	CPRI E60LVII	6,144
	CPRI E96LVIII <sup>(60)</sup>	9,830.4
Gbps Ethernet (GbE)	GbE 1250	1,250
	OBSAI 768	768
ODSAL	OBSAI 1536	1,536
ODSAI	OBSAI 3072	3,072
	OBSAI 6144	6,144
	SDI 270 SD	270
Serial digital interface (SDI)	SDI 1485 HD	1,485
	SDI 2970 3G	2,970



<sup>&</sup>lt;sup>(60)</sup> You can achieve compliance with TX channel restriction of one HSSI channel per six-channel transceiver bank.

Symbol	Parameter	Condition	Min	Тур	Мах	Unit
t a	Period jitter for dedicated clock output	$F_{OUT} \ge 100 \text{ MHz}$			175	ps (p-p)
CASC_OUTPJ_DC	in cascaded PLLs	F <sub>OUT</sub> < 100 MHz			17.5	mUI (p-p)
t <sub>DRIFT</sub>	Frequency drift after PFDENA is disabled for a duration of 100 $\mu s$	_			±10	%
dK <sub>BIT</sub>	Bit number of Delta Sigma Modulator (DSM)	_	8	24	32	bits
k <sub>VALUE</sub>	Numerator of fraction	_	128	8388608	2147483648	_
f <sub>RES</sub>	Resolution of VCO frequency	$f_{INPFD} = 100 \text{ MHz}$	390625	5.96	0.023	Hz

# **Related Information**

Memory Output Clock Jitter Specifications on page 1-57

Provides more information about the external memory interface clock output jitter specifications.

- Upstream PLL: 0.59 MHz ≤ Upstream PLL BW < 1 MHz
- Downstream PLL: Downstream PLL BW > 2 MHz



<sup>&</sup>lt;sup>(71)</sup> The cascaded PLL specification is only applicable with the following conditions:

# DSP Block Performance Specifications

|--|

		Performance		Unit	
	-I3, -C4	–I5, –C5	-C6	Onit	
	Independent $9 \times 9$ multiplication	370	310	220	MHz
	Independent $18 \times 19$ multiplication	370	310	220	MHz
Modes using One DSP	Independent 18 × 25 multiplication	370	310	220	MHz
	Independent $20 \times 24$ multiplication	370	310	220	MHz
Block	Independent 27 $\times$ 27 multiplication	310	250	200	MHz
	Two $18 \times 19$ multiplier adder mode	370	310	220	MHz
	$18 \times 18$ multiplier added summed with 36- bit input	370	310	220	MHz
Modes using Two DSP Blocks	Complex $18 \times 19$ multiplication	370	310	220	MHz

# Memory Block Performance Specifications

To achieve the maximum memory block performance, use a memory block clock that comes through global clock routing from an on-chip PLL and set to 50% output duty cycle. Use the Quartus Prime software to report timing for the memory block clocking schemes.

When you use the error detection cyclical redundancy check (CRC) feature, there is no degradation in  $f_{MAX}$ .

Arria V GX, GT, SX, and ST Device Datasheet



### Figure 1-10: SPI Slave Timing Diagram



#### **Related Information**

#### SPI Controller, Arria V Hard Processor System Technical Reference Manual

Provides more information about rx\_sample\_delay.

# **SD/MMC Timing Characteristics**

# Table 1-54: Secure Digital (SD)/MultiMediaCard (MMC) Timing Requirements for Arria V Devices

After power up or cold reset, the Boot ROM uses drvsel = 3 and smplsel = 0 to execute the code. At the same time, the SD/MMC controller enters the Identification Phase followed by the Data Phase. During this time, the value of interface output clock SDMMC\_CLK\_OUT changes from a maximum of 400 kHz (Identification Phase) up to a maximum of 12.5 MHz (Data Phase), depending on the internal reference clock SDMMC\_CLK and the CSEL setting. The value of SDMMC\_CLK is based on the external oscillator frequency and has a maximum value of 50 MHz.



Variant	Member Code	Configuration .rbf Size (bits)	IOCSR .rbf Size (bits)
	A1	71,015,712	439,960
	A3	71,015,712	439,960
	A5	101,740,800	446,360
Arria V CY	A7	101,740,800	446,360
	B1	137,785,088	457,368
	B3	137,785,088	457,368
	B5	185,915,808	463,128
	B7	185,915,808	463,128
	C3	71,015,712	439,960
Arria V CT	C7	101,740,800	446,360
Allia v GI	D3	137,785,088	457,368
	D7	185,915,808	463,128
Arria V SV	B3	185,903,680	450,968
Allia V SA	B5	185,903,680	450,968
Arria V ST	D3	185,903,680	450,968
Arria V ST	D5	185,903,680	450,968

# **Minimum Configuration Time Estimation**

# Table 1-73: Minimum Configuration Time Estimation for Arria V Devices

The estimated values are based on the configuration .rbf sizes in Uncompressed .rbf Sizes for Arria V Devices table.



Date	Version	Changes
Date December 2015	Version 2015.12.16	<ul> <li>Updated Quad Serial Peripheral Interface (SPI) Flash Timing Requirements for Arria V Devices table.</li> <li>Updated F<sub>clk</sub>, T<sub>dutycycle</sub>, and T<sub>dssfrst</sub> specifications.</li> <li>Added T<sub>qspi_clk</sub>, T<sub>din_starb</sub>, and T<sub>din_end</sub> specifications.</li> <li>Removed T<sub>dinmax</sub> specifications.</li> <li>Updated the minimum specification for T<sub>clk</sub> to 16.67 ns and removed the maximum specification in SPI Master Timing Requirements for Arria V Devices table.</li> <li>Updated Secure Digital (SD)/MultiMediaCard (MMC) Timing Requirements for Arria V Devices table.</li> <li>Updated T<sub>clk</sub> to T<sub>sdmmc_clk_out</sub> symbol.</li> <li>Updated T<sub>sdmmc_clk_out</sub> and T<sub>d</sub> specifications.</li> <li>Added T<sub>sdmmc_clk</sub>, T<sub>su</sub>, and T<sub>h</sub> specifications.</li> <li>Removed T<sub>dinmax</sub> specifications.</li> <li>Updated the following diagrams:</li> <li>Quad SPI Flash Timing Diagram</li> <li>SD/MMC Timing Diagram</li> </ul>
		<ul> <li>Changed instances of <i>Quartus II</i> to <i>Quartus Prime</i>.</li> </ul>



# 1-98 Document Revision History

Date	Version	Changes
July 2014	3.8	<ul> <li>Added a note in Table 3, Table 4, and Table 5: The power supply value describes the budget for the DC (static) power supply tolerance and does not include the dynamic tolerance requirements. Refer to the PDN tool for the additional budget for the dynamic tolerance requirements.</li> <li>Updated V<sub>CC_HPS</sub> specification in Table 5.</li> <li>Added a note in Table 19: Differential inputs are powered by V<sub>CCPD</sub> which requires 2.5 V.</li> <li>Updated "Minimum differential eye opening at the receiver serial input pins" specification in Table 20 and Table 21.</li> <li>Updated description in "HPS PLL Specifications" section.</li> <li>Updated VCO range maximum specification in Table 39.</li> <li>Updated T<sub>d</sub> and T<sub>h</sub> specifications in Table 45.</li> <li>Added T<sub>h</sub> specification in Table 47 and Figure 13.</li> <li>Updated a note in Figure 20, Figure 21, and Figure 23 as follows: Do not leave DCLK floating after configuration. DCLK is ignored after configuration is complete. It can toggle high or low if required.</li> <li>Removed "Remote update only in AS mode" specification in Table 58.</li> <li>Added DCLK device initialization clock source specification in Table 60.</li> <li>Added description in "Configuration Files" section: The IOCSR .rbf size is specifically for the Configuration via Protocol (CvP) feature.</li> <li>Removed f<sub>MAX_RU_CLK</sub> specification in Table 63.</li> </ul>
February 2014	3.7	<ul> <li>Updated V<sub>CCRSTCLK_HPS</sub> maximum specification in Table 1.</li> <li>Added V<sub>CC_AUX_SHARED</sub> specification in Table 1.</li> </ul>
December 2013	3.6	<ul> <li>Added "HPS PLL Specifications".</li> <li>Added Table 24, Table 39, and Table 40.</li> <li>Updated Table 1, Table 3, Table 5, Table 19, Table 20, Table 21, Table 38, Table 41, Table 42, Table 43, Table 44, Table 45, Table 46, Table 47, Table 48, Table 49, Table 50, Table 51, Table 55, Table 56, and Table 59.</li> <li>Updated Figure 7, Figure 13, Figure 15, Figure 16, and Figure 19.</li> <li>Removed table: GPIO Pulse Width for Arria V Devices.</li> </ul>



Date	Version	Changes
June 2012	2.0	<ul> <li>Updated for the Quartus II software v12.0 release:</li> <li>Restructured document.</li> <li>Updated "Supply Current and Power Consumption" section.</li> <li>Updated Table 20, Table 21, Table 24, Table 25, Table 26, Table 35, Table 39, Table 43, and Table 52.</li> <li>Added Table 22, Table 23, and Table 33.</li> <li>Added Figure 1–1 and Figure 1–2.</li> <li>Added "Initialization" and "Configuration Files" sections.</li> </ul>
February 2012	1.3	<ul> <li>Updated Table 2–1.</li> <li>Updated Transceiver-FPGA Fabric Interface rows in Table 2–20.</li> <li>Updated V<sub>CCP</sub> description.</li> </ul>
December 2011	1.2	Updated Table 2–1 and Table 2–3.
November 2011	1.1	<ul> <li>Updated Table 2–1, Table 2–19, Table 2–26, and Table 2–36.</li> <li>Added Table 2–5.</li> <li>Added Figure 2–4.</li> </ul>
August 2011	1.0	Initial release.



# I/O Standard Specifications

The  $V_{OL}$  and  $V_{OH}$  values are valid at the corresponding  $I_{OH}$  and  $I_{OL}$ , respectively.

### Table 2-16: Single-Ended I/O Standards for Arria V GZ Devices

1/O Standard		V <sub>CCIO</sub> (V)		VII	_ (V)	V <sub>IH</sub>	(V)	V <sub>OL</sub> (V)	V <sub>OH</sub> (V)	Ι (mΔ)	Ι (m Λ)
i/O Stanuaru	Min	Тур	Max	Min	Max	Min	Max	Мах	Min	10L (1114)	10H (111A)
LVTTL	2.85	3	3.15	-0.3	0.8	1.7	3.6	0.4	2.4	2	-2
LVCMOS	2.85	3	3.15	-0.3	0.8	1.7	3.6	0.2	V <sub>CCIO</sub> – 0.2	0.1	-0.1
2.5 V	2.375	2.5	2.625	-0.3	0.7	1.7	3.6	0.4	2	1	-1
1.8 V	1.71	1.8	1.89	-0.3	$0.35 \times V_{ m CCIO}$	0.65 × V <sub>CCIO</sub>	V <sub>CCIO</sub> + 0.3	0.45	V <sub>CCIO</sub> – 0.45	2	-2
1.5 V	1.425	1.5	1.575	-0.3	$0.35 \times V_{ m CCIO}$	0.65 × V <sub>CCIO</sub>	V <sub>CCIO</sub> + 0.3	$0.25  imes V_{ m CCIO}$	$0.75 \times V_{CCIO}$	2	-2
1.2 V	1.14	1.2	1.26	-0.3	$0.35 \times V_{\rm CCIO}$	0.65 × V <sub>CCIO</sub>	V <sub>CCIO</sub> + 0.3	$0.25 \times V_{ m CCIO}$	$0.75 \times V_{CCIO}$	2	-2

# Table 2-17: Single-Ended SSTL, HSTL, and HSUL I/O Reference Voltage Specifications for Arria V GZ Devices

I/O Standard		V <sub>CCIO</sub> (V)			V <sub>REF</sub> (V)			V	T (V)		
	Min	Тур	Max	Min	Тур	Max	Min	Тур	Мах		
SSTL-2 Class I, II	2.375	2.5	2.625	$0.49 \times V_{CCIO}$	$0.5  imes V_{ m CCIO}$	$0.51  imes V_{ m CCIO}$	V <sub>REF</sub> - 0.04	V <sub>REF</sub>	V <sub>REF</sub> + 0.04		
SSTL-18 Class I, II	1.71	1.8	1.89	0.833	0.9	0.969	V <sub>REF</sub> - 0.04	V <sub>REF</sub>	V <sub>REF</sub> + 0.04		
SSTL-15 Class I, II	1.425	1.5	1.575	$0.49 \times V_{CCIO}$	$0.5  imes V_{ m CCIO}$	0.51 × V <sub>CCIO</sub>	$0.49 \times V_{CCIO}$	0.5 × VCCIO	$0.51 \times V_{CCIO}$		



AV-51002 2017.02.10

Symbol/Description	Conditions	Trans	Transceiver Speed Grade 2			Transceiver Speed Grade 3			
Symbol/Description	Conditions	Min	Тур	Max	Min	Тур	Max		
Maximum peak-to-peak differential input voltage V <sub>ID</sub> (diff p-p) before device configuration	—			1.6	—	_	1.6	V	
Maximum peak-to-peak differential	$V_{CCR\_GXB} = 1.0 V$ $(V_{ICM} = 0.75 V)$			1.8	—		1.8	V	
device configuration $^{(146)}$	$V_{CCR\_GXB} = 0.85 V$ $(V_{ICM} = 0.6 V)$			2.4	—		2.4	V	
Minimum differential eye opening at receiver serial input pins <sup>(147)(148)</sup>	_	85		_	85	_	—	mV	
	85– $\Omega$ setting		85 ± 30%	—	—	85 ± 30%	_	Ω	
Differential on-chip termination	100– $\Omega$ setting		100 ± 30%	—	—	100 ± 30%	_	Ω	
resistors	120– $\Omega$ setting		120 ± 30%	—	_	120 ± 30%	—	Ω	
	150– $\Omega$ setting		150 ± 30%	_	_	150 ± 30%	_	Ω	



<sup>&</sup>lt;sup>(146)</sup> The maximum peak to peak differential input voltage  $V_{ID}$  after device configuration is equal to 4 × (absolute  $V_{MAX}$  for receiver pin -  $V_{ICM}$ ).

<sup>&</sup>lt;sup>(147)</sup> The differential eye opening specification at the receiver input pins assumes that **Receiver Equalization** is disabled. If you enable **Receiver Equalization**, the receiver circuitry can tolerate a lower minimum eye opening, depending on the equalization level.

<sup>&</sup>lt;sup>(148)</sup> Minimum eye opening of 85 mV is only for the unstressed input eye condition.

Symbol/Description	Conditions	Transceiver Speed Grade 2			Transc	Unit			
Symbol/Description	Conditions	Min	Тур	Мах	Min	Тур	Max		
Supported data range	_	600		3250/ 3125 <sup>(158)</sup>	600		3250/ 3125 <sup>(158)</sup>	Mbps	
t <sub>pll_powerdown</sub> <sup>(159)</sup>	_	1			1			μs	
t <sub>pll_lock</sub> <sup>(160)</sup>	_			10			10	μs	

#### **Related Information**

#### Arria V Device Overview

For more information about device ordering codes.

# **Clock Network Data Rate**

# Table 2-29: Clock Network Maximum Data Rate Transmitter Specifications

Valid data rates below the maximum specified in this table depend on the reference clock frequency and the PLL counter settings. Check the MegaWizard message during the PHY IP instantiation.

		ATX PLL			CMU PLL (161)		fPLL		
Clock Network	Non-bonded Mode (Gbps)	Bonded Mode (Gbps)	Channel Span	Non-bonded Mode (Gbps)	Bonded Mode (Gbps)	Channel Span	Non-bonded Mode (Gbps)	Bonded Mode (Gbps)	Channel Span
x1 <sup>(162)</sup>	12.5	_	6	12.5	_	6	3.125	_	3
x6 <sup>(162)</sup>	_	12.5	6	_	12.5	6	_	3.125	6
x6 PLL Feedback <sup>(163)</sup>	_	12.5	Side-wide	_	12.5	Side-wide	_	_	—

<sup>&</sup>lt;sup>(158)</sup> When you use fPLL as a TXPLL of the transceiver.



 $<sup>^{(159)}</sup>$  t<sub>pll\_powerdown</sub> is the PLL powerdown minimum pulse width.

<sup>(160)</sup>  $t_{pll \ lock}$  is the time required for the transmitter CMU/ATX PLL to lock to the input reference clock frequency after coming out of reset.

<sup>&</sup>lt;sup>(161)</sup> ATX PLL is recommended at 8 Gbps and above data rates for improved jitter performance.

<sup>&</sup>lt;sup>(162)</sup> Channel span is within a transceiver bank.

<sup>&</sup>lt;sup>(163)</sup> Side-wide channel bonding is allowed up to the maximum supported by the PHY IP.

# **Core Performance Specifications**

# **Clock Tree Specifications**

# Table 2-33: Clock Tree Performance for Arria V GZ Devices

Symbol	Perfo	llait		
зульог	C3, I3L	C4, I4	Onic	
Global and Regional Clock	650	580	MHz	
Periphery Clock	500	500	MHz	

# **PLL Specifications**

# Table 2-34: PLL Specifications for Arria V GZ Devices

Symbol	Parameter	Min	Тур	Мах	Unit
<b>f</b> (167)	Input clock frequency (C3, I3L speed grade)	5	—	800	MHz
IIN	Input clock frequency (C4, I4 speed grade)	5	—	650	MHz
f <sub>INPFD</sub>	Input frequency to the PFD	5	_	325	MHz
f <sub>FINPFD</sub>	Fractional Input clock frequency to the PFD	50	_	160	MHz
f	PLL VCO operating range (C3, I3L speed grade)	600	_	1600	MHz
t <sub>VCO</sub> (108)	PLL VCO operating range (C4, I4 speed grade)	600	—	1300	MHz
t <sub>EINDUTY</sub>	Input clock or external feedback clock input duty cycle	40	_	60	%

<sup>(167)</sup> This specification is limited in the Quartus II software by the I/O maximum frequency. The maximum I/O frequency is different for each I/O standard.

<sup>(168)</sup> The VCO frequency reported by the Quartus II software in the **PLL Usage Summary** section of the compilation report takes into consideration the VCO post-scale counter K value. Therefore, if the counter K has a value of 2, the frequency reported can be lower than the f<sub>VCO</sub> specification.

Arria V GZ Device Datasheet



# **DLL Range Specifications**

#### Table 2-47: DLL Range Specifications for Arria V GZ Devices

Arria V GZ devices support memory interface frequencies lower than 300 MHz, although the reference clock that feeds the DLL must be at least 300 MHz. To support interfaces below 300 MHz, multiply the reference clock feeding the DLL to ensure the frequency is within the supported range of the DLL.

Parameter	C3, I3L	C4, I4	Unit
DLL operating frequency range	300 - 890	300 - 890	MHz

# **DQS Logic Block Specifications**

#### Table 2-48: DQS Phase Offset Delay Per Setting for Arria V GZ Devices

The typical value equals the average of the minimum and maximum values.

The delay settings are linear with a cumulative delay variation of 40 ps for all speed grades. For example, when using a -3 speed grade and applying a 10-phase offset setting to a 90° phase shift at 400 MHz, the expected average cumulative delay is  $[625 \text{ ps} + (10 \times 11 \text{ ps}) \pm 20 \text{ ps}] = 735 \text{ ps} \pm 20 \text{ ps}$ .

Speed Grade	Min	Мах	Unit
C3, I3L	8	15	ps
C4, I4	8	16	ps

# Table 2-49: DQS Phase Shift Error Specification for DLL-Delayed Clock (t<sub>DQS\_PSERR</sub>) for Arria V GZ Devices

This error specification is the absolute maximum and minimum error. For example, skew on three DQS delay buffers in a -3 speed grade is  $\pm 84$  ps or  $\pm 42$  ps.

Number of DQS Delay Buffers	C3, I3L	C4, I4	Unit
1	30	32	ps
2	60	64	ps
3	90	96	ps

# FPP Configuration Timing when DCLK to DATA[] = 1

# Figure 2-7: FPP Configuration Timing Waveform When the DCLK-to-DATA[] Ratio is 1

Timing waveform for FPP configuration when using a MAX<sup>®</sup> II or MAX V device as an external host.



Notes:

- 1. The beginning of this waveform shows the device in user mode. In user mode, nCONFIG, nSTATUS, and CONF\_DONE are at logic-high levels. When nCONFIG is pulled low, a reconfiguration cycle begins.
- 2. After power-up, the Arria V GZ device holds nSTATUS low for the time of the POR delay.
- 3. After power-up, before and during configuration, CONF\_DONE is low.
- 4. Do not leave DCLK floating after configuration. DCLK is ignored after configuration is complete. It can toggle high or low if required.
- 5. For FPP ×16, use DATA[15..0]. For FPP ×8, use DATA[7..0]. DATA[31..0] are available as a user I/O pin after configuration. The state of this pin depends on the dual-purpose pin settings.
- 6. To ensure a successful configuration, send the entire configuration data to the Arria V GZ device. CONF\_DONE is released high when the Arria V GZ device receives all the configuration data successfully. After CONF\_DONE goes high, send two additional falling edges on DCLK to begin initialization and enter user mode.
- 7. After the option bit to enable the INIT\_DONE pin is configured into the device, the INIT\_DONE goes low.

Arria V GZ Device Datasheet





#### **Related Information**

- Configuration, Design Security, and Remote System Upgrades in Arria V Devices For more information about the reconfiguration input for the ALTREMOTE\_UPDATE IP core, refer to the "User Watchdog Timer" section.
- Configuration, Design Security, and Remote System Upgrades in Arria V Devices For more information about the reset\_timer input for the ALTREMOTE\_UPDATE IP core, refer to the "Remote System Upgrade State Machine" section.

# User Watchdog Internal Oscillator Frequency Specification

# Table 2-65: User Watchdog Internal Oscillator Frequency Specifications

Minimum	Typical	Maximum	Unit
5.3	7.9	12.5	MHz

# I/O Timing

Altera offers two ways to determine I/O timing—the Excel-based I/O Timing and the Quartus II Timing Analyzer.

Excel-based I/O timing provides pin timing performance for each device density and speed grade. The data is typically used prior to designing the FPGA to get an estimate of the timing budget as part of the link timing analysis.

The Quartus II Timing Analyzer provides a more accurate and precise I/O timing data based on the specifics of the design after you complete placeand-route.

#### **Related Information**

# **Arria V Devices Documentation page**

For the Excel-based I/O Timing spreadsheet

#### Arria V GZ Device Datasheet

Altera Corporation



<sup>&</sup>lt;sup>(226)</sup> This is equivalent to strobing the reconfiguration input of the ALTREMOTE\_UPDATE IP core high for the minimum timing specification. For more information, refer to the "Remote System Upgrade State Machine" section in the Configuration, Design Security, and Remote System Upgrades in Arria V Devices chapter.

<sup>&</sup>lt;sup>(227)</sup> This is equivalent to strobing the reset\_timer input of the ALTREMOTE\_UPDATE IP core high for the minimum timing specification. For more information, refer to the "User Watchdog Timer" section in the Configuration, Design Security, and Remote System Upgrades in Arria V Devices chapter.

Term	Definition
t <sub>C</sub>	High-speed receiver and transmitter input and output clock period.
TCCS (channel-to- channel-skew)	The timing difference between the fastest and slowest output edges, including $t_{CO}$ variation and clock skew, across channels driven by the same PLL. The clock is included in the TCCS measurement (refer to the Timing Diagram figure under SW in this table).
t <sub>DUTY</sub>	High-speed I/O block—Duty cycle on the high-speed transmitter output clock.
t <sub>FALL</sub>	Signal high-to-low transition time (80-20%)
t <sub>INCCJ</sub>	Cycle-to-cycle jitter tolerance on the PLL clock input.
t <sub>OUTPJ_IO</sub>	Period jitter on the general purpose I/O driven by a PLL.
t <sub>OUTPJ_DC</sub>	Period jitter on the dedicated clock output driven by a PLL.
t <sub>RISE</sub>	Signal low-to-high transition time (20-80%)
Timing Unit Interval (TUI)	The timing budget allowed for skew, propagation delays, and the data sampling window. (TUI = $1/(\text{receiver input clock frequency multiplication factor}) = t_C/w)$
V <sub>CM(DC)</sub>	DC common mode input voltage.
V <sub>ICM</sub>	Input common mode voltage—The common mode of the differential signal at the receiver.
V <sub>ID</sub>	Input differential voltage swing—The difference in voltage between the positive and complementary conductors of a differential transmission at the receiver.
V <sub>DIF(AC)</sub>	AC differential input voltage—Minimum AC input differential voltage required for switching.
V <sub>DIF(DC)</sub>	DC differential input voltage— Minimum DC input differential voltage required for switching.
V <sub>IH</sub>	Voltage input high—The minimum positive voltage applied to the input which is accepted by the device as a logic high.
V <sub>IH(AC)</sub>	High-level AC input voltage
V <sub>IH(DC)</sub>	High-level DC input voltage
V <sub>IL</sub>	Voltage input low—The maximum positive voltage applied to the input which is accepted by the device as a logic low.
V <sub>IL(AC)</sub>	Low-level AC input voltage
V <sub>IL(DC)</sub>	Low-level DC input voltage

Altera Corporation

