### Intel - 5AGXFB5H4F35C5N Datasheet





Welcome to <u>E-XFL.COM</u>

#### Understanding <u>Embedded - FPGAs (Field</u> <u>Programmable Gate Array)</u>

Embedded - FPGAs, or Field Programmable Gate Arrays, are advanced integrated circuits that offer unparalleled flexibility and performance for digital systems. Unlike traditional fixed-function logic devices, FPGAs can be programmed and reprogrammed to execute a wide array of logical operations, enabling customized functionality tailored to specific applications. This reprogrammability allows developers to iterate designs quickly and implement complex functions without the need for custom hardware.

#### **Applications of Embedded - FPGAs**

The versatility of Embedded - FPGAs makes them indispensable in numerous fields. In telecommunications.

#### Details

2014.10	
Product Status	Obsolete
Number of LABs/CLBs	19811
Number of Logic Elements/Cells	420000
Total RAM Bits	23625728
Number of I/O	544
Number of Gates	-
Voltage - Supply	1.07V ~ 1.13V
Mounting Type	Surface Mount
Operating Temperature	0°C ~ 85°C (TJ)
Package / Case	1152-BBGA, FCBGA Exposed Pad
Supplier Device Package	1152-FBGA (35x35)
Purchase URL	https://www.e-xfl.com/product-detail/intel/5agxfb5h4f35c5n

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

#### 1-4 Recommended Operating Conditions

Symbol	Description	Condition (V)	Overshoot Duration as % of High Time	Unit
		3.8	100	%
		3.85	68	%
		3.9	45	%
		3.95	28	%
		4	15	%
		4.05	13	%
	4.1	11	%	
		4.15	9	%
Vi (AC)	AC input voltage	4.2	8	%
		4.25	7	%
		4.3	5.4	%
		4.35	3.2	%
		4.4	1.9	%
		4.45	1.1	%
		4.5	0.6	%
		4.55	0.4	%
		4.6	0.2	%

# **Recommended Operating Conditions**

This section lists the functional operation limits for the AC and DC parameters for Arria V devices.

### **Recommended Operating Conditions**

# Table 1-3: Recommended Operating Conditions for Arria V Devices

This table lists the steady-state voltage values expected from Arria V devices. Power supply ramps must all be strictly monotonic, without plateaus.



Symbol	Description	Condition (V)	Ca	Unit		
Symbol			-I3, -C4	–I5, –C5	-C6	Ont
60- $\Omega$ and 120- $\Omega$ $R_{T}$	Internal parallel termination with calibration (60- $\Omega$ and 120- $\Omega$ setting)	$V_{CCIO} = 1.2$	-10 to +40	-10 to +40	-10 to +40	%
25- $\Omega R_{S\_left\_shift}$	Internal left shift series termination with calibration (25- $\Omega R_{s\_left\_shift}$ setting)	V <sub>CCIO</sub> = 3.0, 2.5, 1.8, 1.5, 1.2	±15	±15	±15	%

### **OCT Without Calibration Resistance Tolerance Specifications**

### Table 1-9: OCT Without Calibration Resistance Tolerance Specifications for Arria V Devices

This table lists the Arria V OCT without calibration resistance to PVT changes.

Symbol	Description	Condition (V)	Re	Unit		
Symbol	Description		–I3, –C4	–I5, –C5	-C6	Ont
$25-\Omega R_S$	Internal series termination without calibration (25- $\Omega$ setting)	V <sub>CCIO</sub> = 3.0, 2.5	±30	±40	±40	%
25-Ω R <sub>S</sub>	Internal series termination without calibration (25- $\Omega$ setting)	V <sub>CCIO</sub> = 1.8, 1.5	±30	±40	±40	%
$25-\Omega R_S$	Internal series termination without calibration (25- $\Omega$ setting)	$V_{CCIO} = 1.2$	±35	±50	±50	%
50-Ω R <sub>S</sub>	Internal series termination without calibration (50- $\Omega$ setting)	V <sub>CCIO</sub> = 3.0, 2.5	±30	±40	±40	%
50-Ω R <sub>S</sub>	Internal series termination without calibration (50- $\Omega$ setting)	V <sub>CCIO</sub> = 1.8, 1.5	±30	±40	±40	%
50-Ω R <sub>S</sub>	Internal series termination without calibration (50- $\Omega$ setting)	$V_{CCIO} = 1.2$	±35	±50	±50	%
100-Ω R <sub>D</sub>	Internal differential termination $(100-\Omega \text{ setting})$	$V_{CCIO} = 2.5$	±25	±40	±40	%



Symbol/Description	Condition	Transceiver Speed Grade 4		Transceiver Speed Grade 6			Unit		
Symbol/Description	Condition	Min	Тур	Max	Min	Тур	Max	Onit	
Run length	—	—	_	200	—		200	UI	
Programmable equaliza- tion AC and DC gain	AC gain setting = 0 to $3^{(38)}$ DC gain setting = 0 to 1	Refer to C Gain and Response G	Refer to CTLE Response at Data Rates > 3.25 Gbps across Supported AC Gain and DC Gain for Arria V GX, GT, SX, and ST Devices and CTLE Response at Data Rates ≤ 3.25 Gbps across Supported AC Gain and DC Gain for Arria V GX, GT, SX, and ST Devices diagrams.						

### Table 1-23: Transmitter Specifications for Arria V GX and SX Devices

Symbol/Description	Condition	Transceiver Speed Grade 4		Transceiver Speed Grade 6			Unit	
Symbol/Description	Condition	Min	Тур	Max	Min	Тур	Max	Onit
Supported I/O standards		1.5 V PCML						
Data rate	_	611		6553.6	611	_	3125	Mbps
V <sub>OCM</sub> (AC coupled)	_	_	650	_		650	_	mV
V <sub>OCM</sub> (DC coupled)	$\leq$ 3.2Gbps <sup>(32)</sup>	670	700	730	670	700	730	mV
	85- $\Omega$ setting	_	85	_		85	_	Ω
Differential on-chip	100- $\Omega$ setting	—	100	—	_	100	_	Ω
termination resistors	120- $\Omega$ setting		120			120		Ω
	150-Ω setting	_	150	—		150	_	Ω
Intra-differential pair skew	TX $V_{CM}$ = 0.65 V (AC coupled) and slew rate of 15 ps	—	_	15	_	_	15	ps
Intra-transceiver block transmitter channel-to- channel skew	×6 PMA bonded mode	_	_	180	_	—	180	ps

<sup>(37)</sup> The rate match FIFO supports only up to ±300 parts per million (ppm).
 <sup>(38)</sup> The Quartus Prime software allows AC gain setting = 3 for design with data rate between 611 Mbps and 1.25 Gbps only.



Symbol/Description	Condition	Tran	sceiver Speed Gra	Unit	
Symbol/Description	Condition	Min	Тур	Max	Ont
	85- $\Omega$ setting	—	85	—	Ω
Differential on-chip termination	100- $\Omega$ setting	—	100	—	Ω
resistors	120-Ω setting	—	120	—	Ω
	150-Ω setting		150	_	Ω
Intra-differential pair skew	TX $V_{CM}$ = 0.65 V (AC coupled) and slew rate of 15 ps			15	ps
Intra-transceiver block transmitter channel-to-channel skew	×6 PMA bonded mode			180	ps
Inter-transceiver block transmitter channel-to-channel skew <sup>(55)</sup>	× <i>N</i> PMA bonded mode			500	ps

# Table 1-30: CMU PLL Specifications for Arria V GT and ST Devices

Symbol/Description	Transceiver S	peed Grade 3	Unit	
Symbol Description	Min	Max	onit	
Supported data range	0.611	10.3125	Gbps	
fPLL supported data range	611	3125	Mbps	

<sup>(55)</sup> This specification is only applicable to channels on one side of the device across two transceiver banks.



Symbol	V <sub>OD</sub> Setting <sup>(58)</sup>	V <sub>OD</sub> Value (mV)	V <sub>OD</sub> Setting <sup>(58)</sup>	V <sub>OD</sub> Value (mV)
	25	500	53	1060
	26	520	54	1080
	27	540	55	1100
	28	560	56	1120
	29	580	57	1140
	30	600	58	1160
	31	620	59	1180
	32	640	60	1200
	33	660		

# **Transmitter Pre-Emphasis Levels**

The following table lists the simulation data on the transmitter pre-emphasis levels in dB for the first post tap under the following conditions:

- Low-frequency data pattern—five 1s and five 0s
- Data rate—2.5 Gbps

The levels listed are a representation of possible pre-emphasis levels under the specified conditions only and the pre-emphasis levels may change with data pattern and data rate.

Arria V devices only support 1st post tap pre-emphasis with the following conditions:

- The 1st post tap pre-emphasis settings must satisfy  $|B| + |C| \le 60$  where  $|B| = V_{OD}$  setting with termination value,  $R_{TERM} = 100 \Omega$  and |C| = 1st post tap pre-emphasis setting.
- |B| |C| > 5 for data rates < 5 Gbps and |B| |C| > 8.25 for data rates > 5 Gbps.
- $(V_{MAX}/V_{MIN} 1)\% < 600\%$ , where  $V_{MAX} = |B| + |C|$  and  $V_{MIN} = |B| |C|$ .

Exception for PCIe Gen2 design:  $V_{OD}$  setting = 43 and pre-emphasis setting = 19 are allowed for PCIe Gen2 design with transmit de-emphasis – 6dB setting (pipe\_txdeemp = 1'b0) using Altera PCIe Hard IP and PIPE IP cores.



<sup>&</sup>lt;sup>(58)</sup> Convert these values to their binary equivalent form if you are using the dynamic reconfiguration mode for PMA analog controls.

### Figure 1-12: USB Timing Diagram



# Ethernet Media Access Controller (EMAC) Timing Characteristics

# Table 1-56: Reduced Gigabit Media Independent Interface (RGMII) TX Timing Requirements for Arria V Devices

Symbol	Description	Min	Тур	Мах	Unit
T <sub>clk</sub> (1000Base-T)	TX_CLK clock period	_	8		ns
T <sub>clk</sub> (100Base-T)	TX_CLK clock period	_	40		ns
T <sub>clk</sub> (10Base-T)	TX_CLK clock period		400		ns
T <sub>dutycycle</sub>	TX_CLK duty cycle	45	—	55	%
T <sub>d</sub>	TX_CLK to TXD/TX_CTL output data delay	-0.85	—	0.15	ns

### Figure 1-13: RGMII TX Timing Diagram





# Figure 1-16: I<sup>2</sup>C Timing Diagram



# **NAND Timing Characteristics**

### Table 1-60: NAND ONFI 1.0 Timing Requirements for Arria V Devices

The NAND controller supports Open NAND FLASH Interface (ONFI) 1.0 Mode 5 timing as well as legacy NAND devices. This table lists the requirements for ONFI 1.0 mode 5 timing. The HPS NAND controller can meet this timing by programming the c4 output of the main HPS PLL and timing registers provided in the NAND controller.

Symbol	Description	Min	Max	Unit
T <sub>wp</sub> <sup>(89)</sup>	Write enable pulse width	10	—	ns
T <sub>wh</sub> <sup>(89)</sup>	Write enable hold time	7		ns
T <sub>rp</sub> <sup>(89)</sup>	Read enable pulse width	10		ns
T <sub>reh</sub> <sup>(89)</sup>	Read enable hold time	7		ns
T <sub>clesu</sub> <sup>(89)</sup>	Command latch enable to write enable setup time	10		ns
T <sub>cleh</sub> <sup>(89)</sup>	Command latch enable to write enable hold time	5		ns
T <sub>cesu</sub> <sup>(89)</sup>	Chip enable to write enable setup time	15		ns
T <sub>ceh</sub> <sup>(89)</sup>	Chip enable to write enable hold time	5		ns
T <sub>alesu</sub> <sup>(89)</sup>	Address latch enable to write enable setup time	10		ns
T <sub>aleh</sub> <sup>(89)</sup>	Address latch enable to write enable hold time	5		ns
T <sub>dsu</sub> <sup>(89)</sup>	Data to write enable setup time	10		ns

<sup>(89)</sup> Timing of the NAND interface is controlled through the NAND configuration registers.



Symbol	Description	Min	Max	Unit
$T_{dh}^{(89)}$	Data to write enable hold time	5	—	ns
T <sub>cea</sub>	Chip enable to data access time		25	ns
T <sub>rea</sub>	Read enable to data access time		16	ns
T <sub>rhz</sub>	Read enable to data high impedance		100	ns
T <sub>rr</sub>	Ready to read enable low	20	—	ns

# Figure 1-17: NAND Command Latch Timing Diagram





# Initialization

### Table 1-71: Initialization Clock Source Option and the Maximum Frequency for Arria V Devices

Initialization Clock Source	Configuration Scheme	Maximum Frequency (MHz)	Minimum Number of Clock Cycles		
Internal Oscillator	AS, PS, and FPP	12.5			
(107)	PS and FPP	125	Т		
CLKOSK	AS	100	1 init		
DCLK	PS and FPP	125			

# **Configuration Files**

### Table 1-72: Uncompressed .rbf Sizes for Arria V Devices

Use this table to estimate the file size before design compilation. Different configuration file formats, such as a hexadecimal file (.hex) or tabular text file (.ttf) format, have different file sizes.

For the different types of configuration file and file sizes, refer to the Quartus Prime software. However, for a specific version of the Quartus Prime software, any design targeted for the same device has the same uncompressed configuration file size.

The IOCSR raw binary file (.rbf) size is specifically for the Configuration via Protocol (CvP) feature.

Arria V GX, GT, SX, and ST Device Datasheet



<sup>&</sup>lt;sup>(107)</sup> To enable CLKUSR as the initialization clock source, turn on the **Enable user-supplied start-up clock (CLKUSR)** option in the Quartus Prime software from the **General** panel of the **Device and Pin Options** dialog box.

The Quartus Prime Timing Analyzer provides a more accurate and precise I/O timing data based on the specifics of the design after you complete place-and-route.

### **Related Information**

### Arria V I/O Timing Spreadsheet

Provides the Arria V Excel-based I/O timing spreadsheet.

# Programmable IOE Delay

Parameter <sup>(112</sup>	Available Minimum		Fast Model			l la it				
)	Settings	Offset <sup>(113)</sup>	Industrial	Commercial	-C4	-C5	-C6	- <b>I</b> 3	-15	
D1	32	0	0.508	0.517	0.870	1.063	1.063	0.872	1.057	ns
D3	8	0	1.763	1.795	2.999	3.496	3.571	3.031	3.643	ns
D4	32	0	0.508	0.518	0.869	1.063	1.063	1.063	1.057	ns
D5	32	0	0.508	0.517	0.870	1.063	1.063	0.872	1.057	ns

# Table 1-76: I/O element (IOE) Programmable Delay for Arria V Devices

# Programmable Output Buffer Delay

# Table 1-77: Programmable Output Buffer Delay for Arria V Devices

This table lists the delay chain settings that control the rising and falling edge delays of the output buffer.

You can set the programmable output buffer delay in the Quartus Prime software by setting the **Output Buffer Delay Control** assignment to either positive, negative, or both edges, with the specific values stated here (in ps) for the **Output Buffer Delay** assignment.



<sup>&</sup>lt;sup>(112)</sup> You can set this value in the Quartus Prime software by selecting **D1**, **D3**, **D4**, and **D5** in the **Assignment Name** column of **Assignment Editor**.

<sup>&</sup>lt;sup>(113)</sup> Minimum offset does not include the intrinsic delay.

1-88	Glossary			AV-5100 2017.02.1
	Symbol	Parameter	Typical	Unit
			0 (default)	ps
Л		Dising and/on falling adapt delay	50	ps
DOUTBUF	Rising and/or failing edge delay	100	ps	
			150	ps

# Glossary

# Table 1-78: Glossary

Term	Definition	
Differential I/O standards	Receiver Input Waveforms	
	Single-Ended Waveform	Positive Channel (p) = $V_{IH}$ Negative Channel (n) = $V_{IL}$
		Ground
	Differential Waveform	
		p - n = 0 V



AV-51002

Sumbol	Description	Conditions	Calibration Ac	curacy	Unit
Symbol	Description	Conditions	C3, I3L	C4, I4	Onit
25-Ω R <sub>S</sub>	Internal series termination with calibration (25- $\Omega$ setting)	V <sub>CCIO</sub> = 3.0, 2.5, 1.8, 1.5, 1.2 V	±15	±15	%
50-Ω R <sub>S</sub>	Internal series termination with calibration (50- $\Omega$ setting)	V <sub>CCIO</sub> = 3.0, 2.5, 1.8, 1.5, 1.2 V	±15	±15	%
34- $\Omega$ and 40- $\Omega$ $R_S$	Internal series termination with calibration (34- $\Omega$ and 40- $\Omega$ setting)	V <sub>CCIO</sub> = 1.5, 1.35, 1.25, 1.2 V	±15	±15	%
48-Ω, 60-Ω, 80-Ω, and 240-Ω R <sub>S</sub>	Internal series termination with calibration (48- $\Omega$ , 60- $\Omega$ , 80- $\Omega$ , and 240- $\Omega$ setting)	$V_{CCIO} = 1.2 V$	±15	±15	%
50- $\Omega$ R <sub>T</sub>	Internal parallel termination with calibration (50- $\Omega$ setting)	V <sub>CCIO</sub> = 2.5, 1.8, 1.5, 1.2 V	-10 to +40	-10 to +40	%
20- $\Omega$ , 30- $\Omega$ , 40- $\Omega$ , 60- $\Omega$ , and 120- $\Omega$ R <sub>T</sub>	Internal parallel termination with calibration ( $20-\Omega$ , $30-\Omega$ , $40-\Omega$ , $60-\Omega$ , and $120-\Omega$ setting)	V <sub>CCIO</sub> = 1.5, 1.35, 1.25 V	-10 to +40	-10 to +40	%
60- $\Omega$ and 120- $\Omega$ R <sub>T</sub>	Internal parallel termination with calibration (60- $\Omega$ and 120- $\Omega$ setting)	$V_{CCIO} = 1.2$	-10 to +40	-10 to +40	%
25- $\Omega R_{S\_left\_shift}$	Internal left shift series termination with calibration (25- $\Omega$ R <sub>S_left_shift</sub> setting)	V <sub>CCIO</sub> = 3.0, 2.5, 1.8, 1.5, 1.2 V	±15	±15	%

# Table 2-11: OCT Without Calibration Resistance Tolerance Specifications for Arria V GZ Devices

Symbol	Description	Conditions	Resistance	Unit	
Symbol	Description	Conditions	C3, I3L	13L C4, I4	Onic
25-Ω R, 50-Ω R <sub>S</sub>	Internal series termination without calibration (25- $\Omega$ setting)	V <sub>CCIO</sub> = 3.0 and 2.5 V	±40	±40	%



Symbol	Description	V <sub>CCIO</sub> (V)	Typical	Unit
		3.0	0.0297	
dR/dV		2.5	0.0344	
	OCT variation with voltage without re-calibration	1.8	0.0499	%/mV
		1.5	0.0744	
		1.2	0.1241	
		3.0	0.189	
		2.5	0.208	
dR/dT	OCT variation with temperature without re-calibration	1.8	0.266	%/°C
		1.5	0.273	
		1.2	0.317	

# Pin Capacitance

# Table 2-13: Pin Capacitance for Arria V GZ Devices

Symbol	Description	Maximum	Unit
C <sub>IOTB</sub>	Input capacitance on the top and bottom I/O pins	6	pF
C <sub>IOLR</sub>	Input capacitance on the left and right I/O pins	6	pF
C <sub>OUTFB</sub>	Input capacitance on dual-purpose clock output and feedback pins	6	pF



### Table 2-19: Differential SSTL I/O Standards for Arria V GZ Devices

I/O Standard	V <sub>CCIO</sub> (V)			V <sub>SWING(DC)</sub> (V)		V <sub>X(AC)</sub> (V)			V <sub>SWING(AC)</sub> (V)		
	Min	Тур	Max	Min	Max	Min	Тур	Max	Min	Max	
SSTL-2 Class I, II	2.375	2.5	2.625	0.3	V <sub>CCIO</sub> + 0.6	V <sub>CCIO</sub> /2 - 0.2		V <sub>CCIO</sub> /2 + 0.2	0.62	$V_{CCIO} + 0.6$	
SSTL-18 Class I, II	1.71	1.8	1.89	0.25	V <sub>CCIO</sub> + 0.6	V <sub>CCIO</sub> /2 - 0.175	_	V <sub>CCIO</sub> /2 + 0.175	0.5	$V_{CCIO} + 0.6$	
SSTL-15 Class I, II	1.425	1.5	1.575	0.2	(127)	V <sub>CCIO</sub> /2 - 0.15		V <sub>CCIO</sub> /2 + 0.15	0.35	_	
SSTL-135 Class I, II	1.283	1.35	1.45	0.2	(127)	V <sub>CCIO</sub> /2 - 0.15	V <sub>CCIO</sub> /2	V <sub>CCIO</sub> /2 + 0.15	2(V <sub>IH(AC)</sub> - V <sub>REF</sub> )	$2(V_{IL(AC)} - V_{REF})$	
SSTL-125 Class I, II	1.19	1.25	1.31	0.18	(127)	V <sub>CCIO</sub> /2 - 0.15	V <sub>CCIO</sub> /2	V <sub>CCIO</sub> /2 + 0.15	2(V <sub>IH(AC)</sub> - V <sub>REF</sub> )	_	
SSTL-12 Class I, II	1.14	1.2	1.26	0.18		V <sub>REF</sub> -0.15	V <sub>CCIO</sub> /2	V <sub>REF</sub> + 0.15	-0.30	0.30	

# Table 2-20: Differential HSTL and HSUL I/O Standards for Arria V GZ Devices

I/O Standard -	V <sub>CCIO</sub> (V)		V <sub>DIF(DC)</sub> (V)		V <sub>X(AC)</sub> (V)			V <sub>CM(DC)</sub> (V)			V <sub>DIF(AC)</sub> (V)		
	Min	Тур	Max	Min	Max	Min	Тур	Max	Min	Тур	Max	Min	Мах
HSTL-18 Class I, II	1.71	1.8	1.89	0.2	_	0.78		1.12	0.78	_	1.12	0.4	—
HSTL-15 Class I, II	1.425	1.5	1.575	0.2	_	0.68		0.9	0.68		0.9	0.4	—



 $<sup>^{(127)}</sup>$  The maximum value for  $V_{SWING(DC)}$  is not defined. However, each single-ended signal needs to be within the respective single-ended limits ( $V_{IH(DC)}$  and  $V_{IL(DC)}$ ).

Sumbol/Description	Conditions	Transce	eiver Speed (	Grade 2	Transce	eiver Speed (	Unit		
Symbol/Description	Conditions	Min	Тур	Мах	Min	Тур	Мах	Onic	
Transmitter REFCLK Phase Noise (622 MHz) <sup>(141)</sup>	100 Hz	—	_	-70	_	—	-70	dBc/Hz	
	1 kHz	—	—	-90		—	-90	dBc/Hz	
	10 kHz	—	—	-100	_	—	-100	dBc/Hz	
	100 kHz	—	—	-110	_	—	-110	dBc/Hz	
	≥1 MHz	—	—	-120		—	-120	dBc/Hz	
Transmitter REFCLK Phase Jitter (100 MHz) <sup>(142)</sup>	10 kHz to 1.5 MHz (PCIe)	_	_	3	_	_	3	ps (rms)	
R <sub>REF</sub>	—	—	1800 ±1%	_	_	1800 ±1%		Ω	

#### **Related Information**

### Arria V Device Overview

For more information about device ordering codes.

# **Transceiver Clocks**

### Table 2-23: Transceiver Clocks Specifications for Arria V GZ Devices

Speed grades shown refer to the PMA Speed Grade in the device ordering code. The maximum data rate could be restricted by the Core/PCS speed grade. Contact your Altera Sales Representative for the maximum data rate specifications in each speed grade combination offered. For more information about device ordering codes, refer to the Arria V Device Overview.

Arria V GZ Device Datasheet

**Altera Corporation** 



 $<sup>^{(141)}</sup>$  To calculate the REFCLK phase noise requirement at frequencies other than 622 MHz, use the following formula: REFCLK phase noise at f(MHz) = REFCLK phase noise at 622 MHz + 20 \*log(f/622).

<sup>&</sup>lt;sup>(142)</sup> To calculate the REFCLK rms phase jitter requirement for PCIe at reference clock frequencies other than 100 MHz, use the following formula: REFCLK rms phase jitter at f(MHz) = REFCLK rms phase jitter at 100 MHz  $\times$  100/f.

Symbol/Description	Conditions	Trans	ceiver Spee	d Grade 2	Transc	Unit		
Symbol/Description	Conditions	Min	Тур	Мах	Min	Тур	Max	
Programmable DC gain	DC gain setting = 0	—	0	_	_	0	—	dB
	DC gain setting = 1		2	_		2	_	dB
	DC gain setting = 2		4			4		dB
	DC gain setting = 3		6			6	_	dB
	DC gain setting = 4	_	8			8		dB

#### **Related Information**

#### Arria V Device Overview

For more information about device ordering codes.

# Transmitter

### Table 2-25: Transmitter Specifications for Arria V GZ Devices

Speed grades shown refer to the PMA Speed Grade in the device ordering code. The maximum data rate could be restricted by the Core/PCS speed grade. Contact your Altera Sales Representative for the maximum data rate specifications in each speed grade combination offered. For more information about device ordering codes, refer to the *Arria V Device Overview*.

Symbol/Description	Conditions Tran Min	Trans	Transceiver Speed Grade 2			Transceiver Speed Grade 3		
Symbol/Description		Min	Тур	Мах	Min	Тур	Мах	Onit
Supported I/O Standards	1.4-V and 1.5-V PCML							
Data rate (Standard PCS)	—	600	_	9900	600		8800	Mbps
Data rate (10G PCS)	_	600	_	12500	600	_	10312.5	Mbps



Number of DQS Delay Buffers	C3, I3L	C4, I4	Unit
4	120	128	ps

# **Memory Output Clock Jitter Specifications**

### Table 2-50: Memory Output Clock Jitter Specification for Arria V GZ Devices

The clock jitter specification applies to the memory output clock pins generated using differential signal-splitter and DDIO circuits clocked by a PLL output routed on a PHY, regional, or global clock network as specified. Altera recommends using PHY clock networks whenever possible.

The clock jitter specification applies to the memory output clock pins clocked by an integer PLL.

The memory output clock jitter is applicable when an input jitter of 30 ps peak-to-peak is applied with bit error rate (BER) -12, equivalent to 14 sigma.

Clock Notwork	Paramotor	Symbol	C3, I3L		C4, I4		Unit
	raiailietei	Symbol	Min	Мах	Min	Мах	
	Clock period jitter	t <sub>JIT(per)</sub>	-55	55	-55	55	ps
Regional	Cycle-to-cycle period jitter	t <sub>JIT(cc)</sub>	-110	110	-110	110	ps
	Duty cycle jitter	t <sub>JIT(duty)</sub>	-82.5	82.5	-82.5	82.5	ps
Global	Clock period jitter	t <sub>JIT(per)</sub>	-82.5	82.5	-82.5	82.5	ps
	Cycle-to-cycle period jitter	t <sub>JIT(cc)</sub>	-165	165	-165	165	ps
	Duty cycle jitter	t <sub>JIT(duty)</sub>	-90	90	-90	90	ps
	Clock period jitter	t <sub>JIT(per)</sub>	-30	30	-35	35	ps
PHY Clock	Cycle-to-cycle period jitter	t <sub>JIT(cc)</sub>	-60	60	-70	70	ps
	Duty cycle jitter	t <sub>JIT(duty)</sub>	-45	45	-56	56	ps



### Table 2-57: FPP Timing Parameters for Arria V GZ Devices When the DCLK-to-DATA[] Ratio is >1

Use these timing parameters when you use the decompression and design security features.

Symbol	Parameter	Minimum	Maximum	Unit
t <sub>CF2CD</sub>	nCONFIG low to CONF_DONE low	—	600	ns
t <sub>CF2ST0</sub>	nCONFIG low to nSTATUS low	—	600	ns
t <sub>CFG</sub>	nCONFIG low pulse width	2	_	μs
t <sub>STATUS</sub>	nSTATUS low pulse width	268	1,506 (210)	μs
t <sub>CF2ST1</sub>	nCONFIG high to nSTATUS high	-	1,506 (211)	μs
t <sub>CF2CK</sub> <sup>(212)</sup>	nCONFIG high to first rising edge on DCLK	1,506	_	μs
t <sub>ST2CK</sub> <sup>(212)</sup>	nSTATUS high to first rising edge of DCLK	2	_	μs
t <sub>DSU</sub>	DATA[] setup time before rising edge on DCLK	5.5	_	ns
t <sub>DH</sub>	DATA[] hold time after rising edge on DCLK	N-1/f <sub>DCLK</sub> <sup>(213)</sup>	_	S
t <sub>CH</sub>	DCLK high time	$0.45  imes 1/f_{MAX}$	_	S
t <sub>CL</sub>	DCLK low time	$0.45 \times 1/f_{MAX}$		S
t <sub>CLK</sub>	DCLK period	1/f <sub>MAX</sub>	_	S
£	DCLK frequency (FPP ×8/×16)	-	125	MHz
IMAX	DCLK frequency (FPP ×32)	—	100	MHz
t <sub>R</sub>	Input rise time	-	40	ns
t <sub>F</sub>	Input fall time	—	40	ns
t <sub>CD2UM</sub>	CONF_DONE high to user mode <sup>(214)</sup>	175	437	μs

<sup>(210)</sup> You can obtain this value if you do not delay configuration by extending the nCONFIG or nSTATUS low pulse width.

<sup>(211)</sup> You can obtain this value if you do not delay configuration by externally holding the nSTATUS low.

 $^{(212)}$  If nSTATUS is monitored, follow the  $t_{ST2CK}$  specification. If nSTATUS is not monitored, follow the  $t_{CF2CK}$  specification.

 $^{(213)}$  N is the DCLK-to-DATA ratio and  $f_{DCLK}$  is the DCLK frequency the system is operating.

<sup>(214)</sup> The minimum and maximum numbers apply only if you use the internal oscillator as the clock source for initializing the device.

Arria V GZ Device Datasheet

**Altera Corporation** 



### 2-70 Remote System Upgrades Circuitry Timing Specification

### Table 2-62: Uncompressed .rbf Sizes for Arria V GZ Devices

Variant	Member Code	Configuration .rbf Size (bits)	IOCSR .rbf Size (bits) <sup>(223)</sup>	
Arria V GZ	E1	137,598,880	562,208	
	E3	137,598,880	562,208	
	E5	213,798,880	561,760	
	E7	213,798,880	561,760	

### Table 2-63: Minimum Configuration Time Estimation for Arria V GZ Devices

			Active Serial <sup>(224)</sup>			Fast Passive Parallel <sup>(225)</sup>		
Variant	Member Code	Width	DCLK (MHz)	Min Config Time (ms)	Width	DCLK (MHz)	Min Config Time (ms)	
	E1	4	100	344	32	100	43	
Arria V GZ	E3	4	100	344	32	100	43	
	E5	4	100	534	32	100	67	
	E7	4	100	534	32	100	67	

# **Remote System Upgrades Circuitry Timing Specification**

# Table 2-64: Remote System Upgrade Circuitry Timing Specifications

Parameter	Minimum	Maximum	Unit
t <sub>RU_nCONFIG</sub> <sup>(226)</sup>	250	—	ns
t <sub>RU_nRSTIMER</sub> <sup>(227)</sup>	250	_	ns

<sup>(223)</sup> The IOCSR **.rbf** size is specifically for the Configuration via Protocol (CvP) feature.

<sup>(224)</sup> DCLK frequency of 100 MHz using external CLKUSR.

<sup>(225)</sup> Max FPGA FPP bandwidth may exceed bandwidth available from some external storage or control logic.



Date	Version	Changes
July 2014	3.8	<ul> <li>Updated Table 21.</li> <li>Updated Table 22 V<sub>OCM</sub> (DC Coupled) condition.</li> <li>Updated the DCLK note to Figure 6, Figure 7, and Figure 9.</li> <li>Added note to Table 5 and Table 6.</li> <li>Added the DCLK specification to Table 50.</li> <li>Added note to Table 51.</li> <li>Updated the list of parameters in Table 53.</li> </ul>
February 2014	3.7	Updated Table 28.
December 2013	3.6	<ul> <li>Updated Table 2, Table 13, Table 18, Table 19, Table 22, Table 30, Table 33, Table 37, Table 38, Table 45, Table 46, Table 47, Table 56, Table 49.</li> <li>Updated "PLL Specifications".</li> </ul>
August 2013	3.5	Updated Table 28.
August 2013	3.4	<ul> <li>Removed Preliminary tags for Table 2, Table 4, Table 5, Table 14, Table 27, Table 28, Table 29, Table 31, Table 32, Table 43, Table 45, Table 46, Table 47, Table 48, Table 49, Table 50, and Table 54.</li> <li>Updated Table 2 and Table 28.</li> </ul>
June 2013	3.3	Updated Table 23, Table 28, Table 51, and Table 55.
May 2013	3.2	<ul> <li>Added Table 23.</li> <li>Updated Table 5, Table 22, Table 26, and Table 57.</li> <li>Updated Figure 6, Figure 7, Figure 8, and Figure 9.</li> </ul>
March 2013	3.1	<ul> <li>Updated Table 2, Table 6, Table 7, Table 8, Table 19, Table 22, Table 26, Table 29, Table 52.</li> <li>Updated "Maximum Allowed Overshoot and Undershoot Voltage".</li> </ul>
December 2012	3.0	Initial release.

