## Intel - 5CEBA4F23C8N Datasheet





Welcome to <u>E-XFL.COM</u>

#### Understanding <u>Embedded - FPGAs (Field</u> <u>Programmable Gate Array)</u>

Embedded - FPGAs, or Field Programmable Gate Arrays, are advanced integrated circuits that offer unparalleled flexibility and performance for digital systems. Unlike traditional fixed-function logic devices, FPGAs can be programmed and reprogrammed to execute a wide array of logical operations, enabling customized functionality tailored to specific applications. This reprogrammability allows developers to iterate designs quickly and implement complex functions without the need for custom hardware.

#### **Applications of Embedded - FPGAs**

The versatility of Embedded - FPGAs makes them indispensable in numerous fields. In telecommunications.

Details	
Product Status	Active
Number of LABs/CLBs	18480
Number of Logic Elements/Cells	49000
Total RAM Bits	3464192
Number of I/O	224
Number of Gates	-
Voltage - Supply	1.07V ~ 1.13V
Mounting Type	Surface Mount
Operating Temperature	0°C ~ 85°C (TJ)
Package / Case	484-BGA
Supplier Device Package	484-FBGA (23x23)
Purchase URL	https://www.e-xfl.com/product-detail/intel/5ceba4f23c8n

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong



Cyclone V Device Overview	3
Key Advantages of Cyclone V Devices	3
Summary of Cyclone V Features	4
Cyclone V Device Variants and Packages	5
Cyclone V E	5
Cyclone V GX	7
Cyclone V GT	Э
Cyclone V SE12	2
Cyclone V SX14	4
Cyclone V ST1	5
I/O Vertical Migration for Cyclone V Devices18	3
Adaptive Logic Module	3
Variable-Precision DSP Block19	Э
Embedded Memory Blocks2	1
Types of Embedded Memory2	1
Embedded Memory Capacity in Cyclone V Devices	1
Embedded Memory Configurations22	2
Clock Networks and PLL Clock Sources22	2
FPGA General Purpose I/O2	3
PCIe Gen1 and Gen2 Hard IP 24	4
External Memory Interface 24	4
Hard and Soft Memory Controllers24	4
External Memory Performance2	5
HPS External Memory Performance2	5
Low-Power Serial Transceivers2	5
Transceiver Channels2	5
PMA Features	5
PCS Features22	7
SoC with HPS28	3
HPS Features28	3
FPGA Configuration and Processor Booting	)
Hardware and Software Development	1
Dynamic and Partial Reconfiguration	1
Dynamic Reconfiguration3	1
Partial Reconfiguration	1
Enhanced Configuration and Configuration via Protocol	2
Power Management	3
Document Revision History for Cyclone V Device Overview	3



## **Summary of Cyclone V Features**

## Table 2. Summary of Features for Cyclone V Devices

Feature		Description		
Technology	<ul> <li>TSMC's 28-nm low-p</li> <li>1.1 V core voltage</li> </ul>	<ul> <li>TSMC's 28-nm low-power (28LP) process technology</li> <li>1.1 V core voltage</li> </ul>		
Packaging	<ul> <li>Wirebond low-haloge</li> <li>Multiple device densi different device dens</li> <li>RoHS-compliant and</li> </ul>	<ul> <li>Wirebond low-halogen packages</li> <li>Multiple device densities with compatible package footprints for seamless migration between different device densities</li> <li>RoHS-compliant and leaded<sup>(1)</sup>options</li> </ul>		
High-performance FPGA fabric	Enhanced 8-input ALM v	vith four registers		
Internal memory blocks	<ul> <li>M10K—10-kilobits (K</li> <li>Memory logic array to of the ALMs as MLAB</li> </ul>	<ul> <li>M10K—10-kilobits (Kb) memory blocks with soft error correction code (ECC)</li> <li>Memory logic array block (MLAB)—640-bit distributed LUTRAM where you can use up to 25% of the ALMs as MLAB memory</li> </ul>		
Embedded Hard IP blocks	Variable-precision DSP	<ul> <li>Variable-precision DSP</li> <li>Native support for up to three signal processing precision levels (three 9 x 9, two 18 x 18, or one 27 x 27 multiplier) in the same variable-precision DSP block</li> <li>64-bit accumulator and cascade</li> <li>Embedded internal coefficient memory</li> <li>Preadder/subtractor for improved efficiency</li> </ul>		
	Memory controller	DDR3, DDR2, and LPDDR2 with 16 and 32 bit ECC support		
	Embedded transceiver I/OPCI Express* (PCIe*) Gen2 and Gen1 (x1, x2, or x4) hard IP with multifunction support, endpoint, and root port			
Clock networks	<ul> <li>Up to 550 MHz global clock network</li> <li>Global, quadrant, and peripheral clock networks</li> <li>Clock networks that are not used can be powered down to reduce dynamic power</li> </ul>			
Phase-locked loops (PLLs)	<ul> <li>Precision clock synthesis, clock delay compensation, and zero delay buffering (ZDB)</li> <li>Integer mode and fractional mode</li> </ul>			
FPGA General-purpose I/Os (GPIOs)	<ul> <li>875 megabits per second (Mbps) LVDS receiver and 840 Mbps LVDS transmitter</li> <li>400 MHz/800 Mbps external memory interface</li> <li>On-chip termination (OCT)</li> <li>3.3 V support with up to 16 mA drive strength</li> </ul>			
Low-power high-speed serial interface	<ul> <li>614 Mbps to 6.144 Gbps integrated transceiver speed</li> <li>Transmit pre-emphasis and receiver equalization</li> <li>Dynamic partial reconfiguration of individual channels</li> </ul>			
HPS (Cyclone V SE, SX, and ST devices only)	<ul> <li>Single or dual-core Arm Cortex-A9 MPCore processor-up to 925 MHz maximum frequency with support for symmetric and asymmetric multiprocessing</li> <li>Interface peripherals—10/100/1000 Ethernet media access control (EMAC), USB 2.0 On-The-GO (OTG) controller, quad serial peripheral interface (QSPI) flash controller, NAND flash controller, Secure Digital/MultiMediaCard (SD/MMC) controller, UART, controller area network (CAN), serial peripheral interface (SPI), 1<sup>2</sup>C interface, and up to 85 HPS GPIO interfaces</li> <li>System peripherals—general-purpose timers, watchdog timers, direct memory access (DMA) controller, FPGA configuration manager, and clock and reset managers</li> <li>On-chip RAM and boot ROM</li> </ul>			
		continued		

<sup>&</sup>lt;sup>(1)</sup> Contact Intel for availability.



## **Available Options**

#### Figure 2. Sample Ordering Code and Available Options for Cyclone V GX Devices

The SEU internal scrubbing feature is available for Cyclone V E, GX, SE, and SX devices with the "SC" suffix in the part number. For device availability and ordering, contact your local Intel sales representatives.



## **Maximum Resources**

### Table 6. Maximum Resource Counts for Cyclone V GX Devices

Reso	ource	Member Code				
		C3	C4	C5	C7	С9
Logic Elements	(LE) (K)	36	50	77	150	301
ALM		13,460	18,860	29,080	56,480	113,560
Register		53,840	75,440	116,320	225,920	454,240
Memory (Kb)	M10K	1,350	2,500	4,460	6,860	12,200
	MLAB	182	424	424	836	1,717
Variable-precisio	on DSP Block	57	70	150	156	342
18 x 18 Multiplie	er	114	140	300	312	684
PLL		4	6	6	7	8
3 Gbps Transcei	ver	3	6	6	9	12
GPIO <sup>(4)</sup>		208	336	336	480	560
	continued					

<sup>&</sup>lt;sup>(4)</sup> The number of GPIOs does not include transceiver I/Os. In the Intel Quartus<sup>®</sup> Prime software, the number of user I/Os includes transceiver I/Os.



## **Available Options**

### Figure 3. Sample Ordering Code and Available Options for Cyclone V GT Devices



#### **Maximum Resources**

#### Table 8. Maximum Resource Counts for Cyclone V GT Devices

Resource			Member Code				
		D5	D7	D9			
Logic Elements (LE) (K)		77	150	301			
ALM		29,080	56,480	113,560			
Register		116,320	225,920	454,240			
Memory (Kb)	M10K	4,460	6,860	12,200			
	MLAB	424	836	1,717			
Variable-precision DS	SP Block	150	156	342			
18 x 18 Multiplier		300	312	684			
PLL		6	7	8			
6 Gbps Transceiver		6	9	12			
GPIO <sup>(5)</sup>		336	480	560			
LVDS	Transmitter	84	120	140			
		•	·	continued			

<sup>&</sup>lt;sup>(5)</sup> The number of GPIOs does not include transceiver I/Os. In the Intel Quartus Prime software, the number of user I/Os includes transceiver I/Os.



## **Maximum Resources**

#### Table 10. Maximum Resource Counts for Cyclone V SE Devices

Res	source	Member Code				
		A2	A4	A5	A6	
Logic Elements (LE) (K)		25	40	85	110	
ALM		9,430	15,880	32,070	41,910	
Register		37,736	60,376	128,300	166,036	
Memory (Kb)	M10K	1,400	2,700	3,970	5,570	
	MLAB	138	231	480	621	
Variable-precision DSP Block		36	84	87	112	
18 x 18 Multiplier		72	168	174	224	
FPGA PLL		5	5	6	6	
HPS PLL		3	3	3	3	
FPGA GPIO		145	145	288	288	
HPS I/O		181	181	181	181	
LVDS	Transmitter	32	32	72	72	
Receiver		37	37	72	72	
FPGA Hard Memory Controller		1	1	1	1	
HPS Hard Memory Controller		1	1	1	1	
Arm Cortex-A9 N	1PCore Processor	Single- or dual- core	Single- or dual- core	Single- or dual-core	Single- or dual-core	

#### **Related Information**

True LVDS Buffers in Devices, I/O Features in Cyclone V Devices Provides the number of LVDS channels in each device package.

## **Package Plan**

#### Table 11.Package Plan for Cyclone V SE Devices

The HPS I/O counts are the number of I/Os in the HPS and does not correlate with the number of HPS-specific I/O pins in the FPGA. Each HPS-specific pin in the FPGA may be mapped to several HPS I/Os.

Member Code	U484 (19 mm)		U672 (23 mm)		F896 (31 mm)	
	FPGA GPIO	HPS I/O	FPGA GPIO	HPS I/O	FPGA GPIO	HPS I/O
A2	66	151	145	181	—	—
A4	66	151	145	181	-	-
A5	66	151	145	181	288	181
A6	66	151	145	181	288	181





## **Cyclone V SX**

This section provides the available options, maximum resource counts, and package plan for the Cyclone V SX devices.

The information in this section is correct at the time of publication. For the latest information and to get more details, refer to the *Product Selector Guide*.

#### **Related Information**

#### Product Selector Guide

Provides the latest information about Intel products.

## **Available Options**

#### Figure 5. Sample Ordering Code and Available Options for Cyclone V SX Devices

The SEU internal scrubbing feature is available for Cyclone V E, GX, SE, and SX devices with the "SC" suffix in the part number. For device availability and ordering, contact your local Intel sales representatives.

Cyclone V SE and SX low-power devices (L power option) offer 30% static power reduction for devices with 25K LE and 40K LE, and 20% static power reduction for devices with 85K LE and 110K LE.



#### **Maximum Resources**

#### Table 12. Maximum Resource Counts for Cyclone V SX Devices

Resource Member Code					
		C2	C4	C5	C6
Logic Elements (LE	) (К)	25	40	85	110
ALM		9,430	15,880	32,070	41,910
Register		37,736	60,376	128,300	166,036
Memory (Kb)	M10K	1,400	2,700	3,970	5,570
	MLAB	138	231	480	621
Variable-precision	DSP Block	36	84	87	112
18 x 18 Multiplier		72	168	174	224
FPGA PLL		5	5	6	6
		•	•		continued

	Resource	Member Code					
		C2	C4	C5	C6		
HPS PLL		3	3	3	3		
3 Gbps Transc	eiver	6	6	9	9		
FPGA GPIO <sup>(8)</sup>		145	145	288	288		
HPS I/O		<b></b> 181	181	181	181		
LVDS	Transmitter	32	32	72	72		
	Receiver	37	37	72	72		
PCIe Hard IP	Block	2	2	2 (9)	2 (9)		
FPGA Hard Memory Controller		1	1	1	1		
HPS Hard Memory Controller		1	1	1	1		
Arm Cortex-A	9 MPCore Processor	Dual-core	Dual-core	Dual-core	Dual-core		

#### **Related Information**

Product Selector Guide Provides the latest information about Intel products.

### **Available Options**

#### Figure 6. Sample Ordering Code and Available Options for Cyclone V ST Devices



## **Maximum Resources**

#### Table 14. Maximum Resource Counts for Cyclone V ST Devices

Resource		Membe	r Code
		D5	D6
Logic Elements (LE) (K)		85	110
ALM		32,070	41,910
Register		128,300	166,036
Memory (Kb)	M10K	3,970	5,570
	MLAB	480	621
Variable-precision DSP Block		87	112
18 x 18 Multiplier		174	224
FPGA PLL		6	6
HPS PLL		3	3
6.144 Gbps Transceiver		9	9
FPGA GPIO <sup>(10)</sup>		288	288
HPS I/O		181	181
LVDS	Transmitter	72	72
			continued

Variant	Member Code	Variable- precision	Indepen Multi	dent Input and plications Ope	18 x 18 Multiplier	18 x 18 Multiplier	
		DSP Block	9 x 9 Multiplier	18 x 18 Multiplier	27 x 27 Multiplier	Adder Mode	Summed with 36 bit Input
	C6	112	336	224	112	112	112
Cyclone V ST	D5	87	261	174	87	87	87
	D6	112	336	224	112	112	112



## **Power Management**

Leveraging the FPGA architectural features, process technology advancements, and transceivers that are designed for power efficiency, the Cyclone V devices consume less power than previous generation Cyclone FPGAs:

- Total device core power consumption—less by up to 40%.
- Transceiver channel power consumption—less by up to 50%.

Additionally, Cyclone V devices contain several hard IP blocks that reduce logic resources and deliver substantial power savings of up to 25% less power than equivalent soft implementations.

# **Document Revision History for Cyclone V Device Overview**

Document Version	Changes
2018.05.07	<ul> <li>Added the low power option ("L" suffix) for Cyclone V SE and Cyclone V SX devices in the Sample Ordering Code and Available Options diagrams.</li> <li>Rebranded as Intel</li> </ul>

Date	Version	Changes
December 2017	2017.12.18	Updated ALM resources for Cyclone V E, Cyclone V SE, Cyclone V SX, and Cyclone V ST devices.
June 2016	2016.06.10	Updated Cyclone V GT speed grade to $-7$ in Sample Ordering Code and Available Options for Cyclone V GT Devices diagram.
December 2015	2015.12.21	<ul> <li>Added descriptions to package plan tables for Cyclone V GT and ST devices.</li> <li>Changed instances of <i>Quartus II</i> to <i>Quartus Prime</i>.</li> </ul>
June 2015	2015.06.12	<ul> <li>Replaced a note to partial reconfiguration feature. Note: The partial reconfiguration feature is available for Cyclone V E, GX, SE, and SX devices with the "SC" suffix in the part number. For device availability and ordering, contact your local Altera sales representatives.</li> <li>Updated logic elements (LE) (K) for the following devices: <ul> <li>Cyclone V E A7: Updated from 149.5 to 150</li> <li>Cyclone V GX C3: Updated from 149.5 to 36</li> <li>Cyclone V GX C7: Updated from 149.7 to 150</li> <li>Cyclone V GT D7: Updated from 149.5 to 150</li> </ul> </li> <li>Updated MLAB (Kb) in Maximum Resource Counts for Cyclone V GX Devices table as follows: <ul> <li>Cyclone V GX C3: Updated from 291 to 182</li> <li>Cyclone V GX C4: Updated from 678 to 424</li> <li>Cyclone V GX C7: Updated from 1,338 to 836</li> <li>Cyclone V GX C9: Updated from 1,717</li> </ul> </li> </ul>
	1	continued



#### Figure 10. Device Chip Overview for Cyclone V GX and GT Devices

The figure shows a Cyclone V FPGA with transceivers. Different Cyclone V devices may have a different floorplans than the one shown here.



## **PMA Features**

To prevent core and I/O noise from coupling into the transceivers, the PMA block is isolated from the rest of the chip—ensuring optimal signal integrity. For the transceivers, you can use the channel PLL of an unused receiver PMA as an additional transmit PLL.

#### Table 22. PMA Features of the Transceivers in Cyclone V Devices

Features	Capability
Backplane support	Driving capability up to 6.144 Gbps
PLL-based clock recovery	Superior jitter tolerance
Programmable deserialization and word alignment	Flexible deserialization width and configurable word alignment pattern
Equalization and pre-emphasis	<ul> <li>Up to 14.37 dB of pre-emphasis and up to 4.7 dB of equalization</li> <li>No decision feedback equalizer (DFE)</li> </ul>
Ring oscillator transmit PLLs	614 Mbps to 6.144 Gbps
Input reference clock range	20 MHz to 400 MHz
Transceiver dynamic reconfiguration	Allows the reconfiguration of a single channel without affecting the operation of other channels