

Welcome to E-XFL.COM

What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

Details

E·XFI

Product Status	Active
Core Processor	PIC
Core Size	16-Bit
Speed	32MHz
Connectivity	I ² C, SPI, UART/USART, USB OTG
Peripherals	Brown-out Detect/Reset, LVD, POR, PWM, WDT
Number of I/O	51
Program Memory Size	192KB (65.5K x 24)
Program Memory Type	FLASH
EEPROM Size	-
RAM Size	16K × 8
Voltage - Supply (Vcc/Vdd)	2V ~ 3.6V
Data Converters	A/D 16x10b
Oscillator Type	Internal
Operating Temperature	-40°C ~ 85°C (TA)
Mounting Type	Surface Mount
Package / Case	64-TQFP
Supplier Device Package	64-TQFP (10x10)
Purchase URL	https://www.e-xfl.com/product-detail/microchip-technology/pic24fj192gb106-i-pt

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

Features	64GB108	128GB108	192GB108	256GB108		
Operating Frequency		DC – 3	2 MHz			
Program Memory (bytes)	64K	128K	192K	256K		
Program Memory (instructions)	22,016	44,032	67,072	87,552		
Data Memory (bytes)		16,	384	·		
Interrupt Sources (soft vectors/NMI traps)		66 (6	62/4)			
I/O Ports		Ports A, B, 0	C, D, E, F, G			
Total I/O Pins		6	5			
Remappable Pins	40 (31 I/O, 9 Input only)					
Timers:						
Total Number (16-bit)		5	[1]			
32-Bit (from paired 16-bit timers)		2	2			
Input Capture Channels		9	(1)			
Output Compare/PWM Channels	9 ⁽¹⁾					
Input Change Notification Interrupt	63					
Serial Communications:						
UART	4(1)					
SPI (3-wire/4-wire)	3(1)					
I ² C™	3					
Parallel Communications (PMP/PSP)	Yes					
JTAG Boundary Scan/Programming		Ye	es			
10-Bit Analog-to-Digital Module (input channels)	16					
Analog Comparators	3					
CTMU Interface	Yes					
Resets (and delays)	POR, BOR, RESET Instruction, MCLR, WDT; Illegal Opcode, REPEAT Instruction, Hardware Traps, Configuration Word Misma (PWRT, OST, PLL Lock)					
Instruction Set	76 Base Ins	structions, Multiple	Addressing Mod	e Variations		
Packages		80-Pin	TQFP			

TABLE 1-2: DEVICE FEATURES FOR THE PIC24FJ256GB110 FAMILY: 80-PIN DEVICES

Note 1: Peripherals are accessible through remappable pins.

Features	64GB110 128GB110 192GB110 256GB110					
Operating Frequency		DC – 3	32 MHz			
Program Memory (bytes)	64K	128K	192K	256K		
Program Memory (instructions)	22,016	44,032	67,072	87,552		
Data Memory (bytes)		16,	384	•		
Interrupt Sources (soft vectors/NMI traps)		66 (6	62/4)			
I/O Ports	Ports A, B, C, D, E, F, G					
Total I/O Pins		8	3			
Remappable Pins		44 (32 I/O, 1	2 Input only)			
Timers:						
Total Number (16-bit)		5	(1)			
32-Bit (from paired 16-bit timers)	2					
Input Capture Channels		9	(1)			
Output Compare/PWM Channels	9(1)					
Input Change Notification Interrupt	81					
Serial Communications:						
UART	4(1)					
SPI (3-wire/4-wire)	3(1)					
l ² C™		:	3			
Parallel Communications (PMP/PSP)	Yes					
JTAG Boundary Scan/Programming	Yes					
10-Bit Analog-to-Digital Module (input channels)	16					
Analog Comparators	3					
CTMU Interface	Yes					
Resets (and delays)	POR, BOR, RESET Instruction, MCLR, WDT; Illegal Opcode, REPEAT Instruction, Hardware Traps, Configuration Word Mismatch (PWRT, OST, PLL Lock)					
Instruction Set	76 Base Ins	structions, Multiple	e Addressing Mod	e Variations		
Packages		100-Pii	n TQFP			

TABLE 1-3: DEVICE FEATURES FOR THE PIC24FJ256GB110 FAMILY: 100-PIN DEVICES

Note 1: Peripherals are accessible through remappable pins.

TABLE 3-1: CPU CORE REGISTERS	TABLE 3-1:	CPU CORE REGISTERS
-------------------------------	------------	--------------------

Register(s) Name	Description
W0 through W15	Working Register Array
PC	23-Bit Program Counter
SR	ALU STATUS Register
SPLIM	Stack Pointer Limit Value Register
TBLPAG	Table Memory Page Address Register
PSVPAG	Program Space Visibility Page Address Register
RCOUNT	Repeat Loop Counter Register
CORCON	CPU Control Register

FIGURE 3-2:	PROGRAMMER'S MODEL
-------------	--------------------



U-0	R/W-0	U-0	U-0	U-0	U-0	U-0	U-0		
—	RTCIE	—	_	_		—	_		
bit 15	-						bit 8		
U-0	R/W-0	R/W-0	U-0	U-0	R/W-0	R/W-0	U-0		
_	INT4IE ⁽¹⁾	INT3IE ⁽¹⁾	—	_	MI2C2IE	SI2C2IE	—		
bit 7							bit 0		
Legend:									
R = Readable	e bit	W = Writable	bit	U = Unimplen	nented bit, read	l as '0'			
-n = Value at	POR	'1' = Bit is set		'0' = Bit is clea	ared	x = Bit is unkn	own		
bit 15	Unimplemen	ted: Read as '	כי						
bit 14	RTCIE: Real-	Time Clock/Ca	lendar Interrup	t Enable bit					
	1 = Interrupt r 0 = Interrupt r	equest enabled equest not ena	d Ibled						
bit 13-7	Unimplemen	ted: Read as ')'						
bit 6	INT4IE: Exter 1 = Interrupt r 0 = Interrupt r	nal Interrupt 4 equest enabled equest not ena	Enable bit ⁽¹⁾ d bled						
bit 5	INT3IE: External Interrupt 3 Enabled 1 = Interrupt request enabled 0 = Interrupt request not enabled								
bit 4-3	Unimplemen	ted: Read as '	י'						
bit 2	MI2C2IE: Mas	ster I2C2 Even	t Interrupt Ena	ble bit					
	1 = Interrupt request enabled 0 = Interrupt request not enabled								
bit 1	SI2C2IE: Slav	ve I2C2 Event I	nterrupt Enabl	e bit					
	1 = Interrupt request enabled 0 = Interrupt request not enabled								
bit 0	Unimplemen	ted: Read as ')'						
Note 1: If pi	 Note 1: If an external interrupt is enabled, the interrupt input must also be configured to an available RPn or RPIn pin. See Section 10.4 "Peripheral Pin Select" for more information. 								

REGISTER 7-14: IEC3: INTERRUPT ENABLE CONTROL REGISTER 3

REGISTER 7-31: IPC15: INTERRUPT PRIORITY CONTROL REGISTER 15

U-0	U-0	U-0	U-0	U-0	R/W-1	R/W-0	R/W-0
	—	—	—		RTCIP2	RTCIP1	RTCIP0
bit 15							bit 8

U-0	U-0	U-0	U-0	U-0	U-0	U-0	U-0
—	—	—	—	—	—	—	—
bit 7							bit 0

Legend:			
R = Readable bit	W = Writable bit	U = Unimplemented bit	, read as '0'
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown

bit 15-11 Unimplemented: Read as '0'

- bit 10-8 **RTCIP<2:0>:** Real-Time Clock/Calendar Interrupt Priority bits 111 = Interrupt is priority 7 (highest priority interrupt)
 - •
 - 001 = Interrupt is priority 1
 - 000 = Interrupt source is disabled
- bit 7-0 Unimplemented: Read as '0'

8.5.1 CONSIDERATIONS FOR USB OPERATION

When using the USB On-The-Go module in PIC24FJ256GB110 family devices, users must always observe these rules in configuring the system clock:

- For USB operation, the selected clock source (EC, HS or XT) must meet the USB clock tolerance requirements.
- The Primary Oscillator/PLL modes are the only oscillator configurations that permit USB operation. There is no provision to provide a separate external clock source to the USB module.
- While the FRCPLL Oscillator mode is available in these devices, it should never be used for USB applications. FRCPLL mode is still available when the application is not using the USB module. However, the user must always ensure that the FRC source is configured to provide a frequency of 4 MHz or 8 MHz (RCDIV<2:0> = 001 or 000) and that the USB PLL prescaler is configured appropriately.
- All other oscillator modes are available; however, USB operation is not possible when these modes are selected. They may still be useful in cases where other power levels of operation are desirable and the USB module is not needed (e.g., the application is in Sleep and waiting for bus attachment).

8.6 Reference Clock Output

In addition to the CLKO output (Fosc/2) available in certain oscillator modes, the device clock in the PIC24FJ256GB110 family devices can also be configured to provide a reference clock output signal to a port pin. This feature is available in all oscillator configurations and allows the user to select a greater range of clock submultiples to drive external devices in the application.

This reference clock output is controlled by the REFOCON register (Register 8-4). Setting the ROEN bit (REFOCON<15>) makes the clock signal available on the REFO pin. The RODIV bits (REFOCON<11:8>) enable the selection of 16 different clock divider options.

The ROSSLP and ROSEL bits (REFOCON<13:12>) control the availability of the reference output during Sleep mode. The ROSEL bit determines if the oscillator on OSC1 and OSC2, or the current system clock source, is used for the reference clock output. The ROSSLP bit determines if the reference source is available on REFO when the device is in Sleep mode.

To use the reference clock output in Sleep mode, both the ROSSLP and ROSEL bits must be set. The device clock must also be configured for one of the primary modes (EC, HS or XT); otherwise, if the POSCEN bit is not also set, the oscillator on OSC1 and OSC2 will be powered down when the device enters Sleep mode. Clearing the ROSEL bit allows the reference output frequency to change as the system clock changes during any clock switches.

REGISTER 10-5: RPINR4: PERIPHERAL PIN SELECT INPUT REGISTER 4

U-0	U-0	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1
_	—	T5CKR5	T5CKR4	T5CKR3	T5CKR2	T5CKR1	T5CKR0
bit 15							bit 8

U-0	U-0	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1
—	—	T4CKR5	T4CKR4	T4CKR3	T4CKR2	T4CKR1	T4CKR0
bit 7							bit 0

Legend:			
R = Readable bit	U = Unimplemented bit, read	d as '0'	
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown

bit 15-14	Unimplemented: Read as '0'
bit 13-8	T5CKR<5:0>: Assign Timer5 External Clock (T5CK) to Corresponding RPn or RPIn Pin bits
bit 7-6	Unimplemented: Read as '0'
bit 5-0	T4CKR<5:0>: Assign Timer4 External Clock (T4CK) to Corresponding RPn or RPIn Pin bits

REGISTER 10-6: RPINR7: PERIPHERAL PIN SELECT INPUT REGISTER 7

U-0	U-0	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1
—	—	IC2R5	IC2R4	IC2R3	IC2R2	IC2R1	IC2R0
bit 15							bit 8

U-0	U-0	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1
—	—	IC1R5	IC1R4	IC1R3	IC1R2	IC1R1	IC1R0
bit 7							bit 0

Legend:			
R = Readable bit	W = Writable bit	U = Unimplemented bit, read	l as '0'
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown

bit 15-14 Unimplemented: Read as '0'

bit 13-8 IC2R<5:0>: Assign Input Capture 2 (IC2) to Corresponding RPn or RPIn Pin bits

bit 7-6 Unimplemented: Read as '0'

bit 5-0 IC1R<5:0>: Assign Input Capture 1 (IC1) to Corresponding RPn or RPIn Pin bits

REGISTER 10-11: RPINR15: PERIPHERAL PIN SELECT INPUT REGISTER 15

U-0	U-0	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1
—	—	IC9R5	IC9R4	IC9R3	IC9R2	IC9R1	IC9R0
bit 15							bit 8
U-0	U-0	U-0	U-0	U-0	U-0	U-0	U-0
_		—	—	—			—
bit 7							bit 0
Legend:							
R = Readable bit W = Writable bit			U = Unimplemented bit, read as '0'				
-n = Value at	POR	'1' = Bit is set	Bit is set '0' = Bit is cleared x = Bit is unknown			iown	

bit 15-14 Unimplemented: Read as '0'

bit 13-8 IC9R<5:0>: Assign Input Capture 9 (IC9) to Corresponding RPn or RPIn Pin bits

bit 7-0 Unimplemented: Read as '0'

REGISTER 10-12: RPINR17: PERIPHERAL PIN SELECT INPUT REGISTER 17

U-0	U-0	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1
—	—	U3RXR5	U3RXR4	U3RXR3	U3RXR2	U3RXR1	U3RXR0
bit 15							bit 8
U-0	U-0	U-0	U-0	U-0	U-0	U-0	U-0
—	—	—	—	—	—	—	—
bit 7							bit 0
Legend:							
R = Readable bit W = Writable bit		oit	U = Unimplemented bit, read as '0'				
-n = Value at POR '1' = Bit is set			'0' = Bit is cleared x = Bit is unknown		iown		

bit 15-14 Unimplemented: Read as '0'

bit 13-8 U3RXR<5:0>: Assign UART3 Receive (U3RX) to Corresponding RPn or RPIn Pin bits

bit 7-0 Unimplemented: Read as '0'

REGISTER 10-19: RPINR27: PERIPHERAL PIN SELECT INPUT REGISTER 27

U-0	U-0	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1
—	—	U4CTSR5	U4CTSR4	U4CTSR3	U4CTSR2	U4CTSR1	U4CTSR0
bit 15							bit 8

U-0	U-0	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1
—	—	U4RXR5	U4RXR4	U4RXR3	U4RXR2	U4RXR1	U4RXR0
bit 7							bit 0

Legend:			
R = Readable bit	W = Writable bit	U = Unimplemented bit, read	d as '0'
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown

bit 15-14	Unimplemented: Read as '0'
bit 13-8	U4CTSR<5:0>: Assign UART4 Clear to Send (U4CTS) to Corresponding RPn or RPIn Pin bits
bit 7-6	Unimplemented: Read as '0'
bit 5-0	U4RXR<5:0>: Assign UART4 Receive (U4RX) to Corresponding RPn or RPIn Pin bits

REGISTER 10-20: RPINR28: PERIPHERAL PIN SELECT INPUT REGISTER 28

U-0	U-0	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1
—	—	SCK3R5	SCK3R4	SCK3R3	SCK3R2	SCK3R1	SCK3R0
bit 15							bit 8

U-0	U-0	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1	R/W-1
—	—	SDI3R5	SDI3R4	SDI3R3	SDI3R2	SDI3R1	SDI3R0
bit 7							bit 0

Legend:					
R = Readable bit	W = Writable bit	U = Unimplemented bit, read as '0'			
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown		

bit 15-14 Unimplemented: Read as '0'

bit 13-8 SCK3R<5:0>: Assign SPI3 Clock Input (SCK3IN) to Corresponding RPn or RPIn Pin bits

bit 7-6 Unimplemented: Read as '0'

bit 5-0 SDI3R<5:0>: Assign SPI3 Data Input (SDI3) to Corresponding RPn or RPIn Pin bits

11.0 TIMER1

Note: This data sheet summarizes the features of this group of PIC24F devices. It is not intended to be a comprehensive reference source. For more information, refer to the "PIC24F Family Reference Manual", Section 14. "Timers" (DS39704).

The Timer1 module is a 16-bit timer which can serve as the time counter for the Real-Time Clock (RTC), or operate as a free-running, interval timer/counter. Timer1 can operate in three modes:

- 16-Bit Timer
- 16-Bit Synchronous Counter
- 16-Bit Asynchronous Counter

Timer1 also supports these features:

- Timer Gate Operation
- Selectable Prescaler Settings
- Timer Operation during CPU Idle and Sleep modes
- Interrupt on 16-Bit Period Register Match or Falling Edge of External Gate Signal

Figure 11-1 presents a block diagram of the 16-bit timer module.

To configure Timer1 for operation:

- 1. Set the TON bit (= 1).
- 2. Select the timer prescaler ratio using the TCKPS<1:0> bits.
- 3. Set the Clock and Gating modes using the TCS and TGATE bits.
- 4. Set or clear the TSYNC bit to configure synchronous or asynchronous operation.
- 5. Load the timer period value into the PR1 register.
- 6. If interrupts are required, set the interrupt enable bit, T1IE. Use the priority bits, T1IP<2:0>, to set the interrupt priority.



FIGURE 11-1: 16-BIT TIMER1 MODULE BLOCK DIAGRAM

REGISTER 12-2: TyCON: TIMER3 AND TIMER5 CONTROL REGISTER⁽³⁾

R/W-0	U-0	R/W-0	U-0	U-0	U-0	U-0	U-0
TON ⁽¹⁾	—	TSIDL ⁽¹⁾	—	—	—	—	—
bit 15							bit 8

U-0	R/W-0	R/W-0	R/W-0	U-0	U-0	R/W-0	U-0
—	TGATE ⁽¹⁾	TCKPS1 ⁽¹⁾	TCKPS0 ⁽¹⁾	—	—	TCS ^(1,2)	—
bit 7							bit 0

Legend:				
R = Reada	ble bit W = V	/ritable bit	U = Unimplemented bit,	read as '0'
-n = Value	at POR '1' = B	it is set	'0' = Bit is cleared	x = Bit is unknown
bit 15	TON: Timery On bit ⁽¹)		
	1 = Starts 16-bit Tim	ery		
	0 = Stops 16-bit Tim	ery		
bit 14	Unimplemented: Re	ad as '0'		
bit 13	TSIDL: Stop in Idle N	lode bit ⁽¹⁾		
	1 = Discontinue mod	ule operation whe	n device enters Idle mode	
	0 = Continue module	operation in Idle	mode	
bit 12-7	Unimplemented: Re	ad as '0'		
bit 6	TGATE: Timery Gate	d Time Accumula	tion Enable bit ⁽¹⁾	
	When TCS = 1:			
	This bit is ignored.			
	<u>When TCS = 0:</u>			
	\perp = Gated time accu	mulation enabled		
hit 5_1			cale Select hits(1)	
DIL 3-4	11 = 1.256			
	10 = 1:64			
	01 = 1:8			
	00 = 1:1			
bit 3-2	Unimplemented: Re	ad as '0'		
bit 1	TCS: Timery Clock S	ource Select bit ^{(1,}	2)	
	1 = External clock fr	om pin TyCK (on t	he rising edge)	
	0 = Internal clock (F	osc/2)		
bit 0	Unimplemented: Re	ad as '0'		
Note 1:	When 32-bit operation is operation; all timer functi	enabled (T2CON∙ ons are set throug	<3> or T4CON<3> = 1), these h T2CON and T4CON.	e bits have no effect on Timery
2:	If TCS = 1, RPINRx (Tx	CK) must be config	gured to an available RPn pir	a. See Section 10.4 "Peripheral

- **Pin Select**" for more information.
- **3:** Changing the value of TyCON while the timer is running (TON = 1) causes the timer prescale counter to reset and is not recommended.

14.0 OUTPUT COMPARE WITH DEDICATED TIMERS

Note:	This data sheet summarizes the features
	of this group of PIC24F devices. It is not
	intended to be a comprehensive reference
	source. For more information, refer to the
	"PIC24F Family Reference Manual",
	Section 35. "Output Compare with
	Dedicated Timers" (DS39723).

Devices in the PIC24FJ256GB110 family all feature 9 independent output compare modules. Each of these modules offers a wide range of configuration and operating options for generating pulse trains on internal device events, and can produce pulse-width modulated waveforms for driving power applications.

Key features of the output compare module include:

- Hardware-configurable for 32-bit operation in all modes by cascading two adjacent modules
- Synchronous and Trigger modes of output compare operation, with up to 30 user-selectable trigger/sync sources available
- Two separate period registers (a main register, OCxR, and a secondary register, OCxRS) for greater flexibility in generating pulses of varying widths
- Configurable for single-pulse or continuous pulse generation on an output event, or continuous PWM waveform generation
- Up to 6 clock sources available for each module, driving a separate internal 16-bit counter

14.1 General Operating Modes

14.1.1 SYNCHRONOUS AND TRIGGER MODES

By default, the output compare module operates in a free-running mode. The internal 16-bit counter, OCxTMR, runs counts up continuously, wrapping around from FFFFh to 0000h on each overflow, with its period synchronized to the selected external clock source. Compare or PWM events are generated each time a match between the internal counter and one of the period registers occurs.

In Synchronous mode, the module begins performing its compare or PWM operation as soon as its selected clock source is enabled. Whenever an event occurs on the selected sync source, the module's internal counter is reset. In Trigger mode, the module waits for a sync event from another internal module to occur before allowing the counter to run.

Free-running mode is selected by default, or any time that the SYNCSEL bits (OCxCON2<4:0>) are set to '00000'. Synchronous or Trigger modes are selected any time the SYNCSEL bits are set to any value except '00000'. The OCTRIG bit (OCxCON2<7>) selects either Synchronous or Trigger mode; setting the bit selects Trigger mode operation. In both modes, the SYNCSEL bits determine the sync/trigger source.

14.1.2 CASCADED (32-BIT) MODE

By default, each module operates independently with its own set of 16-bit timer and duty cycle registers. To increase resolution, adjacent even and odd modules can be configured to function as a single 32-bit module. (For example, modules 1 and 2 are paired, as are modules 3 and 4, and so on.) The odd numbered module (OCx) provides the Least Significant 16 bits of the 32-bit register pairs, and the even module (OCy) provides the Most Significant 16 bits. Wraparounds of the OCx registers cause an increment of their corresponding OCy registers.

Cascaded operation is configured in hardware by setting the OC32 bits (OCxCON2<8>) for both modules.

REGISTER 18-7:	U1CON: USB CONTROL REGISTER (DEVICE MODE)

				•	,		
U-0	U-0	U-0	U-0	U-0	U-0	U-0	U-0
—	_	—	—	—	—	-	—
bit 15							bit 8
U-0	R-x, HSC	R/W-0	U-0	R/W-0	R/W-0	R/W-0	R/W-0
—	SE0	PKTDIS	—	HOSTEN	RESUME	PPBRST	USBEN
bit 7							bit 0

Legend:	U = Unimplemented bit, read as '0'				
R = Readable bit	W = Writable bit	bit HSC = Hardware Settable/Clearable bit			
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown		

bit 15-7	Unimplemented: Read as '0'
bit 6	SE0: Live Single-Ended Zero Flag bit
	 1 = Single-ended zero active on the USB bus 0 = No single-ended zero detected
bit 5	PKTDIS: Packet Transfer Disable bit
	 1 = SIE token and packet processing disabled; automatically set when a SETUP token is received 0 = SIE token and packet processing enabled
bit 4	Unimplemented: Read as '0'
bit 3	HOSTEN: Host Mode Enable bit
	 1 = USB host capability enabled; pull-downs on D+ and D- are activated in hardware 0 = USB host capability disabled
bit 2	RESUME: Resume Signaling Enable bit
	1 = Resume signaling activated0 = Resume signaling disabled
bit 1	PPBRST: Ping-Pong Buffers Reset bit
	 Reset all Ping-Pong Buffer Pointers to the EVEN BD banks Ping-Pong Buffer Pointers not reset
bit 0	USBEN: USB Module Enable bit
	 1 = USB module and supporting circuitry enabled (device attached); D+ pull-up is activated in hardware 0 = USB module and supporting circuitry disabled (device detached)

REGISTER 18-18: U1IE: USB INTERRUPT ENABLE REGISTER (ALL USB MODES)

U-0	U-0	U-0	U-0	U-0	U-0	U-0	U-0
—	—	—	—	—	—	—	—
bit 15							bit 8

R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0
STALLIE	ATTACHIE ⁽¹⁾	RESUMEIE	IDLEIE	TRNIE	SOFIE	UERRIE	URSTIE
							DETACHIE
bit 7							

Legend:						
R = Readable bit W = Writable bit			U = Unimplemented bit, read as '0'			
-n = Value a	at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown		
bit 15-8	Unimple	mented: Read as '0'				
bit 7	STALLIE	: STALL Handshake Interrup	ot Enable bit			
	1 = Inter 0 = Inter	rupt enabled rupt disabled				
bit 6	ATTACH	E: Peripheral Attach Interru	ot bit (Host mode only) ⁽¹⁾			
	1 = Inter	rupt enabled				
	0 = Inter	rupt disabled				
bit 5	RESUME	IE: Resume Interrupt bit				
	1 = Inter	rupt enabled				
bit 4		rupt disabled				
DIT 4	1 = Intor					
	1 = 1 Inter 0 = 1 Inter	rupt enabled				
bit 3	TRNIE: T	oken Processing Complete	nterrupt bit			
	1 = Inter	rupt enabled				
	0 = Inter	rupt disabled				
bit 2	SOFIE: S	Start-of-Frame Token Interrup	ot bit			
	1 = Inter	rupt enabled				
	0 = Inter	rupt disabled				
bit 1	UERRIE:	USB Error Condition Interru	pt bit			
	1 = Inter	rupt enabled				
1.11.0						
DIT U	Enable bi	t	Interrupt (Device mode) or U	SB Detach Interrupt (Host mode		
	1 = Inter	rupt enabled				
	0 = Inter	rupt disabled				
Note 1:	Unimplement	ed in Device mode, read as	'0'.			

21.3 Registers

There are four registers used to control programmable CRC operation:

- CRCCON
- CRCXOR
- CRCDAT
- CRCWDAT

REGISTER 21-1: CRCCON: CRC CONTROL REGISTER

U-0	U-0	R/W-0	R-0	R-0	R-0	R-0	R-0
—	—	CSIDL	VWORD4	VWORD3	VWORD2	VWORD1	VWORD0
bit 15 bit 8							

R-0	R-1	U-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0
CRCFUL	CRCMPT	—	CRCGO	PLEN3	PLEN2	PLEN1	PLEN0
bit 7							bit 0

Legend:			
R = Readable bit	W = Writable bit	U = Unimplemented bit, read	1 as '0'
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown

bit 15-14	Unimplemented: Read as '0'
bit 13	CSIDL: CRC Stop in Idle Mode bit
	 1 = Discontinue module operation when device enters Idle mode 0 = Continue module operation in Idle mode
bit 12-8	VWORD<4:0>: Pointer Value bits
	Indicates the number of valid words in the FIFO. Has a maximum value of 8 when PLEN<3:0> > 7, or 16 when PLEN<3:0> \leq 7.
bit 7	CRCFUL: FIFO Full bit
	1 = FIFO is full 0 = FIFO is not full
bit 6	CRCMPT: FIFO Empty Bit
	1 = FIFO is empty0 = FIFO is not empty
bit 5	Unimplemented: Read as '0'
bit 4	CRCGO: Start CRC bit
	1 = Start CRC serial shifter
	0 = CRC serial shifter turned off
bit 3-0	PLEN<3:0>: Polynomial Length bits
	Denotes the length of the polynomial to be generated minus 1.

24.0 COMPARATOR VOLTAGE REFERENCE

Note: This data sheet summarizes the features of this group of PIC24F devices. It is not intended to be a comprehensive reference source. For more information, refer to the "PIC24F Family Reference Manual", "Section 20. Comparator Voltage Reference Module" (DS39709).

24.1 Configuring the Comparator Voltage Reference

The voltage reference module is controlled through the CVRCON register (Register 24-1). The comparator voltage reference provides two ranges of output

voltage, each with 16 distinct levels. The range to be used is selected by the CVRR bit (CVRCON<5>). The primary difference between the ranges is the size of the steps selected by the CVREF Selection bits (CVR<3:0>), with one range offering finer resolution.

The comparator reference supply voltage can come from either VDD and VSS, or the external VREF+ and VREF-. The voltage source is selected by the CVRSS bit (CVRCON<4>).

The settling time of the comparator voltage reference must be considered when changing the CVREF output.



FIGURE 24-1: COMPARATOR VOLTAGE REFERENCE BLOCK DIAGRAM

27.7 MPLAB SIM Software Simulator

The MPLAB SIM Software Simulator allows code development in a PC-hosted environment by simulating the PIC MCUs and dsPIC[®] DSCs on an instruction level. On any given instruction, the data areas can be examined or modified and stimuli can be applied from a comprehensive stimulus controller. Registers can be logged to files for further run-time analysis. The trace buffer and logic analyzer display extend the power of the simulator to record and track program execution, actions on I/O, most peripherals and internal registers.

The MPLAB SIM Software Simulator fully supports symbolic debugging using the MPLAB C Compilers, and the MPASM and MPLAB Assemblers. The software simulator offers the flexibility to develop and debug code outside of the hardware laboratory environment, making it an excellent, economical software development tool.

27.8 MPLAB REAL ICE In-Circuit Emulator System

MPLAB REAL ICE In-Circuit Emulator System is Microchip's next generation high-speed emulator for Microchip Flash DSC and MCU devices. It debugs and programs PIC[®] Flash MCUs and dsPIC[®] Flash DSCs with the easy-to-use, powerful graphical user interface of the MPLAB Integrated Development Environment (IDE), included with each kit.

The emulator is connected to the design engineer's PC using a high-speed USB 2.0 interface and is connected to the target with either a connector compatible with incircuit debugger systems (RJ11) or with the new high-speed, noise tolerant, Low-Voltage Differential Signal (LVDS) interconnection (CAT5).

The emulator is field upgradable through future firmware downloads in MPLAB IDE. In upcoming releases of MPLAB IDE, new devices will be supported, and new features will be added. MPLAB REAL ICE offers significant advantages over competitive emulators including low-cost, full-speed emulation, run-time variable watches, trace analysis, complex breakpoints, a ruggedized probe interface and long (up to three meters) interconnection cables.

27.9 MPLAB ICD 3 In-Circuit Debugger System

MPLAB ICD 3 In-Circuit Debugger System is Microchip's most cost effective high-speed hardware debugger/programmer for Microchip Flash Digital Signal Controller (DSC) and microcontroller (MCU) devices. It debugs and programs PIC[®] Flash microcontrollers and dsPIC[®] DSCs with the powerful, yet easyto-use graphical user interface of MPLAB Integrated Development Environment (IDE).

The MPLAB ICD 3 In-Circuit Debugger probe is connected to the design engineer's PC using a high-speed USB 2.0 interface and is connected to the target with a connector compatible with the MPLAB ICD 2 or MPLAB REAL ICE systems (RJ-11). MPLAB ICD 3 supports all MPLAB ICD 2 headers.

27.10 PICkit 3 In-Circuit Debugger/ Programmer and PICkit 3 Debug Express

The MPLAB PICkit 3 allows debugging and programming of PIC[®] and dsPIC[®] Flash microcontrollers at a most affordable price point using the powerful graphical user interface of the MPLAB Integrated Development Environment (IDE). The MPLAB PICkit 3 is connected to the design engineer's PC using a full speed USB interface and can be connected to the target via an Microchip debug (RJ-11) connector (compatible with MPLAB ICD 3 and MPLAB REAL ICE). The connector uses two device I/O pins and the reset line to implement in-circuit debugging and In-Circuit Serial Programming[™].

The PICkit 3 Debug Express include the PICkit 3, demo board and microcontroller, hookup cables and CDROM with user's guide, lessons, tutorial, compiler and MPLAB IDE software.

Assembly Mnemonic		Assembly Syntax	Description	# of Words	# of Cycles	Status Flags Affected
BTSS	BTSS	f,#bit4	Bit Test f, Skip if Set	1	1 (2 or 3)	None
	BTSS	Ws,#bit4	Bit Test Ws, Skip if Set	1	1 (2 or 3)	None
BTST	BTST	f,#bit4	Bit Test f	1	1	Z
	BTST.C	Ws,#bit4	Bit Test Ws to C	1	1	С
	BTST.Z	Ws,#bit4	Bit Test Ws to Z	1	1	Z
	BTST.C	Ws,Wb	Bit Test Ws <wb> to C</wb>	1	1	С
	BTST.Z	Ws,Wb	Bit Test Ws <wb> to Z</wb>	1	1	Z
BTSTS	BTSTS	f,#bit4	Bit Test then Set f	1	1	Z
	BTSTS.C	Ws,#bit4	Bit Test Ws to C, then Set	1	1	С
	BTSTS.Z	Ws,#bit4	Bit Test Ws to Z, then Set	1	1	Z
CALL	CALL	lit23	Call Subroutine	2	2	None
	CALL	Wn	Call Indirect Subroutine	1	2	None
CLR	CLR	f	f = 0x0000	1	1	None
	CLR	WREG	WREG = 0x0000	1	1	None
	CLR	Ws	Ws = 0x0000	1	1	None
CLRWDT	CLRWDT		Clear Watchdog Timer	1	1	WDTO, Sleep
COM	COM	f	f = f	1	1	N, Z
	СОМ	f,WREG	WREG = f	1	1	N. Z
	COM	Ws.Wd	$Wd = \overline{Ws}$	1	1	N 7
CP	CP	f	Compare f with WREG	1	1	C DC N OV Z
61	CP		Compare Wb with lit5	1	1	C DC N OV Z
	CP	Wb Wg	Compare Wb with Ws (Wb $-$ Ws)	1	1	C DC N OV Z
CDU	CPO	f	Compare f with 0x0000	1	1	C DC N OV Z
61.0	CPO	± We	Compare Ws with 0x0000	1	1	C DC N OV Z
CPB	CPB	f	Compare f with WREG with Borrow	1	1	C DC N OV Z
61.5	CPB		Compare Wb with lit5 with Borrow	1	1	C DC N OV Z
	CPB	Wb Wg	Compare Wb with Ws with Borrow	1	1	C DC N OV Z
			(Wb - Ws - C)			0, 00, 11, 01, 2
CPSEQ	CPSEQ	Wb,Wn	Compare wb with wh, Skip if =	1	1 (2 or 3)	None
CPSGT	CPSGT	Wb,Wn	Compare Wb with Wn, Skip if >	1	1 (2 or 3)	None
CPSLT	CPSLT	Wb,Wn	Compare Wb with Wn, Skip if <	1	1 (2 or 3)	None
CPSNE	CPSNE	Wb,Wn	Compare Wb with Wn, Skip if ≠	1	1 (2 or 3)	None
DAW	DAW.b	Wn	Wn = Decimal Adjust Wn	1	1	С
DEC	DEC	f	f = f -1	1	1	C, DC, N, OV, Z
	DEC	f,WREG	WREG = f –1	1	1	C, DC, N, OV, Z
	DEC	Ws,Wd	Wd = Ws - 1	1	1	C, DC, N, OV, Z
DEC2	DEC2	f	f = f - 2	1	1	C, DC, N, OV, Z
	DEC2	f,WREG	WREG = f – 2	1	1	C, DC, N, OV, Z
	DEC2	Ws,Wd	Wd = Ws - 2	1	1	C, DC, N, OV, Z
DISI	DISI	#lit14	Disable Interrupts for k Instruction Cycles	1	1	None
DIV	DIV.SW	Wm,Wn	Signed 16/16-bit Integer Divide	1	18	N, Z, C, OV
	DIV.SD	Wm,Wn	Signed 32/16-bit Integer Divide	1	18	N, Z, C, OV
	DIV.UW	Wm,Wn	Unsigned 16/16-bit Integer Divide	1	18	N, Z, C, OV
	DIV.UD	Wm,Wn	Unsigned 32/16-bit Integer Divide	1	18	N, Z, C, OV
EXCH	EXCH	Wns,Wnd	Swap Wns with Wnd	1	1	None
FF1L	FF1L	Ws,Wnd	Find First One from Left (MSb) Side	1	1	с
FF1R	FF1R	Ws,Wnd	Find First One from Right (LSb) Side	1	1	С

TABLE 28-2: INSTRUCTION SET OVERVIEW (CONTINUED)

TABLE 29-4: DC CHARACTERISTICS: OPERATING CURRENT (IDD)

DC CHARACTERISTICS			$\begin{array}{llllllllllllllllllllllllllllllllllll$				
Parameter No.	Typical ⁽¹⁾	Мах	Units	Conditions			
Operating Cur	rent (IDD) ⁽²⁾						
DC20	0.83	1.2	mA	-40°C			
DC20a	0.83	1.2	mA	+25°C	2.0V ⁽³⁾		
DC20b	0.83	1.2	mA	+85°C			
DC20d	1.1	1.7	mA	-40°C			
DC20e	1.1	1.7	mA	+25°C	3.3√ ⁽⁴⁾		
DC20f	1.1	1.7	mA	+85°C			
DC23	3.3	4.5	mA	-40°C			
DC23a	3.3	4.5	mA	+25°C	2.0∨ ⁽³⁾ 3.3∨ ⁽⁴⁾	4 MIPS	
DC23b	3.3	4.5	mA	+85°C			
DC23d	4.3	6	mA	-40°C			
DC23e	4.3	6	mA	+25°C			
DC23f	4.3	6	mA	+85°C			
DC24	18.2	24	mA	-40°C			
DC24a	18.2	24	mA	+25°C	2.5V ⁽³⁾		
DC24b	18.2	24	mA	+85°C			
DC24d	18.2	24	mA	-40°C			
DC24e	18.2	24	mA	+25°C	3.3∨ ⁽⁴⁾		
DC24f	18.2	24	mA	+85°C			
DC31	15.0	54	μΑ	-40°C			
DC31a	15.0	54	μA	+25°C	2.0V ⁽³⁾		
DC31b	20.0	69	μA	+85°C			
DC31d	57.0	96	μΑ	-40°C			
DC31e	57.0	96	μA	+25°C	3.3√ ⁽⁴⁾		
DC31f	95.0	145	μA	+85°C			

Note 1: Data in "Typical" column is at 3.3V, 25°C unless otherwise stated. Parameters are for design guidance only and are not tested.

2: The supply current is mainly a function of the operating voltage and frequency. Other factors, such as I/O pin loading and switching rate, oscillator type, internal code execution pattern and temperature, also have an impact on the current consumption. The test conditions for all IDD measurements are as follows: OSCI driven with external square wave from rail to rail. All I/O pins are configured as inputs and pulled to VDD. MCLR = VDD; WDT and FSCM are disabled. CPU, SRAM, program memory and data memory are operational. No peripheral modules are operating and all of the Peripheral Module Disable (PMD) bits are set.

- 3: On-chip voltage regulator disabled (ENVREG tied to Vss).
- 4: On-chip voltage regulator enabled (ENVREG tied to VDD). Low-Voltage Detect (LVD) and Brown-out Detect (BOD) are enabled.

U

UART	
Baud Rate Generator (BRG)200	
Operation of UxCTS and UxRTS Pins	
Receiving	
Transmitting	
8-Bit Data Mode 201	
9-Bit Data Mode201	
Break and Sync Sequence	
Universal Asynchronous Receiver Transmitter. See UART.	
Universal Serial Bus	
Buffer Descriptors	
Assignment in Different Buffering Modes	
Interrupts	
and USB Transactions217	
Universal Serial Bus. See USB OTG.	
USB On-The-Go (OTG)12	
USBOTG	
Buffer Descriptors and BDT212	
Device Mode Operation	
DMA Interface	
Hardware Configuration	
Device Mode	
External Interface211	
Host and OTG Modes210	
Transceiver Power Requirements	
VBUS Voltage Generation	
Host Mode Operation	
Interrupts	
OTG Operation220	
Registers	
VBUS Voltage Generation211	

V

VDDCORE/VCAP Pin	293
Voltage Regulator (On-Chip)	. 293
and BOR	. 294
Standby Mode	. 294
Tracking Mode	293
w	
Watchdog Timer (WDT)	. 294
Control Register	295
Windowed Operation	295
WWW Address	. 348
WWW, On-Line Support	9