



Welcome to E-XFL.COM

Understanding [Embedded - Microcontroller, Microprocessor, FPGA Modules](#)

Embedded - Microcontroller, Microprocessor, and FPGA Modules are fundamental components in modern electronic systems, offering a wide range of functionalities and capabilities. Microcontrollers are compact integrated circuits designed to execute specific control tasks within an embedded system. They typically include a processor, memory, and input/output peripherals on a single chip. Microprocessors, on the other hand, are more powerful processing units used in complex computing tasks, often requiring external memory and peripherals. FPGAs (Field Programmable Gate Arrays) are highly flexible devices that can be configured by the user to perform specific logic functions, making them invaluable in applications requiring customization and adaptability.

Applications of [Embedded - Microcontroller,](#)

Details

Product Status	Discontinued at Digi-Key
Module/Board Type	FPGA Core
Core Processor	Artix-7 A200T
Co-Processor	-
Speed	-
Flash Size	32MB
RAM Size	256KB
Connector Type	SO-DIMM-204
Size / Dimension	2.7" x 2.0" (68mm x 51mm)
Operating Temperature	0°C ~ 85°C
Purchase URL	https://www.e-xfl.com/product-detail/soc-technologies/ec-v-h264-8b-30-1080-mxc-sl

6. The H.264 4K Encoder Modules

- 6.1 Pin Assignments and Pin Voltages**
- 6.2 Signal Formats**
 - 6.2.1 Clock Signals (Input, Output)**
 - 6.2.2 Video Data Signals (Input)**
 - 6.2.3 Audio Data Signals (Input)**
 - 6.2.4 TS Signals (Output)**
 - 6.2.5 Encoder Control Signals (Input and Output)**
- 6.3 Power Rails of MCM-1000Z**
- 6.4 Power Requirement and Supply Amperage**

7. The H.264 4K Decoder Modules

- 7.1 Pin Assignments and Pin Voltages**
- 7.2 Signal Formats**
 - 7.2.1 Video Clock Signal (Input)**
 - 7.2.2 Video Data Signals (Output)**
 - 7.2.3 Audio Data Signals (Output)**
 - 7.2.4 TS Signals (Input)**
 - 7.2.5 Decoder Control Signals (Input and Output)**
- 7.3 Power Rails of MCM-1000Z**
- 7.4 Power Requirement and Supply Amperage**

8. The H.265 HD Encoder Modules

- 8.1 Pin Assignments and Pin Voltages**
- 8.2 Signal Formats**
 - 8.2.1 Clock Signal (Input)**
 - 8.2.2 Video Data Signals (Input)**
 - 8.2.3 Audio Data Signals (Input)**
 - 8.2.4 TS Signals (Output)**
 - 8.2.5 Encoder Control Signals (Input and Output)**
- 8.3 Power Rails of MCM-1000SX**
- 8.4 Power Requirement and Supply Amperage**

9. The H.265 HD Decoder Modules

- 9.1 Pin Assignments and Pin Voltages**
- 9.2 Signal Formats**
 - 9.2.1 Clock Signal (Input)**
 - 9.2.2 Video Data Signals (Output)**
 - 9.2.3 Audio Data Signals (Output)**
 - 9.2.4 TS Signals (Input)**
 - 9.2.5 Encoder Control Signals (Input and Output)**
- 9.3 Power Rails of MCM-1000SX**
- 9.4 Power Requirement and Supply Amperage**

10. The H.265 4K Encoder Modules

- 10.1 Pin Assignments and Pin Voltages**
- 10.2 Signal Formats**
 - 10.2.1 Clock Signals (Input, Output)**
 - 10.2.2 Video Data Signals (Input)**
 - 10.2.3 Audio Data Signals (Input)**
 - 10.2.4 TS Signals (Output)**
 - 10.2.5 Decoder Control Signals (Input and Output)**
- 10.3 Power Rails of MCM-1000SX**
- 10.4 Power Requirement and Supply Amperage**

11. The H.265 4K Decoder Modules

- 11.1 Pin Assignments and Pin Voltages**
- 11.2 Signal Formats**
 - 11.2.1 Clock Signals (Input, Output)**
 - 11.2.2 Video Data Signals (Output)**
 - 11.2.3 Audio Data Signals (Output)**
 - 11.2.4 TS Signals (Input)**
 - 11.2.5 Decoder Control Signals (Input and Output)**
- 11.3 Power Rails of MCM-1000SX**
- 11.4 Power Requirement and Supply Amperage**

12. Carrier Board References

12.1 VTR-S1000 Board

12.2 VTR-4000C Board

13. Ordering Information

14. Contact Information

15. Document Versions

Appendix-A SOC Standard Codec Modules

Appendix-B MCM-1000A Edge Connector Schematics

Appendix-C MCM-1000Z Edge Connector Schematics

1. Overview of SOC SOM Modules

The SOC SOMs are small circuit boards with FPGA, DDRs, Flash, and clocks in one module to support FPGA-based systems. A module can be configured into a SOM by using the applicable firmware. The module is connected to a user PCB through a standard DDR3 SODIMM connector. Customers can order the blank SOMs from SOC and use their own firmware to make SOM products.

SOC configures the modules into MPEG codec SOMs for video/audio compression, decompression, and transcoding functions. Currently available modules are:

	Hardware Product Code	FPGA Chip on the Module	SOC Codec module Resolution Capacity
1	MCM-1000S	Spartan-6 XC6SLX150	H.264 or MPEG-2 HD up to 1080@30
2	MCM-1000A	Artix-7 XC7A200T	H.264 or MPEG-2 HD up to 1080@60
3	MCM-1000Z	Zynq-7 XC7Z035/045	H.264 4k@30/60, or H.265 HD up to 1080@60
4	MCM-1000SX	Arria-10 SX220/270/320/480/570/660	H.264 HD 1080@30/60, or H.264 4k@30/60, or H.265 HD up to 1080@60), or H.265 4k@30/60

Fig. 1 shows a photo of the modules. Fig. 2-5 shows the dimensions of MCM-1000S, MCM-1000A, MCM-1000Z, and MCM-1000SX respectively.



Fig. 1 SOC codec modules

4.2.3 Audio Data Signals (Input)

Input line **SPDIF Audio** (pin # 69) is for PCM audio input, in **SPDIF** frames. An **SPDIF** transmitter is required to send the PCM data to the encoder module. Refer to the **SPDIF** protocol documents for details.

4.2.4 TS stream Signals (Output)

The output of the encoder module is MPEG Transport Stream (TS), which is sent out from the module by 8 parallel lines: **Transport Stream Data[0]** to **Transport Stream Data[7]**; along with the Transport Stream output data clock **Transport Stream Clock** (pin # 113). The frequency of the Transport Stream Data clock is 27MHz.

Transport Stream Buffer Ready (pin # 118) and **Transport Stream Data Valid** (pin # 135) are the signals to inform the user side to take over the signals.

4.2.5 Encoder Control Signals (Input and Output)

Uart_rx and **Uart_tx** are the API pins for controlling the operations of the encoder. **Uart_rx** receives the command from external control device. **Uart_tx** sends the encoder information to the control device. Refer to the **Uart** standard for details of **Uart** operations. The SOC API User Manual provides the register map for the API control. Refer to the [Encoder API User Manual](#) for more details.

An external reset pin (pin # 121) is available. This pin allows the user to reset the encoder when necessary. A high signal will trigger a reset. The reset signal should be maintained at low when in normal operation mode.

4.3 Power Rails of MCM-1000A

Table-2 lists the power and ground pins. Refer to Appendix-A for the pins of power and ground on the edge connector of the MCM-1000A module.

Table-2: MCM-1000A Power and Ground Pins

MCM-1000S Connector Pin	Voltage
1,3,5,7,9,11,13,15	3.3V
10,12,14,16	1.2V
22,24,26,28,30,32	1.5V
189,191,193,195,197,199	2.5V
188,190,192,194	1.3V
43,45,47,49,51,53,55,57	1.0V
2,4,6,8,18,20,34,36,42,44,62,72	Ground
17,35,37,39,41,71	Ground
73,75,129	Ground
74	Ground
163,165,167,169,175,177,185,187,203	Ground
168,170,172,174,176,184,186,200,202,204	Ground

5. The H.264 (and MPEG-2) HD Decoder Modules

5.1 Pin Assignments and Pin Voltages

The decoders for H.264 and MPEG-2 have the same pin assignment. The module for HD resolution decoding uses the MCM-1000A (with the Artix-7 A200T FPGA which is the same as the one used for the HD Encoder). The module MCM-1000Z is used for 4k decoding (the Zynq-7035 for 4k@30, Zynq-7045 for 4k@60).

This section details the pin assignments and pin voltages for the HD decoder (H.264, and MPEG-2) modules. Table-4 shows the pin assignments and the pin voltages.

The schematics of MCM-1000A edge connector are attached in Appendix-B of this document. Appendix-B shows the pin numbers for data, clock, control, and power, which are connected to the FPGA (Artix-7 XC7A200T). It should be noted that the decoder module uses only some of the available edge pins that are connected to the FPGA (some of the pins are not used).

It should also be noted that the HD encoder and decoder pin assignments are symmetrical, i.e. the video input pins on the encoder module become the video output pins on the decoder module.

Table-4: HD Decoder Module (based on MCM-1000A) Pin Assignment

Description	MCM-1000A Edge Connector Pin #	Direction	FPGA Pin #	Voltage	IO Standard
External Reset	121	Input	W21	3.3v	LVCMS33
Decoder Clock	115	Input	U20	3.3v	LVCMS33
Video Clock	105	Output	Y11	3.3v	LVCMS33
Video Horizontal Sync	146	Output	W16	3.3v	LVCMS33
Video Vertical Sync	148	Output	V15	3.3v	LVCMS33
Video Display Enable	150	Output	U15	3.3v	LVCMS33
Video Data Luma[0]	50	Output	W14	3.3v	LVCMS33
Video Data Luma[1]	52	Output	Y14	3.3v	LVCMS33
Video Data Luma[2]	58	Output	V10	3.3v	LVCMS33
Video Data Luma[3]	59	Output	Y13	3.3v	LVCMS33
Video Data Luma[4]	60	Output	W10	3.3v	LVCMS33
Video Data Luma[5]	61	Output	AA14	3.3v	LVCMS33
Video Data Luma[6]	80	Output	AB13	3.3v	LVCMS33
Video Data Luma[7]	82	Output	AA13	3.3v	LVCMS33
Video Data Luma[8]	84	Output	AB17	3.3v	LVCMS33
Video Data Luma[9]	86	Output	AB16	3.3v	LVCMS33
Video Data Chroma[0]	92	Output	AA15	3.3v	LVCMS33
Video Data Chroma[1]	94	Output	AB15	3.3v	LVCMS33
Video Data Chroma[2]	96	Output	AB12	3.3v	LVCMS33
Video Data Chroma[3]	98	Output	AB11	3.3v	LVCMS33
Video Data Chroma[4]	107	Output	Y12	3.3v	LVCMS33
Video Data Chroma[5]	108	Output	W12	3.3v	LVCMS33
Video Data Chroma[6]	110	Output	Y17	3.3v	LVCMS33
Video Data Chroma[7]	140	Output	T14	3.3v	LVCMS33
Video Data Chroma[8]	142	Output	T15	3.3v	LVCMS33
Video Data Chroma[9]	144	Output	W15	3.3v	LVCMS33
Video Frame Sync Relock	56	Input	AB21	3.3v	LVCMS33

Video Data 1 Luma[4]	125	Input	AF23	3.3v	LVC MOS33
Video Data 1 Luma[5]	127	Input	AF24	3.3v	LVC MOS33
Video Data 1 Luma[6]	92	Input	AJ23	3.3v	LVC MOS33
Video Data 1 Luma[7]	94	Input	AJ24	3.3v	LVC MOS33
Video Data 1 Luma[8]	96	Input	AG24	3.3v	LVC MOS33
Video Data 1 Luma[9]	98	Input	AG25	3.3v	LVC MOS33
Video Data 2 Luma[0]	77	Input	AJ16	3.3v	LVC MOS33
Video Data 2 Luma[1]	79	Input	AK16	3.3v	LVC MOS33
Video Data 2 Luma[2]	81	Input	AH17	3.3v	LVC MOS33
Video Data 2 Luma[3]	83	Input	AH16	3.3v	LVC MOS33
Video Data 2 Luma[4]	85	Input	AH18	3.3v	LVC MOS33
Video Data 2 Luma[5]	87	Input	AJ18	3.3v	LVC MOS33
Video Data 2 Luma[6]	78	Input	AF13	3.3v	LVC MOS33
Video Data 2 Luma[7]	82	Input	AG15	3.3v	LVC MOS33
Video Data 2 Luma[8]	84	Input	AG17	3.3v	LVC MOS33
Video Data 2 Luma[9]	86	Input	AG16	3.3v	LVC MOS33
Video Data 3 Luma[0]	107	Input	AH21	3.3v	LVC MOS33
Video Data 3 Luma[1]	122	Input	AH29	3.3v	LVC MOS33
Video Data 3 Luma[2]	115	Input	AE22	3.3v	LVC MOS33
Video Data 3 Luma[3]	146	Input	AF28	3.3v	LVC MOS33
Video Data 3 Luma[4]	148	Input	AF29	3.3v	LVC MOS33
Video Data 3 Luma[5]	150	Input	AG29	3.3v	LVC MOS33
Video Data 3 Luma[6]	100	Input	AH23	3.3v	LVC MOS33
Video Data 3 Luma[7]	102	Input	AH24	3.3v	LVC MOS33
Video Data 3 Luma[8]	104	Input	AJ25	3.3v	LVC MOS33
Video Data 3 Luma[9]	106	Input	AK25	3.3v	LVC MOS33
Video Data 0 Chroma[0]	143	Input	T29	1.5v	LVC MOS15
Video Data 0 Chroma[1]	145	Input	U29	1.5v	LVC MOS15
Video Data 0 Chroma[2]	147	Input	R28	1.5v	LVC MOS15
Video Data 0 Chroma[3]	149	Input	T28	1.5v	LVC MOS15
Video Data 0 Chroma[4]	151	Input	P30	1.5v	LVC MOS15
Video Data 0 Chroma[5]	153	Input	R30	1.5v	LVC MOS15
Video Data 0 Chroma[6]	155	Input	N29	1.5v	LVC MOS15
Video Data 0 Chroma[7]	157	Input	P29	1.5v	LVC MOS15
Video Data 0 Chroma[8]	159	Input	N28	1.5v	LVC MOS15
Video Data 0 Chroma[9]	161	Input	P28	1.5v	LVC MOS15
Video Data 1 Chroma[0]	89	Input	AK17	3.3v	LVC MOS33
Video Data 1 Chroma[1]	91	Input	AK18	3.3v	LVC MOS33
Video Data 1 Chroma[2]	93	Input	AF19	3.3v	LVC MOS33
Video Data 1 Chroma[3]	95	Input	AG19	3.3v	LVC MOS33
Video Data 1 Chroma[4]	97	Input	AH19	3.3v	LVC MOS33
Video Data 1 Chroma[5]	99	Input	AJ19	3.3v	LVC MOS33
Video Data 1 Chroma[6]	101	Input	AF20	3.3v	LVC MOS33
Video Data 1 Chroma[7]	103	Input	AG20	3.3v	LVC MOS33
Video Data 1 Chroma[8]	109	Input	AJ20	3.3v	LVC MOS33
Video Data 1 Chroma[9]	111	Input	AK20	3.3v	LVC MOS33
Video Data 2 Chroma[0]	38	Input	AE12	3.3v	LVC MOS33
Video Data 2 Chroma[1]	40	Input	AF12	3.3v	LVC MOS33

Video Data 2 Chroma[2]	50	Input	AG12	3.3v	LVC MOS33
Video Data 2 Chroma[3]	52	Input	AH12	3.3v	LVC MOS33
Video Data 2 Chroma[4]	54	Input	AH14	3.3v	LVC MOS33
Video Data 2 Chroma[5]	56	Input	AH13	3.3v	LVC MOS33
Video Data 2 Chroma[6]	58	Input	AJ14	3.3v	LVC MOS33
Video Data 2 Chroma[7]	60	Input	AJ13	3.3v	LVC MOS33
Video Data 2 Chroma[8]	59	Input	AK13	3.3v	LVC MOS33
Video Data 2 Chroma[9]	61	Input	AK12	3.3v	LVC MOS33
Video Data 3 Chroma[0]	108	Input	AJ26	3.3v	LVC MOS33
Video Data 3 Chroma[1]	110	Input	AK26	3.3v	LVC MOS33
Video Data 3 Chroma[2]	112	Input	AH26	3.3v	LVC MOS33
Video Data 3 Chroma[3]	114	Input	AH27	3.3v	LVC MOS33
Video Data 3 Chroma[4]	136	Input	AK27	3.3v	LVC MOS33
Video Data 3 Chroma[5]	138	Input	AK28	3.3v	LVC MOS33
Video Data 3 Chroma[6]	139	Input	AJ28	3.3v	LVC MOS33
Video Data 3 Chroma[7]	141	Input	AJ29	3.3v	LVC MOS33
Video Data 3 Chroma[8]	140	Input	AJ30	3.3v	LVC MOS33
Video Data 3 Chroma[9]	142	Input	AK30	3.3v	LVC MOS33
SPDIF Audio	27	Input	Y20	1.5v	LVC MOS15
Transport Stream Buffer	29	Input	AA20	1.5v	LVC MOS15
Transport Stream Clock	31	Output	AA18	1.5v	LVC MOS15
Transport Stream Data	33	Output	AA19	1.5v	LVC MOS15
Transport Stream Data [0]	152	Output	AF30	3.3v	LVC MOS33
Transport Stream Data [1]	154	Output	AG30	3.3v	LVC MOS33
Transport Stream Data [2]	158	Output	AE30	3.3v	LVC MOS33
Transport Stream Data [3]	160	Output	AB29	3.3v	LVC MOS33
Transport Stream Data [4]	162	Output	AB30	3.3v	LVC MOS33
Transport Stream Data [5]	164	Output	AA27	3.3v	LVC MOS33
Transport Stream Data [6]	166	Output	AA28	3.3v	LVC MOS33
Transport Stream Data [7]	120	Output	AH28	3.3v	LVC MOS33
Uart_tx	90	Output	AK15	3.3v	LVC MOS33
Uart_rx	88	Input	AJ15	3.3v	LVC MOS33

6.2 Signal Formats

6.2.1 Clock Signals (Input)

The 4k encoder has 4 input clocks, **Video Clock 0** (pin # 63), **Video Clock 1** (pin # 80), **Video Clock 2** (pin # 144), and **Video Clock 3** (pin # 105). These clocks match the four of 3G SDI inputs for one 4k@30/60 video. However, if one 4k input is used on the carrier board, such as HDMI 2.0 or 12G SDI, only **Video Clock 0** is needed which takes the input video clock (74.5MHz for 4k@30, and 148.5 MHz for 4k@60).

6.2.2 Video Data Signals (Input)

The input to the encoder module is raw video data in YUV format (4:2:2 or 4:2:0), with 40 input lines: **Video Data 0 Luma[0]** to **Video Data 3 Luma[9]**, for Luma. And, 40 input lines: **Video Data 0 Chroma[0]** to **Video Data 3**

Chroma[9], for the Chroma. The precision is either 8 bits or 10 bits. For 8-bit precision, the Most Significant Luma and Chroma pins (Luma[2] to Luma[9], Chroma[2] to Chroma[9]) are used.

In addition to the video Luma and Chroma data signals, the **Video Horizontal Sync** and **Video Vertical Sync** signals are required for frame synchronization if embedded SAV/EAV are not used. The video clocks (refer to Section 6.2.1) provide the timing for the parallel input of luma, chroma, as well as the **Video Horizontal Sync** and **Video Vertical Sync** signals. The **Video Display Enable** signal is a part of the **Video Horizontal Sync** and **Video Vertical Sync** system, where high signal indicates active video pixels. For example, an HDMI input interface chip will output the **Video Display Enable** signal at high, when active pixels are being sent out.

The video data are sampled at the rising edge of the clock. The clock rates will correspond to the resolution and frame rate, as discussed in Section 6.2.1.

6.2.3 Audio Data Signals (Input)

Input line **SPDIF Audio** is for PCM audio input, in **SPDIF** frames. An **SPDIF** transmitter is required to send the PCM data to the encoder module. Refer to the **SPDIF** protocol documents for details.

6.2.4 TS stream Signals (Output)

The output of the encoder module is MPEG Transport Stream (TS), which is sent out from the module by 8 parallel lines: **Transport Stream Data[0]** to **Transport Stream Data[7]**, along with the Transport Stream output data clock **Transport Stream Clock** (pin # 31). The frequency of the Transport Stream Data clock is 27MHz.

Transport Stream Buffer Ready (pin # 28) and **Transport Stream Data Valid** (pin # 33) are the signals to inform the user side to take over the signals.

6.2.5 Encoder Control Signals (Input and Output)

Uart_rx and **Uart_tx** are the API pins for controlling the operations of the encoder. **Uart_rx** receives the command from external control device. **Uart_tx** sends the encoder information to the control device. Refer to the **Uart** standard for details of **Uart** operations. The SOC API User Manual provides the register map for the API control. Refer to the [Encoder API User Manual](#) for more details.

An external reset **PS Soft Reset_B** (pin # 156) is available. This pin allows the user to reset the encoder when necessary. A low signal will trigger a reset. The reset signal should be maintained at high or left unconnected when in normal operation mode.

6.3 Power Rails of MCM-1000Z

Refer to Appendix-B for the pins of power and ground on the edge connector of the MCM-1000Z module. The power rails are: 1.0V, 1.2V, 1.3V, 1.5V, 2.5V, and 3.3V.

7. The H.264 4K Decoder Modules

7.1 Pin Assignments and Pin Voltages

The modules for H.264 4K resolution use the MCM-1000Z, Zynq-7035 (for 4k@30) or Zynq-7045 (4k@60). This section details the pin assignment and pin voltages for H.264 4K decoder modules based on the MCM-1000Z hardware.

Table-8 shows the pin assignments and the pin voltages for H.264 4k decoder modules based on the MCM-1000Z.

The schematics of MCM-1000Z edge connector are attached in Appendix-C of this document. Appendix-C shows the pin numbers for data, clock, control, and power, which are connected to the FPGA (Zynq-7035 or 7045, which are pin-compatible).

It should be noted that the 4K encoder and decoder pin assignments are symmetrical, i.e. the video input pins on the encoder module become the video output pins on the decoder module.

Table-8: 4K Decoder Module (based on MCM-1000Z) Pin Assignment

Description	MCM-1000Z Edge Connector Pin #	Direction	FPGA Pin #	Voltage	IO Standard
PS Soft Reset_B	156	Input	B19	3.3V	LVC MOS33
Video Clock	105	Output	AG21	3.3v	LVC MOS33
Video Horizontal Sync	133	Output	W24	1.5v	LVC MOS15
Video Vertical Sync	113	Output	AF22	3.3v	LVC MOS33
Video Display Enable	67	Output	AD18	1.5v	LVC MOS15
Video Data 0 Luma[0]	135	Output	W25	1.5v	LVC MOS15
Video Data 0 Luma[1]	137	Output	W26	1.5v	LVC MOS15
Video Data 0 Luma[2]	116	Output	V27	1.5v	LVC MOS15
Video Data 0 Luma[3]	118	Output	W28	1.5v	LVC MOS15
Video Data 0 Luma[4]	124	Output	W29	1.5v	LVC MOS15
Video Data 0 Luma[5]	126	Output	W30	1.5v	LVC MOS15
Video Data 0 Luma[6]	128	Output	V28	1.5v	LVC MOS15
Video Data 0 Luma[7]	130	Output	V29	1.5v	LVC MOS15
Video Data 0 Luma[8]	132	Output	T30	1.5v	LVC MOS15
Video Data 0 Luma[9]	134	Output	U30	1.5v	LVC MOS15
Video Data 1 Luma[0]	117	Output	AG22	3.3v	LVC MOS33
Video Data 1 Luma[1]	119	Output	AH22	3.3v	LVC MOS33
Video Data 1 Luma[2]	121	Output	AJ21	3.3v	LVC MOS33
Video Data 1 Luma[3]	123	Output	AK21	3.3v	LVC MOS33
Video Data 1 Luma[4]	125	Output	AF23	3.3v	LVC MOS33
Video Data 1 Luma[5]	127	Output	AF24	3.3v	LVC MOS33
Video Data 1 Luma[6]	92	Output	AJ23	3.3v	LVC MOS33
Video Data 1 Luma[7]	94	Output	AJ24	3.3v	LVC MOS33

Video Data 1 Luma[8]	96	Output	AG24	3.3v	LVC MOS33
Video Data 1 Luma[9]	98	Output	AG25	3.3v	LVC MOS33
Video Data 2 Luma[0]	77	Output	AJ16	3.3v	LVC MOS33
Video Data 2 Luma[1]	79	Output	AK16	3.3v	LVC MOS33
Video Data 2 Luma[2]	81	Output	AH17	3.3v	LVC MOS33
Video Data 2 Luma[3]	83	Output	AH16	3.3v	LVC MOS33
Video Data 2 Luma[4]	85	Output	AH18	3.3v	LVC MOS33
Video Data 2 Luma[5]	87	Output	AJ18	3.3v	LVC MOS33
Video Data 2 Luma[6]	78	Output	AF13	3.3v	LVC MOS33
Video Data 2 Luma[7]	82	Output	AG15	3.3v	LVC MOS33
Video Data 2 Luma[8]	84	Output	AG17	3.3v	LVC MOS33
Video Data 2 Luma[9]	86	Output	AG16	3.3v	LVC MOS33
Video Data 3 Luma[0]	107	Output	AH21	3.3v	LVC MOS33
Video Data 3 Luma[1]	122	Output	AH29	3.3v	LVC MOS33
Video Data 3 Luma[2]	115	Output	AE22	3.3v	LVC MOS33
Video Data 3 Luma[3]	146	Output	AF28	3.3v	LVC MOS33
Video Data 3 Luma[4]	148	Output	AF29	3.3v	LVC MOS33
Video Data 3 Luma[5]	150	Output	AG29	3.3v	LVC MOS33
Video Data 3 Luma[6]	100	Output	AH23	3.3v	LVC MOS33
Video Data 3 Luma[7]	102	Output	AH24	3.3v	LVC MOS33
Video Data 3 Luma[8]	104	Output	AJ25	3.3v	LVC MOS33
Video Data 3 Luma[9]	106	Output	AK25	3.3v	LVC MOS33
Video Data 0 Chroma[0]	143	Output	T29	1.5v	LVC MOS15
Video Data 0 Chroma[1]	145	Output	U29	1.5v	LVC MOS15
Video Data 0 Chroma[2]	147	Output	R28	1.5v	LVC MOS15
Video Data 0 Chroma[3]	149	Output	T28	1.5v	LVC MOS15
Video Data 0 Chroma[4]	151	Output	P30	1.5v	LVC MOS15
Video Data 0 Chroma[5]	153	Output	R30	1.5v	LVC MOS15
Video Data 0 Chroma[6]	155	Output	N29	1.5v	LVC MOS15
Video Data 0 Chroma[7]	157	Output	P29	1.5v	LVC MOS15
Video Data 0 Chroma[8]	159	Output	N28	1.5v	LVC MOS15
Video Data 0 Chroma[9]	161	Output	P28	1.5v	LVC MOS15
Video Data 1 Chroma[0]	89	Output	AK17	3.3v	LVC MOS33
Video Data 1 Chroma[1]	91	Output	AK18	3.3v	LVC MOS33
Video Data 1 Chroma[2]	93	Output	AF19	3.3v	LVC MOS33
Video Data 1 Chroma[3]	95	Output	AG19	3.3v	LVC MOS33
Video Data 1 Chroma[4]	97	Output	AH19	3.3v	LVC MOS33
Video Data 1 Chroma[5]	99	Output	AJ19	3.3v	LVC MOS33
Video Data 1 Chroma[6]	101	Output	AF20	3.3v	LVC MOS33
Video Data 1 Chroma[7]	103	Output	AG20	3.3v	LVC MOS33
Video Data 1 Chroma[8]	109	Output	AJ20	3.3v	LVC MOS33
Video Data 1 Chroma[9]	111	Output	AK20	3.3v	LVC MOS33
Video Data 2 Chroma[0]	38	Output	AE12	3.3v	LVC MOS33

7.2.2 Video Data Signals (Output)

The output of the H.264 4k decoder module is the decoded video data in YUV format (4:2:2 or 4:2:0), with 40 output lines: **Video Data 0 Luma[0]** to **Video Data 3 Luma[9]**, for Luma. And, 40 lines: **Video Data 0 Chroma[0]** to **Video Data 3 Chroma[9]**, for the Chroma. The precision can be either 8-bit precision or 10-bit precision. For 8-bit precision, the Most Significant Bits of luma and chroma output lines (Luma[2] to Luma[9], Chroma[2] to Chroma[9]) are used.

In addition to the video Luma and Chroma data signals, the **Video Horizontal Sync** and **Video Vertical Sync** signals are provided for frame synchronization. The **Video Display Enable** signal is a part of the **Video Horizontal Sync** and **Video Vertical Sync** system, where high signal indicates active video pixels.

7.2.3 Audio Data Signals (Output)

Line **SPDIF Audio** is for PCM audio output, in **SPDIF** frames. An **SPDIF** transmitter is included in the module to send the PCM data out via the decoder edge pins. Refer to the **SPDIF** protocol documents for details.

7.2.4 Decoder Control Signals (Input and output)

Uart_rx and **Uart_tx** are the API pins for controlling the operations of the decoder. **Uart_rx** receives the command from external control device. **Uart_tx** send the decoder information to the control device. Refer to the **Uart** standard for details of **Uart** operations. The SOC API User Manual provides the register map for the API control. Refer to the [Decoder API User Manual](#) for details.

7.3 Power Rails of MCM-1000Z

The power rails for H.264 4K decoder for 4k@30 or 4k@60 are the same and are also the same as the H.264 4k encoder. Refer to Appendix-C for the pins of power and ground on the edge connector of the MCM-1000Z module.

7.4 Power Requirement and Supply Amperage

The total power, at operation, required by a given encoder module ranges from 3 to 5 watts, depending on the resolution and frame rate. Since the total power is delivered over 6 power rails (1.0v, 1.2v, 1.3v, 1.5v, 2.5v, and 3.3v), each individual power rails deliveries only a portion of the total power. However, the power is not evenly distributed among the rails. Table-10 lists the power estimation by Xilinx Vivado FPGA software for each rail, at 4k@60 resolution, and can be used for PCB design. It should be noted that the power rails 1.8v and 2.0v are generated on the module using the input power rails. PCB designers for the carrier boards need not to consider these two rails.

Since the decoder module normally shares the power supplies with the carrier board (user PCB). The power design should be considered for both. SOC licenses the schematics of carrier boards. The VTR-4000C, discussed in Section

12.2 VTR-4000C Evaluation Board

Fig. 12 shows the top view of the VTR-4000C board. Major components and I/O ports are marked in the figure. Refer to the [User Guide of VTR-4000C](#) for further details.

SOC licenses the Schematics of VTR-4000C to the customers that have purchased encoder (or decoder) Modules. Firmware of the VTR-4000C, including I/O drivers and network IP core, is also available for licensing. Please contact SOC sales, sales@soctechnologies.com, for details.




Fig. 12. VTR-4000C evaluation board top view

13. Ordering Information

Fig. 13 shows the product code naming convention for the SOC MPEG codec modules and IP cores. Non-standard codec modules can be ordered following the same naming format (minimum order quantity is required for non-standard modules).




Fig. 13 SOC MPEG codec (IP cores and modules) product code naming convention

14. Contact Information

Please contact SOC head office or distributor for product details and to place an order.

Head Office

System-On-Chip (SOC) Technologies Inc.

60 Baffin Place

Waterloo, ON, Canada N2V 1Z7

Telephone: 1-519-880-8609

E-mail: sales@soctechnologies.com

15. Document Revisions

Version #	Revision Date	Notes
V.1.0	10/05/2017	First release
V.1.1	19/05/2017	Minor revision
V.2.0	20/05/2017	Major revision (adding 4k)
V.2.1	05/06/2017	Minor revision

Appendix-A Factory Standard Codec Modules

A.1 H.265 Encoder Modules

The H.265 encoder modules are based on either the MCM-1000SX or MCM-1000Z hardware. The SOC H.265 encoder IP cores of different configurations are used to configure the FPGAs on the hardware modules to produce the codec modules.

Table-A1 lists the product codes of the factory standard H.265 video encoder (video only) modules, along with the specifications for each module. Table-A2 lists the video/audio encoder modules. The hardware platform, MCM-1000SX or MCM-1000Z, is used for the H.265 video encoder. Customers can order the H.265 encoder modules using the product code, according to the specifications required by the application.

Table-A1: H.265 Video Encoder Modules (video only without audio):

Product #	Specifications						
	Standard	Profile	Resolution	Chroma	Precision	Frame Rate	Audio
EC-V-H265-8b-30-1080-M	H.265	Main 4:2:2 12	up to 1080i/p	4:2:0/4:2:2	8 bits	up to 30fps	no
EC-V-H265-10b-30-1080-M	H.265	Main 4:2:2 12	up to 1080i/p	4:2:0/4:2:2	up to 10 bits	up to 30fps	no
EC-V-H265-10b-30-1080-M	H.265	Main 4:2:2 12	up to 1080i/p	4:2:0/4:2:2	up to 12 bits	up to 30fps	no
EC-V-H265-8b-60-1080-M	H.265	Main 4:2:2 12	up to 1080i/p	4:2:0/4:2:2	8 bits	up to 60fps	no
EC-V-H265-10b-60-1080-M	H.265	Main 4:2:2 12	up to 1080i/p	4:2:0/4:2:2	up to 10 bits	up to 60fps	no
EC-V-H265-10b-60-1080-M	H.265	Main 4:2:2 12	up to 1080i/p	4:2:0/4:2:2	up to 12 bits	up to 60fps	no
EC-V-H265-8b-30-4k-M	H.265	Main 4:2:2 12	4k/UHD	4:2:0/4:2:2	8 bits	up to 30fps	no
EC-V-H265-10b-30-4k-M	H.265	Main 4:2:2 12	4k/UHD	4:2:0/4:2:2	up to 10 bits	up to 30fps	no
EC-V-H265-10b-30-4k-M	H.265	Main 4:2:2 12	4k/UHD	4:2:0/4:2:2	up to 12 bits	up to 30fps	no
EC-V-H265-8b-60-4k-M	H.265	Main 4:2:2 12	4k/UHD	4:2:0/4:2:2	8 bits	up to 60fps	no
EC-V-H265-10b-60-4k-M	H.265	Main 4:2:2 12	4k/UHD	4:2:0/4:2:2	up to 10 bits	up to 60fps	no
EC-V-H265-10b-60-4k-M	H.265	Main 4:2:2 12	4k/UHD	4:2:0/4:2:2	up to 12bits	up to 60fps	no

Table-A4: H.264 Video&Audio Encoder Modules (both video and audio):

Product #	Specifications							Hardware
	Standard	Profile	Resolution	Chroma	Precision	Frame Rate	Audio	
EC-VA-H264-8b-30-720-MS	H.264	up to High	up to 720i/p	4:2:0/4:2:2	8 bits	up to 30fps	AAC/MPEG2 L-2	MCM-1000A
EC-VA-H264-8b-60-720-MS	H.264	up to High	up to 720i/p	4:2:0/4:2:2	8 bits	up to 60fps	AAC/MPEG2 L-2	MCM-1000A
EC-VA-H264-8b-30-1080-MS	H.264	up to High	up to 1080i/p	4:2:0/4:2:2	8 bits	up to 30fps	AAC/MPEG2 L-2	MCM-1000A
EC-VA-H264-10b-30-1080-MS	H.264	up to High	up to 1080i/p	4:2:0/4:2:2	up to 10bits	up to 30fps	AAC/MPEG2 L-2	MCM-1000A
EC-VA-H264-8b-60-1080-MA	H.264	up to High	up to 1080i/p	4:2:0/4:2:2	8 bits	up to 60fps	AAC/MPEG2 L-2	MCM-1000A
EC-VA-H264-10b-60-1080-MA	H.264	up to High	up to 1080i/p	4:2:0/4:2:2	up to 10 bits	up to 60fps	AAC/MPEG2 L-2	MCM-1000A
EC-VA-H264-8b-30-4k-MZ	H.264	High	4kx2k	4:2:0/4:2:2	8 bits	up to 30fps	AAC/MPEG2 L-2	MCM-1000Z
EC-VA-H264-10b-30-4k-MZ	H.264	High	4kx2k	4:2:0/4:2:2	10 bits	up to 30fps	AAC/MPEG2 L-2	MCM-1000Z
EC-VA-H264-8b-60-4k-MZ	H.264	High	4kx2k	4:2:0/4:2:2	8 bits	up to 60fps	AAC/MPEG2 L-2	MCM-1000Z
EC-VA-H264-10b-60-4k-MZ	H.264	High	4kx2k	4:2:0/4:2:2	10 bits	up to 60fps	AAC/MPEG2 L-2	MCM-1000Z

A.3 H.264 Decoder Modules

Hardware platform MCM-1000A is used for the H.264 HD decoders. Table-A5 lists the factory standard H.264 video decoder modules (video only), along with the product code and specifications. Table-A6 lists the factory standard H.264 video and audio decoder modules, product code, specifications.

Table-A5: H.264 Video Decoder Modules (video only without audio):

Product #	Specifications							Hardware
	Standard	Profile	Resolution	Chroma	Precision	Frame Rate	Audio	
DC-V-H264-8b-30-720-MA	H.264	up to High	up to 720i/p	4:2:0/4:2:2	8 bits	up to 30fps	no	MCM-1000A
DC-V-H264-8b-60-720-MA	H.264	up to High	up to 720i/p	4:2:0/4:2:2	8 bits	up to 60fps	no	MCM-1000A
DC-V-H264-8b-30-1080-MA	H.264	up to High	up to 1080i/p	4:2:0/4:2:2	8 bits	up to 30fps	no	MCM-1000A
DC-V-H264-10b-30-1080-MA	H.264	up to High	up to 1080i/p	4:2:0/4:2:2	up to 10 bits	up to 30fps	no	MCM-1000A
DC-V-H264-8b-60-1080-MA	H.264	up to High	up to 1080i/p	4:2:0/4:2:2	8 bits	up to 60fps	no	MCM-1000A
DC-V-H264-10b-60-1080-MA	H.264	up to High	up to 1080i/p	4:2:0/4:2:2	up to 10 bits	up to 60fps	no	MCM-1000A
DC-V-H264-8b-30-4k-MZ	H.264	High	4kx2k	4:2:0/4:2:2	8 bits	up to 30fps	no	MCM-1000Z
DC-V-H264-10b-30-4k-MZ	H.264	High	4kx2k	4:2:0/4:2:2	10 bits	up to 30fps	no	MCM-1000Z
DC-V-H264-8b-60-4k-MZ	H.264	High	4kx2k	4:2:0/4:2:2	8 bits	up to 60fps	no	MCM-1000Z
DC-V-H264-10b-60-4k-MZ	H.264	High	4kx2k	4:2:0/4:2:2	10 bits	up to 60fps	no	MCM-1000Z

Table-A6: H.264 Video&Audio Decoder Modules (both video and audio):

Product #	Specifications							Hardware
	Standard	Profile	Resolution	Chroma	Precision	Frame Rate	Audio	
DC-VA-H264-8b-30-720-MA	H.264	up to High	up to 720i/p	4:2:0/4:2:2	8 bits	up to 30fps	AAC/MPEG2 L-2	MCM-1000A
DC-VA-H264-8b-60-720-MA	H.264	up to High	up to 720i/p	4:2:0/4:2:2	8 bits	up to 60fps	AAC/MPEG2 L-2	MCM-1000A
DC-VA-H264-8b-30-1080-MA	H.264	up to High	up to 1080i/p	4:2:0/4:2:2	8 bits	up to 30fps	AAC/MPEG2 L-2	MCM-1000A
DC-VA-H264-10b-30-1080-MA	H.264	up to High	up to 1080i/p	4:2:0/4:2:2	up to 10 bits	up to 30fps	AAC/MPEG2 L-2	MCM-1000A
DC-VA-H264-8b-60-1080-MA	H.264	up to High	up to 1080i/p	4:2:0/4:2:2	8 bits	up to 60fps	AAC/MPEG2 L-2	MCM-1000A
DC-VA-H264-10b-60-1080-MA	H.264	up to High	up to 1080i/p	4:2:0/4:2:2	up to 10 bits	up to 60fps	AAC/MPEG2 L-2	MCM-1000A
DC-VA-H264-8b-30-4k-MZ	H.264	High	4kx2k	4:2:0/4:2:2	8 bits	up to 30fps	AAC/MPEG2 L-2	MCM-1000Z
DC-VA-H264-10b-30-4k-MZ	H.264	High	4kx2k	4:2:0/4:2:2	10 bits	up to 30fps	AAC/MPEG2 L-2	MCM-1000Z
DC-VA-H264-8b-60-4k-MZ	H.264	High	4kx2k	4:2:0/4:2:2	8 bits	up to 60fps	AAC/MPEG2 L-2	MCM-1000Z
DC-VA-H264-10b-60-4k-MZ	H.264	High	4kx2k	4:2:0/4:2:2	10 bits	up to 60fps	AAC/MPEG2 L-2 L	MCM-1000Z

A.4 MPEG-2 Encoder Modules

Table-A7 lists the standard MPEG-2 video encoder modules. Table-A8 lists the MPEG-2 video/audio encoder modules. The 8-bit precision and 60 frames/second modules are offered as extensions of the MPEG-2 standard.

Table-A7: MPEG-2 Video Encoder Module (video only without audio):

Product #	Specifications							Hardware
	Standard	Profile	Resolution	Chroma	Precision	Frame Rate	Audio	
EC-V-MPEG2-8b-30-720-MA	MPEG-2	up to High	up to 720i/p	4:2:0/4:2:2	8 bits	up to 30fps	no	MCM-1000A
EC-V-MPEG2-8b-60-720-MA	MPEG-2	up to High	up to 720i/p	4:2:0/4:2:2	8 bits	up to 60fps	no	MCM-1000A
EC-V-MPEG2-8b-30-1080-MA	MPEG-2	up to High	up to 1080i/p	4:2:0/4:2:2	8 bits	up to 30fps	no	MCM-1000A
EC-V-MPEG2-8b-60-1080-MA	MPEG-2	up to High	up to 1080i/p	4:2:0/4:2:2	8 bits	up to 60fps	no	MCM-1000A

Table-A8: MPEG-2 Video&Audio Encoder Modules (both video and audio):

Product #	Specifications							Hardware
	Standard	Profile	Resolution	Chroma	Precision	Frame Rate	Audio	
EC-VA-MPEG2-8b-30-720-MA	MPEG-2	up to High	up to 720i/p	4:2:0/4:2:2	8 bits	up to 30fps	AAC/MPEG2 L-2	MCM-1000A
EC-VA-MPEG2-8b-60-720-MA	MPEG-2	up to High	up to 720i/p	4:2:0/4:2:2	8 bits	up to 60fps	AAC/MPEG2 L-2	MCM-1000A
EC-VA-MPEG2-8b-30-1080-MA	MPEG-2	up to High	up to 1080i/p	4:2:0/4:2:2	8 bits	up to 30fps	AAC/MPEG2 L-2	MCM-1000A
EC-VA-MPEG2-8b-60-1080-MA	MPEG-2	up to High	up to 1080i/p	4:2:0/4:2:2	8 bits	up to 60fps	AAC/MPEG2 L-2	MCM-1000A

A.8 MPEG2-to-H.264 Transcoder Modules

Table-A15 lists the standard MPEG2-to-H.264 video transcoder modules, and Table-A16 lists the MPEG2-to-H.264 video/audio transcoder modules. The 60frames/second modules are offered as extensions of the MPEG-2 standard.

Table-A15: MPEG2-to-H.264 Video Transcoder Modules (video only without audio):

Product #	Specifications							Hardware
	Standard	Profile	Resolution	Chroma	Precision	Frame Rate	Audio	
TC-V-MPEG2-to-H.264-8b-30-720-MA	MPEG2	High	up to 720i/p	up to 4:2:2	8 bits	up to 30fps	no	MCM-1000A
TC-V-MPEG2-to-H.264-8b-60-720-MA	MPEG2	High	up to 720i/p	up to 4:2:2	8 bits	up to 60fps	no	MCM-1000A
TC-V-MPEG2-to-H.264-8b-30-1080-MA	MPEG2	High	up to 1080i/p	up to 4:2:2	8 bits	up to 30fps	no	MCM-1000A
TC-V-MPEG2-to-H.264-8b-60-1080-MA	MPEG2	High	up to 1080i/p	up to 4:2:2	8 bits	up to 60fps	no	MCM-1000A

Table-A16: MPEG2-to-H.264 Video&Audio Transcoder Modules (both video and audio):

Product #	Specifications							Hardware
	Standard	Profile	Resolution	Chroma	Precision	Frame Rate	Audio	
TC-VA-MPEG2-to-H.264-8b-30-720-MA	MPEG2	High	up to 720i/p	up to 4:2:2	8 bits	up to 30fps	MPEG2-L2/AAC	MCM-1000A
TC-VA-MPEG2-to-H.264-8b-60-720-MA	MPEG2	High	up to 720i/p	up to 4:2:2	8 bits	up to 60fps	MPEG2-L2/AAC	MCM-1000A
TC-VA-MPEG2-to-H.264-8b-30-1080-MA	MPEG2	High	up to 1080i/p	up to 4:2:2	8 bits	up to 30fps	MPEG2-L2/AAC	MCM-1000A
TC-VA-MPEG2-to-H.264-8b-60-1080-MA	MPEG2	High	up to 1080i/p	up to 4:2:2	8 bits	up to 60fps	MPEG2-L2/AAC	MCM-1000A

A.9 Non-Standard Codec Modules

The previous section provides the information on SOC's factory standard MPEG codec modules. Customers can order modules based on customer specific requirements (non-standard modules). There is a Minimum Order Quantity (MOQ) required for customized configurations. Contact SOC sales sale@soctechologies.com for information.

Appendix - C MCM-1000Z Edge Connector Schematics

