



Welcome to E-XFL.COM

What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

Details

Product Status	Obsolete
Core Processor	Z8
Core Size	8-Bit
Speed	8MHz
Connectivity	-
Peripherals	HLVD, POR, WDT
Number of I/O	32
Program Memory Size	32KB (32K x 8)
Program Memory Type	ОТР
EEPROM Size	-
RAM Size	237 x 8
Voltage - Supply (Vcc/Vdd)	2V ~ 5.5V
Data Converters	-
Oscillator Type	Internal
Operating Temperature	-40°C ~ 105°C (TA)
Mounting Type	Through Hole
Package / Case	40-DIP (0.620", 15.75mm)
Supplier Device Package	-
Purchase URL	https://www.e-xfl.com/product-detail/zilog/zgp323hep4032c

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

ZGP323H Product Specification



Figure 34.	SCLK Circuit	58
Figure 35.	Stop Mode Recovery Source	59
Figure 36.	Stop Mode Recovery Register 2 ((0F)DH:D2–D4, D6 Write Only)	61
Figure 37.	Watch-Dog Timer Mode Register (Write Only)	62
Figure 38.	Resets and WDT	63
Figure 39.	TC8 Control Register ((0D)O0H: Read/Write Except Where Noted)	66
Figure 40.	T8 and T16 Common Control Functions ((0D)01H: Read/Write)	67
Figure 41.	T16 Control Register ((0D) 2H: Read/Write Except Where Noted) .	69
Figure 42.	T8/T16 Control Register (0D)03H: Read/Write (Except Where	
	Noted)	70
Figure 43.	Voltage Detection Register	71
Figure 44.	Port Configuration Register (PCON)(0F)00H: Write Only)	72
Figure 45.	Stop Mode Recovery Register ((0F)0BH: D6–D0=Write Only, D7=Read Only)	73
Figure 46.	Stop Mode Recovery Register 2 ((0F)0DH:D2–D4, D6 Write Only)	74
Figure 47.	Watch-Dog Timer Register ((0F) 0FH: Write Only)	75
Figure 48.	Port 2 Mode Register (F6H: Write Only)	75
Figure 49.	Port 3 Mode Register (F7H: Write Only)	76
Figure 50.	Port 0 and 1 Mode Register (F8H: Write Only)	77
Figure 51.	Interrupt Priority Register (F9H: Write Only)	78
Figure 52.	Interrupt Request Register (FAH: Read/Write)	79
Figure 53.	Interrupt Mask Register (FBH: Read/Write)	79
Figure 54.	Flag Register (FCH: Read/Write)	80
Figure 55.	Register Pointer (FDH: Read/Write)	80
Figure 56.	Stack Pointer High (FEH: Read/Write)	81
Figure 57.	Stack Pointer Low (FFH: Read/Write)	81
Figure 58.	20-Pin CDIP Package	82
Figure 59.	20-Pin PDIP Package Diagram	82
Figure 60.	20-Pin SOIC Package Diagram	83
Figure 61.	20-Pin SSOP Package Diagram	84
Figure 62.	28-Pin SOIC Package Diagram	85
Figure 63.	28-Pin CDIP Package Diagram	86
Figure 64.	28-Pin PDIP Package Diagram	86
Figure 65.	28-Pin SSOP Package Diagram	87
Figure 66.	40-Pin PDIP Package Diagram	87
Figure 67.	40-Pin CDIP Package Diagram	88
-		

ZGP323H Product Specification



List of Tables

Table 1.	Revision History of this Document iii
Table 2.	Features
Table 3.	Power Connections 3
Table 4.	20-Pin PDIP/SOIC/SSOP/CDIP* Pin Identification
Table 5.	28-Pin PDIP/SOIC/SSOP/CDIP* Pin Identification
Table 6.	40- and 48-Pin Configuration 8
Table 7.	Absolute Maximum Ratings 10
Table 8.	Capacitance
Table 9.	GP323HS DC Characteristics 11
Table 10.	GP323HE DC Characteristics 12
Table 11.	GP323HA DC Characteristics 14
Table 12.	EPROM/OTP Characteristics 15
Table 13.	AC Characteristics 17
Table 14.	Port 3 Pin Function Summary 23
Table 15.	CTR1(0D)01H T8 and T16 Common Functions
Table 16.	Interrupt Types, Sources, and Vectors
Table 17.	IRQ Register
Table 18.	SMR2(F)0DH:Stop Mode Recovery Register 2* 58
Table 19.	Stop Mode Recovery Source 60
Table 20.	Watch-Dog Timer Time Select 63
Table 21.	EPROM Selectable Options 64



Table 3. Power Connections

Connection	Circuit	Device	
Power	V _{CC}	V _{DD}	
Ground	GND	V _{SS}	



Note: Refer to the specific package for available pins.

Figure 1. Functional Block Diagram



Pin Functions

XTAL1 Crystal 1 (Time-Based Input)

This pin connects a parallel-resonant crystal or ceramic resonator to the on-chip oscillator input. Additionally, an optional external single-phase clock can be coded to the on-chip oscillator input.

XTAL2 Crystal 2 (Time-Based Output)

This pin connects a parallel-resonant crystal or ceramic resonant to the on-chip oscillator output.

Port 0 (P07-P00)

Port 0 is an 8-bit, bidirectional, CMOS-compatible port. These eight I/O lines are configured under software control as a nibble I/O port. The output drivers are push-pull or open-drain controlled by bit D2 in the PCON register.

If one or both nibbles are needed for I/O operation, they must be configured by writing to the Port 0 mode register. After a hardware reset, Port 0 is configured as an input port.

An optional pull-up transistor is available as a mask option on all Port 0 bits with nibble select.

Notes: Internal pull-ups are disabled on any given pin or group of port pins when programmed into output mode.

The Port 0 direction is reset to its default state following an SMR.





Figure 10. Port 1 Configuration

Port 2 (P27-P20)

Port 2 is an 8-bit, bidirectional, CMOS-compatible I/O port (see Figure 11). These eight I/O lines can be independently configured under software control as inputs or outputs. Port 2 is always available for I/O operation. A mask option is available to connect eight pull-up transistors on this port. Bits programmed as outputs are globally programmed as either push-pull or open-drain. The POR resets with the eight bits of Port 2 configured as inputs.

Port 2 also has an 8-bit input OR and AND gate, which can be used to wake up the part. P20 can be programmed to access the edge-detection circuitry in demodulation mode.





Figure 11. Port 2 Configuration

Port 3 (P37–P30)

Port 3 is a 8-bit, CMOS-compatible fixed I/O port (see Figure 12). Port 3 consists of four fixed input (P33–P30) and four fixed output (P37–P34), which can be configured under software control for interrupt and as output from the counter/timers. P30, P31, P32, and P33 are standard CMOS inputs; P34, P35, P36, and P37 are push-pull outputs.







Figure 12. Port 3 Configuration

Two on-board comparators process analog signals on P31 and P32, with reference to the voltage on Pref1 and P33. The analog function is enabled by programming the Port 3 Mode Register (bit 1). P31 and P32 are programmable as rising, falling, or both edge triggered interrupts (IRQ register bits 6 and 7). Pref1 and P33 are the comparator reference voltage inputs. Access to the Counter Timer edgedetection circuit is through P31 or P20 (see "T8 and T16 Common Functions—





	Z8 [®] Standard (Control Registers	Reset Condition
		Expanded Reg. Bank 0/Group 15	** D7 D6 D5 D4 D3 D2 D1 D
			1
		FE SPH	
		FD BP	
	Register Pointer	FC FLAGS	
7	6 5 4 3 2 1 0	FB IMR	
<u> </u>		FA IBO	
Working Register	er Expanded Registr	er F9 IPR	
Group Fointer	Bank Folitier	F8 P01M	
		F7 P3M	
		F6 P2M	
		F5 Reserved	
		F4 Reserved	
		F3 Reserved	
		F2 Reserved	
	Register File (Bank 0)**	F1 Reserved	
FF F0		F0 Reserved	
		Expanded Reg. Bank F/Group 0*	¢
		(F) OF WDTMR	
		(F) 0E Reserved	
		* (F) 0D SMR2	
		(F) 0C Reserved	╢╴┽┼┼┼┼┼┼┼
		↑ (F) 0B SMR	
7F		(F) 0A Reserved	
		(F) 09 Reserved	╢ ╵┥┥┥┥┥┥
		(F) 08 Reserved	╢ ╵┥┥┥┥┥┥
		(F) 07 Reserved	╢╴┼┼┼┼┼┼┼┼
		(F) 06 Reserved	╢ ╵┥┥┥┥┥┥
		(F) 05 Reserved	╢ ╵┥┥┥┥┥┥
OF	L	(F) 04 Reserved	╢╴┼┼┼┼┼┼┼┼
00	۲. E	(F) 03 Reserved	╢╴┼┼┼┼┼┼┼┼
		(F) 02 Reserved	╢ ╵┥┥┥┥┥┥
	$\langle \rangle$	(F) 01 Reserved	╢╴┼┼┼┼┼┼┼┼
Export	nded Rog, Bank O/Group (0)	(F) 00 PCON	
Lapai	nded Reg. Bank 0/Gloup (0)		1
(0) 03 P3	0 U	Expanded Reg. Bank D/Group 0	1
(0) 02 P2		(D) 0C LVD	
	5	* (D) 0B HI8	
* (0) 01 P1	U	* (D) 0A LO8	
(0) 00 P0	U	* (D) 09 HI16	
		* (D) 08 LO16	
U = Unknown		* (D) 07 TC16H	
* Is not reset with a Stop-Mod	le Recovery	* (D) 06 TC16L	
** All addresses are in hexade	cimal	(D) 05 TC8H	
↑ Is not reset with a Stop-Moc	de Recovery, except Bit 0		
↑↑ Bit 5 Is not reset with a Stop	o-Mode Recovery	↑↑↑ (D) 03 CTR3	
TTT Bits 5,4,3,2 not reset with a	a Stop-Mode Recovery		
TITT Bits 5 and 4 not reset with	a Stop-Mode Recovery	(D) 01 CTR1	
IIIII Bits 5,4,3,2,1 not reset with	a stop-Mode Recovery	(D) 00 CTR0	

Figure 15. Expanded Register File Architecture



The upper nibble of the register pointer (see Figure 16) selects which working register group, of 16 bytes in the register file, is accessed out of the possible 256. The lower nibble selects the expanded register file bank and, in the case of the Z8 GP family, banks 0, F, and D are implemented. A OH in the lower nibble allows the normal register file (bank 0) to be addressed. Any other value from 1H to FH exchanges the lower 16 registers to an expanded register bank.





Figure 16. Register Pointer

Example: Z8 GP: (See Figure 15 on page 28)

R253 RP = 00h R0 = Port 0 R1 = Port 1 R2 = Port 2 R3 = Port 3

But if:

R253 RP = 0Dh R0 = CTR0 R1 = CTR1 R2 = CTR2R3 = Reserved



Capture_INT_Mask

Set this bit to allow an interrupt when data is captured into either LO8 or HI8 upon a positive or negative edge detection in demodulation mode.

Counter_INT_Mask

Set this bit to allow an interrupt when T8 has a timeout.

P34_Out

This bit defines whether P34 is used as a normal output pin or the T8 output.

T8 and T16 Common Functions—CTR1(0D)01H

This register controls the functions in common with the T8 and T16.

Table 16 lists and briefly describes the fields for this register.

Field	Bit Position		Value	Description
Mode	7	R/W	0*	Transmit Mode
				Demodulation Mode
P36_Out/	-6	R/W		Transmit Mode
Demodulator_Input			0*	Port Output
			1	T8/T16 Output
				Demodulation Mode
			0*	P31
			1	P20
T8/T16_Logic/	54	R/W		Transmit Mode
Edge _Detect			00**	AND
			01	OR
			10	NOR
			11	NAND
				Demodulation Mode
			00**	Falling Edge
			01	Rising Edge
			10	Both Edges
			11	Reserved

Table 16. CTR1(0D)01H T8 and T16 Common Functions



Table 18. CTR3 (D)03H: T8/T16 Control Register (Continued)

Field	Bit Position		Value	Description
Reserved	43210	R	1	Always reads 11111
		W	x	No Effect

*Indicates the value upon Power-On Reset.

**Indicates the value upon Power-On Reset. Not reset with a Stop Mode recovery.

Counter/Timer Functional Blocks

Input Circuit

The edge detector monitors the input signal on P31 or P20. Based on CTR1 D5– D4, a pulse is generated at the Pos Edge or Neg Edge line when an edge is detected. Glitches in the input signal that have a width less than specified (CTR1 D3, D2) are filtered out (see Figure 18).



Figure 18. Glitch Filter Circuitry

T8 Transmit Mode

Before T8 is enabled, the output of T8 depends on CTR1, D1. If it is 0, T8_OUT is 1; if it is 1, T8_OUT is 0. See Figure 19.



into LO8; if it is a negative edge, data is put into HI8. From that point, one of the edge detect status bits (CTR1, D1; D0) is set, and an interrupt can be generated if enabled (CTR0, D2). Meanwhile, T8 is loaded with FFh and starts counting again. If T8 reaches 0, the timeout status bit (CTR0, D5) is set, and an interrupt can be generated if enabled (CTR0, D1). T8 then continues counting from FFH (see Figure 23 and Figure 24).



Figure 23. Demodulation Mode Count Capture Flowchart



During PING-PONG Mode

The enable bits of T8 and T16 (CTR0, D7; CTR2, D7) are set and cleared alternately by hardware. The timeout bits (CTR0, D5; CTR2, D5) are set every time the counter/timers reach the terminal count.

Interrupts

The ZGP323H features six different interrupts (Table 19). The interrupts are maskable and prioritized (Figure 30). The six sources are divided as follows: three sources are claimed by Port 3 lines P33–P31, two by the counter/timers (Table 19) and one for low voltage detection. The Interrupt Mask Register (globally or individually) enables or disables the six interrupt requests.

The source for IRQ is determined by bit 1 of the Port 3 mode register (P3M). When in digital mode, Pin P33 is the source. When in analog mode the output of the Stop mode recovery source logic is used as the source for the interrupt. See Figure 35, Stop Mode Recovery Source, on page 59.



Name	Source	Vector Location	Comments
IRQ0	P32	0,1	External (P32), Rising, Falling Edge Triggered
IRQ1	P33	2,3	External (P33), Falling Edge Triggered
IRQ2	P31, T _{IN}	4,5	External (P31), Rising, Falling Edge Triggered
IRQ3	T16	6,7	Internal
IRQ4	Т8	8,9	Internal
IRQ5	LVD	10,11	Internal

Table 19. Interrupt Types, Sources, and Vectors

When more than one interrupt is pending, priorities are resolved by a programmable priority encoder controlled by the Interrupt Priority Register. An interrupt machine cycle activates when an interrupt request is granted. As a result, all subsequent interrupts are disabled, and the Program Counter and Status Flags are saved. The cycle then branches to the program memory vector location reserved for that interrupt. All ZGP323H interrupts are vectored through locations in the program memory. This memory location and the next byte contain the 16-bit address of the interrupt service routine for that particular interrupt request. To accommodate polled interrupt systems, interrupt inputs are masked, and the Interrupt Request register is polled to determine which of the interrupt requests require service.

An interrupt resulting from AN1 is mapped into IRQ2, and an interrupt from AN2 is mapped into IRQ0. Interrupts IRQ2 and IRQ0 can be rising, falling, or both edge triggered. These interrupts are programmable by the user. The software can poll to identify the state of the pin.

Programming bits for the Interrupt Edge Select are located in the IRQ Register (R250), bits D7 and D6. The configuration is indicated in Table 20.

IRQ		Interrupt Edge		
D7	D6	IRQ2 (P31)	IRQ0 (P32)	
0	0	F	F	
0	1	F	R	
1	0	R	F	
1	1	R/F	R/F	
Note: F = Falling Edge; R = Rising Edge				

Table 20. IRQ Register



CTR2(0D)02H



Figure 41. T16 Control Register ((0D) 2H: Read/Write Except Where Noted)



WDTMR(0F)0FH



* Default setting after reset. Not reset with a Stop Mode recovery.

Figure 47. Watch-Dog Timer Register ((0F) 0FH: Write Only)

Standard Control Registers

R246 P2M(F6H)



* Default setting after reset. Not reset with a Stop Mode recovery.

Figure 48. Port 2 Mode Register (F6H: Write Only)









Figure 58. 20-Pin CDIP Package





Figure 59. 20-Pin PDIP Package Diagram





CONTROLLING DIMENSIONS : INCH









Figure 62. 28-Pin SOIC Package Diagram





Figure 67. 40-Pin CDIP Package Diagram



Example

