

Welcome to E-XFL.COM

What is "Embedded - Microcontrollers"?

"Embedded - Microcontrollers" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

Applications of "<u>Embedded -</u> <u>Microcontrollers</u>"

Details

•XF

Product Status	Obsolete
Core Processor	PIC
Core Size	16-Bit
Speed	32MHz
Connectivity	I ² C, IrDA, LINbus, SPI, UART/USART
Peripherals	Brown-out Detect/Reset, LVD, POR, PWM, WDT
Number of I/O	24
Program Memory Size	16KB (5.5K x 24)
Program Memory Type	FLASH
EEPROM Size	512 x 8
RAM Size	1K x 8
Voltage - Supply (Vcc/Vdd)	1.8V ~ 3.6V
Data Converters	A/D 19x10b/12b
Oscillator Type	Internal
Operating Temperature	-40°C ~ 125°C (TA)
Mounting Type	Surface Mount
Package / Case	28-VQFN Exposed Pad
Supplier Device Package	28-QFN (6x6)
Purchase URL	https://www.e-xfl.com/product-detail/microchip-technology/pic24f16km102-e-ml

Email: info@E-XFL.COM

Address: Room A, 16/F, Full Win Commercial Centre, 573 Nathan Road, Mongkok, Hong Kong

Table of Contents

1.0	Device Overview	13
2.0	Guidelines for Getting Started with 16-Bit Microcontrollers	29
3.0	CPU	35
4.0	Memory Organization	41
5.0	Flash Program Memory	67
6.0	Data EEPROM Memory	73
7.0	Resets	79
8.0	Interrupt Controller	85
9.0	Oscillator Configuration	. 121
10.0	Power-Saving Features	. 131
11.0	I/O Ports	. 137
12.0	Timer1	. 141
13.0	Capture/Compare/PWM/Timer Modules (MCCP and SCCP)	. 143
14.0	Master Synchronous Serial Port (MSSP)	. 159
15.0	Universal Asynchronous Receiver Transmitter (UART)	. 173
16.0	Real-Time Clock and Calendar (RTCC)	. 181
17.0	Configurable Logic Cell (CLC)	. 195
18.0	High/Low-Voltage Detect (HLVD)	. 207
19.0	12-Bit A/D Converter with Threshold Detect	. 209
20.0	8-Bit Digital-to-Analog Converter (DAC)	. 229
21.0	Dual Operational Amplifier Module	. 233
22.0	Comparator Module	. 235
23.0	Comparator Voltage Reference	. 239
24.0	Charge Time Measurement Unit (CTMU)	. 241
25.0	Special Features	. 249
26.0	Development Support	. 261
27.0	Electrical Characteristics	. 265
28.0	Packaging Information	. 297
Appe	ndix A: Revision History	. 325
Index	· · · · · · · · · · · · · · · · · · ·	327
The M	/icrochip Web Site	. 333
Custo	omer Change Notification Service	. 333
Custo	omer Support	. 333
Produ	uct Identification System	. 335



TABLE 1-5: PIC24FV16KM204 FAMILY PINOUT DESCRIPTION (CONTINUED)

			F					FV					
			Pin Numb	er			I	Pin Numb	er				
Function	20-Pin PDIP/ SSOP/ SOIC	28-Pin PDIP/ SSOP/ SOIC	28-Pin QFN	44-Pin QFN/ TQFP	48-Pin UQFN	20-Pin PDIP/ SSOP/ SOIC	28-Pin PDIP/ SSOP/ SOIC	28-Pin QFN	44-Pin QFN/ TQFP	48-Pin UQFN	I/O	Buffer	Description
RB9	13	18	15	1	1	13	18	15	1	1	I/O	ST	PORTB Pins
RB10	_	21	18	8	9	_	21	18	8	9	I/O	ST	PORTB Pins
RB11	_	22	19	9	10	_	22	19	9	10	I/O	ST	PORTB Pins
RB12	15	23	20	10	11	15	23	20	10	11	I/O	ST	PORTB Pins
RB13	16	24	21	11	12	16	24	21	11	12	I/O	ST	PORTB Pins
RB14	17	25	22	14	15	17	25	22	14	15	I/O	ST	PORTB Pins
RB15	18	26	23	15	16	18	26	23	15	16	I/O	ST	PORTB Pins
RC0	_	_	_	25	27	_	_	—	25	27	I/O	ST	PORTC Pins
RC1	_	_	_	26	28	_	_	—	26	28	I/O	ST	PORTC Pins
RC2	_	_	_	27	29	_	_	—	27	29	I/O	ST	PORTC Pins
RC3			_	36	39	_		—	36	39	I/O	ST	PORTC Pins
RC4			_	37	40	_		—	37	40	I/O	ST	PORTC Pins
RC5			_	38	41	_		—	38	41	I/O	ST	PORTC Pins
RC6			_	2	2	_		_	2	2	I/O	ST	PORTC Pins
RC7			_	3	3	_		_	3	3	I/O	ST	PORTC Pins
RC8			_	4	4	_		_	4	4	I/O	ST	PORTC Pins
RC9	_	_	_	5	5	_	_	—	5	5	I/O	ST	PORTC Pins
REFO	18	26	23	15	16	18	26	23	15	16	0	_	Reference Clock Output
RTCC		25	22	14	15	_	25	22	14	15	0	_	Real-Time Clock/Calendar Output
SCK1	15	22	19	9	10	15	22	19	9	10	I/O	ST	MSSP1 SPI Clock
SDI1	17	21	18	8	9	17	21	18	8	9	I	ST	MSSP1 SPI Data Input
SDO1	16	24	21	11	12	16	24	21	11	12	0	—	MSSP1 SPI Data Output
SS1	18	26	23	15	16	18	26	23	15	16	I	ST	MSSP1 SPI Slave Select Input
SCK2	_	14	11	38	41	—	14	11	38	41	I/O	ST	MSSP2 SPI Clock
SDI2	_	19	16	36	39	_	19	16	36	39	I	ST	MSSP2 SPI Data Input
SDO2	_	15	12	37	40	_	15	12	37	40	0		MSSP2 SPI Data Output
SS2	_	23	20	35	38	_	23	20	35	38	Ι	ST	MSSP2 SPI Slave Select Input

Legend: ANA = Analog level input/output, ST = Schmitt Trigger input buffer, $I^2C^{TM} = I^2C/SMBus$ input buffer

TABLE 4-4: ICN REGISTER MAP

File Name	Addr.	Bit 15	Bit 14	Bit 13	Bit 12	Bit 11	Bit 10	Bit 9	Bit 8	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0	All Resets
CNPD1	56h	CN15PDE ^(1,2)	CN14PDE	CN13PDE	CN12PDE	CN11PDE	CN10PDE(2)	CN9PDE ^(1,2)	-	CN7PDE ^(1,2)	CN6PDE	CN5PDE	CN4PDE	CN3PDE	CN2PDE	CN1PDE	CN0PDE	0000
CNPD2	58h	CN31PDE ⁽²⁾	CN30PDE	CN29PDE	CN28PDE ⁽²⁾	CN27PDE ^(1,2)	CN26PDE ⁽²⁾	CN25PDE ⁽²⁾	CN24PDE ^(1,2)	CN23PDE	CN22PDE	CN21PDE	CN20PDE(2)	CN19PDE ⁽²⁾	CN18PDE ⁽²⁾	CN17PDE ⁽²⁾	CN16PDE ^(1,2)	0000
CNPD3	5Ah	_	_	_	_	_	_	_	_	_	_	_	CN36PDE ⁽²⁾	CN35PDE ⁽²⁾	CN34PDE ⁽²⁾	CN33PDE ⁽²⁾	CN32PDE ⁽²⁾	0000
CNEN1	62h	CN15IE ^(1,2)	CN14IE	CN13IE	CN12IE	CN11IE	CN10IE ⁽²⁾	CN9IE ^(1,2)	_	CN7IE ^(1,2)	CN6IE	CN5IE	CN4IE	CN3IE	CN2IE	CN1IE	CN0IE	0000
CNEN2	64h	CN31IE ⁽²⁾	CN30IE	CN29IE	CN28IE ⁽²⁾	CN27IE ^(1,2)	CN26IE ⁽²⁾	CN25IE ⁽²⁾	CN24IE ^(1,2)	CN23IE	CN22IE	CN21IE	CN20IE ⁽²⁾	CN19IE ⁽²⁾	CN18IE ⁽²⁾	CN17IE ⁽²⁾	CN16IE ^(1,2)	0000
CNEN3	66h	-	_	—	_	_	_	—	—	—	_	_	CN36IE ⁽²⁾	CN35IE ⁽²⁾	CN34IE ⁽²⁾	CN33IE ⁽²⁾	CN32IE ⁽²⁾	0000
CNPU1	6Eh	CN15PUE ^(1,2)	CN14PUE	CN13PUE	CN12PUE	CN11PUE	CN10PUE ⁽²⁾	CN9PUE ^(1,2)	—	CN7PUE ^(1,2)	CN6PUE	CN5PUE	CN4PUE	CN3PUE	CN2PUE	CN1PUE	CN0PUE	0000
CNPU2	70h	CN31PUE ⁽²⁾	CN30PUE	CN29PUE	CN28PUE(2)	CN27PUE ^(1,2)	CN26PUE ⁽²⁾	CN25PUE ⁽²⁾	CN24PUE ^(1,2)	CN23PUE	CN22PUE	CN21PUE	CN20PUE ⁽²⁾	CN19PUE ⁽²⁾	CN18PUE ⁽²⁾	CN17PUE ⁽²⁾	CN16PUE ^(1,2)	0000
CNPU3	72h	_	_	_		_	_	_	_	_	_	_	CN36PUE ⁽²⁾	CN35PUE ⁽²⁾	CN34PUE ⁽²⁾	CN33PUE ⁽²⁾	CN32PUE ⁽²⁾	0000

Legend: x = unknown, u = unchanged, — = unimplemented, q = value depends on condition, r = reserved.

Note 1: These bits are available only on 28-pin devices

2: These bits are available only on 44-pin devices

TABLE 4-21: PORTA REGISTER MAP

File Name	Addr.	Bit 15	Bit 14	Bit 13	Bit 12	Bit 11 ^(4,5)	Bit 10 ^(4,5)	Bit 9 ^(4,5)	Bit 8 ^(4,5)	Bit 7 ⁽⁴⁾	Bit 6 ⁽³⁾	Bit 5 ⁽²⁾	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0	All Resets
TRISA	2C0h	_	—	_	_	TRISA11	TRISA10	TRISA9	TRISA8	TRISA7	TRISA6	_	TRISA4	TRISA3	TRISA2	TRISA1	TRISA0	0FDF ⁽¹⁾
PORTA	2C2h	_	_	_	_	RA11	RA10	RA9	RA8	RA7	RA6	RA5	RA4	RA3	RA2	RA1	RA0	xxxx
LATA	2C4h	_	_	_	_	LATA11	LATA10	LATA9	LATA8	LATA7	LATA6		LATA4	LATA3	LATA2	LATA1	LATA0	xxxx
ODCA	2C6h	_	_	_	-	ODA11	ODA10	ODA9	ODA8	ODA7	ODA6	_	ODA4	ODA3	ODA2	ODA1	ODA0	0000

Legend: x = unknown, u = unchanged, - = unimplemented, q = value depends on condition, r = reserved.

Note 1: Reset value depends on the device type; the PIC24F16KM204 value is shown.

2: These bits are only available when MCLRE (FPOR<7>) = 0.

3: These bits are not implemented in FV devices.

4: These bits are not implemented in 20-pin devices.

5: These bits are not implemented in 28-pin devices.

TABLE 4-22: PORTB REGISTER MAP

File Name	Addr.	Bit 15	Bit 14	Bit 13	Bit 12	Bit 11 ⁽²⁾	Bit 10 ⁽²⁾	Bit 9	Bit 8	Bit 7	Bit 6 ⁽²⁾	Bit 5 ⁽²⁾	Bit 4	Bit 3 ⁽²⁾	Bit 2	Bit 1	Bit 0	All Resets
TRISB	2C8h	TRISB15	TRISB14	TRISB13	TRISB12	TRISB11	TRISB10	TRISB9	TRISB8	TRISB7	TRISB6	TRISB5	TRISB4	TRISB3	TRISB2	TRISB1	TRISB0	_{FFFF} (1)
PORTB	2CAh	RB15	RB14	RB13	RB12	RB11	RB10	RB9	RB8	RB7	RB6	RB5	RB4	RB3	RB2	RB1	RB0	xxxx
LATB	2CCh	LATB15	LATB14	LATB13	LATB12	LATB11	LATB10	LATB9	LATB8	LATB7	LATB6	LATB5	LATB4	LATB3	LATB2	LATB1	LATB0	xxxx
ODCB	2CEh	ODB15	ODB14	ODB13	ODB12	ODB11	ODB10	ODB9	ODB8	ODB7	ODB6	ODB5	ODB4	ODB3	ODB2	ODB1	ODB0	0000

Legend: x = unknown, u = unchanged, - = unimplemented, q = value depends on condition, r = reserved.

Note 1: Reset value depends on the device type; the PIC24F16KM204 value is shown.

2: These bits are not implemented in 20-pin devices.

TABLE 4-23: PORTC REGISTER MAP

File Name	Addr.	Bit 15	Bit 14	Bit 13	Bit 12	Bit 11	Bit 10	Bit 9 ^(2,3)	Bit 8 ^(2,3)	Bit 7 ^(2,3)	Bit 6 ^(2,3)	Bit 5 ^(2,3)	Bit 4 ^(2,3)	Bit 3 ^(2,3)	Bit 2 ^(2,3)	Bit 1 ^(2,3)	Bit 0 ^(2,3)	All Resets
TRISC	2D0h	—	_		_		_	TRISC9	TRISC8	TRISC7	TRISC6	TRISC5	TRISC4	TRISC3	TRISC2	TRISC1	TRISC0	03FF ⁽¹⁾
PORTC	2D2h	_	_	_		—		RC9	RC8	RC7	RC6	RC5	RC4	RC3	RC2	RC1	RC0	xxxx
LATTC	2D4h	_	_	_	_	_	_	LATC9	LATC8	LATC7	LATC6	LATC5	LATC4	LATC3	LATC2	LATC1	LATC0	xxxx
ODCC	2D6h	_	_	_	_	_	_	ODC9	ODC8	ODC7	ODC6	ODC5	ODC4	ODC3	ODC2	ODC1	ODC0	0000

Legend: x = unknown, u = unchanged, — = unimplemented, q = value depends on condition, r = reserved.

Note 1: Reset value depends on the device type; the PIC24F16KM204 value is shown.

2: These bits are not implemented in 20-pin devices.

3: These bits are not implemented in 28-pin devices.

7.4.2 SOFTWARE ENABLED BOR

When BOREN<1:0> = 01, the BOR can be enabled or disabled by the user in software. This is done with the control bit, SBOREN (RCON<13>). Setting SBOREN enables the BOR to function as previously described. Clearing the SBOREN disables the BOR entirely. The SBOREN bit operates only in this mode; otherwise, it is read as '0'.

Placing BOR under software control gives the user the additional flexibility of tailoring the application to its environment without having to reprogram the device to change the BOR configuration. It also allows the user to tailor the incremental current that the BOR consumes. While the BOR current is typically very small, it may have some impact in low-power applications.

Note:	Even when the BOR is under software con-
	trol, the Brown-out Reset voltage level is
	still set by the BORV<1:0> Configuration
	bits; it can not be changed in software.

7.4.3 DETECTING BOR

When BOR is enabled, the BOR bit (RCON<1>) is always reset to '1' on any BOR or POR event. This makes it difficult to determine if a BOR event has occurred just by reading the state of BOR alone. A more reliable method is to simultaneously check the state of both POR and BOR. This assumes that the POR and BOR bits are reset to '0' in the software immediately after any POR event. If the BOR bit is '1' while POR is '0', it can be reliably assumed that a BOR event has occurred.

7.4.4 DISABLING BOR IN SLEEP MODE

When BOREN<1:0> = 10, BOR remains under hardware control and operates as previously described. However, whenever the device enters Sleep mode, BOR is automatically disabled. When the device returns to any other operating mode, BOR is automatically re-enabled.

This mode allows for applications to recover from brown-out situations, while actively executing code, when the device requires BOR protection the most. At the same time, it saves additional power in Sleep mode by eliminating the small incremental BOR current.

Note: BOR levels differ depending on device type; PIC24FV16KM204 devices are at different levels than those of PIC24F16KM204 devices. See Section 27.0 "Electrical Characteristics" for BOR voltage levels.

REGISTER 8-3: INTCON1: INTERRUPT CONTROL REGISTER 1

R/W-0	U-0						
NSTDIS	—	—	—	—	—	—	—
bit 15							bit 8

U-0	U-0	U-0	R/W-0, HS	R/W-0, HS	R/W-0, HS	R/W-0, HS	U-0
—	—	—	MATHERR	ADDRERR	STKERR	OSCFAIL	—
bit 7							bit 0

Legend:		HS = Hardware Settable bi	t	
R = Readabl	e bit	W = Writable bit	U = Unimplemented bit	, read as '0'
-n = Value at	POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown
bit 15	NSTDIS: Inte	errupt Nesting Disable bit		
	1 = Interrupt 0 = Interrupt	nesting is disabled nesting is enabled		
bit 14-5	Unimplemen	nted: Read as '0'		
bit 4	MATHERR: A	Arithmetic Error Trap Status I	bit	
	1 = Overflow 0 = Overflow	trap has occurred trap has not occurred		
bit 3	ADDRERR: /	Address Error Trap Status bit	t	
	1 = Address 0 = Address	error trap has occurred error trap has not occurred		
bit 2	STKERR: Sta	ack Error Trap Status bit		
	1 = Stack erro 0 = Stack erro	or trap has occurred or trap has not occurred		
bit 1	OSCFAIL: O	scillator Failure Trap Status I	bit	
	1 = Oscillator 0 = Oscillator	r failure trap has occurred r failure trap has not occurred	t	
bit 0	Unimplemen	nted: Read as '0'		

REGISTER	8-5: IFS0:	: INTERRUPT	FLAG STAT	US REGISTE	R 0		
R/W-0, HS	U-0	R/W-0, HS	R/W-0, HS	R/W-0, HS	U-0	U-0	R/W-0, HS
NVMIF	_	AD1IF	U1TXIF	U1RXIF			CCT2IF
bit 15							bit 8
R/W-0, HS	R/W-0, HS	R/W-0, HS	U-0	R/W-0, HS	R/W-0, HS	R/W-0, HS	R/W-0, HS
CCT1IF	CCP4IF	CCP3IF	—	T1IF	CCP2IF	CCP1IF	INT0IF
bit 7	•						bit 0
Legend:		HS = Hardwar	e Settable bit				
R = Readable	e bit	W = Writable b	bit	U = Unimplen	nented bit, read	d as '0'	
-n = Value at	POR	'1' = Bit is set		'0' = Bit is clea	ared	x = Bit is unkr	IOWN
bit 15	NVMIF: NVM	/I Interrupt Flag §	Status bit				
	1 = Interrupt	request has occ	urred				
	0 = Interrupt	request has not	occurred				
bit 14	Unimplemer	nted: Read as '0	3				
bit 13	AD1IF: A/D (Conversion Com	plete Interrupt	t Flag Status bit	t		
	1 = Interrupt	request has occ	urred				
hit 10		PT1 Transmitter	Interrupt Elec	Statua bit			
DIL 12	1 = Interrupt		urred	Status bit			
	0 = Interrupt	request has not	occurred				
bit 11	U1RXIF: UA	RT1 Receiver In	terrupt Flag St	tatus bit			
	1 = Interrupt	request has occ	urred				
	0 = Interrupt	request has not	occurred				
bit 10-9	Unimplemer	nted: Read as '0	3				
bit 8	CCT2IF: Cap	oture/Compare 2	Timer Interru	pt Flag Status b	bit		
	1 = Interrupt	request has occ	urred				
hit 7		request has not	Timor Interru	nt Elaa Status k	sit		
	1 = Interrupt	request has occ		pi Flay Status i	JIL		
	0 = Interrupt	request has not	occurred				
bit 6	CCP4IF: Cap	pture/Compare 4	Event Interru	pt Flag Status I	oit		
	1 = Interrupt	request has occ	urred				
	0 = Interrupt	request has not	occurred				
bit 5	CCP3IF: Cap	pture/Compare 3	Event Interru	pt Flag Status b	oit		
	1 = Interrupt	request has occ	urred .				
L:1 4	0 = Interrupt	request has not	occurred				
DIT 4		nted: Read as 10	tatua hit				
DIL 3	1 - Interrupt	request has ees	urrod				
	1 = Interrupt 0 = Interrupt	request has not	occurred				
bit 2	CCP2IF: Car	pture/Compare 2	Event Interru	pt Flag Status b	oit		
	1 = Interrupt	request has occ	urred				
	0 = Interrupt	request has not	occurred				
bit 1	CCP1IF: Cap	pture/Compare 1	Event Interru	pt Flag Status b	oit		
	1 = Interrupt	request has occ	urred				
1.11.0	0 = Interrupt	request has not					
DIT U	IN I UIF: Exte	rnal Interrupt 0 F	-lag Status bit				
	\perp = interrupt 0 = Interrupt	request has occ request has not	urrea occurred				

REGISTER 9-1: OSCCON: OSCILLATOR CONTROL REGISTER (CONTINUED)

bit 7	CLKLOCK: Clock Selection Lock Enable bit <u>If FSCM is Enabled (FCKSM1 = 1):</u> 1 = Clock and PLL selections are locked 0 = Clock and PLL selections are not locked and may be modified by setting the OSWEN bit <u>If FSCM is Disabled (FCKSM1 = 0):</u> Clock and PLL selections are never locked and may be modified by setting the OSWEN bit.
bit 6	Unimplemented: Read as '0'
bit 5	LOCK: PLL Lock Status bit ⁽²⁾
	 1 = PLL module is in lock or PLL module start-up timer is satisfied 0 = PLL module is out of lock, PLL start-up timer is running or PLL is disabled
bit 4	Unimplemented: Read as '0'
bit 3	CF: Clock Fail Detect bit
	 1 = FSCM has detected a clock failure 0 = No clock failure has been detected
bit 2	SOSCDRV: Secondary Oscillator Drive Strength bit ⁽³⁾
	 1 = High-power SOSC circuit is selected 0 = Low/high-power select is done via the SOSCSRC Configuration bit
bit 1	SOSCEN: 32 kHz Secondary Oscillator (SOSC) Enable bit
	1 = Enables the Secondary Oscillator0 = Disables the Secondary Oscillator
bit 0	OSWEN: Oscillator Switch Enable bit
	 1 = Initiates an oscillator switch to the clock source specified by the NOSC<2:0> bits 0 = Oscillator switch is complete
Note 1:	Reset values for these bits are determined by the FNOSCx Configuration bits.

- 2: This bit also resets to '0' during any valid clock switch or whenever a non-PLL Clock mode is selected.
- **3:** When SOSC is selected to run from a digital clock input, rather than an external crystal (SOSCSRC = 0), this bit has no effect.

REGISTER 16-1: RCFGCAL: RTCC CALIBRATION AND CONFIGURATION REGISTER⁽¹⁾ (CONTINUED)

- **Note 1:** The RCFGCAL register is only affected by a POR.
 - 2: A write to the RTCEN bit is only allowed when RTCWREN = 1.
 - 3: This bit is read-only; it is cleared to '0' on a write to the lower half of the MINSEC register.

REGISTER 10-2: RICPWC: RICC CONFIGURATION REGISTER 2	GISTER 16-2:	RTCPWC: RTCC CONFIGURATION REGISTER 2 ⁽¹⁾
--	--------------	--

R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0				
PWCEN	PWCPOL	PWCCPRE	PWCSPRE	RTCCLK1 ⁽²⁾	RTCCLK0 ⁽²⁾	RTCOUT1	RTCOUT0				
bit 15							bit 8				
U-0	U-0	U-0	U-0	U-0	U-0	U-0	U-0				
—	—	—	—	—		—	—				
bit 7							bit 0				
Legend:											
R = Reada	ble bit	W = Writable	bit	U = Unimpleme	nted bit, read as	'0'					
-n = Value	at POR	'1' = Bit is set		'0' = Bit is cleare	ed	x = Bit is unkr	nown				
bit 15	PWCEN: Po	wer Control Er	able bit								
	1 = Power control is enabled										
	0 = Power control is disabled										
bit 14	PWCPOL: Power Control Polarity bit										
	1 = Power co	ontrol output is	active-high								
	0 = Power co	ontrol output is	active-low								
bit 13	PWCCPRE:	Power Control	Stability Pres	caler bits							
	1 = PWC sta	ability window c	lock is divide-l	by-2 of source R	I CC clock						
hit 12		Power Control		calor bits	I OO CIOCK						
	1 = PWC sat	mple window c	lock is divide-t	ov-2 of source R	FCC clock						
	0 = PWC sa	mple window c	lock is divide l	by 2 of source R	FCC clock						
bit 11-10	RTCCLK<1:	:0>: RTCC Clo	ck Select bits ⁽²	2)							
	Determines	the source of th	ne internal RT	CC clock, which i	s used for all RT	CC timer opera	tions.				
	00 = Externa	al Secondary C	scillator (SOS	C)		-					
	01 = Interna	I LPRC Oscilla	tor								
	10 = External	al power line so	Purce = 50 Hz								
hit 9-8		.0>. BICC Out	nut Select hits								
	Determines	the source of the	ne RTCC nin o	, putput							
	00 = RTCC :	alarm pulse									
	01 = RTCC :	seconds clock									
	10 = RTCC	clock									
hit 7-0		nted: Road an	' ∩'								
	onimpienie	meu. Reau as	U								
Note 1:	The RTCPWC	register is only	affected by a	POR.							

2: When a new value is written to these register bits, the Seconds Value register should also be written to properly reset the clock prescalers in the RTCC.



REGISTER 17-4: CLCxGLSL: CLCx GATE LOGIC INPUT SELECT LOW REGISTER (CONTINUED)

bit 3	G1D2T: Gate 1 Data Source 2 True Enable bit
	1 = The Data Source 2 inverted signal is enabled for Gate 1
bit 2	G1D2N: Gate 1 Data Source 2 Negated Enable bit
	1 = The Data Source 2 inverted signal is enabled for Gate 1
	0 = The Data Source 2 inverted signal is disabled for Gate 1
bit 1	G1D1T: Gate 1 Data Source 1 True Enable bit
	1 = The Data Source 1 inverted signal is enabled for Gate 1
	0 = The Data Source 1 inverted signal is disabled for Gate 1
bit 0	G1D1N: Gate 1 Data Source 1 Negated Enable bit
	1 = The Data Source 1 inverted signal is enabled for Gate 1
	0 = The Data Source 1 inverted signal is disabled for Gate 1

19.4 Buffer Data Formats

The A/D conversions are fully differential 12-bit values when MODE12 = 1 (AD1CON1<10>) and 10-bit values when MODE12 = 0. When absolute fractional or absolute integer formats are used, the results are 12 or 10 bits wide, respectively. When signed decimal formatting is used, the conversion also includes a Sign bit, making 12-bit conversions 13 bits wide and 10-bit conversions 11 bits wide. The signed decimal format yields 12-bit and 10-bit values, respectively. The Sign bit (bit 12 or bit 10) is sign-extended to fill the buffer. The FORM<1:0> bits (AD1CON1<9:8>) select the format. Figure 19-4 and Figure 19-5 show the data output formats that can be selected. Table 19-1 through Table 19-4 show the numerical equivalents for the various conversion result codes.

FIGURE 19-4: A/D OUTPUT DATA FORMATS (12-BIT)

RAM Contents:					d11	d10	d09	d08	d07	d06	d05	d04	d03	d02	d01	d00
Read to Bus:																
Integer	0	0	0	0	d11	d10	d09	d08	d07	d06	d05	d04	d03	d02	d01	d00
					r										r	1
Signed Integer	s0	s0	s0	s0	d11	d10	d09	d08	d07	d06	d05	d04	d03	d02	d01	d00
Fractional (1.15)	d11	d10	d09	d08	d07	d06	d05	d04	d03	d02	d01	d00	0	0	0	0
Signed Fractional (1.15)	s0	d11	d10	d09	d08	d07	d06	d05	d04	d03	d02	d01	d00	0	0	0

TABLE 19-1:NUMERICAL EQUIVALENTS OF VARIOUS RESULT CODES:
12-BIT INTEGER FORMATS

VIN/VREF	12-Bit Differential Output Code (13-bit result)	16-Bit Integer Format/ Equivalent Decimal Value	16-Bit Signed Integer Form Equivalent Decimal Valu	nat/ e						
+4095/4096	0 1111 1111 1111	0000 1111 1111 1111	+4095	0000 1111 1111 1111	+4095					
+4094/4096	0 1111 1111 1110	0000 1111 1111 1110	+4094	0000 1111 1111 1110	+4094					
•••										
+1/4096	0 1000 0000 0001	0000 0000 0000 0001	+1	0000 0000 0000 0001	+1					
0/4096	0 0000 0000 0000	0000 0000 0000 0000	0	0000 0000 0000 0000	0					
-1/4096	1 0111 1111 1111	0000 0000 0000 0000	0	1111 1111 1111 1111	-1					
• • •										
-4095/4096	1 0000 0000 0001	0000 0000 0000 0000	0	1111 0000 0000 0001	-4095					
-4096/4096	1 0000 0000 0000	0000 0000 0000 0000	0	1111 0000 0000 0000	-4096					

NOTES:

R/W-0	U-0	R/W-0	R/W-0	R/W-0	U-0	R/W-0	R/W-0					
DACEN		DACSIDL	DACSLP	DACFM	—	SRDIS	DACTRIG					
bit 15							bit 8					
R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0					
DACOE	DACTSEL4	DACTSEL3	DACTSEL2	DACTSEL1	DACTSEL0	DACREF1	DACREF0					
bit 7 bit												
												
Legend:												
R = Readable	e bit	W = Writable	bit	U = Unimplem	nented bit, read	l as '0'						
-n = Value at	POR	'1' = Bit is set		'0' = Bit is clea	ared	x = Bit is unkr	nown					
bit 15	DACEN: DAC	Cx Enable bit										
	1 = Module is enabled											
hit 14	Unimplemented: Read as '0'											
bit 13	DACSIDI - DACY Stop in Idlo Modo bit											
bit 10	1 = Discontin	ues module op	eration when o	device enters Id	lle mode							
	0 = Continue	s module opera	ation in Idle mo	de								
bit 12	DACSLP: DA	Cx Enable Per	ipheral During	Sleep bit								
	1 = DACx co	ntinues to outp	ut the most rec	ent value of DA	ACxDAT during	Sleep mode						
	0 = DACx is j	powered down	in Sleep mode	; DACxOUT pir	n is controlled b	by the TRISx a	nd LATx bits					
bit 11	DACFM: DAC	Cx Data Format	Select bit									
	1 = Data is let0 = Data is ric	t justified (data the justified (dat	stored in DAC	(xDAT<15:8>) (xDAT<7:0>)								
bit 10	Unimplement	ted: Read as ')'									
bit 9	SRDIS: Soft F	Reset Disable b	pit									
2.1.0	1 = DACxCO	N and DACxD	AT SFRs reset	only on a POR	or BOR Reset							
	0 = DACxCO	N and DACxD/	AT SFRs reset	on any type of	device Reset							
bit 8	DACTRIG: D	ACx Trigger Inp	out Enable bit									
	1 = Analog o	utput value upd	lates when the	selected (by D	ACTSEL<4:0>) event occurs						
	0 = Analog o	utput value upo	lates as soon a	as DACxDAT is	written (DAC 1	rigger is ignor	ed)					
bit 7	DACOE: DAC	Cx Output Enab	le bit									
	1 = DACx out	put pin is enabl	led and driven	on the DACXO	UT PIN	har narinharale	only					
							, only					

REGISTER 20-1: DACxCON: DACx CONTROL REGISTER

Note 1: BGBUF1 voltage is configured by BUFREF<1:0> (BUFCON0<1:0>).

25.2 On-Chip Voltage Regulator

All of the PIC24FXXXXX family devices power their core digital logic at a nominal 3.0V. This may create an issue for designs that are required to operate at a higher typical voltage, as high as 5.0V. To simplify system design, all devices in the "FV" family incorporate an on-chip regulator that allows the device core to run at 3.0V, while the I/O is powered by VDD at a higher voltage.

The regulator is always enabled and provides power to the core from the other VDD pins. A low-ESR capacitor (such as ceramic) must be connected to the VCAP pin (Figure 25-1). This helps to maintain the stability of the regulator. The recommended value for the filter capacitor is provided in Section 27.1 "DC Characteristics" and discussed in detail in Section 2.0 "Guidelines for Getting Started with 16-Bit Microcontrollers".

In all of the "F" family of devices, the regulator is disabled. Instead, the core logic is directly powered from VDD. "F" devices operate at a lower range of VDD voltage, from 1.8V-3.6V.

25.2.1 VOLTAGE REGULATOR TRACKING MODE AND LOW-VOLTAGE DETECTION

For all PIC24FXXXXX devices, the on-chip regulator provides a constant voltage of 3.0V nominal to the digital core logic. The regulator can provide this level from a VDD of about 3.2V, all the way up to the device's VDDMAX. It does not have the capability to boost VDD levels below 3.2V. In order to prevent "brown out" conditions when the voltage drops too low for the regulator, the regulator enters Tracking mode. In Tracking mode, the regulator output follows VDD with a typical voltage drop of 150 mV.

When the device enters Tracking mode, it is no longer possible to operate at full speed. To provide information about when the device enters Tracking mode, the on-chip High/Low-Voltage Detect (HLVD) module can be used. The HLVD trip point should be configured so that if VDD drops close to the minimum voltage for the operating frequency of the device, the HLVD Interrupt Flag, HLVDIF (IFS4<8>), will occur. This can be used to generate an interrupt and put the application into a low-power operational mode or trigger an orderly shutdown. Refer to **Section 27.1 "DC Characteristics"** for the specifications detailing the maximum operating speed based on the applied VDD voltage.

FIGURE 25-1:

CONNECTIONS FOR THE ON-CHIP VOLTAGE REGULATOR



25.2.2 VOLTAGE REGULATOR START-UP TIME

For PIC24FXXXXX family devices, it takes a short time, designated as TPM, for the regulator to generate a stable output. During this time, code execution is disabled. TPM is applied every time the device resumes operation after any power-down, including Sleep mode. TPM is specified in Section 27.2 "AC Characteristics and Timing Parameters".

25.3 Watchdog Timer (WDT)

For the PIC24FXXXXX family of devices, the WDT is driven by the LPRC Oscillator. When the WDT is enabled, the clock source is also enabled.

The nominal WDT clock source from LPRC is 31 kHz. This feeds a prescaler that can be configured for either 5-bit (divide-by-32) or 7-bit (divide-by-128) operation. The prescaler is set by the FWPSA Configuration bit. With a 31 kHz input, the prescaler yields a nominal WDT Time-out period (TWDT) of 1 ms in 5-bit mode or 4 ms in 7-bit mode.

A variable postscaler divides down the WDT prescaler output and allows for a wide range of time-out periods. The postscaler is controlled by the Configuration bits, WDTPS<3:0> (FWDT<3:0>), which allow the selection of a total of 16 settings, from 1:1 to 1:32,768. Using the prescaler and postscaler time-out periods, ranges from 1 ms to 131 seconds can be achieved.

TABLE 27-1: THERMAL OPERATING CONDITIONS

Rating	Symbol	Min	Тур	Max	Unit
Operating Junction Temperature Range	TJ	-40	—	+140	°C
Operating Ambient Temperature Range	TA	-40	—	+125	°C
$\begin{array}{l} \mbox{Power Dissipation} \\ \mbox{Internal Chip Power Dissipation:} \\ \mbox{PINT} = \mbox{VDD } x \ (\mbox{IDD} - \Sigma \ \mbox{IOH}) \\ \mbox{I/O Pin Power Dissipation:} \\ \mbox{PI/O} = \Sigma \ (\{\mbox{VDD} - \mbox{VOH} \} \ x \ \mbox{IOH}) + \Sigma \ (\mbox{VOL } x \ \mbox{IOL}) \end{array}$	PD		Pint + Pi/c)	W
Maximum Allowed Power Dissipation	PDMAX	(Tj — Τα)/θja			W

TABLE 27-2: THERMAL PACKAGING CHARACTERISTICS

Characteristic	Symbol	Тур	Max	Unit	Notes
Package Thermal Resistance, 20-Pin PDIP	θJA	62.4	—	°C/W	1
Package Thermal Resistance, 28-Pin SPDIP	θJA	60		°C/W	1
Package Thermal Resistance, 20-Pin SSOP	θJA	108		°C/W	1
Package Thermal Resistance, 28-Pin SSOP	θJA	71		°C/W	1
Package Thermal Resistance, 20-Pin SOIC	θJA	75		°C/W	1
Package Thermal Resistance, 28-Pin SOIC	θJA	80.2		°C/W	1
Package Thermal Resistance, 20-Pin QFN	θJA	43		°C/W	1
Package Thermal Resistance, 28-Pin QFN	θJA	32		°C/W	1
Package Thermal Resistance, 44-Pin QFN	θJA	29		°C/W	1
Package Thermal Resistance, 44-Pin TQFP	θJA	40		°C/W	1
Package Thermal Resistance, 48-Pin UQFN	θJA	41	—	°C/W	1

Note 1: Junction to ambient thermal resistance, Theta-JA (θ JA) numbers are achieved by package simulations.

TABLE 27-3: DC CHARACTERISTICS: TEMPERATURE AND VOLTAGE SPECIFICATIONS

DC CHA		Standar Operatin	d Operat	t ing Co trature	ondition	s: 1.8V to 3.6V (PIC24F16KMXXX) 2.0V to 5.5V (PIC24FV16KMXXX) $-40^{\circ}C \le TA \le +85^{\circ}C$ for Industrial $-40^{\circ}C \le TA \le +125^{\circ}C$ for Extended	
Param No.	Symbol	Characteristic	Min	Typ ⁽¹⁾	Max	Units	Conditions
DC10	Vdd	Supply Voltage	1.8	—	3.6	V	For PIC24F devices
			2.0		5.5	V	For PIC24FV devices
DC12	Vdr	RAM Data Retention	1.6		—	V	For PIC24F devices
		Voltage ⁽²⁾	1.8		_	V	For PIC24FV devices
DC16	VPOR	VDD Start Voltage to Ensure Internal Power-on Reset Signal	Vss	_	0.7	V	
DC17	SVDD	VDD Rise Rate to Ensure Internal Power-on Reset Signal	0.05	_		V/ms	0-3.3V in 0.1s 0-2.5V in 60 ms

Note 1: Data in "Typ" column is at 3.3V, +25°C unless otherwise stated. Parameters are for design guidance only and are not tested.

2: This is the limit to which VDD can be lowered without losing RAM data.

DC CH	ARACTE	RISTICS	$ \begin{array}{llllllllllllllllllllllllllllllllllll$						
Param No.	Sym	Characteristic	Min Typ ⁽¹⁾ Max Units Condi			litions			
	Vol	Output Low Voltage							
DO10		All I/O Pins	—	—	0.4	V	IOL = 8.0 mA	VDD = 4.5V	
			_	—	0.4	V	IOL = 4.0 mA	VDD = 3.6V	
			—	—	0.4	V	IOL = 3.5 mA	VDD = 2.0V	
DO16		OSC2/CLKO	_	—	0.4	V	IOL = 2.0 mA	VDD = 4.5V	
			_	—	0.4	V	IOL = 1.2 mA	VDD = 3.6V	
			—	—	0.4	V	IOL = 0.4 mA	VDD = 2.0V	
	Vон	Output High Voltage							
DO20		All I/O Pins	3.8	—	—	V	Iон = -3.5 mA	VDD = 4.5V	
			3	—	—	V	Iон = -3.0 mA	VDD = 3.6V	
			1.6	_	—	V	Іон = -1.0 mA	VDD = 2.0V	
DO26		OSC2/CLKO	3.8	—	—	V	Іон = -2.0 mA	VDD = 4.5V	
			3	—	—	V	Іон = -1.0 mA	VDD = 3.6V	
			1.6	_	_	V	Іон = -0.5 mA	VDD = 2.0V	

TABLE 27-10: DC CHARACTERISTICS: I/O PIN OUTPUT SPECIFICATIONS

Note 1: Data in "Typ" column is at 3.3V, +25°C unless otherwise stated. Parameters are for design guidance only and are not tested.

TABLE 27-11: DC CHARACTERISTICS: PROGRAM MEMORY

DC CHA	ARACTE	ERISTICS	Standard Operating	Operatin tempera	g Conditi ture	ons: 1.8 2.0 -40 -40	3V to 3.6V (PIC24F16KM204))V to 5.5V (PIC24FV16KM204) $0^{\circ}C \le TA \le +85^{\circ}C$ for Industrial $0^{\circ}C \le TA \le +125^{\circ}C$ for Extended		
Param No.	Sym	Characteristic	Min	Typ ⁽¹⁾	Max	Units	Conditions		
		Program Flash Memory							
D130	Ер	Cell Endurance	10,000 ⁽²⁾	_	—	E/W			
D131	Vpr	VDD for Read	VMIN	_	3.6	V	VMIN = Minimum operating voltage		
D133A	Tiw	Self-Timed Write Cycle Time	—	2	—	ms			
D134	Tretd	Characteristic Retention	40	_	—	Year	Provided no other specifications are violated		
D135	IDDP	Supply Current During Programming	—	10	—	mA			

Note 1: Data in "Typ" column is at 3.3V, +25°C unless otherwise stated.

2: Self-write and block erase.

20-Lead Plastic Small Outline (SO) - Wide, 7.50 mm Body [SOIC]

Note: For the most current package drawings, please see the Microchip Packaging Specification located at http://www.microchip.com/packaging



RECOMMENDED LAND PATTERN

Units		MILLIMETERS		
Dimension Limits		MIN	NOM	MAX
Contact Pitch	E	1.27 BSC		
Contact Pad Spacing	С		9.40	
Contact Pad Width (X20)	X			0.60
Contact Pad Length (X20)	Y			1.95
Distance Between Pads	Gx	0.67		
Distance Between Pads	G	7.45		

Notes:

1. Dimensioning and tolerancing per ASME Y14.5M

BSC: Basic Dimension. Theoretically exact value shown without tolerances.

Microchip Technology Drawing No. C04-2094A