Welcome to E-XFL.COM

Understanding Embedded - FPGAs (Field Programmable Gate Array)

Embedded - FPGAs, or Field Programmable Gate Arrays, are advanced integrated circuits that offer unparalleled flexibility and performance for digital systems. Unlike traditional fixed-function logic devices, FPGAs can be programmed and reprogrammed to execute a wide array of logical operations, enabling customized functionality tailored to specific applications. This reprogrammability allows developers to iterate designs quickly and implement complex functions without the need for custom hardware.

Applications of Embedded - FPGAs

The versatility of Embedded - FPGAs makes them indispensable in numerous fields. In telecommunications.

Details	
Product Status	Active
Number of LABs/CLBs	2475
Number of Logic Elements/Cells	39600
Total RAM Bits	1161216
Number of I/O	328
Number of Gates	-
Voltage - Supply	0.97V ~ 1.03V
Mounting Type	Surface Mount
Operating Temperature	0°C ~ 85°C (TJ)
Package / Case	484-BGA
Supplier Device Package	484-FBGA (23x23)
Purchase URL	https://www.e-xfl.com/product-detail/intel/ep4ce40f23c9l

Manual Clock Switchover 5–30
Guidelines 5–30
Programmable Bandwidth 5–32
Phase Shift Implementation 5–32
PLL Cascading 5–33
PLL Reconfiguration 5–34
PLL Reconfiguration Hardware Implementation 5–34
Post-Scale Counters (C0 to C4) 5–36
Scan Chain Description 5–37
Charge Pump and Loop Filter 5–38
Bypassing a PLL Counter 5–39
Dynamic Phase Shifting 5–39
Spread-Spectrum Clocking 5–41
PLL Specifications 5–41
Document Revision History 5–42

Section II. I/O Interfaces

Chapter 6. I/O Features in Cyclone IV Devices

Cyclone IV I/O Elements 6–2
I/O Element Features 6–3
Programmable Current Strength 6–3
Slew Rate Control 6–4
Open-Drain Output 6–4
Bus Hold 6–4
Programmable Pull-Up Resistor 6–5
Programmable Delay 6–5
PCI-Clamp Diode 6–6
OCT Support 6–6
On-Chip Series Termination with Calibration 6–8
On-Chip Series Termination Without Calibration 6–10
I/O Standards 6–11
Termination Scheme for I/O Standards 6–13
Voltage-Referenced I/O Standard Termination 6–14
Differential I/O Standard Termination 6–15
I/O Banks 6–16
High-Speed Differential Interfaces 6–22
External Memory Interfacing 6–23
Pad Placement and DC Guidelines 6–23
Pad Placement 6–23
DC Guidelines 6–23
Clock Pins Functionality 6–23
High-Speed I/O Interface 6–24
High-Speed I/O Standards Support 6–28
High Speed Serial Interface (HSSI) Input Reference Clock Support 6–28
LVDS I/O Standard Support in Cyclone IV Devices 6–29
Designing with LVDS 6–30
BLVDS I/O Standard Support in Cyclone IV Devices 6–30
Designing with BLVDS 6–31
RSDS, Mini-LVDS, and PPDS I/O Standard Support in Cyclone IV Devices 6–32
Designing with RSDS, Mini-LVDS, and PPDS 6–32
LVPECL I/O Support in Cyclone IV Devices 6–34
Differential SSTL I/O Standard Support in Cyclone IV Devices 6–35

Cyclone IV Device Family Architecture

This section describes Cyclone IV device architecture and contains the following topics:

- "FPGA Core Fabric"
- "I/O Features"
- "Clock Management"
- "External Memory Interfaces"
- "Configuration"
- "High-Speed Transceivers (Cyclone IV GX Devices Only)"
- "Hard IP for PCI Express (Cyclone IV GX Devices Only)"

FPGA Core Fabric

Cyclone IV devices leverage the same core fabric as the very successful Cyclone series devices. The fabric consists of LEs, made of 4-input look up tables (LUTs), memory blocks, and multipliers.

Each Cyclone IV device M9K memory block provides 9 Kbits of embedded SRAM memory. You can configure the M9K blocks as single port, simple dual port, or true dual port RAM, as well as FIFO buffers or ROM. They can also be configured to implement any of the data widths in Table 1–7.

Table 1–7. M9K Block Data Widths for Cyclone IV Device Family

Mode	Data Width Configurations
Single port or simple dual port	×1, ×2, ×4, ×8/9, ×16/18, and ×32/36
True dual port	×1, ×2, ×4, ×8/9, and ×16/18

The multiplier architecture in Cyclone IV devices is the same as in the existing Cyclone series devices. The embedded multiplier blocks can implement an 18 × 18 or two 9 × 9 multipliers in a single block. Altera offers a complete suite of DSP IP including finite impulse response (FIR), fast Fourier transform (FFT), and numerically controlled oscillator (NCO) functions for use with the multiplier blocks. The Quartus® II design software's DSP Builder tool integrates MathWorks Simulink and MATLAB design environments for a streamlined DSP design flow.

For more information, refer to the *Logic Elements and Logic Array Blocks in Cyclone IV Devices*, *Memory Blocks in Cyclone IV Devices*, and *Embedded Multipliers in Cyclone IV Devices* chapters.