




Welcome to [E-XFL.COM](https://www.e-xfl.com)

### What is "[Embedded - Microcontrollers](#)"?

"[Embedded - Microcontrollers](#)" refer to small, integrated circuits designed to perform specific tasks within larger systems. These microcontrollers are essentially compact computers on a single chip, containing a processor core, memory, and programmable input/output peripherals. They are called "embedded" because they are embedded within electronic devices to control various functions, rather than serving as standalone computers. Microcontrollers are crucial in modern electronics, providing the intelligence and control needed for a wide range of applications.

### Applications of "[Embedded - Microcontrollers](#)"

#### Details

|                            |                                                                                                                                                                     |
|----------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Product Status             | Active                                                                                                                                                              |
| Core Processor             | PIC                                                                                                                                                                 |
| Core Size                  | 8-Bit                                                                                                                                                               |
| Speed                      | 32MHz                                                                                                                                                               |
| Connectivity               | I <sup>2</sup> C, LINbus, SPI, UART/USART                                                                                                                           |
| Peripherals                | Brown-out Detect/Reset, POR, PWM, WDT                                                                                                                               |
| Number of I/O              | 25                                                                                                                                                                  |
| Program Memory Size        | 7KB (4K x 14)                                                                                                                                                       |
| Program Memory Type        | FLASH                                                                                                                                                               |
| EEPROM Size                | -                                                                                                                                                                   |
| RAM Size                   | 512 x 8                                                                                                                                                             |
| Voltage - Supply (Vcc/Vdd) | 2.3V ~ 5.5V                                                                                                                                                         |
| Data Converters            | A/D 24x10b; D/A 1x5b                                                                                                                                                |
| Oscillator Type            | Internal                                                                                                                                                            |
| Operating Temperature      | -40°C ~ 85°C (TA)                                                                                                                                                   |
| Mounting Type              | Surface Mount                                                                                                                                                       |
| Package / Case             | 28-UFQFN Exposed Pad                                                                                                                                                |
| Supplier Device Package    | 28-UQFN (4x4)                                                                                                                                                       |
| Purchase URL               | <a href="https://www.e-xfl.com/product-detail/microchip-technology/pic16f15354-i-mv">https://www.e-xfl.com/product-detail/microchip-technology/pic16f15354-i-mv</a> |

# PIC16(L)F153XX

---

- Communication:
  - Up to two EUSART, RS-232, RS-485, LIN compatible
  - Up to two SPI
  - Two I<sup>2</sup>C, SMBus, PMBus™ compatible
- Up to 44 I/O Pins
  - Individually programmable pull-ups slew rate control Interrupt-on-Change with edge-select

## Analog Peripherals

- Analog-to-Digital Converter (ADC):
  - 10-bit with up to 43 external channels
  - Conversion available during Sleep
- Two Comparator:
  - Low-Power/High-Speed mode
  - Fixed Voltage Reference at (non)inverting input(s)
  - Comparator outputs externally accessible
- 5-Bit Digital-to-Analog Converter (DAC):
  - 5-bit resolution, rail-to-rail
  - Positive Reference Selection
  - Unbuffered I/O pin output
  - Internal connections to ADCs and comparators
- Voltage Reference:
  - Fixed Voltage Reference with 1.024V, 2.048V and 4.096V output level

## Flexible Oscillator Structure

- High-Precision Internal Oscillator:
  - Selectable frequency range up to 32 MHz
  - $\pm 1\%$  at calibration (nominal)
- x2/x4 PLL with Internal and External Sources
- Low-Power Internal 32 kHz Oscillator (LFINTOSC)
- External 32 kHz Crystal Oscillator (SOCS)
- External Oscillator Block with:
  - Three crystal/resonator modes up to 20 MHz
  - Three external clock modes up to 20 MHz
  - Fail-Safe Clock Monitor
  - Allows for safe shutdown if peripherals clock stops
  - Oscillator Start-up Timer (OST)
  - Ensures stability of crystal oscillator sources

# PIC16(L)F153XX

**TABLE 1: PIC16(L)F153XX FAMILY TYPES**

| Device      | Data Sheet Index | Program Flash Memory (KW) | Program Flash Memory (KB) | Storage Area Flash (B) | Data SRAM (bytes) | I/O Pins | 10-Bit ADC | 5-Bit DAC | Comparator | 8-Bit/ (with HLT) Timer | 16-Bit Timer | Window Watchdog Timer | CCP/10-Bit PWM | CWG | NCO | CLC | Zero Cross Detect | Temperature Sensor | Memory Access Partition | Device Information Area | EUSART/ I <sup>2</sup> C/SPI | Peripheral Pin Select | Peripheral Module Disable | Debug <sup>(1)</sup> |
|-------------|------------------|---------------------------|---------------------------|------------------------|-------------------|----------|------------|-----------|------------|-------------------------|--------------|-----------------------|----------------|-----|-----|-----|-------------------|--------------------|-------------------------|-------------------------|------------------------------|-----------------------|---------------------------|----------------------|
| PIC16F15313 | (C)              | 2                         | 3.5                       | 224                    | 256               | 6        | 5          | 1         | 1          | 1                       | 2            | Y                     | 2/4            | 1   | 1   | 4   | Y                 | Y                  | Y                       | Y                       | 1/1                          | Y                     | Y                         | I                    |
| PIC16F15323 | (C)              | 2                         | 3.5                       | 224                    | 256               | 12       | 11         | 1         | 2          | 1                       | 2            | Y                     | 2/4            | 1   | 1   | 4   | Y                 | Y                  | Y                       | Y                       | 1/1                          | Y                     | Y                         | I                    |
| PIC16F15324 | (D)              | 4                         | 7                         | 224                    | 512               | 12       | 11         | 1         | 2          | 1                       | 2            | Y                     | 2/4            | 1   | 1   | 4   | Y                 | Y                  | Y                       | Y                       | 2/1                          | Y                     | Y                         | I                    |
| PIC16F15325 | (B)              | 8                         | 14                        | 224                    | 1024              | 12       | 11         | 1         | 2          | 1                       | 2            | Y                     | 2/4            | 1   | 1   | 4   | Y                 | Y                  | Y                       | Y                       | 2/1                          | Y                     | Y                         | I                    |
| PIC16F15344 | (D)              | 4                         | 7                         | 224                    | 512               | 18       | 17         | 1         | 2          | 1                       | 2            | Y                     | 2/4            | 1   | 1   | 4   | Y                 | Y                  | Y                       | Y                       | 2/1                          | Y                     | Y                         | I                    |
| PIC16F15345 | (B)              | 8                         | 14                        | 224                    | 1024              | 18       | 17         | 1         | 2          | 1                       | 2            | Y                     | 2/4            | 1   | 1   | 4   | Y                 | Y                  | Y                       | Y                       | 2/1                          | Y                     | Y                         | I                    |
| PIC16F15354 | (A)              | 4                         | 7                         | 224                    | 512               | 25       | 24         | 1         | 2          | 1                       | 2            | Y                     | 2/4            | 1   | 1   | 4   | Y                 | Y                  | Y                       | Y                       | 2/2                          | Y                     | Y                         | I                    |
| PIC16F15355 | (A)              | 8                         | 14                        | 224                    | 1024              | 25       | 24         | 1         | 2          | 1                       | 2            | Y                     | 2/4            | 1   | 1   | 4   | Y                 | Y                  | Y                       | Y                       | 2/2                          | Y                     | Y                         | I                    |
| PIC16F15356 | (E)              | 16                        | 28                        | 224                    | 2048              | 25       | 24         | 1         | 2          | 1                       | 2            | Y                     | 2/4            | 1   | 1   | 4   | Y                 | Y                  | Y                       | Y                       | 2/2                          | Y                     | Y                         | I                    |
| PIC16F15375 | (F)              | 8                         | 14                        | 224                    | 1024              | 36       | 35         | 1         | 2          | 1                       | 2            | Y                     | 2/4            | 1   | 1   | 4   | Y                 | Y                  | Y                       | Y                       | 2/2                          | Y                     | Y                         | I                    |
| PIC16F15376 | (E)              | 16                        | 28                        | 224                    | 2048              | 36       | 35         | 1         | 2          | 1                       | 2            | Y                     | 2/4            | 1   | 1   | 4   | Y                 | Y                  | Y                       | Y                       | 2/2                          | Y                     | Y                         | I                    |
| PIC16F15385 | (F)              | 8                         | 14                        | 224                    | 1024              | 44       | 43         | 1         | 2          | 1                       | 2            | Y                     | 2/4            | 1   | 1   | 4   | Y                 | Y                  | Y                       | Y                       | 2/2                          | Y                     | Y                         | I                    |
| PIC16F15386 | (E)              | 16                        | 28                        | 224                    | 2048              | 44       | 43         | 1         | 2          | 1                       | 2            | Y                     | 2/4            | 1   | 1   | 4   | Y                 | Y                  | Y                       | Y                       | 2/2                          | Y                     | Y                         | I                    |

**Note 1:** I - Debugging integrated on chip.

**Data Sheet Index:**

|           |                |                                               |
|-----------|----------------|-----------------------------------------------|
| <b>A:</b> | Future Release | PIC16(L)F15354/5 Data Sheet, 28-Pin           |
| <b>B:</b> | Future Release | PIC16(L)F15325/45 Data Sheet, 14/20-Pin       |
| <b>C:</b> | Future Release | PIC16(L)F15313/23 Data Sheet, 8/14-Pin        |
| <b>D:</b> | Future Release | PIC16(L)F15324/44 Data Sheet, 14/20-Pin       |
| <b>E:</b> | Future Release | PIC16(L)F15356/76/86 Data Sheet, 28/40/48-Pin |
| <b>F:</b> | Future Release | PIC16(L)F15375/85 Data Sheet, 40/48-Pin       |

**Note:** For other small form-factor package availability and marking information, visit [www.microchip.com/packaging](http://www.microchip.com/packaging) or contact your local sales office.

# PIC16(L)F153XX


**TABLE 2: PACKAGES**

| Device         | (S)PDIP | SOIC | SSOP | TSSOP | (U)DFN<br>(3x3) | QFN<br>(4x4) | QFN<br>(6x6) | UQFN<br>(4x4) | TQFP | QFN<br>(8x8) | UQFN<br>(5x5) | UQFN<br>(6x6) |
|----------------|---------|------|------|-------|-----------------|--------------|--------------|---------------|------|--------------|---------------|---------------|
| PIC16(L)F15313 | X       | X    | —    | —     | X               | —            | —            | —             | —    | —            | —             | —             |
| PIC16(L)F15323 | X       | X    | —    | X     | —               | X            | —            | X             | —    | —            | —             | —             |
| PIC16(L)F15324 | X       | X    | —    | X     | —               | X            | —            | X             | —    | —            | —             | —             |
| PIC16(L)F15325 | X       | X    | —    | X     | —               | X            | —            | X             | —    | —            | —             | —             |
| PIC16(L)F15344 | X       | X    | X    | —     | —               | X            | —            | X             | —    | —            | —             | —             |
| PIC16(L)F15345 | X       | X    | X    | —     | —               | X            | —            | X             | —    | —            | —             | —             |
| PIC16(L)F15354 | X       | X    | X    | —     | —               | —            | X            | X             | —    | —            | —             | —             |
| PIC16(L)F15355 | X       | X    | X    | —     | —               | —            | X            | X             | —    | —            | —             | —             |
| PIC16(L)F15356 | X       | X    | X    | —     | —               | —            | X            | X             | —    | —            | —             | —             |
| PIC16(L)F15375 | X       | —    | —    | —     | —               | —            | —            | —             | X    | X            | X             | —             |
| PIC16(L)F15376 | X       | —    | —    | —     | —               | —            | —            | —             | X    | X            | X             | —             |
| PIC16(L)F15385 | —       | —    | —    | —     | —               | —            | —            | —             | X    | —            | —             | X             |
| PIC16(L)F15386 | —       | —    | —    | —     | —               | —            | —            | —             | X    | —            | —             | X             |


**Note:** Pin details are subject to change.

## PIN DIAGRAMS


**FIGURE 1: 8-PIN PDIP, SOIC, MSOP, FOR PIC16(L)F15313**




**FIGURE 2: 14-PIN PDIP, SOIC, TSSOP FOR PIC16(L)F15323**



**FIGURE 3: 14-PIN PDIP, TSSOP FOR PIC16(L)F15324 AND PIC16(L)F15325**




**FIGURE 4: 20-PIN PDIP, SOIC, SSOP FOR PIC16(L)F15344, PIC16(L)F15345**




# PIC16(L)F153XX

**FIGURE 5: 28-PIN PDIP, SOIC, SSOP FOR PIC16(L)F15354, PIC16(L)F15355, PIC16(L)F15356**



**FIGURE 6: 40-PIN PDIP FOR PIC16(L)F15375, PIC16(L)F15376**



# PIC16(L)F153XX

FIGURE 9: 28-PIN UQFN (4X4) FOR PIC16(L)F15354, PIC16(L)F15355, PIC16(L)F15356







FIGURE 10: 28-PIN QFN (6X6) FOR PIC16(L)F15354, PIC16(L)F15355, PIC16(L)F15356



**FIGURE 11: 40-PIN UQFN (5X5) FOR PIC16(L)F15375, PIC16(L)F15376**




**FIGURE 12: 44-PIN TQFP (10X10) FOR PIC16(L)F15375, PIC16(L)F15376**






# PIC16(L)F153XX


**FIGURE 13: 44-PIN QFN (8X8X0.9) FOR PIC16(L)F15375, PIC16(L)F15376**



**FIGURE 14: 48-PIN UQFN (6X6) FOR PIC16(L)F15385, PIC16(L)F15386**



**FIGURE 15: 48-PIN TQFP (7X7) FOR PIC16(L)F15385, PIC16(L)F15386**



**Note:** See Table 7 for location of all peripheral functions.

## PIN ALLOCATION TABLES

**TABLE 3: 8-PIN ALLOCATION TABLE (PIC16(L)F15313)**

| I/O I <sup>(2)</sup> | 8-Pin PDIP/SOIC/MSOP | ADC                          | Reference         | Comparator | NCO     | DAC                  | Timers                                                         | CCP                                        | PWM  | CWG                 | MSSP                                                     | ZCD  | EUSART               | CLC                   | CLKR | Interrupt                   | Pull-up | Basic                   |
|----------------------|----------------------|------------------------------|-------------------|------------|---------|----------------------|----------------------------------------------------------------|--------------------------------------------|------|---------------------|----------------------------------------------------------|------|----------------------|-----------------------|------|-----------------------------|---------|-------------------------|
| RA0                  | 7                    | ANA0                         | —                 | C1IN0+     | —       | DAC1OUT              | —                                                              | —                                          | —    | —                   | —                                                        | —    | TX/CK <sup>(1)</sup> | CLCIN3 <sup>(1)</sup> | —    | IOCA0                       | Y       | ICDDAT/<br>ICSPDAT      |
| RA1                  | 6                    | ANA1                         | V <sub>REF+</sub> | C1IN0-     | —       | DA1 <sub>REF+</sub>  | T0CKI <sup>(1)</sup>                                           | —                                          | —    | —                   | SSP1CLK <sup>(1),(4)</sup><br>SSP1DAT <sup>(1),(4)</sup> | —    | RX/DT <sup>(1)</sup> | CLCIN2 <sup>(1)</sup> | —    | IOCA1                       | Y       | ICDCLK/<br>ICSPCLK      |
| RA2                  | 5                    | ANA2                         | V <sub>REF-</sub> | —          | —       | DAC1 <sub>REF-</sub> | —                                                              | —                                          | —    | CWG1 <sup>(1)</sup> | SSP1CLK <sup>(1),(4)</sup><br>SSP1DAT <sup>(1),(4)</sup> | ZCD1 | —                    | —                     | —    | INT <sup>(1)</sup><br>IOCA2 | Y       | —                       |
| RA3                  | 4                    | —                            | —                 | —          | —       | —                    | —                                                              | —                                          | —    | —                   | SSP1SS <sup>(1)</sup>                                    | —    | —                    | CLCIN0 <sup>(1)</sup> | —    | IOCA3                       | Y       | MCLR<br>V <sub>PP</sub> |
| RA4                  | 3                    | ANA4                         | —                 | C1IN1-     | —       | —                    | T1G <sup>(1)</sup><br>SOSCO                                    | —                                          | —    | —                   | —                                                        | —    | —                    | —                     | —    | IOCA4                       | Y       | CLKOUT<br>OSC2          |
| RA5                  | 2                    | ANA5<br>ADACT <sup>(1)</sup> | —                 | —          | —       | —                    | T1CKI <sup>(1)</sup><br>T2IN <sup>(1)</sup><br>SOSCIN<br>SOSCI | CCP1 <sup>(1)</sup><br>CCP2 <sup>(1)</sup> | —    | —                   | —                                                        | —    | —                    | CLCIN1 <sup>(1)</sup> | —    | IOCA5                       | Y       | CLKIN<br>OSC1<br>EIN    |
| V <sub>DD</sub>      | 1                    | —                            | —                 | —          | —       | —                    | —                                                              | —                                          | —    | —                   | —                                                        | —    | —                    | —                     | —    | —                           | —       | V <sub>DD</sub>         |
| V <sub>SS</sub>      | 8                    | —                            | —                 | —          | —       | —                    | —                                                              | —                                          | —    | —                   | —                                                        | —    | —                    | —                     | —    | —                           | —       | V <sub>SS</sub>         |
| OUT <sup>(2)</sup>   | —                    | —                            | —                 | C1OUT      | NCO1OUT | —                    | TMR0                                                           | CCP1                                       | PWM3 | CWG1A               | SDO1                                                     | —    | DT1 <sup>(3)</sup>   | CLC1OUT               | CLKR | —                           | —       | —                       |
|                      | —                    | —                            | —                 | C2OUT      | —       | —                    | —                                                              | CCP2                                       | PWM4 | CWG1B               | SCK1                                                     | —    | CK1                  | CLC2OUT               | —    | —                           | —       | —                       |
|                      | —                    | —                            | —                 | —          | —       | —                    | —                                                              | —                                          | PWM5 | CWG1C               | SCL1 <sup>(3),(4)</sup>                                  | —    | TX1                  | CLC3OUT               | —    | —                           | —       | —                       |
|                      | —                    | —                            | —                 | —          | —       | —                    | —                                                              | —                                          | PWM6 | CWG1D               | SDA1 <sup>(3),(4)</sup>                                  | —    | —                    | CLC4OUT               | —    | —                           | —       | —                       |

- Note**
- 1: This is a PPS remappable input signal. The input function may be moved from the default location shown to one of several other PORTx pins.
  - 2: All digital output signals shown in this row are PPS re-mappable. These signals may be mapped to output onto one of several PORTx pin options.
  - 3: This is a bidirectional signal. For normal module operation, the firmware should map this signal to the same pin in both the PPS input and PPS output registers.
  - 4: These pins are configured for I<sup>2</sup>C logic levels. PPS assignments to the other pins will operate, but input logic levels will be standard TTL/ST as selected by the INLV<sub>L</sub> register, instead of the I<sup>2</sup>C specific or SMBUS input buffer thresholds.

**TABLE 4: 14/16/20-PIN ALLOCATION TABLE (PIC16(L)F15323, PIC16(L)F15324, PIC16(L)F15325, PIC16(L)F15344, PIC16(L)F15345)**

| I/O(2) | 14-Pin PDIP/SSOP | 16-Pin QFN/UQFN | 20-Pin PDIP/SSOP | 20-Pin QFN | ADC                          | Reference         | Comparator       | NCO | DAC                  | Timers                                          | CCP  | PWM | CWG                 | MSSP                                                     | ZCD  | EUSART                 | CLC                                                    | CLKR | Interrupt                   | Pull-up | Basic                   |
|--------|------------------|-----------------|------------------|------------|------------------------------|-------------------|------------------|-----|----------------------|-------------------------------------------------|------|-----|---------------------|----------------------------------------------------------|------|------------------------|--------------------------------------------------------|------|-----------------------------|---------|-------------------------|
| RA0    | 13               | 12              | 19               | 16         | ANA0                         | —                 | C1IN0+           | —   | DAC1OUT              | —                                               | —    | —   | —                   | —                                                        | —    | —                      | —                                                      | —    | IOCA0                       | Y       | ICDDAT/<br>ICSPDAT      |
| RA1    | 12               | 11              | 18               | 15         | ANA1                         | V <sub>REF+</sub> | C1IN0-           | —   | DA1 <sub>REF+</sub>  | T0CKI <sup>(1)</sup>                            | —    | —   | —                   | —                                                        | —    | —                      | —                                                      | —    | IOCA1                       | Y       | ICDCLK/<br>ICSPCLK      |
| RA2    | 11               | 10              | 17               | 14         | ANA2                         | V <sub>REF-</sub> | —                | —   | DAC1 <sub>REF-</sub> | —                                               | —    | —   | CWG1 <sup>(1)</sup> | —                                                        | ZCD1 | —                      | CLCIN0 <sup>(1),(6)</sup>                              | —    | INT <sup>(1)</sup><br>IOCA2 | Y       | —                       |
| RA3    | 4                | 3               | 4                | 1          | —                            | —                 | —                | —   | —                    | —                                               | —    | —   | —                   | —                                                        | —    | —                      | —                                                      | —    | IOCA3                       | Y       | MCLR<br>V <sub>PP</sub> |
| RA4    | 3                | 2               | 3                | 20         | ANA4                         | —                 | C1IN1-           | —   | —                    | T1G <sup>(1)</sup><br>SOSCO                     | —    | —   | —                   | —                                                        | —    | —                      | —                                                      | —    | IOCA4                       | Y       | CLKOUT<br>OSC2          |
| RA5    | 2                | 1               | 2                | 19         | ANA5                         | —                 | —                | —   | —                    | T1CKI <sup>(1)</sup><br>T2IN<br>SOSCIN<br>SOSCI | —    | —   | —                   | —                                                        | —    | —                      | CLCIN3 <sup>(1),(5)</sup>                              | —    | IOCA5                       | Y       | CLKIN<br>OSC1<br>EIN    |
| RC0    | 10               | 9               | 16               | 13         | ANC0                         | —                 | C2IN0+           | —   | —                    | —                                               | —    | —   | —                   | SSP1CLK <sup>(1),(5)</sup><br>SSP1DAT <sup>(1),(5)</sup> | —    | —                      | —                                                      | —    | IOCC0                       | Y       | —                       |
| RC1    | 9                | 8               | 15               | 12         | ANC1                         | —                 | C1IN1-<br>C2IN1- | —   | —                    | —                                               | —    | —   | —                   | SSP1CLK <sup>(1),(5)</sup><br>SSP1DAT <sup>(1),(5)</sup> | —    | —                      | CLCIN2 <sup>(1),(5)</sup>                              | —    | IOCC1                       | Y       | —                       |
| RC2    | 8                | 7               | 14               | 11         | ANC2                         | —                 | C1IN2-<br>C2IN2- | —   | —                    | —                                               | —    | —   | —                   | —                                                        | —    | —                      | —                                                      | —    | IOCC2                       | Y       | —                       |
| RC3    | 7                | 6               | 7                | 4          | ANC3                         | —                 | C1IN3-<br>C2IN3- | —   | —                    | —                                               | CCP2 | —   | —                   | SSP1SS <sup>(5)</sup>                                    | —    | —                      | CLCIN1 <sup>(1),(6)</sup><br>CLCIN0 <sup>(1),(5)</sup> | —    | IOCC3                       | Y       | —                       |
| RC4    | 6                | 5               | 6                | 3          | ANC4                         | —                 | —                | —   | —                    | —                                               | —    | —   | —                   | SSP2CLK <sup>(1),(5)</sup><br>SSP2DAT <sup>(1),(5)</sup> | —    | TX1/CK1 <sup>(5)</sup> | CLCIN1 <sup>(1),(5)</sup>                              | —    | IOCC4                       | Y       | —                       |
| RC5    | 5                | 4               | 5                | 2          | ANC5                         | —                 | —                | —   | —                    | —                                               | CCP1 | —   | —                   | SSP1CLK <sup>(1),(5)</sup><br>SSP1DAT <sup>(1),(5)</sup> | —    | RX1/DT1 <sup>(5)</sup> | —                                                      | —    | IOCC5                       | Y       | —                       |
| RC6    | —                | —               | 8                | 5          | ANC6                         | —                 | —                | —   | —                    | —                                               | —    | —   | —                   | SSP1SS1 <sup>(6)</sup>                                   | —    | —                      | —                                                      | —    | IOCC6                       | Y       | —                       |
| RC7    | —                | —               | 9                | 6          | ANC7                         | —                 | —                | —   | —                    | —                                               | —    | —   | —                   | —                                                        | —    | —                      | —                                                      | —    | IOCC7                       | Y       | —                       |
| RB4    | —                | —               | 13               | 10         | ANB4<br>ADACT <sup>(1)</sup> | —                 | —                | —   | —                    | —                                               | —    | —   | —                   | SSP1CLK <sup>(1),(6)</sup><br>SSP1DAT <sup>(1),(6)</sup> | —    | —                      | CLCIN2 <sup>(1),(6)</sup>                              | —    | IOCB4                       | —       | —                       |
| RB5    | —                | —               | 12               | 9          | ANB5                         | —                 | —                | —   | —                    | —                                               | —    | —   | —                   | SSP2CLK <sup>(1),(6)</sup><br>SSP2DAT <sup>(1),(6)</sup> | —    | RX1/DT1 <sup>(6)</sup> | CLCIN3 <sup>(1),(6)</sup>                              | —    | IOCB5                       | —       | —                       |

**PIC16(L)F153XX**

**TABLE 4: 14/16/20-PIN ALLOCATION TABLE (PIC16(L)F15323, PIC16(L)F15324, PIC16(L)F15325, PIC16(L)F15344, PIC16(L)F15345)**

| I/O <sup>(2)</sup> | 14-Pin PDIP/SOIC/TSSOP | 16-Pin QFN/UQFN | 20-Pin PDIP/SOIC/SSOP | 20-Pin QFN | ADC  | Reference | Comparator | NCO     | DAC | Timers | CCP  | PWM  | CWG   | MSSP                                                     | ZCD | EUSART                 | CLC     | CLKR | Interrupt | Pull-up | Basic           |
|--------------------|------------------------|-----------------|-----------------------|------------|------|-----------|------------|---------|-----|--------|------|------|-------|----------------------------------------------------------|-----|------------------------|---------|------|-----------|---------|-----------------|
| RB6                | —                      | —               | 11                    | 8          | ANB6 | —         | —          | —       | —   | —      | —    | —    | —     | SSP1CLK <sup>(1),(6)</sup><br>SSP1DAT <sup>(1),(6)</sup> | —   | —                      | —       | —    | IOCB6     | Y       | —               |
| RB7                | —                      | —               | 10                    | 7          | ANB7 | —         | —          | —       | —   | —      | —    | —    | —     | SSP2CLK <sup>(1),(6)</sup><br>SSP2DAT <sup>(1),(6)</sup> | —   | TX1/CK1 <sup>(6)</sup> | —       | —    | IOCB7     | Y       | —               |
| V <sub>DD</sub>    | 1                      | 16              | 1                     | 18         | —    | —         | —          | —       | —   | —      | —    | —    | —     | —                                                        | —   | —                      | —       | —    | —         | —       | V <sub>DD</sub> |
| V <sub>SS</sub>    | 14                     | 13              | 20                    | 17         | —    | —         | —          | —       | —   | —      | —    | —    | —     | —                                                        | —   | —                      | —       | —    | —         | —       | V <sub>SS</sub> |
| OUT <sup>(2)</sup> | —                      | —               | —                     | —          | —    | —         | C1OUT      | NCO1OUT | —   | TMR0   | CCP1 | PWM3 | CWG1A | SDO1<br>SDO2                                             | —   | DT1 <sup>(3)</sup>     | CLC1OUT | CLKR | —         | —       | —               |
|                    | —                      | —               | —                     | —          | —    | —         | C2OUT      | —       | —   | —      | CCP2 | PWM4 | CWG1B | SCK1<br>SCK2                                             | —   | CK1                    | CLC2OUT | —    | —         | —       | —               |
|                    | —                      | —               | —                     | —          | —    | —         | —          | —       | —   | —      | —    | PWM5 | CWG1C | SCL1 <sup>(3),(4)</sup><br>SCL2 <sup>(3),(4)</sup>       | —   | TX1                    | CLC3OUT | —    | —         | —       | —               |
|                    | —                      | —               | —                     | —          | —    | —         | —          | —       | —   | —      | —    | PWM6 | CWG1D | SDA1 <sup>(3),(4)</sup><br>SDA2 <sup>(3),(4)</sup>       | —   | —                      | CLC4OUT | —    | —         | —       | —               |

- Note**
- 1: This is a PPS re-mappable input signal. The input function may be moved from the default location shown to one of several other PORTx pins.
  - 2: All digital output signals shown in this row are PPS re-mappable. These signals may be mapped to output onto one of several PORTx pin options.
  - 3: This is a bidirectional signal. For normal module operation, the firmware should map this signal to the same pin in both the PPS input and PPS output registers.
  - 4: These pins are configured for I<sup>2</sup>C logic levels. PPS assignments to the other pins will operate, but input logic levels will be standard TTL/ST as selected by the INLVL register, instead of the I<sup>2</sup>C specific or SMBUS input buffer thresholds.
  - 5: For 14 and 16-pin package only.
  - 6: For 20-pin package only.

**TABLE 5: 28-PIN ALLOCATION TABLE (PIC16(L)F15354, PIC16(L)F15355, PIC16(L)F15356)**

| I/O <sup>(2)</sup> | 28-Pin PDIP/SSOP | 28-Pin (U)QFN | ADC                          | Reference | Comparator       | NCO | DAC      | Timers              | CCP                 | PWM | CWG                 | MSSP                                             | ZCD  | EUSART                    | CLC                   | CLKR | Interrupt                   | Pull-up | Basic             |
|--------------------|------------------|---------------|------------------------------|-----------|------------------|-----|----------|---------------------|---------------------|-----|---------------------|--------------------------------------------------|------|---------------------------|-----------------------|------|-----------------------------|---------|-------------------|
| RA0                | 2                | 27            | ANA0                         | —         | C1IN0-<br>C2IN0- | —   | —        | —                   | —                   | —   | —                   | —                                                | —    | —                         | CLCIN0 <sup>(1)</sup> | —    | IOCA0                       | Y       | —                 |
| RA1                | 3                | 28            | ANA1                         | —         | C1IN1-<br>C2IN1- | —   | —        | —                   | —                   | —   | —                   | —                                                | —    | —                         | CLCIN1 <sup>(1)</sup> | —    | IOCA1                       | Y       | —                 |
| RA2                | 4                | 1             | ANA2                         | —         | C1IN0+<br>C2IN0+ | —   | —        | —                   | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCA2                       | Y       | —                 |
| RA3                | 5                | 2             | ANA3                         | VREF+     | C1IN1+           | —   | DACREF+  | —                   | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCA3                       | Y       | —                 |
| RA4                | 6                | 3             | ANA4                         | —         | —                | —   | —        | T0CKI               | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCA4                       | Y       | —                 |
| RA5                | 7                | 4             | ANA5                         | —         | —                | —   | —        | T1G <sup>(1)</sup>  | —                   | —   | —                   | SSP1SS <sup>(1)</sup>                            | —    | —                         | —                     | —    | IOCA5                       | Y       | —                 |
| RA6                | 10               | 7             | ANA6                         | —         | —                | —   | —        | —                   | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCA6                       | Y       | CLKOUT            |
| RA7                | 9                | 6             | ANA7                         | —         | —                | —   | —        | —                   | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCA7                       | Y       | CLKIN             |
| RB0                | 21               | 18            | ANB0                         | —         | C2IN1+           | —   | —        | —                   | —                   | —   | CWG1 <sup>(1)</sup> | SSP2SS <sup>(1)</sup>                            | ZCD1 | —                         | —                     | —    | INT <sup>(1)</sup><br>IOCB0 | Y       | —                 |
| RB1                | 22               | 19            | ANB1                         | —         | C1IN3-<br>C2IN3- | —   | —        | —                   | —                   | —   | —                   | SSP1CLK <sup>(1)</sup><br>SSP1DAT <sup>(1)</sup> | —    | —                         | —                     | —    | IOCB1                       | Y       | —                 |
| RB2                | 23               | 20            | ANB2                         | —         | —                | —   | —        | —                   | —                   | —   | —                   | SSP1CLK <sup>(1)</sup><br>SSP1DAT <sup>(1)</sup> | —    | —                         | —                     | —    | IOCB2                       | Y       | —                 |
| RB3                | 24               | 21            | ANB3                         | —         | C1IN2-<br>C2IN2- | —   | —        | —                   | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCB3                       | Y       | —                 |
| RB4                | 25               | 22            | ANB4<br>ADACT <sup>(1)</sup> | —         | —                | —   | —        | —                   | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCB4                       | Y       | —                 |
| RB5                | 26               | 23            | ANB5                         | —         | —                | —   | —        | —                   | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCB5                       | Y       | —                 |
| RB6                | 27               | 24            | ANB6                         | —         | —                | —   | —        | —                   | —                   | —   | —                   | —                                                | —    | TX2<br>CK2 <sup>(1)</sup> | CLCIN2 <sup>(1)</sup> | —    | IOCB6                       | Y       | ICDCLK<br>ICSPCLK |
| RB7                | 28               | 25            | ANB7                         | —         | —                | —   | DAC1OUT2 | —                   | —                   | —   | —                   | —                                                | —    | RX2<br>DT2 <sup>(1)</sup> | CLCIN3 <sup>(1)</sup> | —    | IOCB7                       | Y       | ICDDAT<br>ICSPDAT |
| RC0                | 11               | 8             | ANC0                         | —         | —                | —   | —        | SOSCO<br>T1CKI      | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCC0                       | Y       | —                 |
| RC1                | 12               | 9             | ANC1                         | —         | —                | —   | —        | SOSCI               | CCP2 <sup>(1)</sup> | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCC1                       | Y       | —                 |
| RC2                | 13               | 10            | ANC2                         | —         | —                | —   | —        | —                   | CCP1 <sup>(1)</sup> | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCC2                       | Y       | —                 |
| RC3                | 14               | 11            | ANC3                         | —         | —                | —   | —        | T2IN <sup>(1)</sup> | —                   | —   | —                   | SSP1CLK <sup>(1)</sup><br>SSP1DAT <sup>(1)</sup> | —    | —                         | —                     | —    | IOCC3                       | Y       | —                 |
| RC4                | 15               | 12            | ANC4                         | —         | —                | —   | —        | —                   | —                   | —   | —                   | SSP1CLK <sup>(1)</sup><br>SSP1DAT <sup>(1)</sup> | —    | —                         | —                     | —    | IOCC4                       | Y       | —                 |

**TABLE 5: 28-PIN ALLOCATION TABLE (PIC16(L)F15354, PIC16(L)F15355, PIC16(L)F15356) (CONTINUED)**

| I/O <sup>(2)</sup> | 28-Pin PDIP/SSOP | 28-Pin (U)QFN | ADC  | Reference | Comparator | NCO     | DAC | Timers | CCP  | PWM  | CWG            | MSSP                   | ZCD | EUSART                    | CLC     | CLKR | Interrupt | Pull-up | Basic                   |
|--------------------|------------------|---------------|------|-----------|------------|---------|-----|--------|------|------|----------------|------------------------|-----|---------------------------|---------|------|-----------|---------|-------------------------|
| RC5                | 16               | 13            | ANC5 | —         | —          | —       | —   | —      | —    | —    | —              | —                      | —   | —                         | —       | —    | IOCC5     | Y       | —                       |
| RC6                | 17               | 14            | ANC6 | —         | —          | —       | —   | —      | —    | —    | —              | —                      | —   | TX1<br>CK1 <sup>(1)</sup> | —       | —    | IOCC6     | Y       | —                       |
| RC7                | 18               | 15            | ANC7 | —         | —          | —       | —   | —      | —    | —    | —              | —                      | —   | RX1<br>DT1 <sup>(1)</sup> | —       | —    | IOCC7     | Y       | —                       |
| RE3                | 1                | 26            | ANE3 | —         | —          | —       | —   | —      | —    | —    | —              | —                      | —   | —                         | —       | —    | IOCE3     | Y       | MCLR<br>V <sub>PP</sub> |
| VDD                | 20               | 17            | —    | —         | —          | —       | —   | —      | —    | —    | —              | —                      | —   | —                         | —       | —    | —         | —       | VDD                     |
| VSS                | 8                | 16            | —    | —         | —          | —       | —   | —      | —    | —    | —              | —                      | —   | —                         | —       | —    | —         | —       | VSS                     |
| VSS                | 19               | 5             | —    | —         | —          | —       | —   | —      | —    | —    | —              | —                      | —   | —                         | —       | —    | —         | —       | VSS                     |
| VSEL0              | 19               | 17            | —    | —         | —          | —       | —   | —      | —    | —    | —              | —                      | —   | —                         | —       | —    | —         | —       | —                       |
| OUT <sup>(2)</sup> | —                | —             | —    | —         | C1OUT      | NCO1OUT | —   | TMR0   | CCP1 | PWM3 | CWG1A<br>CWG2A | SDO                    | —   | DT <sup>(3)</sup>         | CLC1OUT | CLKR | —         | —       | —                       |
|                    | —                | —             | —    | —         | C2OUT      | —       | —   | —      | CCP2 | PWM4 | CWG1B<br>CWG2B | SCK                    | —   | CK                        | CLC2OUT | —    | —         | —       | —                       |
|                    | —                | —             | —    | —         | —          | —       | —   | —      | —    | PWM5 | CWG1C<br>CWG2C | SCL <sup>(3),(4)</sup> | —   | TX                        | CLC3OUT | —    | —         | —       | —                       |
|                    | —                | —             | —    | —         | —          | —       | —   | —      | —    | PWM6 | CWG1D<br>CWG2D | SDA <sup>(3),(4)</sup> | —   | —                         | CLC4OUT | —    | —         | —       | —                       |

- Note**
- 1: This is a PPS re-mappable input signal. The input function may be moved from the default location shown to one of several other PORTx pins.
  - 2: All digital output signals shown in this row are PPS re-mappable. These signals may be mapped to output onto one of several PORTx pin options.
  - 3: This is a bidirectional signal. For normal module operation, the firmware should map this signal to the same pin in both the PPS input and PPS output registers.
  - 4: These pins are configured for I<sup>2</sup>C logic levels. PPS assignments to the other pins will operate, but input logic levels will be standard TTL/ST as selected by the INLVL register, instead of the I<sup>2</sup>C specific or SMBUS input buffer thresholds.

**TABLE 6: 40/44-PIN ALLOCATION TABLE (PIC16(L)F15375, PIC16(L)F15376)**

| I/O <sup>(2)</sup> | 40-Pin PDIP | 40-Pin UQFN | 44-Pin QFN | 44-Pin TQFP | ADC                          | Reference | Comparator       | NCO | DAC      | Timers                        | CCP                 | PWM | CWG                 | MSSP                                             | ZCD  | EUSART                    | CLC                   | CLKR | Interrupt                   | Pull-up | Basic             |
|--------------------|-------------|-------------|------------|-------------|------------------------------|-----------|------------------|-----|----------|-------------------------------|---------------------|-----|---------------------|--------------------------------------------------|------|---------------------------|-----------------------|------|-----------------------------|---------|-------------------|
| RA0                | 2           | 17          | 19         | 19          | ANA0                         | —         | C1IN0-<br>C2IN0- | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | CLCIN0 <sup>(1)</sup> | —    | IOCA0                       | Y       | —                 |
| RA1                | 3           | 18          | 20         | 20          | ANA1                         | —         | C1IN1-<br>C2IN1- | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | CLCIN1 <sup>(1)</sup> | —    | IOCA1                       | Y       | —                 |
| RA2                | 4           | 19          | 21         | 21          | ANA2                         | —         | C1IN0+<br>C2IN0+ | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCA2                       | Y       | —                 |
| RA3                | 5           | 20          | 22         | 22          | ANA3                         | VREF+     | C1IN1+           | —   | DACREF+  | —                             | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCA3                       | Y       | —                 |
| RA4                | 6           | 21          | 23         | 23          | ANA4                         | —         | —                | —   | —        | T0CKI <sup>(1)</sup>          | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCA4                       | Y       | —                 |
| RA5                | 7           | 22          | 24         | 24          | ANA5                         | —         | —                | —   | —        | T1G <sup>(1)</sup>            | —                   | —   | —                   | SSP1SS <sup>(1)</sup>                            | —    | —                         | —                     | —    | IOCA5                       | Y       | —                 |
| RA6                | 14          | 29          | 33         | 31          | ANA6                         | —         | —                | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCA6                       | Y       | CLKOUT            |
| RA7                | 13          | 28          | 32         | 30          | ANA7                         | —         | —                | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCA7                       | Y       | CLKIN             |
| RB0                | 33          | 8           | 9          | 8           | ANB0                         | —         | C2IN1+           | —   | —        | —                             | —                   | —   | CWG1 <sup>(1)</sup> | SSP2SS <sup>(1)</sup>                            | ZCD1 | —                         | —                     | —    | INT <sup>(1)</sup><br>IOCB0 | Y       | —                 |
| RB1                | 34          | 9           | 10         | 9           | ANB1                         | —         | C1IN3-<br>C2IN3- | —   | —        | —                             | —                   | —   | —                   | SSP1CLK <sup>(1)</sup><br>SSP1DAT <sup>(1)</sup> | —    | —                         | —                     | —    | IOCB1                       | Y       | —                 |
| RB2                | 34          | 10          | 11         | 10          | ANB2                         | —         | —                | —   | —        | —                             | —                   | —   | —                   | SSP1CLK <sup>(1)</sup><br>SSP1DAT <sup>(1)</sup> | —    | —                         | —                     | —    | IOCB2                       | Y       | —                 |
| RB3                | 36          | 11          | 12         | 11          | ANB3                         | —         | C1IN2-<br>C2IN2- | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCB3                       | Y       | —                 |
| RB4                | 37          | 12          | 14         | 14          | ANB4<br>ADACT <sup>(1)</sup> | —         | —                | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCB4                       | Y       | —                 |
| RB5                | 38          | 13          | 15         | 15          | ANB5                         | —         | —                | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCB5                       | Y       | —                 |
| RB6                | 39          | 14          | 16         | 16          | ANB6                         | —         | —                | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | TX2<br>CK2 <sup>(1)</sup> | CLCIN2 <sup>(1)</sup> | —    | IOCB6                       | Y       | ICDCLK<br>ICSPCLK |
| RB7                | 40          | 15          | 17         | 17          | ANB7                         | —         | —                | —   | DAC1OUT2 | —                             | —                   | —   | —                   | —                                                | —    | RX2<br>DT2 <sup>(1)</sup> | CLCIN3 <sup>(1)</sup> | —    | IOCB7                       | Y       | ICDDAT<br>ICSPDAT |
| RC0                | 15          | 30          | 34         | 32          | ANC0                         | —         | —                | —   | —        | SOSCO<br>T1CKI <sup>(1)</sup> | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCC0                       | Y       | —                 |
| RC1                | 16          | 31          | 35         | 35          | ANC1                         | —         | —                | —   | —        | SOSCI                         | CCP2 <sup>(1)</sup> | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCC1                       | Y       | —                 |
| RC2                | 17          | 32          | 36         | 36          | ANC2                         | —         | —                | —   | —        | —                             | CCP1 <sup>(1)</sup> | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCC2                       | Y       | —                 |
| RC3                | 18          | 33          | 37         | 37          | ANC3                         | —         | —                | —   | —        | T2IN <sup>(1)</sup>           | —                   | —   | —                   | SSP1CLK <sup>(1)</sup><br>SSP1DAT <sup>(1)</sup> | —    | —                         | —                     | —    | IOCC3                       | Y       | —                 |
| RC4                | 23          | 38          | 42         | 42          | ANC4                         | —         | —                | —   | —        | —                             | —                   | —   | —                   | SSP1CLK <sup>(1)</sup><br>SSP1DAT <sup>(1)</sup> | —    | —                         | —                     | —    | IOCC4                       | Y       | —                 |



**TABLE 6: 40/44-PIN ALLOCATION TABLE (PIC16(L)F15375, PIC16(L)F15376) (CONTINUED)**

| I/O <sup>(2)</sup> | 40-Pin PDIP | 40-Pin UQFN | 44-Pin QFN | 44-Pin TQFP | ADC | Reference | Comparator | NCO     | DAC | Timers | CCP  | PWM  | CWG            | MSSP                                               | ZCD | EUSART            | CLC     | CLKR | Interrupt | Pull-up | Basic |
|--------------------|-------------|-------------|------------|-------------|-----|-----------|------------|---------|-----|--------|------|------|----------------|----------------------------------------------------|-----|-------------------|---------|------|-----------|---------|-------|
| OUT <sup>(2)</sup> | —           | —           | —          | —           | —   | —         | C1OUT      | NCO1OUT | —   | TMR0   | CCP1 | PWM3 | CWG1A<br>CWG2A | SDO1<br>SDO2                                       | —   | DT <sup>(3)</sup> | CLC1OUT | CLKR | —         | —       | —     |
|                    | —           | —           | —          | —           | —   | —         | C2OUT      | —       | —   | —      | CCP2 | PWM4 | CWG1B<br>CWG2B | SCK1<br>SCK2                                       | —   | CK1<br>CK2        | CLC2OUT | —    | —         | —       | —     |
|                    | —           | —           | —          | —           | —   | —         | —          | —       | —   | —      | —    | PWM5 | CWG1C<br>CWG2C | SCK1 <sup>(3),(4)</sup><br>SCL2 <sup>(3),(4)</sup> | —   | TX1<br>TX2        | CLC3OUT | —    | —         | —       | —     |
|                    | —           | —           | —          | —           | —   | —         | —          | —       | —   | —      | —    | PWM6 | CWG1D<br>CWG2D | SDA1 <sup>(3),(4)</sup><br>SDA2 <sup>(3),(4)</sup> | —   | —                 | CLC4OUT | —    | —         | —       | —     |

- Note**
- 1: This is a PPS re-mappable input signal. The input function may be moved from the default location shown to one of several other PORTx pins.
  - 2: All digital output signals shown in this row are PPS remappable. These signals may be mapped to output onto one of several PORTx pin options.
  - 3: This is a bidirectional signal. For normal module operation, the firmware should map this signal to the same pin in both the PPS input and PPS output registers.
  - 4: These pins are configured for I<sup>2</sup>C logic levels. PPS assignments to the other pins will operate, but input logic levels will be standard TTL/ST as selected by the INLV register, instead of the I<sup>2</sup>C specific or SMBUS input buffer thresholds.

**TABLE 7: 48-PIN ALLOCATION TABLE (PIC16(L)F15385, PIC16(L)F15386)**

| I/O <sup>(2)</sup> | 48-Pin UQFN/TQFP | ADC                          | Reference | Comparator       | NCO | DAC      | Timers                        | CCP                 | PWM | CWG                 | MSSP                                             | ZCD  | EUSART                    | CLC                   | CLKR | Interrupt                   | Pull-up | Basic             |
|--------------------|------------------|------------------------------|-----------|------------------|-----|----------|-------------------------------|---------------------|-----|---------------------|--------------------------------------------------|------|---------------------------|-----------------------|------|-----------------------------|---------|-------------------|
| RA0                | 21               | ANA0                         | —         | C1IN0-<br>C2IN0- | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | CLCIN0 <sup>(1)</sup> | —    | IOCA0                       | Y       | —                 |
| RA1                | 22               | ANA1                         | —         | C1IN1-<br>C2IN1- | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | CLCIN1 <sup>(1)</sup> | —    | IOCA1                       | Y       | —                 |
| RA2                | 23               | ANA2                         | —         | C1IN0+<br>C2IN0+ | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCA2                       | Y       | —                 |
| RA3                | 24               | ANA3                         | VREF+     | C1IN1+           | —   | DACREF+  | —                             | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCA3                       | Y       | —                 |
| RA4                | 25               | ANA4                         | —         | C1IN1-           | —   | —        | T0CKI <sup>(1)</sup>          | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCA4                       | Y       | —                 |
| RA5                | 26               | ANA5<br>ADACT                | —         | —                | —   | —        | T1G <sup>(1)</sup>            | —                   | —   | —                   | SSP1SS <sup>(1)</sup>                            | —    | —                         | —                     | —    | IOCA5                       | Y       | —                 |
| RA6                | 33               | ANA6                         | —         | —                | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCA6                       | Y       | CLKOUT            |
| RA7                | 32               | ANA7                         | —         | —                | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCA7                       | Y       | CLKIN             |
| RB0                | 8                | ANB0                         | —         | C2IN1+           | —   | —        | —                             | —                   | —   | CWG1 <sup>(1)</sup> | SSP2SS <sup>(1)</sup>                            | ZCD1 | —                         | —                     | —    | INT <sup>(1)</sup><br>IOCB0 | Y       | —                 |
| RB1                | 9                | ANB1                         | —         | C1IN3-<br>C2IN3- | —   | —        | —                             | —                   | —   | —                   | SSP1CLK <sup>(1)</sup><br>SSP1DAT <sup>(1)</sup> | —    | —                         | —                     | —    | IOCB1                       | Y       | —                 |
| RB2                | 10               | ANB2                         | —         | —                | —   | —        | —                             | —                   | —   | —                   | SSP1CLK <sup>(1)</sup><br>SSP1DAT <sup>(1)</sup> | —    | —                         | —                     | —    | IOCB2                       | Y       | —                 |
| RB3                | 11               | ANB3                         | —         | C1IN3-<br>C2IN3- | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCB3                       | Y       | —                 |
| RB4                | 16               | ANB4<br>ADACT <sup>(1)</sup> | —         | —                | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCB4                       | Y       | —                 |
| RB5                | 17               | ANB5                         | —         | —                | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCB5                       | Y       | —                 |
| RB6                | 18               | ANB6                         | —         | —                | —   | —        | —                             | —                   | —   | —                   | —                                                | —    | TX2<br>CK2 <sup>(1)</sup> | CLCIN2 <sup>(1)</sup> | —    | IOCB6                       | Y       | ICDCLK<br>ICSPCLK |
| RB7                | 19               | ANB7                         | —         | —                | —   | DAC1OUT2 | —                             | —                   | —   | —                   | —                                                | —    | RX2<br>DT2 <sup>(1)</sup> | CLCIN3 <sup>(1)</sup> | —    | IOCB7                       | Y       | ICDDAT<br>ICSPDAT |
| RC0                | 34               | ANC0                         | —         | —                | —   | —        | SOSCO<br>T1CKI <sup>(1)</sup> | —                   | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCC0                       | Y       | —                 |
| RC1                | 35               | ANC1                         | —         | —                | —   | —        | SOSCI                         | CCP2 <sup>(1)</sup> | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCC1                       | Y       | —                 |
| RC2                | 40               | ANC2                         | —         | —                | —   | —        | —                             | CCP1 <sup>(1)</sup> | —   | —                   | —                                                | —    | —                         | —                     | —    | IOCC2                       | Y       | —                 |
| RC3                | 41               | ANC3                         | —         | —                | —   | —        | T2IN <sup>(1)</sup>           | —                   | —   | —                   | SSP1CLK <sup>(1)</sup><br>SSP1DAT <sup>(1)</sup> | —    | —                         | —                     | —    | IOCC3                       | Y       | —                 |

**TABLE 7: 48-PIN ALLOCATION TABLE (PIC16(L)F15385, PIC16(L)F15386) (CONTINUED)**

| I/O <sup>(2)</sup> | 48-Pin UQFN/TQFP | ADC | Reference | Comparator | NCO     | DAC | Timers | CCP  | PWM  | CWG            | MSSP                                               | ZCD | EUSART            | CLC     | CLKR | Interrupt | Pull-up | Basic           |
|--------------------|------------------|-----|-----------|------------|---------|-----|--------|------|------|----------------|----------------------------------------------------|-----|-------------------|---------|------|-----------|---------|-----------------|
| V <sub>SS</sub>    | 6                | —   | —         | —          | —       | —   | —      | —    | —    | —              | —                                                  | —   | —                 | —       | —    | —         | —       | V <sub>SS</sub> |
| V <sub>SS</sub>    | 31               | —   | —         | —          | —       | —   | —      | —    | —    | —              | —                                                  | —   | —                 | —       | —    | —         | —       | V <sub>SS</sub> |
| VSEL0              | —                | —   | —         | —          | —       | —   | —      | —    | —    | —              | —                                                  | —   | —                 | —       | —    | —         | —       | —               |
| OUT <sup>(2)</sup> | —                | —   | —         | C1OUT      | NCO1OUT | —   | TMR0   | CCP1 | PWM3 | CWG1A<br>CWG2A | SDO1<br>SDO2                                       | —   | DT <sup>(3)</sup> | CLC1OUT | CLKR | —         | —       | —               |
|                    | —                | —   | —         | C2OUT      | —       | —   | —      | CCP2 | PWM4 | CWG1B<br>CWG2B | SCK1<br>SCK2                                       | —   | CK1<br>CK2        | CLC2OUT | —    | —         | —       | —               |
|                    | —                | —   | —         | —          | —       | —   | —      | —    | PWM5 | CWG1C<br>CWG2C | SCK1 <sup>(3),(4)</sup><br>SCL2 <sup>(3),(4)</sup> | —   | TX1<br>TX2        | CLC3OUT | —    | —         | —       | —               |
|                    | —                | —   | —         | —          | —       | —   | —      | —    | PWM6 | CWG1D<br>CWG2D | SDA1 <sup>(3),(4)</sup><br>SDA2 <sup>(3),(4)</sup> | —   | —                 | CLC4OUT | —    | —         | —       | —               |

- Note**
- 1: This is a PPS re-mappable input signal. The input function may be moved from the default location shown to one of several other PORTx pins.
  - 2: All digital output signals shown in this row are PPS re-mappable. These signals may be mapped to output onto one of several PORTx pin options.
  - 3: This is a bidirectional signal. For normal module operation, the firmware should map this signal to the same pin in both the PPS input and PPS output registers.
  - 4: These pins are configured for I<sup>2</sup>C logic levels. PPS assignments to the other pins will operate, but input logic levels will be standard TTL/ST as selected by the INLVL register, instead of the I<sup>2</sup>C specific or SMBUS input buffer thresholds.

---

**Note the following details of the code protection feature on Microchip devices:**

- Microchip products meet the specification contained in their particular Microchip Data Sheet.
- Microchip believes that its family of products is one of the most secure families of its kind on the market today, when used in the intended manner and under normal conditions.
- There are dishonest and possibly illegal methods used to breach the code protection feature. All of these methods, to our knowledge, require using the Microchip products in a manner outside the operating specifications contained in Microchip's Data Sheets. Most likely, the person doing so is engaged in theft of intellectual property.
- Microchip is willing to work with the customer who is concerned about the integrity of their code.
- Neither Microchip nor any other semiconductor manufacturer can guarantee the security of their code. Code protection does not mean that we are guaranteeing the product as "unbreakable."

Code protection is constantly evolving. We at Microchip are committed to continuously improving the code protection features of our products. Attempts to break Microchip's code protection feature may be a violation of the Digital Millennium Copyright Act. If such acts allow unauthorized access to your software or other copyrighted work, you may have a right to sue for relief under that Act.

---

Information contained in this publication regarding device applications and the like is provided only for your convenience and may be superseded by updates. It is your responsibility to ensure that your application meets with your specifications. MICROCHIP MAKES NO REPRESENTATIONS OR WARRANTIES OF ANY KIND WHETHER EXPRESS OR IMPLIED, WRITTEN OR ORAL, STATUTORY OR OTHERWISE, RELATED TO THE INFORMATION, INCLUDING BUT NOT LIMITED TO ITS CONDITION, QUALITY, PERFORMANCE, MERCHANTABILITY OR FITNESS FOR PURPOSE. Microchip disclaims all liability arising from this information and its use. Use of Microchip devices in life support and/or safety applications is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless Microchip from any and all damages, claims, suits, or expenses resulting from such use. No licenses are conveyed, implicitly or otherwise, under any Microchip intellectual property rights unless otherwise stated.

*Microchip received ISO/TS-16949:2009 certification for its worldwide headquarters, design and wafer fabrication facilities in Chandler and Tempe, Arizona; Gresham, Oregon and design centers in California and India. The Company's quality system processes and procedures are for its PIC® MCUs and dsPIC® DSCs, KEELOQ® code hopping devices, Serial EEPROMs, microperipherals, nonvolatile memory and analog products. In addition, Microchip's quality system for the design and manufacture of development systems is ISO 9001:2000 certified.*

**QUALITY MANAGEMENT SYSTEM**  
**CERTIFIED BY DNV**  
**== ISO/TS 16949 ==**

### Trademarks

The Microchip name and logo, the Microchip logo, AnyRate, dsPIC, FlashFlex, flexPWR, Helder, JukeBlox, KEELOQ, KEELOQ logo, Klear, LANCheck, LINK MD, MediaLB, MOST, MOST logo, MPLAB, OptoLyzer, PIC, PICSTART, PIC32 logo, RightTouch, SpyNIC, SST, SST Logo, SuperFlash and UNI/O are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

ClockWorks, The Embedded Control Solutions Company, ETHERSYNCH, Hyper Speed Control, HyperLight Load, IntelliMOS, mTouch, Precision Edge, and QUIET-WIRE are registered trademarks of Microchip Technology Incorporated in the U.S.A.

Analog-for-the-Digital Age, Any Capacitor, AnyIn, AnyOut, BodyCom, chipKIT, chipKIT logo, CodeGuard, dsPICDEM, dsPICDEM.net, Dynamic Average Matching, DAM, ECAN, EtherGREEN, In-Circuit Serial Programming, ICSP, Inter-Chip Connectivity, JitterBlocker, KlearNet, KlearNet logo, MiWi, motorBench, MPASM, MPF, MPLAB Certified logo, MPLIB, MPLINK, MultiTRAK, NetDetach, Omniscient Code Generation, PICDEM, PICDEM.net, PICkit, PICtail, PureSilicon, RightTouch logo, REAL ICE, Ripple Blocker, Serial Quad I/O, SQL, SuperSwitcher, SuperSwitcher II, Total Endurance, TSHARC, USBCheck, VariSense, ViewSpan, WiperLock, Wireless DNA, and ZENA are trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

SQTP is a service mark of Microchip Technology Incorporated in the U.S.A.

Silicon Storage Technology is a registered trademark of Microchip Technology Inc. in other countries.

GestIC is a registered trademarks of Microchip Technology Germany II GmbH & Co. KG, a subsidiary of Microchip Technology Inc., in other countries.

All other trademarks mentioned herein are property of their respective companies.

© 2016, Microchip Technology Incorporated, Printed in the U.S.A., All Rights Reserved.

ISBN: 978-1-5224-0407-1

# Worldwide Sales and Service

## AMERICAS

**Corporate Office**  
2355 West Chandler Blvd.  
Chandler, AZ 85224-6199  
Tel: 480-792-7200  
Fax: 480-792-7277  
Technical Support:  
<http://www.microchip.com/support>  
Web Address:  
[www.microchip.com](http://www.microchip.com)

**Atlanta**  
Duluth, GA  
Tel: 678-957-9614  
Fax: 678-957-1455

**Austin, TX**  
Tel: 512-257-3370

**Boston**  
Westborough, MA  
Tel: 774-760-0087  
Fax: 774-760-0088

**Chicago**  
Itasca, IL  
Tel: 630-285-0071  
Fax: 630-285-0075

**Cleveland**  
Independence, OH  
Tel: 216-447-0464  
Fax: 216-447-0643

**Dallas**  
Addison, TX  
Tel: 972-818-7423  
Fax: 972-818-2924

**Detroit**  
Novi, MI  
Tel: 248-848-4000

**Houston, TX**  
Tel: 281-894-5983

**Indianapolis**  
Noblesville, IN  
Tel: 317-773-8323  
Fax: 317-773-5453

**Los Angeles**  
Mission Viejo, CA  
Tel: 949-462-9523  
Fax: 949-462-9608

**New York, NY**  
Tel: 631-435-6000

**San Jose, CA**  
Tel: 408-735-9110

**Canada - Toronto**  
Tel: 905-673-0699  
Fax: 905-673-6509

## ASIA/PACIFIC

**Asia Pacific Office**  
Suites 3707-14, 37th Floor  
Tower 6, The Gateway  
Harbour City, Kowloon

**Hong Kong**  
Tel: 852-2943-5100  
Fax: 852-2401-3431

**Australia - Sydney**  
Tel: 61-2-9868-6733  
Fax: 61-2-9868-6755

**China - Beijing**  
Tel: 86-10-8569-7000  
Fax: 86-10-8528-2104

**China - Chengdu**  
Tel: 86-28-8665-5511  
Fax: 86-28-8665-7889

**China - Chongqing**  
Tel: 86-23-8980-9588  
Fax: 86-23-8980-9500

**China - Dongguan**  
Tel: 86-769-8702-9880

**China - Hangzhou**  
Tel: 86-571-8792-8115  
Fax: 86-571-8792-8116

**China - Hong Kong SAR**  
Tel: 852-2943-5100  
Fax: 852-2401-3431

**China - Nanjing**  
Tel: 86-25-8473-2460  
Fax: 86-25-8473-2470

**China - Qingdao**  
Tel: 86-532-8502-7355  
Fax: 86-532-8502-7205

**China - Shanghai**  
Tel: 86-21-5407-5533  
Fax: 86-21-5407-5066

**China - Shenyang**  
Tel: 86-24-2334-2829  
Fax: 86-24-2334-2393

**China - Shenzhen**  
Tel: 86-755-8864-2200  
Fax: 86-755-8203-1760

**China - Wuhan**  
Tel: 86-27-5980-5300  
Fax: 86-27-5980-5118

**China - Xian**  
Tel: 86-29-8833-7252  
Fax: 86-29-8833-7256

## ASIA/PACIFIC

**China - Xiamen**  
Tel: 86-592-2388138  
Fax: 86-592-2388130

**China - Zhuhai**  
Tel: 86-756-3210040  
Fax: 86-756-3210049

**India - Bangalore**  
Tel: 91-80-3090-4444  
Fax: 91-80-3090-4123

**India - New Delhi**  
Tel: 91-11-4160-8631  
Fax: 91-11-4160-8632

**India - Pune**  
Tel: 91-20-3019-1500

**Japan - Osaka**  
Tel: 81-6-6152-7160  
Fax: 81-6-6152-9310

**Japan - Tokyo**  
Tel: 81-3-6880-3770  
Fax: 81-3-6880-3771

**Korea - Daegu**  
Tel: 82-53-744-4301  
Fax: 82-53-744-4302

**Korea - Seoul**  
Tel: 82-2-554-7200  
Fax: 82-2-558-5932 or  
82-2-558-5934

**Malaysia - Kuala Lumpur**  
Tel: 60-3-6201-9857  
Fax: 60-3-6201-9859

**Malaysia - Penang**  
Tel: 60-4-227-8870  
Fax: 60-4-227-4068

**Philippines - Manila**  
Tel: 63-2-634-9065  
Fax: 63-2-634-9069

**Singapore**  
Tel: 65-6334-8870  
Fax: 65-6334-8850

**Taiwan - Hsin Chu**  
Tel: 886-3-5778-366  
Fax: 886-3-5770-955

**Taiwan - Kaohsiung**  
Tel: 886-7-213-7828

**Taiwan - Taipei**  
Tel: 886-2-2508-8600  
Fax: 886-2-2508-0102

**Thailand - Bangkok**  
Tel: 66-2-694-1351  
Fax: 66-2-694-1350

## EUROPE

**Austria - Wels**  
Tel: 43-7242-2244-39  
Fax: 43-7242-2244-393

**Denmark - Copenhagen**  
Tel: 45-4450-2828  
Fax: 45-4485-2829

**France - Paris**  
Tel: 33-1-69-53-63-20  
Fax: 33-1-69-30-90-79

**Germany - Dusseldorf**  
Tel: 49-2129-3766400

**Germany - Karlsruhe**  
Tel: 49-721-625370

**Germany - Munich**  
Tel: 49-89-627-144-0  
Fax: 49-89-627-144-44

**Italy - Milan**  
Tel: 39-0331-742611  
Fax: 39-0331-466781

**Italy - Venice**  
Tel: 39-049-7625286

**Netherlands - Drunen**  
Tel: 31-416-690399  
Fax: 31-416-690340

**Poland - Warsaw**  
Tel: 48-22-3325737

**Spain - Madrid**  
Tel: 34-91-708-08-90  
Fax: 34-91-708-08-91

**Sweden - Stockholm**  
Tel: 46-8-5090-4654

**UK - Wokingham**  
Tel: 44-118-921-5800  
Fax: 44-118-921-5820

07/14/15